

Network Working Group
Internet-Draft
Intended Status: Standards Track
Expires: August 14 2014

M. Chandramouli
B. Claise
Cisco Systems, Inc.
B. Schoening
Independent Consultant
J. Quittek
T. Dietz
NEC Europe Ltd.
February 14, 2014

Power and Energy Monitoring MIB
draft-ietf-eman-energy-monitoring-mib-09

Status of this Memo

This Internet-Draft is submitted to IETF in full conformance with the provisions of BCP 78 and BCP 79.

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/lid-abstracts.txt>

The list of Internet-Draft Shadow Directories can be accessed at <http://www.ietf.org/shadow.html>

This Internet-Draft will expire on August 2014.

<Claise, et. Al>

Expires August 14, 2014

[Page 1]

Copyright Notice

Copyright (c) 2013 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to BCP 78 and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

Abstract

This document defines a subset of the Management Information Base (MIB) for power and energy monitoring of devices.

Conventions used in this document

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "NOT RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in RFC 2119 [RFC2119].

Table of Contents

1. Introduction.....	3
2. The Internet-Standard Management Framework.....	4
3. Use Cases.....	4
4. Terminology.....	4
5. Architecture Concepts Applied to the MIB Modules.....	5
5.1. Energy Object Tables.....	5
5.1.1. ENERGY-OBJECT-MIB.....	5
5.1.2. POWER-ATTRIBUTES-MIB.....	7
5.1.3. UML Diagram.....	9
5.2. Energy Object Identity.....	11
5.3. Power State.....	12
5.3.1. Power State Set.....	13
5.4. Energy Object Usage Information.....	13
5.5. Optional Power Usage Attributes.....	14
5.6. Optional Energy Measurement.....	14
5.7. Fault Management.....	18

6. Discovery.....	18
7. Link with the other IETF MIBs.....	19
7.1. Link with the ENTITY-MIB and the ENTITY-SENSOR MIB...	19
7.2. Link with the ENTITY-STATE MIB.....	20
7.3. Link with the POWER-OVER-ETHERNET MIB.....	21
7.4. Link with the UPS MIB.....	21
7.5. Link with the LLDP and LLDP-MED MIBs.....	22
8. Structure of the MIB.....	23
9. MIB Definitions.....	24
10. Implementation Status.....	62
10.1. SNMP Research.....	62
10.2. Cisco Systems.....	62
11. Security Considerations.....	63
12. IANA Considerations.....	64
13. Contributors.....	64
14. Acknowledgment.....	65
15. References.....	65
15.1. Normative References.....	65
15.2. Informative References.....	66

1. Introduction

This document defines a subset of the Management Information Base (MIB) for use in energy management of devices within or connected to communication networks. The MIB modules in this document are designed to provide a model for energy management, which includes monitoring for Power State and energy consumption of networked elements. This MIB takes into account the Energy Management Framework [EMAN-FMWK], which, in turn, is based on the Requirements for Energy Management [RFC6988].

Energy management can be applied to devices in communication networks. Target devices for this specification include (but are not limited to): routers, switches, Power over Ethernet (PoE) endpoints, protocol gateways for building management systems, intelligent meters, home energy gateways, hosts and servers, sensor proxies, etc. Target devices and the use cases for Energy Management are discussed in Energy Management Applicability Statement [EMAN-AS].

Where applicable, device monitoring extends to the individual components of the device and to any attached dependent devices. For example: A device can contain components that are independent from a power-state point of view, such as line cards, processor cards, hard drives. A device can also have dependent attached devices, such as a switch with PoE endpoints or a power distribution unit with attached endpoints.

2. The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to section 7 of RFC 3410 [RFC3410].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies MIB modules that are compliant to SMIv2, which is described in STD 58, RFC 2578 [RFC2578], STD 58, RFC 2579 [RFC2579] and STD 58, RFC 2580 [RFC2580].

3. Use Cases

Requirements for power and energy monitoring for networking devices are specified in [RFC6988]. The requirements in [RFC6988] cover devices typically found in communications networks, such as switches, routers, and various connected endpoints. For a power monitoring architecture to be useful, it should also apply to facility meters, power distribution units, gateway proxies for commercial building control, home automation devices, and devices that interface with the utility and/or smart grid. Accordingly, the scope of the MIB modules in this document are broader than that specified in [RFC6988]. Several use cases for Energy Management have been identified in the "Energy Management (EMAN) Applicability Statement" [EMAN-AS].

4. Terminology

Please refer to [EMAN-FMWK] for the definitions of the following terminology used in this draft.

- Energy Management
- Energy Management System (EnMS)
- Energy Monitoring
- Energy Control
- electrical equipment

- non-electrical equipment (mechanical equipment)
- device
- component
- power inlet

- power outlet
- energy
- power
- demand
- provide energy
- receive energy
- meter (energy meter)
- battery
- Power Interface
- Nameplate Power
- Power Attributes
- Power Quality
- Power State
- Power State Set

5. Architecture Concepts Applied to the MIB Modules

This section describes the concepts specified in the Energy Management Framework [EMAN-FMWK] that pertain to power usage, with specific information related to the MIB module specified in this document. This subsection maps concepts developed in the Energy Management Framework [EMAN-FMWK].

The Energy Monitoring MIB has 2 independent MIB modules, ENERGY-OBJECT-MIB and POWER-ATTRIBUTES-MIB. The first, ENERGY-OBJECT-MIB, is focused on measurement of power and energy. The second, POWER-ATTRIBUTES-MIB, is focused on power quality measurements for Energy Objects.

Devices and their sub-components can be modeled using the containment tree of the ENTITY-MIB [RFC6933].

5.1. Energy Object Tables

5.1.1. ENERGY-OBJECT-MIB

The ENERGY-OBJECT-MIB module consists of five tables.

The first table is the eoMeterCapabilitiesTable. It indicates the instrumentation available for each Energy Object. Entries in this table indicate which other tables from the ENERGY-OBJECT-MIB and POWER-ATTRIBUTES-MIB are available for each Energy Object. The eoMeterCapabilitiesTable is indexed by entPhysicalIndex [RFC6933].

The second table is the eoPowerTable. It reports the power consumption of each Energy Object, as well as the units, sign, measurement accuracy, and related objects. The eoPowerTable is indexed by entPhysicalIndex.


```

+---eoPowerStateEntry(1)
|       [entPhysicalIndex, eoPowerStateIndex]
|
+--- --n IANAPowerStateSet eoPowerStateIndex(1)
+--- r-n Integer32          eoPowerStateMaxPower(2)
+--- r-n UnitMultiplier
|       eoPowerStatePowerUnitMultiplier(3)
+--- r-n TimeTicks          eoPowerStateTotalTime(4)
+--- r-n Counter32          eoPowerStateEnterCount(5)
+eoEnergyParametersTable(4)
+----eoEnergyParametersEntry(1) [eoEnergyParametersIndex]
|
+--- --n PhysicalIndex      eoEnergyObjectIndex(1)
+   r-n Integer32          eoEnergyParametersIndex(2)
+--- r-n TimeInterval      eoEnergyParametersIntervalLength(3)
+--- r-n Integer32         eoEnergyParametersIntervalNumber(4)
+--- r-n INTEGER           eoEnergyParametersIntervalMode(5)
+--- r-n TimeInterval      eoEnergyParametersIntervalWindow(6)
+--- r-n Integer32         eoEnergyParametersSampleRate(7)
+--- r-n RowStatus         eoEnergyParametersStatus(8)
+eoEnergyTable(5)
+----eoEnergyEntry(1)
|       [eoEnergyParametersIndex, eoEnergyCollectionStartTime]
|
+--- r-n TimeTicks          eoEnergyCollectionStartTime(1)
+--- r-n Integer32          eoEnergyConsumed(2)
+--- r-n Integer32          eoEnergyProvided(3)
+--- r-n Integer32          eoEnergyStored(4)
+--- r-n UnitMultiplier    eoEnergyUnitMultiplier(5)
+--- r-n Integer32          eoEnergyAccuracy(6)
+--- r-n Integer32          eoEnergyMaxConsumed(7)
+--- r-n Integer32          eoEnergyMaxProduced(8)
+--- r-n TimeTicks          eoEnergyDiscontinuityTime(9)

```

5.1.2. POWER-ATTRIBUTES-MIB

The POWER-ATTRIBUTES-MIB module consists of three tables.

The first table is the eoACPwrAttributesTable. It indicates the power quality available for each Energy Object. The eoACPwrAttributesTable is indexed by entPhysicalIndex [RFC6933].

The second table is the eoACPwrAttributesDelPhaseTable. The entries in this table configure the parameters of energy and demand measurement collection. This table is indexed by eoEnergyParametersIndex.

The third table is the eoACPwrAttributesWyePhaseTable. For each Energy Object, it reports information and statistics about the supported Power States. The eoPowerStateTable is indexed by entPhysicalIndex and eoPowerStateIndex.

```

eoACPwrAttributesTable(1)
|
+---eoACPwrAttributesEntry(1) [ entPhysicalIndex]
|
|   +---r-n INTEGER      eoACPwrAttributesConfiguration(1)
|   +--- r-n Integer32  eoACPwrAttributesAvgVoltage(2)
|   +--- r-n Integer32  eoACPwrAttributesAvgCurrent(3)
|   +--- r-n Integer32  eoACPwrAttributesFrequency(4)
|   +--- r-n UnitMultiplier
|                       eoACPwrAttributesPowerUnitMultiplier(5)
|   +--- r-n Integer32  eoACPwrAttributesPowerAccuracy(6)
|   +--- r-n Integer32
|                       eoACPwrAttributesTotalActivePower(7)
|   +--- r-n Integer32
|                       eoACPwrAttributesTotalReactivePower(8)
|   +--- r-n Integer32
|                       eoACPwrAttributesTotalApparentPower(9)
|   +--- r-n Integer32
|                       eoACPwrAttributesTotalPowerFactor(10)
|   +--- r-n Integer32  eoACPwrAttributesThdCurrent(11)
|   +--- r-n Integer32  eoACPwrAttributesThdVoltage(12)
|
+eoACPwrAttributesDelPhaseTable(2)
+--- eoACPwrAttributesDelPhaseEntry(1)
|   [entPhysicalIndex, eoACPwrAttributesDelPhaseIndex]
|   |
|   +--- r-n Integer32
|   |   eoACPwrAttributesDelPhaseIndex(1)
|   +--- r-n Integer32
|   |   eoACPwrAttributesDelPhaseToNextPhaseVoltage(2)
|   +--- r-n Integer32
|   |   eoACPwrAttributesDelThdPhaseToNextPhaseVoltage(3)
|
+eoACPwrAttributesWyePhaseTable(3)
+--- eoACPwrAttributesWyePhaseEntry(1)
|   [entPhysicalIndex, eoACPwrAttributesWyePhaseIndex]
|   |
|   +--- r-n Integer32
|   |   eoACPwrAttributesWyePhaseIndex(1)
|   +--- r-n Integer32
|   |   eoACPwrAttributesWyePhaseToNeutralVoltage(2)
|   +--- r-n Integer32
|   |   eoACPwrAttributesWyeCurrent(3)
|   +--- r-n Integer32

```


```

|      |      eoACPwrAttributesWyeActivePower(4)
+-- r-n Integer32
|      |      eoACPwrAttributesWyeReactivePower(5)
+-- r-n Integer32
|      |      eoACPwrAttributesWyeApparentPower(6)
+-- r-n Integer32
|      |      eoACPwrAttributesWyePowerFactor(7)
+-- r-n Integer32
|      |      eoACPwrAttributesWyeThdCurrent(9)
+-- r-n Integer32
|      |      eoACPwrAttributesWyeThdPhaseToNeutralVoltage(10)

```

5.1.3. UML Diagram

A UML diagram representation of the MIB objects in the two MIB modules ENERGY-OBJECT-MIB and POWER-ATTRIBUTES-MIB is presented.







Figure 1:UML diagram for energyObjectMib

(*) Compliance with the ENERGY-OBJECT-CONTEXT-MIB






Figure 2: UML diagram for the POWER-ATTRIBUTES-MIB

(*) Compliance with the ENERGY-OBJECT-CONTEXT-MIB

5.2. Energy Object Identity

The Energy Object identity information is specified in the ENERGY-OBJECT-CONTEXT-MIB module [EMAN-AWARE-MIB] primary table, i.e., the eoTable. In this table, Energy Object context such as

domain, role description, and importance are specified. In addition, the ENERGY-OBJECT-CONTEXT-MIB module specifies the relationship between Energy Objects. There are several possible relationships between Energy Objects, such as meteredBy, metering, poweredBy, powering, aggregatedBy, and aggregating as defined in the IANA-ENERGY-RELATION-MIB module [EMAN-AWARE-MIB].

5.3. Power State

An Energy Object may have energy conservation modes called Power States. Between the ON and OFF states of a device, there can be several intermediate energy saving modes. Those energy saving modes are called Power States.

Power States, which represent universal states of power management of an Energy Object, are specified by the eoPowerState MIB object. The actual Power State is specified by the eoPowerOperState MIB object, while the eoPowerAdminState MIB object specifies the Power State requested for the Energy Object. The difference between the values of eoPowerOperState and eoPowerAdminState indicate that the Energy Object is busy transitioning from eoPowerAdminState into the eoPowerOperState, at which point it will update the content of eoPowerOperState. In addition, the possible reason for change in Power State is reported in eoPowerStateEnterReason. Regarding eoPowerStateEnterReason, management stations and Energy Objects should support any format of the owner string dictated by the local policy of the organization. It is suggested that this name contain at least the reason for the transition change, and one or more of the following: IP address, management station name, network manager's name, location, or phone number.

The MIB objects eoPowerOperState, eoPowerAdminState, and eoPowerStateEnterReason are contained in the eoPowerTable MIB table.

The eoPowerStateTable table enumerates the maximum power usage in watts for every single supported Power State of each Power State Set supported by the Energy Object. In addition, PowerStateTable provides additional statistics such as eoPowerStateEnterCount, i.e., the number of times an entity has visited a particular Power State, and eoPowerStateTotalTime, i.e., the total time spent in a particular Power State of an Energy Object.

5.3.1. Power State Set

There are several standards and implementations of Power State Sets. An Energy Object can support one or multiple Power State Set implementations concurrently.

There are currently three Power State Sets defined:

IEEE1621(256)	-	[IEEE1621]
DMTF(512)	-	[DMTF]
EMAN(768)	-	[EMAN-FMWK]

The Power State Sets are listed in [EMAN-FMWK] along with each Power State within the Power Set.

5.4. Energy Object Usage Information

For an Energy Object, power usage is reported using eoPower. The magnitude of measurement is based on the eoPowerUnitMultiplier MIB variable, based on the UnitMultiplier Textual Convention (TC). Power measurement magnitude should conform to the IEC 62053-21 [IEC.62053-21] and IEC 62053-22 [IEC.62053-22] definition of unit multiplier for the SI (System International) units of measure. Measured values are represented in SI units obtained by BaseValue * 10 raised to the power of the unit multiplier.

For example, if current power usage of an Energy Object is 3, it could be 3 W, 3 mW, 3 KW, or 3 MW, depending on the value of eoPowerUnitMultiplier. Note that other measurements throughout the two MIB modules in this document use the same mechanism, including eoPowerStatePowerUnitMultiplier, eoEnergyUnitMultiplier, and eoACPwrAttributesPowerUnitMultiplier.

In addition to knowing the usage and magnitude, it is useful to know how an eoPower measurement was obtained. An NMS can use this to account for the accuracy and nature of the reading between different implementations. For this eoPowerMeasurementLocal describes whether the measurements were made at the device itself or from a remote source. The eoPowerMeasurementCaliber describes the method that was used to measure the power and can distinguish actual or estimated values. There may be devices in the network, which may not be able to measure or report power consumption. For those devices, the object eoPowerMeasurementCaliber shall report that the measurement mechanism is "unavailable" and the eoPower measurement shall be "0".

The nameplate power rating of an Energy Object is specified in eoPowerNameplate MIB object.

5.5. Optional Power Usage Attributes

The optional POWER-ATTRIBUTES-MIB module can be implemented to further describe power usage attributes measurement. The POWER-ATTRIBUTES-MIB module is aligned with IEC 61850 7-2 standard to describe AC measurements.

The POWER-ATTRIBUTES-MIB module contains a primary table, eoACPwrAttributesTable, that defines power attributes measurements for supported entPhysicalIndex entities, as a sparse extension of the eoPowerTable (with entPhysicalIndex as primary index). This eoACPwrAttributesTable table contains such information as the configuration (single phase, DEL 3 phases, WYE 3 phases), voltage, frequency, power accuracy, total active/reactive power/apparent power, amperage, and voltage.

In case of 3-phase power, an additional table is populated with Power Attributes measurements per phase (hence, double indexed by the entPhysicalIndex and a phase index). This table, describes attributes specific to either WYE or DEL configurations.

In a DEL configuration, the eoACPwrAttributesDelPhaseTable describes the phase-to-phase power attributes measurements, i.e., voltage. In a DEL configuration, the current is equal in all three phases.

In a WYE configuration, the eoACPwrAttributesWyePhaseTable describes the phase-to-neutral power attributes measurements, i.e., voltage, current, active/reactive/apparent power, and power factor.

5.6. Optional Energy Measurement

It is only relevant to measure energy and demand when there are actual power measurements obtained from measurement hardware. If the eoPowerMeasurementCaliber MIB object has values of unavailable, unknown, estimated, or presumed, then the energy and demand values are not useful.

Two tables are introduced to characterize energy measurement of an Energy Object: eoEnergyTable and eoEnergyParametersTable. Both energy and demand information can be represented via the eoEnergyTable. Energy information will be an accumulation with no interval. Demand information can be represented.

The eoEnergyParametersTable consists of the parameters defining

eoEnergyParametersIndex - an index of that specifies the setting for collection of energy measurements for an Energy Object, eoEnergyObjectIndex - linked to the entPhysicalIndex of the Energy Object, the duration of measurement intervals in seconds, (eoEnergyParametersIntervalLength), the number of successive intervals to be stored in the eoEnergyTable, (eoEnergyParametersIntervalNumber), the type of measurement technique (eoEnergyParametersIntervalMode), and a sample rate used to calculate the average (eoEnergyParametersSampleRate). Judicious choice of the sampling rate will ensure accurate measurement of energy while not imposing an excessive polling burden.

There are three eoEnergyParametersIntervalMode types used for energy measurement collection: period, sliding, and total. The choices of the three different modes of collection are based on IEC standard 61850-7-4. Note that multiple eoEnergyParametersIntervalMode types MAY be configured simultaneously. It is important to note that for a given Energy Object, multiple modes (periodic, total, sliding window) of energy measurement collection can be configured with the use of eoEnergyParametersIndex. However, simultaneous measurement in multiple modes for a given Energy Object depends on the Energy Object capability.

These three eoEnergyParametersIntervalMode types are illustrated by the following three figures, for which:

- The horizontal axis represents the current time, with the symbol <--- L ---> expressing the eoEnergyParametersIntervalLength, and the eoEnergyCollectionStartTime is represented by S1, S2, S3, S4, ..., Sx where x is the value of eoEnergyParametersIntervalNumber.
- The vertical axis represents the time interval of sampling and the value of eoEnergyConsumed can be obtained at the end of the sampling period. The symbol ===== denotes the duration of the sampling period.




Figure 3 : Period eoEnergyParametersIntervalMode

A eoEnergyParametersIntervalMode type of 'period' specifies non-overlapping periodic measurements. Therefore, the next eoEnergyCollectionStartTime is equal to the previous eoEnergyCollectionStartTime plus eoEnergyParametersIntervalLength. $S2=S1+L$; $S3=S2+L$, ...




Figure 4 : Sliding eoEnergyParametersIntervalMode

A eoEnergyParametersIntervalMode type of 'sliding' specifies overlapping periodic measurements.




Figure 5 : Total eoEnergyParametersIntervalMode

A eoEnergyParametersIntervalMode type of 'total' specifies a continuous measurement since the last reset. The value of eoEnergyParametersIntervalNumber should be (1) one and eoEnergyParametersIntervalLength is ignored.

The eoEnergyParametersStatus is used to start and stop energy usage logging. The status of this variable is "active" when all the objects in eoEnergyParametersTable are appropriate which in turn indicates if eoEnergyTable entries exist or not.

The eoEnergyTable consists of energy measurements in eoEnergyConsumed, eoEnergyProvided and eoEnergyStored, the units of the measured energy eoEnergyUnitMultiplier, and the maximum observed energy within a window eoEnergyMaxConsumed, eoEnergyMaxProduced.

Measurements of the total energy consumed by an Energy Object may suffer from interruptions in the continuous measurement of energy consumption. In order to indicate such interruptions, the object eoEnergyDiscontinuityTime is provided for indicating the time of the last interruption of total energy measurement. eoEnergyDiscontinuityTime shall indicate the sysUpTime [RFC3418] when the device was reset.

The following example illustrates the eoEnergyTable and eoEnergyParametersTable:

First, in order to estimate energy, a time interval to sample energy should be specified, i.e., eoEnergyParametersIntervalLength can be set to "900 seconds" or 15 minutes and the number of consecutive intervals over which the maximum energy is calculated (eoEnergyParametersIntervalNumber) as "10". The sampling rate internal to the Energy Object for measurement of power usage (eoEnergyParametersSampleRate) can be "1000 milliseconds", as set by the Energy Object as a reasonable value. Then, the eoEnergyParametersStatus is set to active to indicate that the Energy Object should start monitoring the usage per the eoEnergyTable.

The indices for the eoEnergyTable are eoEnergyParametersIndex, which identifies the index for the setting of energy measurement collection Energy Object, and eoEnergyCollectionStartTime, which denotes the start time of the energy measurement interval based on sysUpTime [RFC3418]. The value of eoEnergyConsumed is the measured energy consumption over the time interval specified (eoEnergyParametersIntervalLength) based on the Energy Object

internal sampling rate (eoEnergyParametersSampleRate). While choosing the values for the eoEnergyParametersIntervalLength and eoEnergyParametersSampleRate, it is recommended to take into consideration either the network element resources adequate to process and store the sample values, and the mechanism used to calculate the eoEnergyConsumed. The units are derived from eoEnergyUnitMultiplier. For example, eoEnergyConsumed can be "100" with eoEnergyUnitMultiplier equal to 0, the measured energy consumption of the Energy Object is 100 watt-hours. The eoEnergyMaxConsumed is the maximum energy observed and that can be "150 watt-hours".

The eoEnergyTable has a buffer to retain a certain number of intervals, as defined by eoEnergyParametersIntervalNumber. If the default value of "10" is kept, then the eoEnergyTable contains 10 energy measurements, including the maximum.

Here is a brief explanation of how the maximum energy can be calculated. The first observed energy measurement value is taken to be the initial maximum. With each subsequent measurement, based on numerical comparison, maximum energy may be updated. The maximum value is retained as long as the measurements are taking place. Based on periodic polling of this table, an NMS could compute the maximum over a longer period, e.g., a month, 3 months, or a year.

5.7. Fault Management

[RFC6988] specifies requirements about Power States such as "the current Power State" , "the time of the last state change", "the total time spent in each state", "the number of transitions to each state" etc. Some of these requirements are fulfilled explicitly by MIB objects such as eoPowerOperState, eoPowerStateTotalTime and eoPowerStateEnterCount. Some of the other requirements are met via the SNMP NOTIFICATION mechanism. eoPowerStateChange SNMP notification which is generated when the value of oPowerStateIndex, eoPowerOperState, or eoPowerAdminState have changed.

6. Discovery

It is probable that most Energy Objects will require the implementation of the ENERGY-OBJECT-CONTEXT-MIB [EMAN-AWARE-MIB] as a prerequisite for this MIB module. In such a case, eoPowerTable of the EMAN-ENERGY-OBJECT-MIB is cross-referenced with the eoTable of ENERGY-OBJECT-CONTEXT-MIB via entPhysicalIndex. Every Energy Object MUST implement entPhysicalIndex, entPhysicalClass, entPhysicalName and

entPhysicalUUID from the ENTITY-MIB [RFC6933]. As the primary index for the Energy Object, entPhysicalIndex is used: It characterizes the Energy Object in the ENERGY-OBJECT-MIB and the POWER-ATTRIBUTES-MIB MIB modules (this document).

The NMS must first poll the ENERGY-OBJECT-CONTEXT-MIB MIB module [EMAN-AWARE-MIB], if available, in order to discover all the Energy Objects and the relationships between those Energy Objects. In the ENERGY-OBJECT-CONTEXT-MIB module tables, the Energy Objects are indexed by the entPhysicalIndex.

From there, the NMS must poll the eoPowerStateTable (specified in the ENERGY-OBJECT-MIB module in this document), which enumerates, amongst other things, the maximum power usage. As the entries in eoPowerStateTable table are indexed by the Energy Object (entPhysicalIndex) and by the Power State Set (eoPowerStateIndex), the maximum power usage is discovered per Energy Object, and the power usage per Power State of the Power State Set. In other words, reading the eoPowerStateTable allows the discovery of each Power State within every Power State Set supported by the Energy Object.

If the Energy Object is an Aggregator, the MIB module would be populated with the Energy Object relationship information, which have its own Energy Object index value (entPhysicalIndex). However, the Energy Object relationship must be discovered via the ENERGY-OBJECT-CONTEXT-MIB module.

Finally, the NMS can monitor the power attributes with the POWER-ATTRIBUTES-MIB MIB module, which reuses the entPhysicalIndex to index the Energy Object.

7. Link with the other IETF MIBs

7.1. Link with the ENTITY-MIB and the ENTITY-SENSOR MIB

RFC 6933 [RFC6933] defines the ENTITY-MIB module that lists the physical entities of a networking device (router, switch, etc.) and those physical entities indexed by entPhysicalIndex. From an energy-management standpoint, the physical entities that consume or produce energy are of interest.

RFC 3433 [RFC3433] defines the ENTITY-SENSOR MIB module that provides a standardized way of obtaining information (current value of the sensor, operational status of the sensor, and the data units precision) from sensors embedded in networking devices. Sensors are associated with each index of entPhysicalIndex of the ENTITY-MIB [RFC6933]. While the focus

of the Power and Energy Monitoring MIB is on measurement of power usage of networking equipment indexed by the ENTITY-MIB, this MIB supports a customized power scale for power measurement and different Power States of networking equipment, and functionality to configure the Power States.

The Energy Objects are modeled by the entPhysicalIndex through the entPhysicalEntity MIB object specified in the eoTable in the ENERGY-OBJECT-CONTEXT-MIB MIB module [EMAN-AWARE-MIB].

The ENTITY-SENSOR MIB [RFC3433] does not have the ANSI C12.x accuracy classes required for electricity (e.g., 1%, 2%, 0.5% accuracy classes). Indeed, entPhySensorPrecision [RFC3433] represents "The number of decimal places of precision in fixed-point sensor values returned by the associated entPhySensorValue object". The ANSI and IEC Standards are used for power measurement and these standards require that we use an accuracy class, not the scientific-number precision model specified in RFC3433. The eoPowerAccuracy MIB object models this accuracy. Note that eoPowerUnitMultiplier represents the scale factor per IEC 62053-21 [IEC.62053-21] and IEC 62053-22 [IEC.62053-22], which is a more logical representation for power measurements (compared to entPhySensorScale), with the mantissa and the exponent values $X * 10 ^ Y$.

Power measurements specifying the qualifier 'UNITS' for each measured value in watts are used in the LLDP-EXT-MED-MIB, POE [RFC3621], and UPS [RFC1628] MIBs. The same 'UNITS' qualifier is used for the power measurement values.

One cannot assume that the ENTITY-MIB and ENTITY-SENSOR MIB are implemented for all Energy Objects that need to be monitored. A typical example is a converged building gateway, which can monitor other devices in a building and provides a proxy between SNMP and a protocol like BACNET. Another example is the home energy controller. In such cases, the eoPhysicalEntity value contains the zero value, using the PhysicalIndexOrZero textual convention.

The eoPower is similar to entPhySensorValue [RFC3433] and the eoPowerUnitMultiplier is similar to entPhySensorScale.

7.2. Link with the ENTITY-STATE MIB

For each entity in the ENTITY-MIB [RFC6933], the ENTITY-STATE MIB [RFC4268] specifies the operational states (entStateOper: unknown, enabled, disabled, testing), the alarm (entStateAlarm: unknown, underRepair, critical, major, minor, warning, indeterminate) and the possible values of standby states

(entStateStandby: unknown, hotStandby, coldStandby, providingService).

From a power monitoring point of view, in contrast to the entity operational states of entities, Power States are required, as proposed in the Power and Energy Monitoring MIB module. Those Power States can be mapped to the different operational states in the ENTITY-STATE MIB, if a formal mapping is required. For example, the entStateStandby "unknown", "hotStandby", "coldStandby", states could map to the Power State "unknown", "ready", "standby", respectively, while the entStateStandby "providingService" could map to any "low" to "high" Power State.

7.3. Link with the POWER-OVER-ETHERNET MIB

Power-over-Ethernet MIB [RFC3621] provides an energy monitoring and configuration framework for power over Ethernet devices. RFC 3621 defines a port group entity on a switch for power monitoring and management policy and does not use the entPhysicalIndex index. Indeed, pethMainPseConsumptionPower is indexed by the pethMainPseGroupIndex, which has no mapping with the entPhysicalIndex.

If the Power-over-Ethernet MIB [RFC3621] is supported, the Energy Object eoethPortIndex and eoethPortGrpIndex contain the pethPsePortIndex and pethPsePortGroupIndex, respectively. However, one cannot assume that the Power-over-Ethernet MIB is implemented for most or all Energy Objects. In such cases, the eoethPortIndex and eoethPortGrpIndex values contain the zero value, via the new PethPsePortIndexOrZero and textual PethPsePortGroupIndexOrZero conventions.

In either case, the entPhysicalIndex MIB object is used as the unique Energy Object index.

Note that, even though the Power-over-Ethernet MIB [RFC3621] was created after the ENTITY-SENSOR MIB [RFC3433], it does not reuse the precision notion from the ENTITY-SENSOR MIB, i.e., the entPhySensorPrecision MIB object.

7.4. Link with the UPS MIB

To protect against unexpected power disruption, data centers and buildings make use of Uninterruptible Power Supplies (UPS). To protect critical assets, a UPS can be restricted to a particular subset or domain of the network. UPS usage typically lasts only for a finite period of time, until normal power supply is restored. Planning is required to decide on the capacity of the

UPS based on output power and duration of probable power outage. To properly provision UPS power in a data center or building, it is important to first understand the total demand required to support all the entities in the site. This demand can be assessed and monitored via the Power and Energy Monitoring MIB.

UPS MIB [RFC1628] provides information on the state of the UPS network. Implementation of the UPS MIB is useful at the aggregate level of a data center or a building. The MIB module contains several groups of variables:

- upsIdent: Identifies the UPS entity (name, model, etc.).
- upsBattery group: Indicates the battery state (upsbatteryStatus, upsEstimatedMinutesRemaining, etc.)
- upsInput group: Characterizes the input load to the UPS (number of input lines, voltage, current, etc.).
- upsOutput: Characterizes the output from the UPS (number of output lines, voltage, current, etc.)
- upsAlarms: Indicates the various alarm events.

The measurement of power in the UPS MIB is in volts, amperes and watts. The units of power measurement are RMS volts and RMS Amperes. They are not based on the EntitySensorDataScale and EntitySensorDataPrecision of ENTITY-SENSOR-MIB.

Both the Power and Energy Monitoring MIB and the UPS MIB may be implemented on the same UPS SNMP agent, without conflict. In this case, the UPS device itself is the Energy Object and any of the UPS meters or submeters are the Energy Objects with a possible relationship as defined in [EMAN-FMWK].

7.5. Link with the LLDP and LLDP-MED MIBs

The LLDP Protocol is a Data Link Layer protocol used by network devices to advertise their identities, capabilities, and interconnections on a LAN network.

The Media Endpoint Discovery is an enhancement of LLDP, known as LLDP-MED. The LLDP-MED enhancements specifically address voice applications. LLDP-MED covers 6 basic areas: capability discovery, LAN speed and duplex discovery, network policy discovery, location identification discovery, inventory discovery, and power discovery.

Of particular interest to the current MIB module is the power discovery, which allows the endpoint device (such as a PoE

phone) to convey power requirements to the switch. In power discovery, LLDP-MED has four Type Length Values (TLVs): power type, power source, power priority and power value. Respectively, those TLVs provide information related to the type of power (power sourcing entity versus powered device), how the device is powered (from the line, from a backup source, from external power source, etc.), the power priority (how important is it that this device has power?), and how much power the device needs.

The power priority specified in the LLDP-MED MIB [LLDP-MED-MIB] actually comes from the Power-over-Ethernet MIB [RFC3621]. If the Power-over-Ethernet MIB [RFC3621] is supported, the exact value from the pethPsePortPowerPriority [RFC3621] is copied over into the lldpXMedRemXPoEPDPowerPriority [LLDP-MED-MIB]; otherwise the value in lldpXMedRemXPoEPDPowerPriority is "unknown". From the Power and Energy Monitoring MIB, it is possible to identify the pethPsePortPowerPriority [RFC3621], via the eoethPortIndex and eoethPortGrpIndex.

The lldpXMedLocXPoEPDPowerSource [LLDP-MED-MIB] is similar to eoPowerMeasurementLocal in indicating if the power for an attached device is local or from a remote device. If the LLDP-MED MIB is supported, the following mapping can be applied to the eoPowerMeasurementLocal: lldpXMedLocXPoEPDPowerSource fromPSE(2) and local(3) can be mapped to false and true, respectively.

8. Structure of the MIB

The primary MIB object in this MIB module is the energyObjectMibObjects root. The eoPowerTable table of energyObjectMibObjects describes the power measurement attributes of an Energy Object entity. The identity of a device in terms of uniquely identification of the Energy Object and its relationship to other entities in the network are addressed in [EMAN-AWARE-MIB].

Logically, this MIB module is a sparse extension of the ENERGY-OBJECT-CONTEXT-MIB module [EMAN-AWARE-MIB]. Thus the following requirements which are applied to [EMAN-AWARE-MIB] are also applicable. As a requirement for this MIB module, [EMAN-AWARE-MIB] SHOULD be implemented and as Module Compliance of ENTITY-MIB V4 [RFC6933] with respect to entity4CRCompliance MUST be supported which requires 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID MUST be implemented.

eoMeterCapabilitiesTable is useful to enable applications to determine the capabilities supported by the local management agent. This table indicates the energy monitoring MIB groups that are supported by the local management system. By reading the value of this object, it is possible for applications to know which tables contain the information and are usable without walking through the table and querying every element which involves a trial-and-error process.

The power measurement of an Energy Object contains information describing its power usage (eoPower) and its current Power State (eoPowerOperState). In addition to power usage, additional information describing the units of measurement (eoPowerAccuracy, eoPowerUnitMultiplier), how power usage measurement was obtained (eoPowerMeasurementCaliber), the source of power measurement (eoPowerMeasurementLocal) and the type of power (eoPowerCurrentType) are described.

An Energy Object may contain an optional eoPowerAttributes table that describes the electrical characteristics associated with the current Power State and usage.

An Energy Object may contain an optional eoEnergyTable to describe energy measurement information over time.

An Energy Object may also contain optional battery information associated with this entity.

9. MIB Definitions

```
-- *****  
--  
--  
-- This MIB is used to monitor power usage of network  
-- devices  
--  
-- *****
```

```
ENERGY-OBJECT-MIB DEFINITIONS ::= BEGIN
```

```
IMPORTS  
    MODULE-IDENTITY,  
    OBJECT-TYPE,  
    NOTIFICATION-TYPE,  
    mib-2,  
    Integer32, Counter32, TimeTicks  
    FROM SNMPv2-SMI
```

TEXTUAL-CONVENTION, RowStatus, TimeInterval,
TimeStamp, TruthValue
FROM SNMPv2-TC
MODULE-COMPLIANCE, NOTIFICATION-GROUP, OBJECT-GROUP
FROM SNMPv2-CONF
OwnerString
FROM RMON-MIB
entPhysicalIndex
FROM ENTITY-MIB
IANAPowerStateSet
FROM IANA-POWERSTATE-SET-MIB;

energyObjectMib MODULE-IDENTITY
LAST-UPDATED "201402140000Z" -- 14 Feb 2014

ORGANIZATION "IETF EMAN Working Group"
CONTACT-INFO
"WG charter:
<http://datatracker.ietf.org/wg/eman/charter/>

Mailing Lists:
General Discussion: eman@ietf.org

To Subscribe:
<https://www.ietf.org/mailman/listinfo/eman>

Archive:
<http://www.ietf.org/mail-archive/web/eman>

Editors:
Mouli Chandramouli
Cisco Systems, Inc.
Sarjapur Outer Ring Road
Bangalore 560103
IN
Phone: +91 80 4429 2409
Email: moulchan@cisco.com

Brad Schoening
44 Rivers Edge Drive
Little Silver, NJ 07739
US
Email: brad.schoening@verizon.net

Juergen Quittek
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36

Heidelberg 69115
DE
Phone: +49 6221 4342-115
Email: quittek@neclab.eu

Thomas Dietz
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36
69115 Heidelberg
DE
Phone: +49 6221 4342-128
Email: Thomas.Dietz@nw.neclab.eu

Benoit Claise
Cisco Systems, Inc.
De Kleetlaan 6a b1
Degem 1831
Belgium
Phone: +32 2 704 5622
Email: bclaise@cisco.com"

DESCRIPTION

"This MIB is used to monitor power and energy in devices.

The tables eoMeterCapabilitiesTable and eoPowerTable are a sparse extension of the eoTable from the ENERGY-OBJECT-CONTEXT-MIB. As a requirement [EMAN-AWARE-MIB] SHOULD be implemented.

Module Compliance of ENTITY-MIB v4 with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

REVISION

"201402140000Z" -- 14 Feb 2014

DESCRIPTION

"Initial version, published as RFC XXXX."

::= { mib-2 xxx }

energyObjectMibNotifs OBJECT IDENTIFIER
::= { energyObjectMib 0 }

energyObjectMibObjects OBJECT IDENTIFIER

```
::= { energyObjectMib 1 }
```

```
energyObjectMibConform OBJECT IDENTIFIER
```

```
::= { energyObjectMib 2 }
```

```
-- Textual Conventions
```

```
IANAPowerStateSet ::= TEXTUAL-CONVENTION
```

```
STATUS current
```

```
DESCRIPTION
```

"IANAPowerState is a textual convention that describes Power State Sets and Power State Set Values an Energy Object supports. IANA has created a registry of Power State supported by an Energy Object and IANA shall administer the list of Power State Sets and Power States.

The textual convention assumes that Power States in a power state set are limited to 255 distinct values. For a Power State Set S, the named number with the value S * 256 is allocated to indicate the Power State set. For a Power State X in the Power State S, the named number with the value S * 256 + X + 1 is allocated to represent the Power State."

```
REFERENCE
```

```
"http://www.iana.org/assignments/eman
```

```
RFC EDITOR NOTE: please change the previous URL if this is not the correct one after IANA assigned it."
```

```
SYNTAX
```

```
INTEGER {
```

```
other(0), -- indicates other set  
unknown(255), -- unknown
```

```
ieee1621(256), -- indicates IEEE1621 set  
ieee1621On(257),  
ieee1621Off(258),  
ieee1621Sleep(259),
```

```
dmtf(512), -- indicates DMTF set  
dmtfOn(513),  
dmtfSleepLight(514),  
dmtfSleepDeep(515),  
dmtfOffHard(516),  
dmtfOffSoft(517),  
dmtfHibernate(518),  
dmtfPowerOffSoft(519),
```

```
    dmtfPowerOffHard(520),
    dmtfMasterBusReset(521),
    dmtfDiagnosticInterrupt(522),
    dmtfOffSoftGraceful(523),
    dmtfOffHardGraceful(524),
    dmtfMasterBusResetGraceful(525),
    dmtfPowerCycleOffSoftGraceful(526),
    dmtfPowerCycleHardGraceful(527),

    eman(1024),          -- indicates EMAN set
    emanmechoff(1025),
    emansoftoff(1026),
    emanhibernate(1027),
    emansleep(1028),
    emanstandby(1029),
    emanready(1030),
    emanlowMinus(1031),
    emanlow(1032),
    emanmediumMinus(1033),
    emanmedium(1034),
    emanhighMinus(1035),
    emanhigh(1036)
}
```

UnitMultiplier ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION

"The Unit Multiplier is an integer value that represents the IEEE 61850 Annex A units multiplier associated with the integer units used to measure the power or energy.

For example, when used with eoPowerUnitMultiplier, -3 represents 10⁻³ or milliwatts."

REFERENCE

"The International System of Units (SI), National Institute of Standards and Technology, Spec. Publ. 330, August 1991."

SYNTAX INTEGER {

```
    yocto(-24),  -- 10^-24
    zepto(-21),  -- 10^-21
    atto(-18),   -- 10^-18
    femto(-15),  -- 10^-15
    pico(-12),   -- 10^-12
    nano(-9),    -- 10^-9
    micro(-6),   -- 10^-6
    milli(-3),   -- 10^-3
    units(0),    -- 10^0
    kilo(3),     -- 10^3
    mega(6),     -- 10^6
    giga(9),     -- 10^9
```

```

        tera(12),      -- 10^12
        peta(15),     -- 10^15
        exa(18),      -- 10^18
        zetta(21),    -- 10^21
        yotta(24)     -- 10^24
    }

```

-- Objects

eoMeterCapabilitiesTable OBJECT-TYPE

```

    SYNTAX          SEQUENCE OF EoMeterCapabilitiesEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION

```

"This table is useful for helping applications determine the monitoring capabilities supported by the local management agents. It is possible for applications to know which tables are usable without going through a trial-and-error process."

```

    ::= { energyObjectMibObjects 1 }

```

eoMeterCapabilitiesEntry OBJECT-TYPE

```

    SYNTAX          EoMeterCapabilitiesEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION

```

"An entry describes the metering capability of an Energy Object."

```

    INDEX          { entPhysicalIndex }
    ::= { eoMeterCapabilitiesTable 1 }

```

```

EoMeterCapabilitiesEntry ::= SEQUENCE {
    eoMeterCapability          BITS
}

```

eoMeterCapability OBJECT-TYPE

```

    SYNTAX  BITS {
        none(0),
        powermetering(1),      -- power measurement
        energymetering(2),     -- energy measurement
        powerattributes(3)     -- power attributes
    }

```

```

    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION

```

"An indication of the energy monitoring capabilities supported by this agent. This object use a BITS syntax and indicates the

MIB groups supported by the probe. By reading the value of this object, it is possible to determine the MIB tables supported. "
 ::= { eoMeterCapabilitiesEntry 1 }

eoPowerTable OBJECT-TYPE
SYNTAX SEQUENCE OF EoPowerEntry
MAX-ACCESS not-accessible
STATUS current
DESCRIPTION
"This table lists Energy Objects."
 ::= { energyObjectMibObjects 2 }

eoPowerEntry OBJECT-TYPE
SYNTAX EoPowerEntry
MAX-ACCESS not-accessible
STATUS current
DESCRIPTION
"An entry describes the power usage of an Energy Object."

INDEX { entPhysicalIndex }
 ::= { eoPowerTable 1 }

EoPowerEntry ::= SEQUENCE {

 eoPower Integer32,
 eoPowerNameplate Integer32,
 eoPowerUnitMultiplier UnitMultiplier,
 eoPowerAccuracy Integer32,
 eoPowerMeasurementCaliber INTEGER,
 eoPowerCurrentType INTEGER,
 eoPowerMeasurementLocal TruthValue,
 eoPowerAdminState IANAPowerStateSet,
 eoPowerOperState IANAPowerStateSet,
 eoPowerStateEnterReason OwnerString
}

eoPower OBJECT-TYPE
SYNTAX Integer32
UNITS "watts"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"This object indicates the power measured for the Energy Object. For alternating current, this value is obtained as an average over fixed number of AC cycles. This value

is specified in SI units of watts with the magnitude of watts (milliwatts, kilowatts, etc.) indicated separately in eoPowerUnitMultiplier. The accuracy of the measurement is specified in eoPowerAccuracy. The direction of power flow is indicated by the sign on eoPower. If the Energy Object is consuming power, the eoPower value will be positive. If the Energy Object is producing power, the eoPower value will be negative.

The eoPower MUST be less than or equal to the maximum power that can be consumed at the power state specified by eoPowerState.

The eoPowerMeasurementCaliber object specifies how the usage value reported by eoPower was obtained. The eoPower value must report 0 if the eoPowerMeasurementCaliber is 'unavailable'. For devices that can not measure or report power, this option can be used."
 ::= { eoPowerEntry 1 }

eoPowerNameplate OBJECT-TYPE
SYNTAX Integer32
UNITS "watts"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"This object indicates the rated maximum consumption for the fully populated Energy Object. The nameplate power requirements are the maximum power numbers and, in almost all cases, are well above the expected operational consumption. Nameplate power is widely used for power provisioning. This value is specified in either units of watts or voltage and current. The units are therefore SI watts or equivalent Volt-Amperes with the magnitude (milliwatts, kilowatts, etc.) indicated separately in eoPowerUnitMultiplier."
 ::= { eoPowerEntry 2 }

eoPowerUnitMultiplier OBJECT-TYPE
SYNTAX UnitMultiplier
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"The magnitude of watts for the usage value in eoPower and eoPowerNameplate."
 ::= { eoPowerEntry 3 }

eoPowerAccuracy OBJECT-TYPE
SYNTAX Integer32 (0..10000)

UNITS "hundredths of percent"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"This object indicates a percentage value, in 100ths of a percent, representing the assumed accuracy of the usage reported by eoPower. For example: The value 1010 means the reported usage is accurate to +/- 10.1 percent. This value is zero if the accuracy is unknown or not applicable based upon the measurement method.

ANSI and IEC define the following accuracy classes for power measurement:
IEC 62053-22 60044-1 class 0.1, 0.2, 0.5, 1 3.
ANSI C12.20 class 0.2, 0.5"
 ::= { eoPowerEntry 4 }

eoPowerMeasurementCaliber OBJECT-TYPE
SYNTAX INTEGER {
unavailable(1) ,
unknown(2) ,
actual(3) ,
estimated(4) ,
static(5) }
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"This object specifies how the usage value reported by eoPower was obtained:

- unavailable(1): Indicates that the usage is not available. In such a case, the eoPower value must be 0 for devices that can not measure or report power this option can be used.

- unknown(2): Indicates that the way the usage was determined is unknown. In some cases, entities report aggregate power on behalf of another device. In such cases it is not known whether the usage reported is actual, estimated or static.

- actual(3): Indicates that the reported usage was measured by the entity through some hardware or direct physical means. The usage data reported is not estimated or static but is the measured consumption rate.

- estimated(4): Indicates that the usage was not determined by physical measurement. The value is a derivation based upon the device type, state, and/or

current utilization using some algorithm or heuristic. It is presumed that the entity's state and current configuration were used to compute the value.

- static(5): Indicates that the usage was not determined by physical measurement, algorithm or derivation. The usage was reported based upon external tables, specifications, and/or model information. For example, a PC Model X draws 200W, while a PC Model Y draws 210W."

::= { eoPowerEntry 5 }

eoPowerCurrentType OBJECT-TYPE

SYNTAX INTEGER {
ac(1),
dc(2),
unknown(3)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object indicates whether the eoPower for the Energy Object reports alternating current 'ac', direct current 'dc', or that the current type is unknown."

::= { eoPowerEntry 6 }

eoPowerMeasurementLocal OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object indicates the source of power measurement and can be useful when modeling the power usage of attached devices. The power measurement can be performed by the entity itself or the power measurement of the entity can be reported by another trusted entity using a protocol extension. A value of true indicates the measurement is performed by the entity, whereas false indicates that the measurement was performed by another entity."

::= { eoPowerEntry 7 }

eoPowerAdminState OBJECT-TYPE

SYNTAX IANAPowerStateSet

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"This object specifies the desired Power State and the Power State Set for the Energy Object. Note that other(0) is not a Power State Set and unknown(255) is

not a Power State as such, but simply an indication that the Power State of the Energy Object is unknown. Possible values of eoPowerAdminState within the Power State Set are registered at IANA. A current list of assignments can be found at <<http://www.iana.org/assignments/eman>> RFC-EDITOR: please check the location after IANA"

```
::= { eoPowerEntry 8 }
```

eoPowerOperState OBJECT-TYPE

SYNTAX IANAPowerStateSet
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"This object specifies the current operational Power State and the Power State Set for the Energy Object. other(0) is not a Power State Set and unknown(255) is not a Power State as such, but simply an indication that the Power State of the Energy Object is unknown.

Possible values of eoPowerOperState within the Power State Set are registered at IANA. A current list of assignments can be found at <<http://www.iana.org/assignments/eman>> RFC-EDITOR: please check the location after IANA"

```
::= { eoPowerEntry 9 }
```

eoPowerStateEnterReason OBJECT-TYPE

SYNTAX OwnerString
MAX-ACCESS read-write
STATUS current

DESCRIPTION

"This string object describes the reason for the eoPowerAdminState transition. Alternatively, this string may contain with the entity that configured this Energy Object to this Power State."

DEFVAL { "" }

```
::= { eoPowerEntry 10 }
```

eoPowerStateTable OBJECT-TYPE

SYNTAX SEQUENCE OF EoPowerStateEntry
MAX-ACCESS not-accessible
STATUS current

DESCRIPTION

"This table enumerates the maximum power usage, in watts, for every single supported Power State of each Energy Object.

This table has cross-reference with the eoPowerTable, containing rows describing each Power State for the corresponding Energy Object. For every Energy Object in the eoPowerTable, there is a corresponding entry in this table."

```
::= { energyObjectMibObjects 3 }
```

eoPowerStateEntry OBJECT-TYPE

SYNTAX EoPowerStateEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A eoPowerStateEntry extends a corresponding eoPowerEntry. This entry displays max usage values at every single possible Power State supported by the Energy Object.

For example, given the values of a Energy Object corresponding to a maximum usage of 0 W at the state emanmechoff, 8 W at state 6 (ready), 11 W at state emanmediumMinus, and 11 W at state emanhigh:

State	MaxUsage	Units
emanmechoff	0	W
emansoftoff	0	W
emanhibernate	0	W
emansleep	0	W
emanstandby	0	W
emanready	8	W
emanlowMinus	8	W
emanlow	11	W
emanmediumMinus	11	W
emanmedium	11	W
emanhighMinus	11	W
emanhigh	11	W

Furthermore, this table also includes the total time in each Power State, along with the number of times a particular Power State was entered."

```
INDEX { entPhysicalIndex,
        eoPowerStateIndex
      }
```

```
::= { eoPowerStateTable 1 }
```

EoPowerStateEntry ::= SEQUENCE {

eoPowerStateIndex	IANAPowerStateSet,
eoPowerStateMaxPower	INTEGER,
eoPowerStatePowerUnitMultiplier	UnitMultiplier,
eoPowerStateTotalTime	TimeTicks,
eoPowerStateEnterCount	Counter32

```
}

eoPowerStateIndex OBJECT-TYPE
    SYNTAX          IANAPowerStateSet
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION
        "
        This object specifies the index of the Power State of
        the Energy Object within a Power State Set. The
        semantics of the specific Power State can be obtained
        from the Power State Set definition."
    ::= { eoPowerStateEntry 1 }

eoPowerStateMaxPower OBJECT-TYPE
    SYNTAX          Integer32
    UNITS           "watts"
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION
        "This object indicates the maximum power for the Energy
        Object at the particular Power State. This value is
        specified in SI units of watts with the magnitude of the
        units (milliwatts, kilowatts, etc.) indicated separately
        in eoPowerStatePowerUnitMultiplier. If the maximum power
        is not known for a certain Power State, then the value is
        encoded as 0xFFFFFFFF.

        For Power States not enumerated, the value of
        eoPowerStateMaxPower might be interpolated by using the
        next highest supported Power State."
    ::= { eoPowerStateEntry 2 }

eoPowerStatePowerUnitMultiplier OBJECT-TYPE
    SYNTAX          UnitMultiplier
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION
        "The magnitude of watts for the usage value in
        eoPowerStateMaxPower."
    ::= { eoPowerStateEntry 3 }

eoPowerStateTotalTime OBJECT-TYPE
    SYNTAX          TimeTicks
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION
        "This object indicates the total time in hundredths
```

of second that the Energy Object has been in this power state since the last reset, as specified in the sysUpTime."

::= { eoPowerStateEntry 4 }

eoPowerStateEnterCount OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object indicates how often the Energy Object has entered this power state, since the last reset of the device as specified in the sysUpTime."

::= { eoPowerStateEntry 5 }

eoEnergyParametersTable OBJECT-TYPE

SYNTAX SEQUENCE OF EoEnergyParametersEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"This table is used to configure the parameters for energy measurement collection in the table eoEnergyTable. This table allows the configuration of different measurement settings on the same Energy Object. Implementation of this table only makes sense for Energy Objects that an eoPowerMeasurementCaliber of actual."

::= { energyObjectMibObjects 4 }

eoEnergyParametersEntry OBJECT-TYPE

SYNTAX EoEnergyParametersEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry controls an energy measurement in eoEnergyTable."

INDEX { entPhysicalIndex, eoEnergyParametersIndex }

::= { eoEnergyParametersTable 1 }

EoEnergyParametersEntry ::= SEQUENCE {

eoEnergyParametersIndex	Integer32,
eoEnergyParametersIntervalLength	TimeInterval,
eoEnergyParametersIntervalNumber	Integer32,
eoEnergyParametersIntervalMode	INTEGER,
eoEnergyParametersIntervalWindow	TimeInterval,
eoEnergyParametersSampleRate	Integer32,
eoEnergyParametersStatus	RowStatus

}

```
eoEnergyParametersIndex OBJECT-TYPE
    SYNTAX          Integer32 (0..2147483647)
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION
        "This object specifies the index of the Energy
        Parameters setting for collection of energy measurements
        for an Energy Object. An Energy Object can have multiple
        eoEnergyParametersIndex, depending on the capabilities
        of the Energy Object"
    ::= { eoEnergyParametersEntry 2 }
```

```
eoEnergyParametersIntervalLength OBJECT-TYPE
    SYNTAX          TimeInterval
    MAX-ACCESS      read-create
    STATUS          current
    DESCRIPTION
        "This object indicates the length of time in hundredths
        of seconds over which to compute the average
        eoEnergyConsumed measurement in the eoEnergyTable table.
        The computation is based on the Energy Object's internal
        sampling rate of power consumed or produced by the Energy
        Object. The sampling rate is the rate at which the Energy
        Object can read the power usage and may differ based on
        device capabilities. The average energy consumption is
        then computed over the length of the interval. The
        default value of 15 minutes is a common interval used in
        industry."
    DEFVAL { 90000 }
    ::= { eoEnergyParametersEntry 3 }
```

```
eoEnergyParametersIntervalNumber OBJECT-TYPE
    SYNTAX          Integer32
    MAX-ACCESS      read-create
    STATUS          current
    DESCRIPTION
        "The number of intervals maintained in the eoEnergyTable.
        Each interval is characterized by a specific
        eoEnergyCollectionStartTime, used as an index to the
        table eoEnergyTable. Whenever the maximum number of
        entries is reached, the measurement over the new interval
        replaces the oldest measurement. There is one exception
        to this rule: when the eoEnergyMaxConsumed and/or
        eoEnergyMaxProduced are in (one of) the two oldest
        measurement(s), they are left untouched and the next
        oldest measurement is replaced."
    DEFVAL { 10 }
    ::= { eoEnergyParametersEntry 4 }
```

eoEnergyParametersIntervalMode OBJECT-TYPE

SYNTAX INTEGER {
 period(1),
 sliding(2),
 total(3)
}

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"A control object to define the mode of interval calculation for the computation of the average eoEnergyConsumed or eoEnergyProvided measurement in the eoEnergyTable table.

A mode of period(1) specifies non-overlapping periodic measurements.

A mode of sliding(2) specifies overlapping sliding windows where the interval between the start of one interval and the next is defined in eoEnergyParametersIntervalWindow.

A mode of total(3) specifies non-periodic measurement. In this mode only one interval is used as this is a continuous measurement since the last reset. The value of eoEnergyParametersIntervalNumber should be (1) one and eoEnergyParametersIntervalLength is ignored. "

::= { eoEnergyParametersEntry 5 }

eoEnergyParametersIntervalWindow OBJECT-TYPE

SYNTAX TimeInterval

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The length of the duration window between the starting time of one sliding window and the next starting time in hundredths of seconds, in order to compute the average of eoEnergyConsumed, eoEnergyProvided measurements in the eoEnergyTable table. This is valid only when the eoEnergyParametersIntervalMode is sliding(2). The eoEnergyParametersIntervalWindow value should be a multiple of eoEnergyParametersSampleRate."

::= { eoEnergyParametersEntry 6 }

eoEnergyParametersSampleRate OBJECT-TYPE

SYNTAX Integer32

UNITS "Milliseconds"

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The sampling rate, in milliseconds, at which the Energy Object should poll power usage in order to compute the average eoEnergyConsumed, eoEnergyProvided measurements in the table eoEnergyTable. The Energy Object should initially set this sampling rate to a reasonable value, i.e., a compromise between intervals that will provide good accuracy by not being too long, but not so short that they affect the Energy Object performance by requesting continuous polling. If the sampling rate is unknown, the value 0 is reported. The sampling rate should be selected so that eoEnergyParametersIntervalWindow is a multiple of eoEnergyParametersSampleRate. The default value is one second."

```
DEFVAL { 1000 }  
 ::= { eoEnergyParametersEntry 7 }
```

eoEnergyParametersStatus OBJECT-TYPE

```
SYNTAX          RowStatus  
MAX-ACCESS      read-create  
STATUS          current
```

DESCRIPTION

"The status of this row. The eoEnergyParametersStatus is used to start or stop energy usage logging. An entry status may not be active(1) unless all objects in the entry have an appropriate value. If this object is not equal to active, all associated usage-data logged into the eoEnergyTable will be deleted. The data can be destroyed by setting up the eoEnergyParametersStatus to destroy."

```
 ::= { eoEnergyParametersEntry 8 }
```

eoEnergyTable OBJECT-TYPE

```
SYNTAX          SEQUENCE OF EoEnergyEntry  
MAX-ACCESS      not-accessible  
STATUS          current
```

DESCRIPTION

"This table lists Energy Object energy measurements. Entries in this table are only created if the corresponding value of object eoPowerMeasurementCaliber is active(3), i.e., if the power is actually metered."

```
 ::= { energyObjectMibObjects 5 }
```

eoEnergyEntry OBJECT-TYPE

```
SYNTAX          EoEnergyEntry  
MAX-ACCESS      not-accessible  
STATUS          current
```

DESCRIPTION

```

        "An entry describing energy measurements."
    INDEX { eoEnergyParametersIndex,
eoEnergyCollectionStartTime }
    ::= { eoEnergyTable 1 }

EoEnergyEntry ::= SEQUENCE {
    eoEnergyCollectionStartTime      TimeTicks,
    eoEnergyConsumed                 Integer32,
    eoEnergyProvided                 Integer32,
    eoEnergyStored                   Integer32,
    eoEnergyUnitMultiplier           UnitMultiplier,
    eoEnergyAccuracy                 Integer32,
    eoEnergyMaxConsumed              Integer32,
    eoEnergyMaxProduced              Integer32,
    eoEnergyDiscontinuityTime        TimeStamp
}

eoEnergyCollectionStartTime OBJECT-TYPE
    SYNTAX      TimeTicks
    UNITS       "hundredths of seconds"
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "The time (in hundredths of a second) since the
        network management portion of the system was last
        re-initialized, as specified in the sysUpTime [RFC3418].
        This object specifies the start time of the energy
        measurement sample. "
    ::= { eoEnergyEntry 1 }

eoEnergyConsumed OBJECT-TYPE
    SYNTAX      Integer32
    UNITS       "Watt-hours"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "This object indicates the energy consumed in units of watt-
        hours for the Energy Object over the defined interval.
        This value is specified in the common billing units of watt-
        hours with the magnitude of watt-hours (kW-Hr, MW-Hr, etc.)
        indicated separately in eoEnergyUnitMultiplier."
    ::= { eoEnergyEntry 2 }

eoEnergyProvided OBJECT-TYPE
    SYNTAX      Integer32
    UNITS       "Watt-hours"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION

```

"This object indicates the energy produced in units of watt-hours for the Energy Object over the defined interval. This value is specified in the common billing units of watt-hours with the magnitude of watt-hours (kW-Hr, MW-Hr, etc.) indicated separately in eoEnergyUnitMultiplier."
 ::= { eoEnergyEntry 3 }

eoEnergyStored OBJECT-TYPE

SYNTAX Integer32
UNITS "Watt-hours"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"This object indicates the difference of the energy consumed and energy produced for an Energy Object in units of watt-hours for the Energy Object over the defined interval. This value is specified in the common billing units of watt-hours with the magnitude of watt-hours (kW-Hr, MW-Hr, etc.) indicated separately in eoEnergyUnitMultiplier."
 ::= { eoEnergyEntry 4 }

eoEnergyUnitMultiplier OBJECT-TYPE

SYNTAX UnitMultiplier
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"This object is the magnitude of watt-hours for the energy field in eoEnergyConsumed, eoEnergyProvided, eoEnergyStored, eoEnergyMaxConsumed, and eoEnergyMaxProduced."
 ::= { eoEnergyEntry 5 }

eoEnergyAccuracy OBJECT-TYPE

SYNTAX Integer32 (0..10000)
UNITS "hundredths of percent"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"This object indicates a percentage accuracy, in 100ths of a percent, of Energy usage reporting. eoEnergyAccuracy is applicable to all Energy measurements in the eoEnergyTable.

For example: 1010 means the reported usage is accurate to +/- 10.1 percent.

This value is zero if the accuracy is unknown."

::= { eoEnergyEntry 6 }

```
eoEnergyMaxConsumed OBJECT-TYPE
    SYNTAX      Integer32
    UNITS       "Watt-hours"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "This object is the maximum energy observed in
        eoEnergyConsumed since the monitoring started or was
        reinitialized. This value is specified in the common
        billing units of watt-hours with the magnitude of watt-
        hours (kW-Hr, MW-Hr, etc.) indicated separately in
        eoEnergyUnitMultiplier."
    ::= { eoEnergyEntry 7 }
```

```
eoEnergyMaxProduced OBJECT-TYPE
    SYNTAX      Integer32
    UNITS       "Watt-hours"
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "This object is the maximum energy ever observed in
        eoEnergyEnergyProduced since the monitoring started. This
        value is specified in the units of watt-hours with the
        magnitude of watt-hours (kW-Hr, MW-Hr, etc.) indicated
        separately in eoEnergyEnergyUnitMultiplier."
    ::= { eoEnergyEntry 8 }
```

```
eoEnergyDiscontinuityTime OBJECT-TYPE
    SYNTAX      TimeStamp
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION

        "The value of sysUpTime [RFC3418] on the most recent
        occasion at which any one or more of this entity's energy
        counters in this table suffered a discontinuity:
        eoEnergyConsumed, eoEnergyProvided or eoEnergyStored. If
        no such discontinuities have occurred since the last re-
        initialization of the local management subsystem, then
        this object contains a zero value."
    ::= { eoEnergyEntry 9 }
```

-- Notifications

```
eoPowerEnableStatusNotification OBJECT-TYPE
    SYNTAX      TruthValue
```

```
MAX-ACCESS      read-write
STATUS          current
DESCRIPTION
  "This object controls whether the system produces
  notifications for eoPowerStateChange. A false value will
  prevent these notifications from being generated."
DEFVAL         { false }
 ::= { energyObjectMibNotifs 1 }
```

```
eoPowerStateChange NOTIFICATION-TYPE
  OBJECTS      {eoPowerAdminState, eoPowerOperState,
eoPowerStateEnterReason}
  STATUS      current
  DESCRIPTION
    "The SNMP entity generates the eoPowerStateChange when
    the values of eoPowerAdminState or eoPowerOperState,
    in the context of the Power State Set, have changed for
    the Energy Object represented by the entPhysicalIndex."
 ::= { energyObjectMibNotifs 2 }
```

-- Conformance

```
energyObjectMibCompliances OBJECT IDENTIFIER
 ::= { energyObjectMibConform 1 }
```

```
energyObjectMibGroups OBJECT IDENTIFIER
 ::= { energyObjectMibConform 2 }
```

```
energyObjectMibFullCompliance MODULE-COMPLIANCE
  STATUS      current
  DESCRIPTION
    "When this MIB is implemented with support for
    read-create, then such an implementation can
    claim full compliance. Such devices can then
    be both monitored and configured with this MIB.

    Module Compliance of [RFC6933]
    with respect to entity4CRCompliance MUST
    be supported which requires implementation
    of 4 MIB objects: entPhysicalIndex, entPhysicalClass,
    entPhysicalName and entPhysicalUUID."
```

```
MODULE      -- this module
MANDATORY-GROUPS {
  energyObjectMibTableGroup,
  energyObjectMibStateTableGroup,
  eoPowerEnableStatusNotificationGroup,
  energyObjectMibNotifGroup
```

}

GROUP energyObjectMibEnergyTableGroup

DESCRIPTION "A compliant implementation does not have to implement.

Module Compliance of [RFC6933] with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

GROUP energyObjectMibEnergyParametersTableGroup

DESCRIPTION "A compliant implementation does not have to implement.

Module Compliance of {RFC6933} with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

GROUP energyObjectMibMeterCapabilitiesTableGroup

DESCRIPTION "A compliant implementation does not have to implement.

Module Compliance of [RFC6933] with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

::= { energyObjectMibCompliances 1 }

energyObjectMibReadOnlyCompliance MODULE-COMPLIANCE

STATUS current

DESCRIPTION

"When this MIB is implemented without support for read-create (i.e., in read-only mode), then such an implementation can claim read-only compliance. Such a device can then be monitored but cannot be configured with this MIB.

Module Compliance of [RFC6933]

with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

```

MODULE          -- this module
MANDATORY-GROUPS {
    energyObjectMibTableGroup,
    energyObjectMibStateTableGroup,
    energyObjectMibNotifGroup
}

OBJECT          eoPowerOperState
MIN-ACCESS      read-only
DESCRIPTION
    "Write access is not required."
 ::= { energyObjectMibCompliances 2 }

-- Units of Conformance

energyObjectMibTableGroup OBJECT-GROUP
    OBJECTS      {
        eoPower,
        eoPowerNameplate,
        eoPowerUnitMultiplier,
        eoPowerAccuracy,
        eoPowerMeasurementCaliber,
        eoPowerCurrentType,
        eoPowerMeasurementLocal,
        eoPowerAdminState,
        eoPowerOperState,
        eoPowerStateEnterReason
    }
    STATUS        current
DESCRIPTION
    "This group contains the collection of all the objects
    related to the Energy Object."
 ::= { energyObjectMibGroups 1 }

energyObjectMibStateTableGroup OBJECT-GROUP
    OBJECTS      {
        eoPowerStateMaxPower,
        eoPowerStatePowerUnitMultiplier,
        eoPowerStateTotalTime,
        eoPowerStateEnterCount
    }
    STATUS        current
DESCRIPTION
    "This group contains the collection of all the
    objects related to the Power State."

```

```
::= { energyObjectMibGroups 2 }
```

```
energyObjectMibEnergyParametersTableGroup OBJECT-GROUP
OBJECTS          {
    eoEnergyParametersIntervalLength,
    eoEnergyParametersIntervalNumber,
    eoEnergyParametersIntervalMode,
    eoEnergyParametersIntervalWindow,
    eoEnergyParametersSampleRate,
    eoEnergyParametersStatus
}
STATUS           current
DESCRIPTION
    "This group contains the collection of all the objects
    related to the configuration of the Energy Table."
 ::= { energyObjectMibGroups 3 }
```

```
energyObjectMibEnergyTableGroup OBJECT-GROUP
OBJECTS          {
    -- Note that object
    -- eoEnergyCollectionStartTime is not
    -- included since it is not-accessible

    eoEnergyConsumed,
    eoEnergyProvided,
    eoEnergyStored,
    eoEnergyUnitMultiplier,
    eoEnergyAccuracy,
    eoEnergyMaxConsumed,
    eoEnergyMaxProduced,
    eoEnergyDiscontinuityTime
}
STATUS           current
DESCRIPTION
    "This group contains the collection of all the objects
    related to the Energy Table."
 ::= { energyObjectMibGroups 4 }
```

```
energyObjectMibMeterCapabilitiesTableGroup OBJECT-GROUP
OBJECTS          {
    eoMeterCapability
}
STATUS           current
DESCRIPTION
```

```
"This group contains the object indicating the
capability of the Energy Object"
 ::= { energyObjectMibGroups 5 }

eoPowerEnableStatusNotificationGroup OBJECT-GROUP
  OBJECTS      { eoPowerEnableStatusNotification }
  STATUS       current
  DESCRIPTION   "The collection of objects which are used
                to enable notification."
 ::= { energyObjectMibGroups 6 }

energyObjectMibNotifGroup NOTIFICATION-GROUP
  NOTIFICATIONS {
    eoPowerStateChange
  }
  STATUS       current
  DESCRIPTION   "This group contains the notifications for
                the power and energy monitoring MIB Module."
 ::= { energyObjectMibGroups 7 }
```

END

```
-- *****
--
-- This MIB module is used to monitor power attributes of
-- networked devices with measurements.
--
-- This MIB module is an extension of energyObjectMib module.
--
-- *****
```

POWER-ATTRIBUTES-MIB DEFINITIONS ::= BEGIN

```
IMPORTS
  MODULE-IDENTITY,
  OBJECT-TYPE,
  mib-2,
  Integer32
    FROM SNMPv2-SMI
  MODULE-COMPLIANCE,
  OBJECT-GROUP
    FROM SNMPv2-CONF
  UnitMultiplier
    FROM ENERGY-OBJECT-MIB
  entPhysicalIndex
    FROM ENTITY-MIB;
```

powerAttributesMIB MODULE-IDENTITY

LAST-UPDATED "201402140000Z" -- 14 Feb 2014

ORGANIZATION "IETF EMAN Working Group"

CONTACT-INFO

"WG charter:

<http://datatracker.ietf.org/wg/eman/charter/>

Mailing Lists:

General Discussion: eman@ietf.org

To Subscribe:

<https://www.ietf.org/mailman/listinfo/eman>

Archive:

<http://www.ietf.org/mail-archive/web/eman>

Editors:

Mouli Chandramouli
Cisco Systems, Inc.
Sarjapur Outer Ring Road
Bangalore 560103
IN
Phone: +91 80 4429 2409
Email: moulchan@cisco.com

Brad Schoening
44 Rivers Edge Drive
Little Silver, NJ 07739
US
Email: brad.schoening@verizon.net

Juergen Quittek
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36
Heidelberg 69115
DE
Phone: +49 6221 4342-115
Email: quittek@neclab.eu

Thomas Dietz
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36

69115 Heidelberg
DE
Phone: +49 6221 4342-128
Email: Thomas.Dietz@nw.neclab.eu

Benoit Claise
Cisco Systems, Inc.
De Kleetlaan 6a b1
Degem 1831
Belgium
Phone: +32 2 704 5622
Email: bclaise@cisco.com"

DESCRIPTION

"This MIB is used to report AC power attributes in devices. The table is a sparse augmentation of the eoPowerTable table from the energyObjectMib module. Both three-phase and single-phase power configurations are supported.

As a requirement for this MIB module, [EMAN-AWARE-MIB] SHOULD be implemented.

Module Compliance of ENTITY-MIB v4 with respect to entity4CRCompliance MUST be supported which requires implementation of 4 MIB objects: entPhysicalIndex, entPhysicalClass, entPhysicalName and entPhysicalUUID."

REVISION

"201402140000Z" -- 14 Feb 2014

DESCRIPTION

"Initial version, published as RFC YYY."

::= { mib-2 yyy }

powerAttributesMIBConform OBJECT IDENTIFIER
 ::= { powerAttributesMIB 0 }

powerAttributesMIBObjects OBJECT IDENTIFIER
 ::= { powerAttributesMIB 1 }

-- Objects

eoACPwrAttributesTable OBJECT-TYPE

```

SYNTAX          SEQUENCE OF EoACPwrAttributesEntry
MAX-ACCESS      not-accessible
STATUS          current
DESCRIPTION
    "This table contains power attributes measurements for
    supported entPhysicalIndex entities. It is a sparse
    extension of the eoPowerTable."
 ::= { powerAttributesMIBObjects 1 }

```

```

eoACPwrAttributesEntry OBJECT-TYPE
SYNTAX          EoACPwrAttributesEntry
MAX-ACCESS      not-accessible
STATUS          current
DESCRIPTION
    "This is a sparse extension of the eoPowerTable with
    entries for power attributes measurements or
    configuration. Each measured value corresponds to an
    attribute in IEC 61850-7-4 for non-phase measurements
    within the object MMUX."

```

```

INDEX {entPhysicalIndex }
 ::= { eoACPwrAttributesTable 1 }

```

```

EoACPwrAttributesEntry ::= SEQUENCE {
    eoACPwrAttributesConfiguration      INTEGER,
    eoACPwrAttributesAvgVoltage        Integer32,
    eoACPwrAttributesAvgCurrent        Integer32,
    eoACPwrAttributesFrequency         Integer32,
    eoACPwrAttributesPowerUnitMultiplier UnitMultiplier,
    eoACPwrAttributesPowerAccuracy     Integer32,
    eoACPwrAttributesTotalActivePower  Integer32,
    eoACPwrAttributesTotalReactivePower Integer32,
    eoACPwrAttributesTotalApparentPower Integer32,
    eoACPwrAttributesTotalPowerFactor  Integer32,
    eoACPwrAttributesThdCurrent        Integer32,
    eoACPwrAttributesThdVoltage        Integer32
}

```

```

eoACPwrAttributesConfiguration OBJECT-TYPE
SYNTAX INTEGER {
    sngl(1),
    del(2),
    wye(3)
}
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION
    "Configuration describes the physical configurations
    of the power supply lines:"

```

- * alternating current, single phase (SNGL)
- * alternating current, three phase delta (DEL)
- * alternating current, three phase Y (WYE)

Three-phase configurations can be either connected in a triangular delta (DEL) or star Y (WYE) system. WYE systems have a shared neutral voltage, while DEL systems do not. Each phase is offset 120 degrees to each other."

::= { eoACPwrAttributesEntry 1 }

eoACPwrAttributesAvgVoltage OBJECT-TYPE

SYNTAX Integer32

UNITS "0.1 Volt AC"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A measured value for average of the voltage measured over an integral number of AC cycles For a 3-phase system, this is the average voltage $(V1+V2+V3)/3$. IEC 61850-7-4 measured value attribute 'Vol'"

::= { eoACPwrAttributesEntry 2 }

eoACPwrAttributesAvgCurrent OBJECT-TYPE

SYNTAX Integer32

UNITS "amperes"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

" A measured value for average of the current measured over an integral number of AC cycles For a 3-phase system, this is the average current $(I1+I2+I3)/3$. IEC 61850-7-4 attribute 'Amp'"

::= { eoACPwrAttributesEntry 3 }

eoACPwrAttributesFrequency OBJECT-TYPE

SYNTAX Integer32 (4500..6500)

UNITS "0.01 hertz"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A measured value for the basic frequency of the AC circuit. IEC 61850-7-4 attribute 'Hz'."

::= { eoACPwrAttributesEntry 4 }

eoACPwrAttributesPowerUnitMultiplier OBJECT-TYPE

SYNTAX UnitMultiplier

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The magnitude of watts for the usage value in eoACPwrAttributesTotalActivePower, eoACPwrAttributesTotalReactivePower and eoACPwrAttributesTotalApparentPower measurements. For 3-phase power systems, this will also include eoACPwrAttributesWyeActivePower, eoACPwrAttributesWyeReactivePower and eoACPwrAttributesWyeApparentPower"
 ::= { eoACPwrAttributesEntry 5 }

eoACPwrAttributesPowerAccuracy OBJECT-TYPE

SYNTAX Integer32 (0..10000)
UNITS "hundredths of percent"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"This object indicates a percentage value, in 100ths of a percent, representing the presumed accuracy of active, reactive, and apparent power usage reporting. For example: 1010 means the reported usage is accurate to +/- 10.1 percent. This value is zero if the accuracy is unknown.

ANSI and IEC define the following accuracy classes for power measurement: IEC 62053-22 & 60044-1 class 0.1, 0.2, 0.5, 1 & 3.

ANSI C12.20 class 0.2 & 0.5"

::= { eoACPwrAttributesEntry 6 }

eoACPwrAttributesTotalActivePower OBJECT-TYPE

SYNTAX Integer32
UNITS "watts"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"A measured value of the actual power delivered to or consumed by the load. IEC 61850-7-4 attribute 'TotW'."
 ::= { eoACPwrAttributesEntry 7 }

eoACPwrAttributesTotalReactivePower OBJECT-TYPE

SYNTAX Integer32
UNITS "volt-amperes reactive"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"A measured value of the reactive portion of the apparent power. IEC 61850-7-4 attribute 'TotVar'."
 ::= { eoACPwrAttributesEntry 8 }

eoACPwrAttributesTotalApparentPower OBJECT-TYPE

```
SYNTAX          Integer32
UNITS           "volt-amperes"
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION
    "A measured value of the voltage and current which
    determines the apparent power. The apparent power is
    the vector sum of real and reactive power.

    Note: watts and volt-amperes are equivalent units and
    may be combined. IEC 61850-7-4 attribute 'TotVA'."
 ::= { eoACPwrAttributesEntry 9 }
```

```
eoACPwrAttributesTotalPowerFactor OBJECT-TYPE
SYNTAX          Integer32 (-10000..10000)
UNITS           "hundredths of percent"
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION
    "A measured value ratio of the real power flowing to
    the load versus the apparent power. It is dimensionless
    and expressed here as a percentage value in 100ths of a
    percent. A power factor of 100% indicates there is no
    inductance load and thus no reactive power. Power
    Factor can be positive or negative, where the sign
    should be in lead/lag (IEEE) form. IEC 61850-7-4
    attribute 'TotPF'."
 ::= { eoACPwrAttributesEntry 10 }
```

```
eoACPwrAttributesThdCurrent OBJECT-TYPE
SYNTAX          Integer32 (0..10000)
UNITS           "hundredths of percent"
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION
    "A calculated value for the current total harmonic
    distortion (THD). Method of calculation is not
    specified. IEC 61850-7-4 attribute 'ThdAmp'."
 ::= { eoACPwrAttributesEntry 11 }
```

```
eoACPwrAttributesThdVoltage OBJECT-TYPE
SYNTAX          Integer32 (0..10000)
UNITS           "hundredths of percent"
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION
    "A calculated value for the voltage total harmonic
    distortion (THD). Method of calculation is not
    specified. IEC 61850-7-4 attribute 'ThdVol'."
 ::= { eoACPwrAttributesEntry 12 }
```

```

eoACPwrAttributesDelPhaseTable OBJECT-TYPE
    SYNTAX          SEQUENCE OF EoACPwrAttributesDelPhaseEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION
        "This optional table describes 3-phase power attributes
        measurements in a DEL configuration with phase-to-phase
        power attributes measurements. Entities having single
        phase power shall not have any entities. This is a
        sparse extension of the eoACPwrAttributesTable.

        These attributes correspond to IEC 61850-7.4 MMXU phase
        related measurements and MHAI phase related measured
        harmonic or interharmonics."
    ::= { powerAttributesMIBObjects 2 }

```

```

eoACPwrAttributesDelPhaseEntry OBJECT-TYPE
    SYNTAX          EoACPwrAttributesDelPhaseEntry
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION
        "An entry describes power measurements of a phase in a
        DEL 3-phase power. Three entries are required for each
        supported entPhysicalIndex entry. Voltage measurements
        are provided relative to each other.

```

For phase-to-phase measurements, the eoACPwrAttributesDelPhaseIndex is compared against the following phase at +120 degrees. Thus, the possible values are:

eoACPwrAttributesDelPhaseIndex	Next Phase Angle
0	120
120	240
240	0

```

"
INDEX { entPhysicalIndex, eoACPwrAttributesDelPhaseIndex}
::= { eoACPwrAttributesDelPhaseTable 1}

```

```

EoACPwrAttributesDelPhaseEntry ::= SEQUENCE {
    eoACPwrAttributesDelPhaseIndex          Integer32,
    eoACPwrAttributesDelPhaseToNextPhaseVoltage Integer32,
    eoACPwrAttributesDelThdPhaseToNextPhaseVoltage Integer32
}

```

```

eoACPwrAttributesDelPhaseIndex OBJECT-TYPE
    SYNTAX          Integer32 (0..359)
    MAX-ACCESS      not-accessible
    STATUS          current

```

DESCRIPTION

"A phase angle typically corresponding to 0, 120, 240."
 ::= { eoACPwrAttributesDelPhaseEntry 1 }

eoACPwrAttributesDelPhaseToNextPhaseVoltage OBJECT-TYPE

SYNTAX Integer32
UNITS "0.1 Volt AC"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"A measured value of phase to next phase voltages, where the next phase is IEC 61850-7-4 attribute 'PPV'. "
 ::= { eoACPwrAttributesDelPhaseEntry 2 }

eoACPwrAttributesDelThdPhaseToNextPhaseVoltage OBJECT-TYPE

SYNTAX Integer32 (0..10000)
UNITS "hundredths of percent"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"A calculated value for the voltage total harmonic distortion for phase to next phase. Method of calculation is not specified. IEC 61850-7-4 attribute 'ThdPPV'. "
 ::= { eoACPwrAttributesDelPhaseEntry 3 }

eoACPwrAttributesWyePhaseTable OBJECT-TYPE

SYNTAX SEQUENCE OF EoACPwrAttributesWyePhaseEntry
MAX-ACCESS not-accessible
STATUS current

DESCRIPTION

"This optional table describes 3-phase power attributes measurements in a WYE configuration with phase-to-neutral power attributes measurements. Entities having single phase power shall not have any entities. This is a sparse extension of the eoACPwrAttributesTable.

These attributes correspond to IEC 61850-7.4 MMXU phase related measurements and MHAI phase related measured harmonic or interharmonics."

::= { powerAttributesMIBObjects 3 }

eoACPwrAttributesWyePhaseEntry OBJECT-TYPE

SYNTAX EoACPwrAttributesWyePhaseEntry
MAX-ACCESS not-accessible
STATUS current

DESCRIPTION

"This table describes measurements of a phase in a WYE 3-phase power system. Three entries are required for each supported entPhysicalIndex entry. Voltage measurements are relative to neutral.

Each entry describes power attributes of one phase of a WYE 3-phase power system."
 INDEX { entPhysicalIndex, eoACPwrAttributesWyePhaseIndex }
 ::= { eoACPwrAttributesWyePhaseTable 1}

```
EoACPwrAttributesWyePhaseEntry ::= SEQUENCE {
    eoACPwrAttributesWyePhaseIndex          Integer32,
    eoACPwrAttributesWyePhaseToNeutralVoltage Integer32,
    eoACPwrAttributesWyeCurrent             Integer32,
    eoACPwrAttributesWyeActivePower         Integer32,
    eoACPwrAttributesWyeReactivePower      Integer32,
    eoACPwrAttributesWyeApparentPower      Integer32,
    eoACPwrAttributesWyePowerFactor        Integer32,
    eoACPwrAttributesWyeThdCurrent         Integer32,
    eoACPwrAttributesWyeThdPhaseToNeutralVoltage Integer32
}
```

```
eoACPwrAttributesWyePhaseIndex OBJECT-TYPE
    SYNTAX          Integer32 (0..359)
    MAX-ACCESS      not-accessible
    STATUS          current
    DESCRIPTION
        "A phase angle typically corresponding to 0, 120, 240."
    ::= { eoACPwrAttributesWyePhaseEntry 1 }
```

```
eoACPwrAttributesWyePhaseToNeutralVoltage OBJECT-TYPE
    SYNTAX          Integer32
    UNITS           "0.1 Volt AC"
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION
        "A measured value of phase to neutral voltage. IEC
        61850-7-4 attribute 'PNV'."
    ::= { eoACPwrAttributesWyePhaseEntry 2 }
```

```
eoACPwrAttributesWyeCurrent OBJECT-TYPE
    SYNTAX          Integer32
    UNITS           "0.1 amperes AC"
    MAX-ACCESS      read-only
    STATUS          current
    DESCRIPTION
        "A measured value of phase currents. IEC 61850-7-4
        attribute 'A'."
    ::= { eoACPwrAttributesWyePhaseEntry 3 }
```

```
eoACPwrAttributesWyeActivePower OBJECT-TYPE
    SYNTAX          Integer32
    UNITS           "watts"
```

MAX-ACCESS read-only
STATUS current
DESCRIPTION
"A measured value of the actual power delivered to or consumed by the load with the magnitude indicated separately in eoPowerUnitMultiplier. IEC 61850-7-4 attribute 'W'"
::= { eoACPwrAttributesWyePhaseEntry 4 }

eoACPwrAttributesWyeReactivePower OBJECT-TYPE
SYNTAX Integer32
UNITS "volt-amperes reactive"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"A measured value of the reactive portion of the apparent power with the magnitude of indicated separately in eoPowerUnitMultiplier. IEC 61850-7-4 attribute 'VAr'"
::= { eoACPwrAttributesWyePhaseEntry 5 }

eoACPwrAttributesWyeApparentPower OBJECT-TYPE
SYNTAX Integer32
UNITS "volt-amperes"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"A measured value of the voltage and current determines the apparent power with the indicated separately in eoPowerUnitMultiplier. Active plus reactive power equals the total apparent power."

Note: Watts and volt-amperes are equivalent units and may be combined. IEC 61850-7-4 attribute 'VA'."
::= { eoACPwrAttributesWyePhaseEntry 6 }

eoACPwrAttributesWyePowerFactor OBJECT-TYPE
SYNTAX Integer32 (-10000..10000)
UNITS "hundredths of percent"
MAX-ACCESS read-only
STATUS current
DESCRIPTION
"A measured value ratio of the real power flowing to the load versus the apparent power for this phase. IEC 61850-7-4 attribute 'PF'. Power Factor can be positive or negative where the sign should be in lead/lag (IEEE) form."
::= { eoACPwrAttributesWyePhaseEntry 7 }

eoACPwrAttributesWyeThdCurrent OBJECT-TYPE

```
SYNTAX          Integer32 (0..10000)
UNITS           "hundredths of percent"
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
  "A calculated value for the voltage total harmonic
  distortion (THD) for phase to phase. Method of
  calculation is not specified.
  IEC 61850-7-4 attribute 'ThdA'."
 ::= { eoACPwrAttributesWyePhaseEntry 8 }
```

```
eoACPwrAttributesWyeThdPhaseToNeutralVoltage OBJECT-TYPE
SYNTAX          Integer32 (0..10000)
UNITS           "hundredths of percent"
MAX-ACCESS     read-only
STATUS         current
DESCRIPTION
  "A calculated value of the voltage total harmonic
  distortion (THD) for phase to neutral. IEC 61850-7-4
  attribute 'ThdPhV'."
 ::= { eoACPwrAttributesWyePhaseEntry 9 }
```

-- Conformance

```
powerAttributesMIBCompliances OBJECT IDENTIFIER
 ::= { powerAttributesMIB 2 }
```

```
powerAttributesMIBGroups OBJECT IDENTIFIER
 ::= { powerAttributesMIB 3 }
```

```
powerAttributesMIBFullCompliance MODULE-COMPLIANCE
STATUS         current
DESCRIPTION
  "When this MIB is implemented with support for read-create,
  then such an implementation can claim full compliance.
  Such devices can then be both monitored and configured with
  this MIB.
```

```
Module Compliance of [RFC6933] with respect to
entity4CRCompliance MUST be supported which requires
implementation of 4 MIB objects: entPhysicalIndex,
entPhysicalClass, entPhysicalName and entPhysicalUUID."
```

```
MODULE          -- this module
MANDATORY-GROUPS {
  powerACPwrAttributesMIBTableGroup
```

}

```
GROUP          powerACPwrAttributesOptionalMIBTableGroup
DESCRIPTION
  "A compliant implementation does not have
  to implement."
```

```
GROUP          powerACPwrAttributesDelPhaseMIBTableGroup
DESCRIPTION
  "A compliant implementation does not have to
  implement."
```

```
GROUP          powerACPwrAttributesWyePhaseMIBTableGroup
DESCRIPTION
  "A compliant implementation does not have to
  implement."
```

```
::= { powerAttributesMIBCompliances 1 }
```

-- Units of Conformance

```
powerACPwrAttributesMIBTableGroup OBJECT-GROUP
  OBJECTS
    {
      -- Note that object entPhysicalIndex is NOT
      -- included since it is not-accessible

      eoACPwrAttributesAvgVoltage,
      eoACPwrAttributesAvgCurrent,
      eoACPwrAttributesFrequency,
      eoACPwrAttributesPowerUnitMultiplier,
      eoACPwrAttributesPowerAccuracy,
      eoACPwrAttributesTotalActivePower,
      eoACPwrAttributesTotalReactivePower,
      eoACPwrAttributesTotalApparentPower,
      eoACPwrAttributesTotalPowerFactor
    }
  STATUS          current
  DESCRIPTION
    "This group contains the collection of all the power
    attributes objects related to the Energy Object."
  ::= { powerAttributesMIBGroups 1 }
```

```
powerACPwrAttributesOptionalMIBTableGroup OBJECT-GROUP
  OBJECTS
    {
      eoACPwrAttributesConfiguration,
      eoACPwrAttributesThdCurrent,
```

```

        eoACPwrAttributesThdVoltage
    }
    STATUS          current
    DESCRIPTION
        "This group contains the collection of all the power
        attributes objects related to the Energy Object."
    ::= { powerAttributesMIBGroups 2 }

powerACPwrAttributesDelPhaseMIBTableGroup OBJECT-GROUP
    OBJECTS
        {
            -- Note that object entPhysicalIndex and
            -- eoACPwrAttributesDelPhaseIndex are NOT
            -- included since they are not-accessible
            eoACPwrAttributesDelPhaseToNextPhaseVoltage,
            eoACPwrAttributesDelThdPhaseToNextPhaseVoltage
        }
    STATUS          current
    DESCRIPTION
        "This group contains the collection of all power
        attributes of a phase in a DEL 3-phase power system."
    ::= { powerAttributesMIBGroups 3 }

powerACPwrAttributesWyePhaseMIBTableGroup OBJECT-GROUP
    OBJECTS
        {
            -- Note that object entPhysicalIndex and
            -- eoACPwrAttributesWyePhaseIndex are NOT
            -- included since they are not-accessible
            eoACPwrAttributesWyePhaseToNeutralVoltage,
            eoACPwrAttributesWyeCurrent,
            eoACPwrAttributesWyeActivePower,
            eoACPwrAttributesWyeReactivePower,
            eoACPwrAttributesWyeApparentPower,
            eoACPwrAttributesWyePowerFactor,
            eoACPwrAttributesWyeThdPhaseToNeutralVoltage,
            eoACPwrAttributesWyeThdCurrent
        }
    STATUS          current
    DESCRIPTION
        "This group contains the collection of all power
        attributes of a phase in a WYE 3-phase power system."
    ::= { powerAttributesMIBGroups 4 }

END
```

10. Implementation Status

[Note to RFC Editor: Please remove this section and the reference to [RFC6982] before publication.]

This section records the status of known implementations of the EMAN-Monitoring MIB at the time of posting of this Internet-Draft, and is based on a proposal described in [RFC6982].

The description of implementations in this section is intended to assist the IETF in its decision processes in progressing drafts to RFCs.

10.1. SNMP Research

Organization: SNMP Research, Inc.

Maturity: Prototype based upon early drafts of the MIBs. We anticipate updating it to more recent documents as development schedules allow.

Coverage: Code was generated to implement all MIB objects in ENTITY-MIB (Version 4), ENERGY-OBJECT-CONTEXT-MIB, ENERGY-OBJECT-MIB, POWER-ATTRIBUTES-MIB, and BATTERY-MIB.

Implementation experience: The documents are implementable.

Comments: Technical comments about the ENERGY-OBJECT-CONTEXT-MIB, ENERGY-OBJECT-MIB, and BATTERY-MIB were submitted to the EMAN Working Group E-mail list.

Licensing: Proprietary, royalty licensing

Contact: Alan Luchuk, luchuk at snmp.com

URL: <http://www.snmp.com/>

10.2. Cisco Systems

Organization: Cisco Systems, Inc.

<Claise, et. Al>

Expires August 14, 2014

[Page 62]

Maturity: Prototype based upon early version drafts of the MIBs. We anticipate updating the MIB modules as when the drafts are updated.

Coverage: Code was generated to implement all MIB objects in the ENTITY-MIB (Version 4), and ENERGY-OBJECT-MIB.

Implementation experience: The MIB modules are implemented on Cisco router platforms to measure and report router energy measurements. The documents are implementable.

Licensing: Proprietary

URL: <http://www.cisco.com>

11. Security Considerations

Some of the readable objects in these MIB modules (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

There are a number of management objects defined in these MIB modules with a MAX-ACCESS clause of read-write and/or read-create. Such objects MAY be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations. The following are the tables and objects and their sensitivity/vulnerability:

- Unauthorized changes to the eoPowerOperState (via theeoPowerAdminState) MAY disrupt the power settings of the differentEnergy Objects, and therefore the state of functionality of the respective Energy Objects.
- Unauthorized changes to the eoEnergyParametersTable MAY disrupt energy measurement in the eoEnergyTable table.

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example, by using IPsec), there is still no secure control over who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in these MIB modules.

It is RECOMMENDED that implementers consider the security features as provided by the SNMPv3 framework (see [RFC3410], section 8), including full support for the SNMPv3 cryptographic mechanisms (for authentication and privacy).

Further, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of these MIB modules is properly configured to give access to the objects only to those principals (users) that have legitimate rights to GET or SET (change/create/delete) them.

12. IANA Considerations

The MIB modules in this document use the following IANA-assigned OBJECT IDENTIFIER values recorded in the SMI Numbers registry:

Descriptor	OBJECT IDENTIFIER value
-----	-----
energyObjectMIB	{ mib-2 xxx }
powerAttributesMIB	{ mib-2 yyy }

Editor's Note (to be removed prior to publication): IANA is requested to assign a value for "XXX" and "YYY" under the 'mib-2' subtree and to record the assignment in the SMI Numbers registry. When the assignment has been made, the RFC Editor is asked to replace "XXX" and "YYY"(here and in the MIB module) with the assigned value and to remove this note.

13. Contributors

This document results from the merger of two initial proposals. The following persons made significant contributions either in one of the initial proposals or in this document.

John Parello

Rolf Winter

Dominique Dudkowski

14. Acknowledgment

The authors would like to thank Shamita Pisal for her prototype of this MIB module, and her valuable feedback. The authors would like to Michael Brown for improving the text dramatically.

The authors would like to thank Juergen Schoenwalder for proposing the design of the Textual Convention for IANAPowerStateSet and Ira McDonald for his feedback. Special appreciation to Laurent Guise for his review and input on power quality measurements. Thanks for the many comments on the design of the EnergyTable from Minoru Teraoka and Hiroto Ogaki.

Many thanks to Alan Luchuk for the detailed review of the MIB and his comments.

And finally, thanks to the EMAN chairs: Nevil Brownlee and Tom Nadeau.

15. References

15.1. Normative References

- [RFC2119] S. Bradner, Key words for use in RFCs to Indicate Requirement Levels, BCP 14, RFC 2119, March 1997.
- [RFC2578] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Structure of Management Information Version 2 (SMIV2)", STD 58, RFC 2578, April 1999.
- [RFC2579] McCloghrie, K., Ed., Perkins, D., Ed., and J. Schoenwaelder, Ed., "Textual Conventions for SMIV2", STD 58, RFC 2579, April 1999.
- [RFC2580] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Conformance Statements for SMIV2", STD 58, RFC 2580, April 1999.
- [RFC3621] Berger, A., and D. Romascanu, "Power Ethernet MIB", RFC3621, December 2003.
- [RFC6933] A. Bierman, D. Romascanu, J. Quittek and M. Chandramouli " Entity MIB (Version 4)", RFC 6933, May 2013.
- [EMAN-AWARE-MIB] J. Parello, B. Claise and M. Chandramoili, "draft-ietf-eman-energy-aware-mib-14", work in progress, February 10 2013.

[LLDP-MED-MIB] ANSI/TIA-1057, "The LLDP Management Information Base extension module for TIA-TR41.4 media endpoint discovery information", July 2005.

15.2. Informative References

[RFC1628] S. Bradner, "UPS Management Information Base", RFC 1628, May 1994

[RFC3410] Case, J., Mundy, R., Partain, D., and B. Stewart, "Introduction and Applicability Statements for Internet Standard Management Framework ", RFC 3410, December 2002.

[RFC3418] Presun, R., Case, J., McCloghrie, K., Rose, M, and S. Waldbusser, "Management Information Base (MIB) for the Simple Network Management Protocol (SNMP)", RFC3418, December 2002.

[RFC3433] Bierman, A., Romascanu, D., and K. Norseth, "Entity Sensor Management Information Base", RFC 3433, December 2002.

[RFC4268] Chisholm, S. and D. Perkins, "Entity State MIB", RFC 4268, November 2005.

[RFC5226] Narten, T. Alverstrand, H., A. and K. McCloghrie, "Guidelines for Writing an IANA Considerations Section in RFCs ", BCP 26, RFC 5226, May 2008.

[RFC6982] Sheffer, Y. and A. Farrel, "Improving Awareness of Running Code: The Implementation Status Section", RFC 6982, July 2013.

[RFC6988] Quittek, J., Winter, R., Dietz, T., Claise, B., and M. Chandramouli, " Requirements for Energy Management", RFC 6988, September 2013.

[EMAN-FMWK] Parello, J. Claise, B., Schoening, B. and Quittek, J., "Energy Management Framework", draft-ietf-eman-framework-11, October 2013.

[EMAN-AS] Schoening, B., Chandramouli, M. and Nordman, B. "Energy Management (EMAN) Applicability Statement", draft-ietf-eman-applicability-statement-04, October 2013.

[ACPI] "Advanced Configuration and Power Interface Specification", <http://www.acpi.info/DOWNLOADS/ACPIspec30b.pdf>

[DMTF] "Power State Management Profile DMTF DSP1027 Version 2.0" December 2009
http://www.dmtf.org/sites/default/files/standards/documents/DSP1027_2.0.0.pdf

[IEEE1621] "Standard for User Interface Elements in Power Control of Electronic Devices Employed in Office/Consumer Environments", IEEE 1621, December 2004.

[IEC.61850-7-4] International Electrotechnical Commission, "Communication networks and systems for power utility automation Part 7-4: Basic communication structure Compatible logical node classes and data object classes", 2010.

[IEC.62053-21] International Electrotechnical Commission, "Electricity metering equipment (a.c.) Particular requirements Part 22: Static meters for active energy (classes 1 and 2)", 2003.

[IEC.62053-22] International Electrotechnical Commission, "Electricity metering equipment (a.c.) Particular requirements Part 22: Static meters for active energy (classes 0,2 S and 0,5 S)", 2003.

Authors' Addresses

Mouli Chandramouli
Cisco Systems, Inc.
Sarjapur Outer Ring Road
Bangalore 560103
IN

Phone: +91 80 4429 2409
Email: moulchan@cisco.com

Benoit Claise
Cisco Systems, Inc.
De Kleetlaan 6a b1
Diegem 1813
BE

Phone: +32 2 704 5622
Email: bclaise@cisco.com

Brad Schoening
44 Rivers Edge Drive
Little Silver, NJ 07739
US
Email: brad.schoening@verizon.net

Juergen Quittek
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36
Heidelberg 69115
DE

Phone: +49 6221 4342-115
Email: quittek@neclab.eu

Thomas Dietz
NEC Europe Ltd.
NEC Laboratories Europe
Network Research Division
Kurfuersten-Anlage 36
Heidelberg 69115
DE

Phone: +49 6221 4342-128
Email: Thomas.Dietz@neclab.eu