

BFD Working Group
Standard Track

Thomas D. Nadeau
Zafar Ali
Cisco Systems, Inc.

Document: [draft-ietf-bfd-mib-01.txt](#)
Expires: January 2006

July 2005

**Bidirectional Forwarding Detection Management Information Base
draft-ietf-bfd-mib-01.txt**

Status of this Memo

By submitting this Internet-Draft, each author represents that any applicable patent or other IPR claims of which he or she is aware have been or will be disclosed, and any of which he or she becomes aware will be disclosed, in accordance with [Section 6 of BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/1id-abstracts.txt>.

The list of Internet-Draft Shadow Directories can be accessed at <http://www.ietf.org/shadow.html>.

Abstract

This draft defines a portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it describes managed objects for modeling Bidirectional Forwarding Detection (BFD) protocol [[BFD](#)].

Conventions used in this document

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [RFC 2119](#) [[RFC2119](#)].

SUMMARY

This draft defines Management Information Base (MIB) for

Bidirectional Forwarding Detection (BFD) protocol [[BFD](#)].

RELATED REFERENCES

Please refer to the reference section.

Table of Contents

1.	Introduction.....	2
2.	Terminology.....	3
3.	The Internet-Standard Management Framework.....	3
3.	Brief Description of MIB Objects.....	3
3.1	General Variables.....	3
3.2	Session Table (bfdSessionTable).....	3
3.3	Session Performance Table (bfdSessionPerfTable).....	3
3.4	Session Mapping Table (bfdSessMapTable).....	3
4.	BFD MIB Module Definitions.....	4
5.	Security Considerations.....	21
6.	Acknowledgements.....	22
7.	Reference.....	23
7.1	Normative References.....	23
7.2	Informative References.....	23
8.	Author's Addresses.....	23
9.	Full Copyright Statement.....	24
10.	IANA Considerations.....	41
10.1.	IANA Considerations for BFD-STD-MIB.....	41
11.	Intellectual Property Statement.....	41

[1.](#) Introduction

This memo defines an portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it describes managed objects to configure and/or monitor Bi-Directional Forwarding Detection on devices supporting this feature.

This document adopts the definitions, acronyms and mechanisms described in [[BFD](#)], [[BFD-SHARED](#)] and [[BFD-LSP](#)]. Unless otherwise stated, the mechanisms described therein will not be re-described here.

Comments should be made directly to the BFD mailing list at rtg-bfd@ietf.org.

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [[RFC2119](#)].

2. Terminology

This document adopts the definitions, acronyms and mechanisms described in [\[BFD\]](#), [\[BFD-SHARED\]](#) and [\[BFD-LSP\]](#). Unless otherwise stated, the mechanisms described therein will not be re-described here.

3. The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to [section 7 of RFC 3410](#) [\[RFC3410\]](#).

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIV2, which is described in STD 58, [RFC 2578](#) [\[RFC2578\]](#), STD 58, [RFC 2579](#) [\[RFC2579\]](#) and STD 58, [RFC 2580](#) [\[RFC2580\]](#).

4. Brief Description of MIB Objects

This section describes objects pertaining to BFD. The MIB objects are derived from the BFD document [\[BFD\]](#).

4.1 General Variables

The General Variables are used to identify parameters that are global to the BFD process.

4.2 Session Table (bfdSessionTable)

The session table is used to identify a BFD session between a pair of nodes.

4.3 Session Performance Table (bfdSessionPerfTable)

The session performance table is used for collecting BFD performance counts on a per session basis. This table is an AUGMENT to the bfdSessionTable.

3.4 Session Mapping Table (bfdSessMapTable)

The BFD Session Mapping Table maps the complex indexing of the BFD sessions to the flat BFDIndex used in the BfdSessionTable.

5. BFD MIB Module Definitions

```
BFD-DRAFT-01-MIB DEFINITIONS ::= BEGIN
    -- RFC-editor pls change BFD-DRAFT-*-MIB to
    -- BFD-STD-MIB

IMPORTS
    MODULE-IDENTITY, OBJECT-TYPE,
    Unsigned32, Counter32, Counter64,
    NOTIFICATION-TYPE, mib-2
        FROM SNMPv2-SMI

    MODULE-COMPLIANCE, OBJECT-GROUP, NOTIFICATION-GROUP
        FROM SNMPv2-CONF

    TEXTUAL-CONVENTION, TruthValue, RowStatus, StorageType,
    TimeStamp
        FROM SNMPv2-TC

    InetAddress, InetAddressType, InetPortNumber
        FROM INET-ADDRESS-MIB
;

bfdMIB MODULE-IDENTITY
    LAST-UPDATED "200507221200Z" -- 04 July 2005 12:00:00 EST
    ORGANIZATION "IETF"
    CONTACT-INFO
        "          Thomas D. Nadeau
          Cisco Systems, Inc.
        Email: tnadeau@cisco.com

          Zafar Ali
          Cisco Systems, Inc.
        Email: zali@cisco.com
        "
    DESCRIPTION
        "Bidirectional Forwarding Management Information Base."

    -- Revision history.
    REVISION
        "200507221200Z" -- 04 July 2005 12:00:00 EST
    DESCRIPTION
        "Initial version. Published as RFC xxxx." -- RFC-editor pls fill
                                                -- in xxx
::= { mib-2 XXX } -- assigned by IANA, see section 18.1 for details

-- Top level components of this MIB module.
```



```
bfdNotifications OBJECT IDENTIFIER ::= { bfdMIB 0 }

bfdObjects          OBJECT IDENTIFIER ::= { bfdMIB 1 }

bfdConformance     OBJECT IDENTIFIER ::= { bfdMIB 3 }

bfdScalarObjects   OBJECT IDENTIFIER ::= { bfdObjects 1 }
```

-- Textual Conventions

```
BfdSessIndexTC ::= TEXTUAL-CONVENTION
DISPLAY-HINT "d"
STATUS          current
DESCRIPTION
    "An index used to uniquely identify BFD sessions."
SYNTAX Unsigned32 (1..4294967295)
```

```
BfdInterval ::= TEXTUAL-CONVENTION
STATUS          current
DESCRIPTION
    "The BFD interval delay in microseconds."
SYNTAX          Unsigned32 (1..4294967295)
```

```
BfdDiag ::=          TEXTUAL-CONVENTION
STATUS          current
DESCRIPTION
    "A common BFD diagnostic code."

SYNTAX INTEGER { noDiagnostic(1),
                  controlDetectionTimeExpired(2),
                  echoFunctionFailed(3),
                  neighborSignaledSessionDown(4),
                  forwardingPlaneReset(5),
                  pathDown(6),
                  concatenatedPathDown(7),
                  administrativelyDown(8),
                  reverseConcatenatedPathDown (9)
                }
```

-- BFD General Variables

```
-- These parameters apply globally to the Router's
-- BFD Process.
```

```
bfdAdminStatus OBJECT-TYPE
```



```
SYNTAX    INTEGER { enabled(1), disabled(2) }
MAX-ACCESS read-write
STATUS    current
DESCRIPTION
    "The global administrative status of BFD in this router.
    The value 'enabled' denotes that the BFD Process is
    active on at least one interface; 'disabled' disables
    it on all interfaces."
DEFVAL { enabled }
::= { bfdScalarObjects 1 }
```

```
bfdVersionNumber OBJECT-TYPE
    SYNTAX    Unsigned32
    MAX-ACCESS read-only
    STATUS    current
    DESCRIPTION
        "The current version number of the BFD protocol."
    REFERENCE
        " BFD Version 0 (draft-katz-ward-bfd-02.txt)"
    DEFVAL { 0 }
    ::= { bfdScalarObjects 3 }
```

```
-- BFD Session Table
-- The BFD Session Table specifies BFD session specific
-- information.
```

```
bfdSessTable OBJECT-TYPE
    SYNTAX    SEQUENCE OF BfdSessEntry
    MAX-ACCESS not-accessible
    STATUS    current
    DESCRIPTION
        "The BFD Session Table describes the BFD sessions."
    REFERENCE
        "BFD Version 0 (draft-katz-ward-bfd-02.txt)"
    ::= { bfdObjects 2 }
```

```
bfdSessEntry OBJECT-TYPE
    SYNTAX    BfdSessEntry
    MAX-ACCESS not-accessible
    STATUS    current
    DESCRIPTION
        "The BFD Session Entry describes BFD session."
    INDEX { bfdSessIndex }
    ::= { bfdSessTable 1 }
```

```
BfdSessEntry ::= SEQUENCE {
```

bfdSessIndex

BfdSessIndexTC,

BFD Working Group

Expires January 2005

[Page 6]

```

bfdSessApplicationId      Unsigned32,
bfdSessDiscriminator      Unsigned32,
bfdSessRemoteDiscr        Unsigned32,
bfdSessUdpPort             InetPortNumber,
bfdSessState               INTEGER,
bfdSessRemoteHeardFlag     TruthValue,
bfdSessDiag                Unsigned32,
bfdSessOperMode            INTEGER,
bfdSessDemandModeDesiredFlag TruthValue,
bfdSessEchoFuncModeDesiredFlag TruthValue,
bfdSessControlPlanIndepFlag TruthValue,
bfdSessAddrType            InetAddressType,
bfdSessAddr                InetAddress,
bfdSessDesiredMinTxInterval BfdInterval,
bfdSessDesiredMinRxInterval BfdInterval,
bfdSessDesiredMinEchoRxInterval BfdInterval,
bfdSessDetectMult          Unsigned32,
bfdSessStorType            StorageType,
bfdSessRowStatus            RowStatus,
bfdSessAuthPresFlag        TruthValue,
bfdSessAuthenticationType  INTEGER
}

```

```

bfdSessIndex  OBJECT-TYPE
SYNTAX        BfdSessIndexTC
MAX-ACCESS    not-accessible
STATUS        current

```

DESCRIPTION

"This object contains an index used to represent a unique BFD session on this device."

```
::= { bfdSessEntry 1 }
```

```
bfdSessApplicationId  OBJECT-TYPE
```

```

SYNTAX        Unsigned32
MAX-ACCESS    read-only
STATUS        current

```

DESCRIPTION

"This object contains an index used to indicate a local application which owns or maintains this BFD session. For instance, the MPLS VPN process may maintain a subset of the total number of BFD sessions. This application ID provides a convenient way to segregate sessions by the applications which maintain them."

```
::= { bfdSessEntry 2 }
```

```
bfdSessDiscriminator      OBJECT-TYPE
```

SYNTAX

Unsigned32 (1..4294967295)

BFD Working Group

Expires January 2005

[Page 7]

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object specifies the local discriminator for this BFD session, used to uniquely identify it."

::= { bfdSessEntry 3 }

bfdSessRemoteDiscr OBJECT-TYPE

SYNTAX Unsigned32 (1..4294967295)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object specifies the session discriminator chosen by the remote system for this BFD session."

::= { bfdSessEntry 4 }

bfdSessUdpPort OBJECT-TYPE

SYNTAX InetPortNumber

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The UDP Port for BFD. The default value is the well-known value for this port."

REFERENCE

"[draft-katz-ward-bfd-02.txt](#) and
[draft-raggarwa-mpls-bfd-00.txt](#)"

DEFVAL { 0 }

::= { bfdSessEntry 5 }

bfdSessState OBJECT-TYPE

SYNTAX INTEGER {
adminDown(1),
down(2),
init(3),
up(4)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The perceived state of the BFD session."

::= { bfdSessEntry 6 }

bfdSessRemoteHeardFlag OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object specifies status of BFD packet reception from

the remote system. Specifically, it is set to true(1) if the local system is actively receiving BFD packets from the remote system, and is set to false(0) if the local system has not received BFD packets recently (within the detection time) or if the local system is attempting to tear down the BFD session."

::= { bfdSessEntry 7 }

bfdSessDiag OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS accessible-for-notify

STATUS current

DESCRIPTION

"A diagnostic code specifying the local system's reason for the last transition of the session from up(1) to some other state."

::= { bfdSessEntry 8 }

bfdSessOperMode OBJECT-TYPE

SYNTAX INTEGER { asyncModeWEchoFun(1),
asynchModeW0EchoFun(2),
demandModeWEchoFunction(3),
demandModeW0EchoFunction(4)

}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object specifies current operating mode that BFD session is operating in.

A value of AsyncModeWEchoFun(1) ...

A value of AsynchModeW0EchoFun(2) ...

A value of DemandModeWEchoFunction(3) ...

A value of DemandModeW0EchoFunction(4) ...

"

::= { bfdSessEntry 9 }

bfdSessDemandModeDesiredFlag OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object indicates that the local system's desire to use Demand mode. Specifically, it is set to true(1) if the local system wishes to use Demand mode or false(0) if not"

DEFVAL { false }

```
::= { bfdSessEntry 10 }
```

bfdSessEchoFuncModeDesiredFlag OBJECT-TYPE

SYNTAX TruthValue
MAX-ACCESS read-create
STATUS current
DESCRIPTION

"This object indicates that the local system's desire to use Echo mode. Specifically, it is set to true(1) if the local system wishes to use Echo mode or false(0) if not"

DEFVAL { false }
::= { bfdSessEntry 11 }

bfdSessControlPlanIndepFlag OBJECT-TYPE

SYNTAX TruthValue
MAX-ACCESS read-create
STATUS current
DESCRIPTION

"This object indicates that the local system's ability to continue to function through a disruption of the control plane. Specifically, it is set to true(1) if the local system BFD implementation is independent of the control plane. Otherwise, the value is set to false(0)"

DEFVAL { false }
::= { bfdSessEntry 12 }

bfdSessAddrType OBJECT-TYPE

SYNTAX InetAddressType
MAX-ACCESS read-create
STATUS current
DESCRIPTION

"This object specifies IP address of the interface associated with this BFD session.

Only values unknown(0), ipv4(1) or ipv6(2) have to be supported.

A value of unknown(0) is allowed only when the outgoing interface is of type point-to-point, or when the BFD session is not associated with a specific interface.

If any other unsupported values are attempted in a set operation, the agent MUST return an inconsistentValue error.

"

```
::= { bfdSessEntry 13 }
```

bfdSessAddr OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object specifies IP address of the interface associated with this BFD session.

It can also be used to enabled BFD on a specific interface. The value is set to zero when BFD session is not associated with a specific interface. "

::= { bfdSessEntry 14 }

bfdSessDesiredMinTxInterval OBJECT-TYPE

SYNTAX BfdInterval

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object specifies the minimum interval, in microseconds, that the local system would like to use when transmitting BFD Control packets."

::= { bfdSessEntry 15 }

bfdSessDesiredMinRxInterval OBJECT-TYPE

SYNTAX BfdInterval

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object specifies the minimum interval, in microseconds, between received BFD Control packets the local system is capable of supporting."

::= { bfdSessEntry 16 }

bfdSessDesiredMinEchoRxInterval OBJECT-TYPE

SYNTAX BfdInterval

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object specifies the minimum interval, in microseconds, between received BFD Echo packets that this system is capable of supporting."

::= { bfdSessEntry 17 }

bfdSessDetectMult OBJECT-TYPE

SYNTAX Unsigned32

MAX-ACCESS read-create

STATUS current

DESCRIPTION

BFD Working Group

Expires January 2005

[Page 11]

"This object specifies the Detect time multiplier."
 ::= { bfdSessEntry 18 }

bfdSessStorType OBJECT-TYPE

SYNTAX StorageType

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This variable indicates the storage type for this object. Conceptual rows having the value 'permanent' need not allow write-access to any columnar objects in the row."

::= { bfdSessEntry 19 }

bfdSessRowStatus OBJECT-TYPE

SYNTAX RowStatus

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This variable is used to create, modify, and/or delete a row in this table. When a row in this table has a row in the active(1) state, no objects in this row can be modified except the bfdSessRowStatus and bfdSessStorageType."

::= { bfdSessEntry 20 }

bfdSessAuthPresFlag OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This object indicates that the local system's desire to use Authentication. Specifically, it is set to true(1) if the local system wishes the session to be authenticated or false(0) if not"

DEFVAL { false }

::= { bfdSessEntry 21 }

bfdSessAuthenticationType OBJECT-TYPE

SYNTAX INTEGER { simplePassword(1),
 keyedMD5(2),
 meticulousKeyedMD5(3),
 keyedSHA1(4),
 meticulousKeyedSHA1(5)
 }

MAX-ACCESS read-create

STATUS current

DESCRIPTION

BFD Working Group

Expires January 2005

[Page 12]

"The Authentication Type used for this BFD session. This field is valid only when the Authentication Present bit is set"

::= { bfdSessEntry 22 }

-- BFD Session Performance Table

bfdSessPerfTable OBJECT-TYPE

SYNTAX SEQUENCE OF BfdSessPerfEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"This table specifies BFD Session performance counters."

::= { bfdObjects 3 }

bfdSessPerfEntry OBJECT-TYPE

SYNTAX BfdSessPerfEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry in this table is created by a BFD-enabled node for every BFD Session. bfdCounterDiscontinuityTime is used to indicate potential discontinuity for all counter objects in this table."

AUGMENTS { bfdSessEntry }

::= { bfdSessPerfTable 1 }

BfdSessPerfEntry ::= SEQUENCE {

bfdSessPerfPktIn Counter32,

bfdSessPerfPktOut Counter32,

bfdSessUpTime TimeStamp,

bfdSessPerfLastSessDownTime TimeStamp,

bfdSessPerfLastCommLostDiag BfdDiag,

bfdSessPerfSessUpCount Counter32,

bfdSessPerfDiscTime TimeStamp,

-- High Capacity Counters

bfdSessPerfPktInHC Counter64,

bfdSessPerfPktOutHC Counter64

}

-- Ed Note: should we add per-diag code counts here,

bfdSessPerfPktIn OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The total number of BFD messages received for this BFD

session."

::= { bfdSessPerfEntry 1 }

bfdSessPerfPktOut OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The total number of BFD messages sent for this BFD session."

::= { bfdSessPerfEntry 2 }

bfdSessUpTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of sysUpTime on the most recent occasion at which the session came up. If no such up event exists this object contains a zero value."

::= { bfdSessPerfEntry 3 }

bfdSessPerfLastSessDownTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of sysUpTime on the most recent occasion at which the last time communication was lost with the neighbor. If no such down event exist this object contains a zero value."

::= { bfdSessPerfEntry 4 }

bfdSessPerfLastCommLostDiag OBJECT-TYPE

SYNTAX BfdDiag

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The BFD diag code for the last time communication was lost with the neighbor. If no such down event exists this object contains a zero value."

::= { bfdSessPerfEntry 5 }

bfdSessPerfSessUpCount OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of times this session has gone into the Up

state since the router last rebooted."

```
::= { bfdSessPerfEntry 6 }
```

bfdSessPerfDiscTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of sysUpTime on the most recent occasion at which
any

one or more of the session counters suffered a
discontinuity.

The relevant counters are the specific instances associated
with this BFD session of any Counter32 object contained in
the

BfdSessPerfTable. If no such discontinuities have occurred
since the last re-initialization of the local management
subsystem,

then this object contains a zero value."

```
::= { bfdSessPerfEntry 7 }
```

bfdSessPerfPktInHC OBJECT-TYPE

SYNTAX Counter64

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This value represents the total number of BFD messages
received for this BFD session. It MUST be equal to the
least significant 32 bits of bfdSessPerfPktIn
if bfdSessPerfPktInHC is supported according to
the rules spelled out in [RFC2863](#)."

```
::= { bfdSessPerfEntry 8 }
```

bfdSessPerfPktOutHC OBJECT-TYPE

SYNTAX Counter64

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This value represents the total number of
total number of BFD messages transmitted for this
BFD session. It MUST be equal to the
least significant 32 bits of bfdSessPerfPktIn
if bfdSessPerfPktOutHC is supported according to
the rules spelled out in [RFC2863](#)."

```
::= { bfdSessPerfEntry 9 }
```

-- BFD Session Mapping Table

bfdSessMapTable OBJECT-TYPE

SYNTAX SEQUENCE OF BfdSessMapEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"The BFD Session Mapping Table maps the complex indexing of the BFD sessions to the flat BfdIndex used in the BfdSessionTable.

Implementors need to be aware that if the value of the bfdSessAddr (an OID) has more than 111 sub-identifiers, then OIDs of column instances in this table will have more than 128 sub-identifiers and cannot be accessed using SNMPv1, SNMPv2c, or SNMPv3.

"

REFERENCE

"BFD Version 0 ([draft-katz-ward-bfd-02.txt](#))"

::= { bfdObjects 4 }

bfdSessMapEntry OBJECT-TYPE

SYNTAX BfdSessMapEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"The BFD Session Entry describes BFD session that is mapped to this index.

Implementors need to be aware that if the value of the mplsInSegmentMapLabelPtrIndex (an OID) has more than 111 sub-identifiers, then OIDs of column instances in this table will have more than 128 sub-identifiers and cannot be accessed using SNMPv1, SNMPv2c, or SNMPv3."

INDEX { bfdSessApplicationId,
 bfdSessDiscriminator,
 bfdSessAddrType,
 bfdSessAddr

}

::= { bfdSessMapTable 1 }

BfdSessMapEntry ::= SEQUENCE {

bfdSessMapBfdIndex

BfdSessIndexTC

}

bfdSessMapBfdIndex OBJECT-TYPE

SYNTAX BfdSessIndexTC

MAX-ACCESS read-only

BFD Working Group

Expires January 2005

[Page 16]

STATUS current

DESCRIPTION

"This object specifies the BfdIndex referred to by the indexes of this row. In essence, a mapping is provided between these indexes and the BfdSessTable."

::= { bfdSessMapEntry 1 }

-- Notification Configuration

bfdSessNotificationsEnable OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"If this object is set to true(1), then it enables the emission of bfdSessUp and bfdSessDown notifications; otherwise these notifications are not emitted."

REFERENCE

"See also [RFC3413](#) for explanation that notifications are under the ultimate control of the MIB modules in this document."

DEFVAL { false }

::= { bfdScalarObjects 4 }

bfdSessUp NOTIFICATION-TYPE

OBJECTS { bfdSessDiag, -- low range value
 bfdSessDiag -- high range value

}

STATUS current

DESCRIPTION

"This notification is generated when the bfdSessState object for one or more contiguous entries in bfdSessTable are about to enter the up(2) state from some other state. The included values of bfdSessDiag MUST both be set equal to this new state (i.e: up(1)). The two instances of bfdSessDiag in this notification indicate the range of indexes that are affected. Note that all the indexes of the two ends of the range can be derived from the instance identifiers of these two objects. For the cases where a contiguous range of sessions have transitioned into the up(1) state at roughly the same time, the device SHOULD issue a single notification for each range of contiguous indexes in an effort to minimize the emission of a large number of notifications. If a notification has to be

issued for just a single bfdSessEntry, then

the instance identifier (and values) of the two
bfdSessDiag objects MUST be the identical."
::= { bfdNotifications 1 }

bfdSessDown NOTIFICATION-TYPE

OBJECTS { bfdSessDiag, -- low range value
 bfdSessDiag -- high range value
}

STATUS current

DESCRIPTION

"This notification is generated when the
bfdSessState object for one or more contiguous
entries in bfdSessTable are about to enter the down(4)
or adminDown(5) states from some other state. The included
values of bfdSessDiag MUST both be set equal to this
new state (i.e: down(4) or adminDown(5)). The two instances
of bfdSessDiag in this notification indicate the range
of indexes that are affected. Note that all the indexes
of the two ends of the range can be derived from the
instance identifiers of these two objects. For
cases where a contiguous range of sessions
have transitioned into the down(4) or adminDown(5) states
at roughly the same time, the device SHOULD issue a single
notification for each range of contiguous indexes in
an effort to minimize the emission of a large number
of notifications. If a notification has to be
issued for just a single bfdSessEntry, then
the instance identifier (and values) of the two
bfdSessDiag objects MUST be the identical."

::= { bfdNotifications 2 }

- Ed Note: We need to add notification for changes
- when the two ends automatically negotiate to a new detection time
- value or when detection multiplier changes.
- Similarly, changes in the operating mode (bfdSessOperMode)
- also need to be notified.

- Module compliance.

bfdGroups

OBJECT IDENTIFIER ::= { bfdConformance 1 }

bfdCompliances

OBJECT IDENTIFIER ::= { bfdConformance 2 }

- Compliance requirement for fully compliant implementations.

bfdModuleFullCompliance MODULE-COMPLIANCE

STATUS current
DESCRIPTION "Compliance statement for agents that provide full support for BFD-MIB. Such devices can then be monitored and also be configured using this MIB module."

MODULE -- This module.

MANDATORY-GROUPS {
 bfdSessionGroup,
 bfdSessionPerfGroup,
 bfdSessionPerfHCGroup,
 bfdNotificationGroup
}

GROUP bfdSessionPerfHCGroup
DESCRIPTION "This group is mandatory for those bfdPerfTable entries for which any of the objects bfdSessPerfPktInHC or bfdSessPerfPktOutHC wraps around too quickly based on the criteria specified in [RFC 2863](#) for high-capacity counters."

GROUP bfdNotificationGroup
DESCRIPTION "This group is only mandatory for those implementations which can efficiently implement the notifications contained in this group."

OBJECT bfdSessAddrType
SYNTAX InetAddressType { unknown(0), ipv4(1), ipv6(2) }
DESCRIPTION "Only unknown(0), ipv4(1) and ipv6(2) support is required."

OBJECT bfdSessAddr
SYNTAX InetAddress (SIZE(0|4|16))
DESCRIPTION "An implementation is only required to support unknown(0), ipv4(1) and ipv6(2) sizes."

::= { bfdCompliances 1 }

-- Read-Only Conformance TBD...

-- Units of conformance.

bfdSessionGroup OBJECT-GROUP
OBJECTS {
 bfdSessNotificationsEnable,
 bfdAdminStatus,


```
    bfdVersionNumber,
    bfdSessApplicationId,
    bfdSessDiscriminator,
    bfdSessAddrType,
    bfdSessAddr,
    bfdSessRemoteDiscr,
    bfdSessUdpPort,
    bfdSessState,
    bfdSessRemoteHeardFlag,
    bfdSessDiag,
    bfdSessOperMode,
    bfdSessDemandModeDesiredFlag,
    bfdSessEchoFuncModeDesiredFlag,
    bfdSessControlPlanIndepFlag,
    bfdSessDesiredMinTxInterval,
    bfdSessDesiredMinRxInterval,
    bfdSessDesiredMinEchoRxInterval,
    bfdSessDetectMult,
    bfdSessStorType,
    bfdSessRowStatus,
    bfdSessMapBfdIndex,
    bfdSessAuthPresFlag,
    bfdSessAuthenticationType
}
STATUS current
DESCRIPTION
    "Collection of objects needed for BFD sessions."
::= { bfdGroups 1 }
```

```
bfdSessionPerfGroup OBJECT-GROUP
    OBJECTS {
        bfdSessPerfPktIn,
        bfdSessPerfPktOut,
        bfdSessUpTime,
        bfdSessPerfLastSessDownTime,
        bfdSessPerfLastCommLostDiag,
        bfdSessPerfSessUpCount,
        bfdSessPerfDiscTime
    }
STATUS current
DESCRIPTION
    "Collection of objects needed to monitor the
    performance of BFD sessions."
::= { bfdGroups 2 }
```

```
bfdSessionPerfHCGroup OBJECT-GROUP
```

OBJECTS {

BFD Working Group

Expires January 2005

[Page 20]


```
        bfdSessPerfPktInHC,
        bfdSessPerfPktOutHC
    }
    STATUS    current
    DESCRIPTION
        "Collection of objects needed to monitor the
        performance of BFD sessions for which the
        values of bfdSessPerfPktIn, bfdSessPerfPktOut
        wrap around too quickly."
    ::= { bfdGroups 3 }

bfdNotificationGroup NOTIFICATION-GROUP
    NOTIFICATIONS {
        bfdSessUp,
        bfdSessDown
    }
    STATUS    current
    DESCRIPTION
        "Set of notifications implemented in this
        module."
    ::= { bfdGroups 4 }

END
```

6. Security Considerations

There are a number of management objects defined in this MIB module with a MAX-ACCESS clause of read-write and/or read-create. Such objects may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure "for example by using IPsec", even then, there is no control as to who on the secure network is allowed to access and GET/SET "read/change/create/delete" the objects in these MIB modules.

It is RECOMMENDED that implementers consider the security features as provided by the SNMPv3 framework "see [\[RFC3410\]](#), [section 8](#)",

including full support for the SNMPv3 cryptographic mechanisms "for authentication and privacy".

Further, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of this MIB module, is properly configured to give access to the objects only to those principals "users" that have legitimate rights to indeed GET or SET "change/create/delete" them.

7. Acknowledgements

We would like to thank David Ward for his comments and suggestions.

8. Reference

8.1 Normative References

- [BFD] Katz, D., and Ward, D., "Bidirectional Forwarding Detection", [draft-ietf-bfd-base-02.txt](#).
- [BFD-SHARED] Bidirectional Forwarding Detection over Shared Interfaces, work in progress.
- [BFD-LSP] Aggarwal, R., Kompella, K., T. D. Nadeau, and G. Swallow BFD For MPLS LSPs, [draft-ietf-bfd-mpls-01.txt](#).

8.2 Informative References

- [RFC3410] Case, J., Mundy, R., Partain, D. and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Management Framework", [RFC 3410](#), December 2002.
- [RFC3413] Levi, D., Meyer, P., Stewart, B., "SNMP Applications", [RFC 3413](#), December 2002.
- [RFC2434] Narten, T. and H. Alvestrand., "Guidelines for Writing an IANA Considerations Section in RFCs", [BCP 26](#), [RFC 2434](#), October 1998.

9. Authors' Addresses

Thomas D. Nadeau
Cisco Systems, Inc.
300 Beaver Brook Road
Boxboro, MA 01719

Phone: +1-978-936-1470

Email: tnadeau@cisco.com

Zafar Ali
Cisco Systems Inc.
100 South Main St. #200
Ann Arbor, MI 48104, USA.
Phone: +1-734-276-2459
Email: zali@cisco.com

10. Full Copyright Statement

Copyright (C) The Internet Society (2005). This document is subject to the rights, licenses and restrictions contained in [BCP 78](#), and except as set forth therein, the authors retain all their rights.

This document and the information contained herein are provided on an "AS IS" basis and THE CONTRIBUTOR, THE ORGANIZATION HE/SHE REPRESENTS OR IS SPONSORED BY (IF ANY), THE INTERNET SOCIETY AND THE INTERNET ENGINEERING TASK FORCE DISCLAIM ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

11. IANA Considerations

There is one MIB module contained in this document. The following "IANA Considerations" subsection requests IANA for a new assignment under the mib-2 subtree. New assignments can only be made via a Standards Action as specified in [[RFC2434](#)].

11.1. IANA Considerations for BFD-STD-MIB

The IANA is requested to assign { mib-2 XXX } to the MPLS-L3VPN-STD-MIB module specified in this document.

12. Intellectual Property Statement

The IETF takes no position regarding the validity or scope of any Intellectual Property Rights or other rights that might be claimed to pertain to the implementation or use of the technology described in this document or the extent to which any license under such rights might or might not be available; nor does it represent that it has made any independent effort to identify any such rights. Information on the procedures with respect to rights in RFC documents can be found in [BCP 78](#) and [BCP 79](#).

Copies of IPR disclosures made to the IETF Secretariat and any assurances of licenses to be made available, or the result of an attempt made to obtain a general license or permission for the use of such proprietary rights by implementers or users of this specification can be obtained from the IETF on-line IPR repository at <http://www.ietf.org/ipr>.

The IETF invites any interested party to bring to its attention any copyrights, patents or patent applications, or other proprietary rights that may cover technology that may be required to implement this standard. Please address the information to the IETF at ietf-ipr@ietf.org.

