

Workgroup: CCAMP Working Group
Internet-Draft:
draft-ietf-ccamp-rfc9093-bis-00
Obsoletes: [9093](#) (if approved)
Published: 7 March 2022
Intended Status: Standards Track
Expires: 8 September 2022
Authors: H. Zheng Y. Lee A. Guo
 Huawei Samsung Futurewei Technologies
 V. Lopez D. King D. Beller
 Nokia University of Lancaster Nokia
 S. Belotti I. Busi E. Le Rouzic
 Nokia Huawei Orange

A YANG Data Model for Layer 0 Types

Abstract

This document defines a collection of common data types and groupings in the YANG data modeling language. These derived common types and groupings are intended to be imported by modules that model Layer 0 optical Traffic Engineering (TE) configuration and state capabilities such as Wavelength Switched Optical Networks (WSOs) and flexi-grid Dense Wavelength Division Multiplexing (DWDM) networks.

This document obsoletes RFC 9093.

Status of This Memo

This Internet-Draft is submitted in full conformance with the provisions of BCP 78 and BCP 79.

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF). Note that other groups may also distribute working documents as Internet-Drafts. The list of current Internet-Drafts is at <https://datatracker.ietf.org/drafts/current/>.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

This Internet-Draft will expire on 8 September 2022.

Copyright Notice

Copyright (c) 2022 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to BCP 78 and the IETF Trust's Legal Provisions Relating to IETF Documents (<https://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Revised BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Revised BSD License.

Table of Contents

- [1. Introduction](#)
 - [1.1. Terminology and Notations](#)
 - [1.2. Prefix in Data Node Names](#)
- [2. Layer 0 Types Module Contents](#)
- [3. YANG Module for Layer 0 Types](#)
- [4. Security Considerations](#)
- [5. IANA Considerations](#)
- [6. References](#)
 - [6.1. Normative References](#)
 - [6.2. Informative References](#)
- [Appendix A. Changes from RFC 9093](#)
- [Acknowledgments](#)
- [Contributors](#)
- [Authors' Addresses](#)

1. Introduction

YANG [[RFC7950](#)] is a data modeling language used to model configuration data, state data, Remote Procedure Calls, and notifications for network management protocols such as the Network Configuration Protocol (NETCONF) [[RFC6241](#)]. The YANG language supports a small set of built-in data types and provides mechanisms to derive other types from the built-in types.

This document introduces a collection of common data types derived from the built-in YANG data types. The derived types and groupings are designed to be the common types applicable for modeling Traffic Engineering (TE) features as well as non-TE features (e.g., physical network configuration aspects) for Layer 0 optical networks in model(s) defined outside of this document. The applicability of Layer 0 types specified in this document includes Wavelength Switched Optical Networks (WSONs) [[RFC6163](#)] [[ITU-T G.698.2](#)] and flexi-grid Dense Wavelength Division Multiplexing (DWDM) networks [[RFC7698](#)] [[ITU-T G.694.1](#)].

[Editors' Note]: This is the introduction from draft-ietf-ccamp-layer0-types-ext-01, to be reconciled with the introduction from RFC9093 above

YANG [RFC7950] is a data modeling language used to model configuration data, state data, Remote Procedure Calls, and notifications for network management protocols such as NETCONF [RFC6241]. The YANG language supports a small set of built-in data types and provides mechanisms to derive other types from the built-in types.

This document introduces a collection of common data types derived from the built-in YANG data types. The derived types and groupings are designed to be the common types applicable for modeling Traffic Engineering (TE) features as well as non-TE features (e.g., physical network configuration aspect) for Layer 0 optical networks in model(s) defined outside of this document.

This document adds new type definitions to the YANG modules and obsoletes [RFC9093]. For further details, see the revision statements of the YANG module in [Section 3](#) or the summary in [Appendix A](#).

1.1. Terminology and Notations

Refer to [RFC7446] and [RFC7581] for the key terms used in this document, and the terminology for describing YANG data models can be found in [RFC7950].

The YANG data model in this document conforms to the Network Management Datastore Architecture defined in [RFC8342].

1.2. Prefix in Data Node Names

In this document, names of data nodes and other data model objects are prefixed using the standard prefix associated with the corresponding YANG imported modules.

Prefix	YANG module	Reference
l0-types	ietf-layer0-types	RFCXXXX

Table 1: Prefixes and corresponding YANG modules

RFC Editor Note: Please replace XXXX with the RFC number assigned to this document.

The YANG module "ietf-layer0-types" (defined in [Section 3](#)) references [RFC4203], [RFC6163], [RFC6205], [RFC7698], [RFC7699], [RFC8363], [ITU-T_G.694.1], and [ITU-T_G.694.2].

2. Layer 0 Types Module Contents

This document defines a YANG module for common Layer 0 types, `ietf-layer0-types`. This module is used for WSON and flexi-grid DWDM networks. The "ietf-layer0-types" module contains the following YANG reusable types and groupings:

l0-grid-type A base YANG identity for the grid type as defined in [\[RFC6163\]](#) and [\[RFC7698\]](#).

dwdm-ch-spc-type A base YANG identity for the DWDM channel-spacing type as defined in [\[RFC6205\]](#).

cwdm-ch-spc-type A base YANG identity for the Coarse Wavelength Division Multiplexing (CWDM) channel-spacing type as defined in [\[RFC6205\]](#).

wson-label-start-end The WSON label range was defined in [\[RFC6205\]](#), and the generic topology model defines the label-start/label-end in [\[RFC8795\]](#). This grouping shows the WSON-specific label-start and label-end information.

wson-label-hop The WSON label range was defined in [\[RFC6205\]](#), and the generic topology model defines the label-hop in [\[RFC8795\]](#). This grouping shows the WSON-specific label-hop information.

l0-label-range-info A YANG grouping that defines the Layer 0 label range information applicable for WSON as defined in [\[RFC6205\]](#). This grouping is used in the flexi-grid DWDM by adding more flexi-grid-specific parameters.

wson-label-step A YANG grouping that defines label steps for WSON as defined in [\[RFC8776\]](#).

flexi-grid-label-start-end The flexi-grid label range was defined in [\[RFC7698\]](#), and the generic topology model defines the label-start/label-end in [\[RFC8795\]](#). This grouping shows the flexi-grid-specific label- start and label-end information.

flexi-grid-label-hop The flexi-grid label range was defined in [\[RFC7698\]](#), and the generic topology model defines the label-hop in [\[RFC8795\]](#). This grouping shows the WSON-specific label-hop information.

flexi-grid-label-range-info A YANG grouping that defines flexi-grid label range information as defined in [\[RFC7698\]](#) and [\[RFC8363\]](#).

flexi-grid-label-step A YANG grouping that defines flexi-grid label steps as defined in [\[RFC8776\]](#).

transceiver-capabilities

a YANG grouping to define the transceiver capabilities (also called "modes") needed to determine optical signal compatibility.

standard-mode a YANG grouping for ITU-T G.698.2 standard mode that guarantees interoperability.

organizational-mode :a YANG grouping to define transponder operational mode supported by organizations or vendors.

common-explicit-mode a YANG grouping to define the list of attributes related to optical impairments limits in case of transceiver explicit mode. This grouping should be the same used in [[I-D.ietf-ccamp-dwdm-if-param-yang](#)].

common-organizational-explicit-mode a YANG grouping to define the common capabilities attributes limit range in case of operational mode and explicit mode. Also this grouping should be used in [[I-D.ietf-ccamp-dwdm-if-param-yang](#)].

cd-pmd-penalty a YANG grouping to define the triplet used as entries in the list optional penalty associated with a given accumulated CD and PMD. This list of triplet cd, pmd, penalty can be used to sample the function $\text{penalty} = f(\text{CD}, \text{PMD})$.

3. YANG Module for Layer 0 Types

<CODE BEGINS> file "ietf-layer0-types@2022-03-07.yang"

```
module ietf-layer0-types {
  yang-version 1.1;
  namespace "urn:ietf:params:xml:ns:yang:ietf-layer0-types";
  prefix l0-types;

  organization
    "IETF CCAMP Working Group";
  contact
    "WG Web: <https://datatracker.ietf.org/wg/ccamp/>
    WG List: <mailto:ccamp@ietf.org>

    Editor: Haomian Zheng
      <mailto:zhenghaomian@huawei.com>

    Editor: Young Lee
      <mailto:younglee.tx@gmail.com>

    Editor: Aihua Guo
      <mailto:aihuaguo.ietf@gmail.com>

    Editor: Victor Lopez
      <mailto:victor.lopez@nokia.com>

    Editor: Daniel King
      <mailto:d.king@lancaster.ac.uk>";

  description
    "This module defines Optical Layer 0 types. This module
    provides groupings that can be applicable to Layer 0
    Fixed Optical Networks (e.g., CWDM (Coarse Wavelength
    Division Multiplexing) and DWDM (Dense Wavelength Division
    Multiplexing)) and flexi-grid optical networks.

    Copyright (c) 2022 IETF Trust and the persons identified
    as authors of the code. All rights reserved.

    Redistribution and use in source and binary forms, with
    or without modification, is permitted pursuant to, and
    subject to the license terms contained in, the Simplified
    BSD License set forth in Section 4.c of the IETF Trust's
    Legal Provisions Relating to IETF Documents
    (https://trustee.ietf.org/license-info).

    This version of this YANG module is part of RFC 9093; see
    the RFC itself for full legal notices.";

  revision 2022-03-07 {
    description
```

```

        "To be updated";
    reference
        "RFC XXXX: A YANG Data Model for Layer 0 Types";
}
revision 2021-08-13 {
    description
        "Initial version";
    reference
        "RFC 9093: A YANG Data Model for Layer 0 Types";
}

/*
 * Identities
 */

identity l0-grid-type {
    description
        "Layer 0 grid type";
    reference
        "RFC 6163: Framework for GMPLS and Path Computation Element
        (PCE) Control of Wavelength Switched Optical Networks (WSONs),
        ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
        DWDM frequency grid,
        ITU-T G.694.2 (12/2003): Spectral grids for WDM applications:
        CWDM wavelength grid";
}

identity flexi-grid-dwdm {
    base l0-grid-type;
    description
        "Flexi-grid";
    reference
        "RFC 7698: Framework and Requirements for GMPLS-Based Control
        of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
        Networks,
        ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
        DWDM frequency grid";
}

identity wson-grid-dwdm {
    base l0-grid-type;
    description
        "DWDM grid";
    reference
        "RFC 6163: Framework for GMPLS and Path Computation Element
        (PCE) Control of Wavelength Switched Optical Networks (WSONs),
        ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
        DWDM frequency grid";
}

```

```
identity wson-grid-cwdm {
  base l0-grid-type;
  description
    "CWDM grid";
  reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers,
    ITU-T G.694.2 (12/2003): Spectral grids for WDM applications:
    CWDM wavelength grid";
}
```

```
identity dwdm-ch-spc-type {
  description
    "DWDM channel-spacing type";
  reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers,
    ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
    DWDM frequency grid";
}
```

```
identity dwdm-100ghz {
  base dwdm-ch-spc-type;
  description
    "100 GHz channel spacing";
}
```

```
identity dwdm-50ghz {
  base dwdm-ch-spc-type;
  description
    "50 GHz channel spacing";
}
```

```
identity dwdm-25ghz {
  base dwdm-ch-spc-type;
  description
    "25 GHz channel spacing";
}
```

```
identity dwdm-12p5ghz {
  base dwdm-ch-spc-type;
  description
    "12.5 GHz channel spacing";
}
```

```
identity flexi-ch-spc-type {
  description
    "Flexi-grid channel-spacing type";
}
```

```

reference
  "RFC 7698: Framework and Requirements for GMPLS-Based Control
    of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
    Networks,
    ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
    DWDM frequency grid";
}

identity flexi-ch-spc-6p25ghz {
  base flexi-ch-spc-type;
  description
    "6.25 GHz channel spacing";
}

identity flexi-slot-width-granularity {
  description
    "Flexi-grid slot width granularity";
}

identity flexi-swg-12p5ghz {
  base flexi-slot-width-granularity;
  description
    "12.5 GHz slot width granularity";
}

identity cwdm-ch-spc-type {
  description
    "CWDM channel-spacing type";
  reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
      Label Switching Routers,
      ITU-T G.694.2 (12/2003): Spectral grids for WDM applications:
      CWDM wavelength grid";
}

identity cwdm-20nm {
  base cwdm-ch-spc-type;
  description
    "20nm channel spacing";
}

identity modulation {
  description "base identity for modulation type";
}

identity QPSK {
  base modulation;
  description
    "QPSK (Quadrature Phase Shift Keying) modulation";
}

```

```

}

identity DP-QPSK {
    base modulation;
    description
        "DP-QPSK (Dual Polarization Quadrature
        Phase Shift Keying) modulation";
}

identity QAM8 {
    base modulation;
    description
        "8QAM (8-State Quadrature Amplitude Modulation) modulation";
}

identity QAM16 {
    base modulation;
    description
        "QAM16 (Quadrature Amplitude Modulation)";
}

identity DP-QAM8 {
    base modulation;
    description
        "DP-QAM8 (Dual Polarization Quadrature Amplitude Modulation)";
}

identity DC-DP-QAM8 {
    base modulation;
    description
        "DC DP-QAM8 (Dual Carrier Dual Polarization Quadrature
        Amplitude Modulation)";
}

identity DP-QAM16 {
    base modulation;
    description
        "DP-QAM16 (Dual Polarization Quadrature Amplitude
        Modulation)";
}

identity DC-DP-QAM16 {
    base modulation;
    description
        "DC DP-QAM16 (Dual Carrier Dual Polarization Quadrature
        Amplitude Modulation)";
}

identity fec-type {
    description

```

```

    "Base identity from which specific FEC
    (Forward Error Correction) type identities are derived.";
}

identity g-fec {
    base fec-type;
    description
        "G-FEC (Generic-FEC)";
}
identity e-fec {
    base fec-type;
    description
        "E-FEC (Enhanced-FEC)";
}
identity no-fec {
    base fec-type;
    description
        "No FEC";
}

identity reed-solomon {
    base fec-type;
    description
        "Reed-Solomon error correction";
}

identity hamming-code {
    base fec-type;
    description
        "Hamming Code error correction";
}

identity golay {
    base fec-type;
    description "Golay error correction";
}

identity line-coding {
    description
        "base line-coding class";
    reference
        "ITU-T G.698.2-201811 section 7";
}

identity line-coding-NRZ-2p5G {
    base line-coding;
    description
        "ITU-T G.698.2-201811 section 7 table 8-1";
}

```

```

identity line-coding-NRZ-OTU1 {
    base line-coding;
    description
        "ITU-T G.698.2-201811 section 7 table 8-2";
}

identity line-coding-NRZ-10G {
    base line-coding;
    description
        "ITU-T G.698.2-201811 section 7 table 8-3/8-5";
}

identity line-coding-NRZ-OTU2 {
    base line-coding;
    description
        "ITU-T G.698.2-201811 section 7 table 8-4/8-6";
}

identity wavelength-assignment {
    description
        "Wavelength selection base";
    reference
        "RFC6163:Framework for GMPLS and Path Computation Element
        (PCE) Control of Wavelength Switched Optical Networks (WSOs)";
}

identity first-fit-wavelength-assignment {
    base wavelength-assignment;
    description
        "All the available wavelengths are numbered,
        and this WA (Wavelength Assignment) method chooses
        the available wavelength with the lowest index";
}

identity random-wavelength-assignment {
    base wavelength-assignment;
    description
        "This WA method chooses an available
        wavelength randomly";
}

identity least-loaded-wavelength-assignment {
    base wavelength-assignment;
    description
        "This WA method selects the wavelength that
        has the largest residual capacity on the most loaded
        link along the route (in multi-fiber networks)";
}

```

```
identity term-type {
    description
        "Termination type";
    reference
        "ITU-T G.709: Interfaces for the Optical Transport Network";
}

identity term-phys {
    base term-type;
    description
        "Physical layer termination";
}

identity term-otu {
    base term-type;
    description
        "OTU (Optical Transport Unit) termination";
}

identity term-odu {
    base term-type;
    description
        "ODU (Optical Data Unit) termination";
}

identity term-opu {
    base term-type;
    description
        "OPU (Optical Payload Unit) termination";
}

identity otu-type {
    description
        "Base identity from which specific OTU identities are derived";
    reference
        "ITU-T G.709: Interfaces for the Optical Transport Network";
}

identity OTU1 {
    base otu-type;
    description
        "OTU1 (2.66 Gb/s)";
}

identity OTU1e {
    base otu-type;
    description
        "OTU1e (11.04 Gb/s)";
}
```

```
identity OTU1f {
    base otu-type;
    description
        "OTU1f (11.27 Gb/s)";
}

identity OTU2 {
    base otu-type;
    description
        "OTU2 (10.70 Gb/s)";
}

identity OTU2e {
    base otu-type;
    description
        "OTU2e (11.09 Gb/s)";
}

identity OTU2f {
    base otu-type;
    description
        "OTU2f (11.31G)";
}

identity OTU3 {
    base otu-type;
    description
        "OTU3 (43.01 Gb/s)";
}

identity OTU3e1 {
    base otu-type;
    description
        "OTU3e1 (44.57 Gb/s)";
}

identity OTU3e2 {
    base otu-type;
    description
        "OTU3e2 (44.58 Gb/s)";
}

identity OTU4 {
    base otu-type;
    description
        "OTU4 (111.80 Gb/s)";
}

identity OTUCn {
    base otu-type;
```

```

    description
        "OTUCn (n x 105.25 Gb/s)";
}

identity type-power-mode {
    description
        "power equalization mode used within the
        OMS and its elements";
}

identity power-spectral-density {
    base type-power-mode;
    description
        "all elements must use power spectral density (W/Hz)";
}

identity carrier-power {
    base type-power-mode;
    description
        "all elements must use power (dBm)";
}

/*
 * Typedefs
 */

typedef dwdm-n {
    type int16;
    description
        "The given value 'N' is used to determine the nominal central
        frequency.

        The nominal central frequency, 'f', is defined by:
        
$$f = 193100.000 \text{ GHz} + N \times \text{channel spacing (measured in GHz),}$$


        where 193100.000 GHz (193.100000 THz) is the ITU-T 'anchor
        frequency' for transmission over the DWDM grid, and where
        'channel spacing' is defined by the dwdm-ch-spc-type.";
    reference
        "RFC6205: Generalized Labels for Lambda-Switch-Capable (LSC)
        Label Switching Routers,
        ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
        DWDM frequency grid";
}

typedef cwdm-n {
    type int16;
    description
        "The given value 'N' is used to determine the nominal central
        wavelength.

```

```

    The nominal central wavelength is defined by:
        Wavelength = 1471 nm + N x channel spacing (measured in nm)

    where 1471 nm is the conventional 'anchor wavelength' for
    transmission over the CWDM grid, and where 'channel spacing'
    is defined by the cwm-ch-spc-type.";
reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers,
    ITU-T G.694.2 (12/2003): Spectral grids for WDM applications:
    CWDM wavelength grid";
}

typedef flexi-n {
    type int16;
    description
        "The given value 'N' is used to determine the nominal central
        frequency.

        The nominal central frequency, 'f', is defined by:
            f = 193100.000 GHz + N x channel spacing (measured in GHz),

        where 193100.000 GHz (193.100000 THz) is the ITU-T 'anchor
        frequency' for transmission over the DWDM grid, and where
        'channel spacing' is defined by the flexi-ch-spc-type.

        Note that the term 'channel spacing' can be substituted by the
        term 'nominal central frequency granularity' defined in
        clause 8 of ITU-T G.694.1.";
reference
    "RFC 7698: Framework and Requirements for GMPLS-Based Control
    of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
    Networks,
    ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
    DWDM frequency grid";
}

typedef flexi-m {
    type uint16;
    description
        "The given value 'M' is used to determine the slot width.

        A slot width is defined by:
            slot width = M x SWG (measured in GHz),

        where SWG is defined by the flexi-slot-width-granularity.";
reference
    "RFC 7698: Framework and Requirements for GMPLS-Based Control
    of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)

```

```

    Networks.
    ITU-T G.694.1 (10/2020): Spectral grids for WDM applications:
    DWDM frequency grid";
}

typedef operational-mode {
    type string;
    description
        "Organization/vendor specific mode that guarantees
        interoperability.";
    reference "ITU-T G.698.2 (11/2018)";
}

typedef standard-mode {
    type string;
    description
        "ITU-T G.698.2 standard mode that guarantees
        interoperability.
        It must be an string with the following format:
        B-DScW-ytz(v) where all these attributes
        are conformant
        to the ITU-T recommendation";
    reference "ITU-T G.698.2 (11/2018)";
}

typedef organization-identifier {
    type string;
    description
        "vendor/organization identifier that uses a private mode
        out of already defined in G.698.2 ITU-T application-code";
    reference
        "RFC7581: Routing and Wavelength Assignment Information
        Encoding for Wavelength Switched Optical Networks";
}

typedef frequency-thz {
    type decimal64 {
        fraction-digits 6;
    }
    units THz;
    description
        "The DWDM frequency in THz, e.g., 193.112500";
    reference
        "RFC6205: Generalized Labels for
        Lambda-Switch-Capable (LSC) Label Switching Routers";
}

typedef frequency-ghz {
    type decimal64 {
        fraction-digits 3;
    }

```

```

    }
    units GHz;
    description
        "The DWDM frequency in GHz, e.g., 193112.500";
    reference
        "RFC6205: Generalized Labels for
        Lambda-Switch-Capable (LSC) Label Switching Routers";
}

typedef dbm-t {
    type int32;
    units ".01dbm";
    description
        "Amplifiers and Transceivers Power in dBm.";
}

typedef snr {
    type decimal64 {
        fraction-digits 2;
    }
    units "dB@0.1nm";
    description
        "(Optical) Signal to Noise Ratio measured over 0.1 nm
        resolution bandwidth";
}

typedef snr-or-null {
    type union {
        type snr;
        type empty;
    }
    description
        "(Optical) Signal to Noise Ratio measured over 0.1 nm
        resolution bandwidth, when known, or an empty value when
        unknown.";
}

typedef fiber-type {
    type enumeration {
        enum G.652 {
            description "G.652 Standard Singlemode Fiber";
        }
        enum G.654 {
            description "G.654 Cutoff Shifted Fiber";
        }
        enum G.653 {
            description "G.653 Dispersion Shifted Fiber";
        }
        enum G.655 {

```

```

        description "G.655 Non-Zero Dispersion Shifted Fiber";
    }
    enum G.656 {
        description "G.656 Non-Zero Dispersion for Wideband
            Optical Transport";
    }
    enum G.657 {
        description "G.657 Bend-Insensitive Fiber";
    }
}
description
    "ITU-T based fiber-types";
}

typedef decimal-2-digits {
    type decimal64 {
        fraction-digits 2;
    }
    description
        "A decimal64 value with two digits.";
}

typedef decimal-2-digits-or-null {
    type union {
        type decimal-2-digits;
        type empty;
    }
    description
        "A decimal64 value with two digits, when the value is know or
        an empty value when the value is not known.";
}

typedef power-in-db {
    type decimal-2-digits;
    units dB;
    description
        "The power in dB.";
}

typedef power-in-db-or-null {
    type union {
        type power-in-db;
        type empty;
    }
    description
        "The power in dB, when it is known or an empty value when the
        power is not known.";
}

```

```

typedef power-in-dbm {
    type decimal-2-digits;
    units dBm;
    description
        "The power in dBm.";
}

typedef power-in-dbm-or-null {
    type union {
        type power-in-dbm;
        type empty;
    }
    description
        "The power in dBm, when it is known or an empty value when the
        power is not known.";
}

/*
 * Groupings
 */

grouping wson-label-start-end {
    description
        "The WSON label-start or label-end used to specify WSON label
        range.";
    choice grid-type {
        description
            "Label for DWDM or CWDM grid";
        case dwdm {
            leaf dwdm-n {
                when "derived-from-or-self ../../../../grid-type,
                    \"wson-grid-dwdm\")" {
                    description
                        "Valid only when grid type is DWDM.";
                }
                type 10-types:dwdm-n;
                description
                    "The central frequency of DWDM.";
                reference
                    "RFC 6205: Generalized Labels for Lambda-Switch-Capable
                    (LSC) Label Switching Routers";
            }
        }
        case cwdm {
            leaf cwdm-n {
                when "derived-from-or-self ../../../../grid-type,
                    \"wson-grid-cwdm\")" {
                    description
                        "Valid only when grid type is CWDM.";
                }
            }
        }
    }
}

```

```

    }
    type l0-types:cwdm-n;
    description
        "Channel wavelength computing input.";
    reference
        "RFC 6205: Generalized Labels for Lambda-Switch-Capable
        (LSC) Label Switching Routers";
    }
}
}
reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers";
}

```

```

grouping wson-label-hop {
    description
        "Generic label-hop information for WSON";
    choice grid-type {
        description
            "Label for DWDM or CWDM grid";
        case dwdm {
            choice single-or-super-channel {
                description
                    "single or super channel";
                case single {
                    leaf dwdm-n {
                        type l0-types:dwdm-n;
                        description
                            "The given value 'N' is used to determine the
                            nominal central frequency.";
                    }
                }
            }
        case super {
            leaf-list subcarrier-dwdm-n {
                type l0-types:dwdm-n;
                description
                    "The given values 'N' are used to determine the
                    nominal central frequency for each subcarrier
                    channel.";
                reference
                    "ITU-T Recommendation G.694.1: Spectral grids for
                    WDM applications: DWDM frequency grid";
            }
        }
    }
}
case cwdm {
    leaf cwdm-n {

```

```

        type l0-types:cwdm-n;
        description
            "The given value 'N' is used to determine the nominal
            central wavelength.";
        reference
            "RFC 6205: Generalized Labels for Lambda-Switch-Capable
            (LSC) Label Switching Routers";
    }
}
reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers";
}

grouping l0-label-range-info {
    description
        "Information about Layer 0 label range.";
    leaf grid-type {
        type identityref {
            base l0-grid-type;
        }
        description
            "Grid type";
    }
    leaf priority {
        type uint8;
        description
            "Priority in Interface Switching Capability Descriptor
            (ISCD).";
        reference
            "RFC 4203: OSPF Extensions in Support of Generalized
            Multi-Protocol Label Switching (GMPLS)";
    }
    reference
        "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
        Label Switching Routers";
}

grouping wson-label-step {
    description
        "Label step information for WSON";
    choice l0-grid-type {
        description
            "Grid type: DWDM, CWDM, etc.";
        case dwdm {
            leaf wson-dwdm-channel-spacing {
                when "derived-from-or-self(..../grid-type,
                \"wson-grid-dwdm\")" {

```

```

        description
            "Valid only when grid type is DWDM.";
    }
    type identityref {
        base dwdm-ch-spc-type;
    }
    description
        "Label-step is the channel spacing (GHz), e.g., 100.000,
        50.000, 25.000, or 12.500 GHz for DWDM.";
    reference
        "RFC 6205: Generalized Labels for Lambda-Switch-Capable
        (LSC) Label Switching Routers";
    }
}
case cwdm {
    leaf wson-cwdm-channel-spacing {
        when "derived-from-or-self ../../grid-type,
            \"wson-grid-cwdm\"" {
            description
                "Valid only when grid type is CWDM.";
        }
        type identityref {
            base cwdm-ch-spc-type;
        }
        description
            "Label-step is the channel spacing (nm), i.e., 20 nm
            for CWDM, which is the only value defined for CWDM.";
        reference
            "RFC 6205: Generalized Labels for Lambda-Switch-Capable
            (LSC) Label Switching Routers";
        }
    }
}
reference
    "RFC 6205: Generalized Labels for Lambda-Switch-Capable (LSC)
    Label Switching Routers,
    ITU-T G.694.2 (12/2003): Spectral grids for WDM applications:
    CWDM wavelength grid";
}

grouping flexi-grid-label-start-end {
    description
        "The flexi-grid label-start or label-end used to specify
        flexi-grid label range.";
    leaf flexi-n {
        type l0-types:flexi-n;
        description
            "The given value 'N' is used to determine the nominal
            central frequency.";
    }
}

```

```

    }
    reference
        "RFC 7698: Framework and Requirements for GMPLS-Based Control
        of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
        Networks";
    }

grouping flexi-grid-frequency-slot {
    description
        "Flexi-grid frequency slot grouping.";
    uses flexi-grid-label-start-end;
    leaf flexi-m {
        type l0-types:flexi-m;
        description
            "The given value 'M' is used to determine the slot width.";
    }
    reference
        "RFC 7698: Framework and Requirements for GMPLS-Based Control
        of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
        Networks";
    }

grouping flexi-grid-label-hop {
    description
        "Generic label-hop information for flexi-grid";
    choice single-or-super-channel {
        description
            "single or super channel";
        case single {
            uses flexi-grid-frequency-slot;
        }
        case super {
            list subcarrier-flexi-n {
                key "flexi-n";
                uses flexi-grid-frequency-slot;
                description
                    "List of subcarrier channels for flexi-grid super
                    channel.";
            }
        }
    }
    reference
        "RFC 7698: Framework and Requirements for GMPLS-Based Control
        of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM)
        Networks";
    }

grouping flexi-grid-label-range-info {
    description

```

```

    "Flexi-grid-specific label range related information";
uses l0-label-range-info;
container flexi-grid {
    description
        "flexi-grid definition";
    leaf slot-width-granularity {
        type identityref {
            base flexi-slot-width-granularity;
        }
        default "flexi-swg-12p5ghz";
        description
            "Minimum space between slot widths. Default is 12.500
            GHz.";
        reference
            "RFC 7698: Framework and Requirements for GMPLS-Based
            Control of Flexi-Grid Dense Wavelength Division
            Multiplexing (DWDM) Networks";
    }
    leaf min-slot-width-factor {
        type uint16 {
            range "1..max";
        }
        default "1";
        description
            "A multiplier of the slot width granularity, indicating
            the minimum slot width supported by an optical port.

            Minimum slot width is calculated by:
            Minimum slot width (GHz) =
            min-slot-width-factor * slot-width-granularity.";
        reference
            "RFC 8363: GMPLS OSPF-TE Extensions in Support of Flexi-
            Grid Dense Wavelength Division Multiplexing (DWDM)
            Networks";
    }

    leaf max-slot-width-factor {
        type uint16 {
            range "1..max";
        }
        must '. >= ../min-slot-width-factor' {
            error-message
                "Maximum slot width must be greater than or equal to
                minimum slot width.";
        }
        description
            "A multiplier of the slot width granularity, indicating
            the maximum slot width supported by an optical port.

```

Maximum slot width is calculated by:

Maximum slot width (GHz) =
max-slot-width-factor * slot-width-granularity

If specified, maximum slot width must be greater than or equal to minimum slot width. If not specified, maximum slot width is equal to minimum slot width.";

reference

"RFC 8363: GMPLS OSPF-TE Extensions in Support of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM) Networks";

```
}  
}  
}
```

grouping flexi-grid-label-step {

description

"Label step information for flexi-grid";

leaf flexi-grid-channel-spacing {

type identityref {

base flexi-ch-spc-type;

}

default "flexi-ch-spc-6p25ghz";

description

"Label-step is the nominal central frequency granularity (GHz), e.g., 6.25 GHz.";

reference

"RFC 7699: Generalized Labels for the Flexi-Grid in Lambda Switch Capable (LSC) Label Switching Routers";

}

leaf flexi-n-step {

type uint8;

description

"This attribute defines the multiplier for the supported values of 'N'.

For example, given a grid with a nominal central frequency granularity of 6.25 GHz, the granularity of the supported values of the nominal central frequency could be 12.5 GHz. In this case, the values of flexi-n should be even and this constraint is reported by setting the flexi-n-step to 2.

This attribute is also known as central frequency granularity in RFC 8363.";

reference

"RFC 8363: GMPLS OSPF-TE Extensions in Support of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM) Networks";

```
}  
}
```

```

/* supported inverse multiplexing capabilities such as
   max. OTSiG:OTSi cardinality
   It is a transponder attribute not transceiver
*/

/*    leaf multiplexing-cap {
        type uint32;
        config false;
        description "supported inverse multiplexing capabilities
            such as max. OTSiG:OTSi cardinality";
    }
*/

grouping transceiver-mode {
    description
        "This grouping is intended to be used for reporting the
        information of a transceiver's mode.";
    choice mode {
        mandatory true;
        description
            "Indicates whether the transceiver's mode is a standard
            mode, an organizational mode or an explicit mode.";
        case G.698.2 {
            uses standard-mode;
        }
        case organizational-mode {
            container organizational-mode {
                description
                    "The set of attributes for an organizational mode";
                uses organizational-mode;
                uses common-organizational-explicit-mode;
            } // container organizational-mode
        }
        case explicit-mode {
            container explicit-mode {
                description
                    "The set of attributes for an explicit mode";
                container supported-modes {
                    description
                        "Container for all the standard and organizational
                        modes supported by the transceiver's explicit
                        mode.";
                }
                leaf-list supported-application-codes {
                    type leafref {
                        path "../.../.../mode-id";
                    }
                }
                must ".../.../.../"
                    + "supported-mode[mode-id=current()]/"

```

```

        + "standard-mode" {
        description
            "The pointer is only for application codes
            supported by transceiver.";
        }
        description
            "List of pointers to the application codes
            supported by the transceiver's explicit mode.";
    }
    leaf-list supported-organizational-modes {
        type leafref {
            path "../.../.../mode-id";
        }
        must "../.../.../..."
            + "supported-mode[mode-id=current()]/"
            + "organizational-mode" {
            description
                "The pointer is only for organizational modes
                supported by transceiver.";
        }
        description
            "List of pointers to the organizational modes
            supported by the transceiver's explicit mode.";
    }
} // container supported-modes
uses common-explicit-mode;
uses common-organizational-explicit-mode;
} // container explicit-mode
} // end of case explicit-mode
} // end of choice
}
grouping transceiver-capabilities {
    description
        "This grouping is intended to be used for reporting the
        capabilities of a transceiver.";

    container supported-modes {
        description
            "Transceiver's supported modes.";
        list supported-mode {
            key "mode-id";
            config false;
            description "list of supported transceiver's modes.";
            leaf mode-id {
                type string {
                    length "1..255";
                }
            }
            description "ID for the supported transceiver's mode.";
        }
    }
}

```

```

        uses transceiver-mode;
    } // list supported-modes
} // container supported-modes
} // grouping transceiver-capabilities

grouping standard-mode {
    description
        "ITU-T G.698.2 standard mode that guarantees interoperability.
        It must be an string with the following format:
        B-DScW-ytz(v) where all these attributes are conformant
        to the ITU-T recomendation";

    leaf standard-mode {
        type standard-mode;
        config false;
        description
            "G.698.2 standard mode";
    }
}

grouping organizational-mode {
    description
        "Transponder operational mode supported by organizations or
        vendor";

    leaf operational-mode {
        type operational-mode;
        config false;
        description
            "configured organization- or vendor-specific
            application identifiers (AI) supported by the transponder";
    }
    leaf organization-identifier {
        type organization-identifier;
        config false;
        description
            "organization identifier that uses organizational
            mode";
    }
}

grouping cd-pmd-penalty {
    description "entries of table; triplet chromatic
    dispersion, polarization mode dispersion and
    associated penalty";

    leaf chromatic-dispersion {
        type union {
            type decimal64 {

```

```

        fraction-digits 2;
        range "0..max";
    }
    type empty;
}
units "ps/nm";
config false;
mandatory true;
description "chromatic dispersion";
}
leaf polarization-mode-dispersion {
    type union {
        type decimal64 {
            fraction-digits 2;
            range "0..max";
        }
        type empty;
    }
    units "ps";
    config false;
    mandatory true;
    description "Polarization mode dispersion";
}
leaf penalty {
    type union {
        type decimal64 {
            fraction-digits 2;
            range "0..max";
        }
        type empty;
    }
    units "dB";
    config false;
    mandatory true;
    description "Associated penalty on the receiver";
}
}

grouping pdl-penalty {
    description
        "entries of table; pair of values polarization dependent loss
        and associated penalty";

    leaf max-polarization-dependent-loss {
        type power-in-db-or-null;
        config false;
        mandatory true;
        description
            "Maximum acceptable accumulate polarization dependent loss";
    }
}

```

```

    }
    leaf penalty {
        type union {
            type uint8;
            type empty;
        }
        units "dB";
        config false;
        mandatory true;
        description "Associated penalty on the receiver";
    }
}

/*
 * This grouping represent the list of attributes related to
 * optical impairment limits for explicit mode
 * (min OSNR, max PMD, max CD, max PDL, Q-factor limit, etc.)
 * In case of standard and operational mode the attributes are
 * implicit
 */

grouping common-explicit-mode {
    description "Attributes capabilities related to
explicit mode of an optical transceiver";

    leaf line-coding-bitrate {
        type identityref {
            base line-coding;
        }
        config false;
        description
            "Bit rate/line coding of the optical tributary signal.";
        reference
            "ITU-T G.698.2 section 7.1.2";
    }
    leaf bitrate {
        type uint16;
        units "Gbit/sec";
        config false;
        description
            "The gross bitrate (e.g., 100, 200) of the optical tributary
            signal.";
    }
    leaf max-polarization-mode-dispersion {
        type decimal64 {
            fraction-digits 2;
            range "0..max";
        }
        units "ps";
    }
}

```

```

    config false;
    description
        "Maximum acceptable accumulated polarization mode
        dispersion on the receiver";
}
leaf max-chromatic-dispersion {
    type decimal64 {
        fraction-digits 2;
        range "0..max";
    }
    units "ps/nm";
    config false;
    description
        "Maximum acceptable accumulated chromatic dispersion
        on the receiver";
}
list chromatic-and-polarization-dispersion-penalty {
    config false;
    description
        "Optional penalty associated with a given accumulated
        CD and PMD.
        This list of triplet cd, pmd, penalty can be used to
        sample the function penalty = f(CD, PMD).";
    uses cd-pmd-penalty ;
}
leaf max-diff-group-delay {
    type int32;
    config false;
    description "Maximum Differential group delay of this mode
        for this lane";
}
list max-polarization-dependent-loss-penalty {
    config false;
    description
        "Optional penalty associated with the maximum acceptable
        accumulated polarization dependent loss.
        This list of pair pdl and penalty can be used to
        sample the function pdl = f(penalty).";
    uses pdl-penalty ;
}
leaf available-modulation-type {
    type identityref {
        base modulation;
    }
    config false;
    description
        "Modulation type the specific transceiver in the list
        can support";
}

```

```

leaf min-OSNR {
    type snr;
    config false;
    description "min OSNR measured over 0.1 nm
resolution bandwidth:
if received OSNR at minimum Rx-power is lower than MIN-OSNR,
an increased level of bit-errors post-FEC needs
to be expected.";
    // change resolution BW from 12.5 GHz to 0.1 nm
}
leaf min-Q-factor {
    type int32;
    units "dB";
    config false;
    description "min Qfactor at FEC threshold";
}
leaf available-baud-rate {
    type uint32;
    units Bd;
    config false;
    description
        "Baud-rate the specific transceiver in
the list can support.
        Baud-rate is the unit for
symbol rate or modulation rate
in symbols per second or
pulses per second.
It is the number of distinct symbol
changes (signal events) made to the
transmission medium
per second in a digitally
modulated signal or a line code";
}
leaf roll-off {
    type decimal64 {
        fraction-digits 4;
        range "0..1";
    }
    config false;
    description
        "the roll-off factor (beta with values from 0 to 1)
identifies how the real signal shape exceed
the baud rate. If=0 it is exactly matching
the baud rate.If=1 the signal exceeds the
50% of the baud rate at each side.";
}
leaf min-carrier-spacing {
    type frequency-ghz;
    config false;

```

```

description
    "This attribute specifies the minimum nominal difference
    between the carrier frequencies of two homogeneous OTSis
    (which have the same optical characteristics but the central
    frequencies) such that if they are placed next to each other
    the interference due to spectrum overlap between them can be
    considered negligible.

    In case of heterogeneous OTSi it is up to path computation
    engine to determine the minimum distance between the carrier
    frequency of the two adjacent OTSi.";
}
leaf available-fec-type {
    type identityref {
        base fec-type;
    }
    config false;
    description "Available FEC";
}
leaf fec-code-rate {
    type decimal64 {
        fraction-digits 8;
        range "0..max";
    }
    config false;
    description "FEC-code-rate";
}
leaf fec-threshold {
    type decimal64 {
        fraction-digits 8;
        range "0..max";
    }
    config false;
    description
        "Threshold on the BER, for which FEC
        is able to correct errors";
}
} // grouping common-explicit-mode

grouping common-organizational-explicit-mode {
    description "Common capability attributes limit range
    in case of operational mode and explicit mode.
    These attributes are supported separately in
    case of application codes";

    /* transmitter tuning range (f_tx-min, f_tx-max) */

    leaf min-central-frequency {
        type frequency-thz;

```

```

        config false;
        description
            "This parameter indicates the minimum frequency for the
            transmitter tuning range.";
    }
    leaf max-central-frequency {
        type frequency-thz;
        config false;
        description
            "This parameter indicates the maximum frequency for the
            transmitter tuning range.";
    }

/* transmitter-tunability-grid */

    leaf central-frequency-step {
        type frequency-ghz;
        config false;
        description
            "This parameter indicates the transmitter tunability grid as
            the distance between two adjacent carrier frequencies of
            the transmitter tuning range.";
    }

/* supported transmitter power range [p_tx-min, p_tx_max] */

    leaf tx-channel-power-min {
        type dbm-t;
        config false;
        description "The minimum output power of this interface";
    }
    leaf tx-channel-power-max {
        type dbm-t;
        config false;
        description "The maximum output power of this interface";
    }

/* supported receiver power range [p_rx-min, p_rx_max] */

    leaf rx-channel-power-min {
        type dbm-t;
        config false;
        description "The minimum input power of this interface";
    }
    leaf rx-channel-power-max {
        type dbm-t;
        config false;
        description "The maximum input power of this interface";
    }

```

```

    leaf rx-total-power-max {
        type dbm-t;
        config false;
        description "Maximum rx optical power for
all the channels";
    }
} // grouping common-organizational-explicit-mode

/* This grouping represent the list of configured parameters */
/* values independent of operational mode */

grouping common-transceiver-configured-param {
    description "Capability of an optical transceiver";

    leaf otsi-carrier-frequency {
        type union {
            type frequency-thz;
            type empty;
        }
        description
            "OTSi carrier frequency, equivalent to the
            actual configured transmitter frequency";
    }
    leaf tx-channel-power {
        type union {
            type dbm-t;
            type empty;
        }
        description "The current channel transmit power";
    }
    leaf rx-channel-power {
        type union {
            type dbm-t;
            type empty;
        }
        config false;
        description "The current channel received power ";
    }
    leaf rx-total-power {
        type union {
            type dbm-t;
            type empty;
        }
        config false;
        description "Current total received power";
    }
} // grouping for configured attributes out of mode

```

```

grouping l0-tunnel-attributes {
  description
    "Parameters for Layer0 (WSON or Flexi-Grid) Tunnels.";
  leaf fec-type {
    type identityref {
      base fec-type;
    }
    description
      "FEC type.";
  }
  leaf termination-type {
    type identityref {
      base term-type;
    }
    description
      "Termination type.";
  }
  leaf bit-stuffing {
    type boolean;
    description
      "Bit stuffing enabled/disabled.";
  }
  leaf wavelength-assignment {
    type identityref {
      base wavelength-assignment;
    }
    description "Wavelength Allocation Method";
  }
}

grouping frequency-range {
  description
    "The parameters that define a frequency range.";
  leaf lower-frequency {
    type frequency-thz;
    mandatory true;
    description
      "The lower frequency boundary of the
        frequency range.";
  }
  leaf upper-frequency {
    type frequency-thz;
    must '. > ../lower-frequency' {
      error-message
        "The upper frequency must be greater than the lower
          frequency.";
    }
    mandatory true;
    description

```

```

        "The upper frequency boundary of the
        frequency range.";
    }
}

grouping l0-path-constraints {
    description
        "Common attribute for Layer 0 path constraints to be used by
        Layer 0 computation.";
    leaf gsnr-margin {
        type snr {
            range 0..max;
        }
        default 0;
        description
            "An additional margin to be added to the OSNR-min of the
            transceiver when checking the estimated received Generalized
            SNR (GSNR).";
    }
}

grouping l0-path-properties {
    description
        "Common attribute for reporting the Layer 0 computed path
        properties.";
    leaf estimated-gsnr {
        type snr;
        config false;
        description
            "The estimate received GSNR for the computed path.";
    }
}
}

<CODE ENDS>

```

4. Security Considerations

The YANG module specified in this document defines a schema for data that is designed to be accessed via network management protocols such as NETCONF [RFC6241] or RESTCONF [RFC8040]. The lowest NETCONF layer is the secure transport layer, and the mandatory-to-implement secure transport is Secure Shell (SSH) [RFC6242]. The lowest RESTCONF layer is HTTPS, and the mandatory-to-implement secure transport is TLS [RFC8446].

The Network Configuration Access Control Model (NACM) [[RFC8341](#)] provides the means to restrict access for particular NETCONF or RESTCONF users to a preconfigured subset of all available NETCONF or RESTCONF protocol operations and content. The NETCONF protocol over Secure Shell (SSH) specification [[RFC6242](#)] describes a method for invoking and running NETCONF within a Secure Shell (SSH) session as an SSH subsystem.

The objects in this YANG module are common data types and groupings. No object in this module can be read or written to. These definitions can be imported and used by other Layer 0 specific modules. It is critical to consider how imported definitions will be utilized and accessible via RPC operations, as the resultant schema will have data nodes that can be writable, or readable, and will have a significant effect on the network operations if used incorrectly or maliciously. All of these considerations belong in the document that defines the modules that import from this YANG module. Therefore, it is important to manage access to resultant data nodes that are considered sensitive or vulnerable in some network environments.

The security considerations spelled out in the YANG 1.1 specification [[RFC7950](#)] apply for this document as well.

5. IANA Considerations

IANA has assigned new URIs from the "IETF XML Registry" [[RFC3688](#)] as follows:

URI: urn:ietf:params:xml:ns:yang:ietf-layer0-types
Registrant Contact: The IESG
XML: N/A; the requested URI is an XML namespace.

This document registers the following YANG module in the "YANG Module Names" registry [[RFC7950](#)].

Name: ietf-layer0-types
Namespace: urn:ietf:params:xml:ns:yang:ietf-layer0-types
Prefix: l0-types
Reference: RFC 9093

[Editors' Note] Check the IANA considerations in other bis documents

6. References

6.1. Normative References

[[ITU-T_G.698.2](#)] ITU-T Recommendation G.698.2, "Amplified multichannel dense wavelength division multiplexing

applications with single channel optical interfaces",
ITU-T G.698.2 , November 2018.

- [RFC4203] Kompella, K., Ed. and Y. Rekhter, Ed., "OSPF Extensions in Support of Generalized Multi-Protocol Label Switching (GMPLS)", RFC 4203, DOI 10.17487/RFC4203, October 2005, <<https://www.rfc-editor.org/info/rfc4203>>.
- [RFC6163] Lee, Y., Ed., Bernstein, G., Ed., and W. Imajuku, "Framework for GMPLS and Path Computation Element (PCE) Control of Wavelength Switched Optical Networks (WSOs)", RFC 6163, DOI 10.17487/RFC6163, April 2011, <<https://www.rfc-editor.org/info/rfc6163>>.
- [RFC6205] Otani, T., Ed. and D. Li, Ed., "Generalized Labels for Lambda-Switch-Capable (LSC) Label Switching Routers", RFC 6205, DOI 10.17487/RFC6205, March 2011, <<https://www.rfc-editor.org/info/rfc6205>>.
- [RFC6241] Enns, R., Ed., Bjorklund, M., Ed., Schoenwaelder, J., Ed., and A. Bierman, Ed., "Network Configuration Protocol (NETCONF)", RFC 6241, DOI 10.17487/RFC6241, June 2011, <<https://www.rfc-editor.org/info/rfc6241>>.
- [RFC6242] Wasserman, M., "Using the NETCONF Protocol over Secure Shell (SSH)", RFC 6242, DOI 10.17487/RFC6242, June 2011, <<https://www.rfc-editor.org/info/rfc6242>>.
- [RFC7698] Gonzalez de Dios, O., Ed., Casellas, R., Ed., Zhang, F., Fu, X., Ceccarelli, D., and I. Hussain, "Framework and Requirements for GMPLS-Based Control of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM) Networks", RFC 7698, DOI 10.17487/RFC7698, November 2015, <<https://www.rfc-editor.org/info/rfc7698>>.
- [RFC7699] Farrel, A., King, D., Li, Y., and F. Zhang, "Generalized Labels for the Flexi-Grid in Lambda Switch Capable (LSC) Label Switching Routers", RFC 7699, DOI 10.17487/RFC7699, November 2015, <<https://www.rfc-editor.org/info/rfc7699>>.
- [RFC7950] Bjorklund, M., Ed., "The YANG 1.1 Data Modeling Language", RFC 7950, DOI 10.17487/RFC7950, August 2016, <<https://www.rfc-editor.org/info/rfc7950>>.
- [RFC8040] Bierman, A., Bjorklund, M., and K. Watsen, "RESTCONF Protocol", RFC 8040, DOI 10.17487/RFC8040, January 2017, <<https://www.rfc-editor.org/info/rfc8040>>.
- [RFC8341] Bierman, A. and M. Bjorklund, "Network Configuration Access Control Model", STD 91, RFC 8341, DOI 10.17487/

RFC8341, March 2018, <<https://www.rfc-editor.org/info/rfc8341>>.

- [RFC8342] Bjorklund, M., Schoenwaelder, J., Shafer, P., Watsen, K., and R. Wilton, "Network Management Datastore Architecture (NMDA)", RFC 8342, DOI 10.17487/RFC8342, March 2018, <<https://www.rfc-editor.org/info/rfc8342>>.
- [RFC8363] Zhang, X., Zheng, H., Casellas, R., Gonzalez de Dios, O., and D. Ceccarelli, "GMPLS OSPF-TE Extensions in Support of Flexi-Grid Dense Wavelength Division Multiplexing (DWDM) Networks", RFC 8363, DOI 10.17487/RFC8363, May 2018, <<https://www.rfc-editor.org/info/rfc8363>>.
- [RFC8446] Rescorla, E., "The Transport Layer Security (TLS) Protocol Version 1.3", RFC 8446, DOI 10.17487/RFC8446, August 2018, <<https://www.rfc-editor.org/info/rfc8446>>.
- [RFC8776] Saad, T., Gandhi, R., Liu, X., Beeram, V., and I. Bryskin, "Common YANG Data Types for Traffic Engineering", RFC 8776, DOI 10.17487/RFC8776, June 2020, <<https://www.rfc-editor.org/info/rfc8776>>.
- [RFC8795] Liu, X., Bryskin, I., Beeram, V., Saad, T., Shah, H., and O. Gonzalez de Dios, "YANG Data Model for Traffic Engineering (TE) Topologies", RFC 8795, DOI 10.17487/RFC8795, August 2020, <<https://www.rfc-editor.org/info/rfc8795>>.

6.2. Informative References

[I-D.ietf-ccamp-dwdm-if-param-yang]

Galimberti, G., Kunze, R., Burk, A., Hiremagalur, D., and G. Grammel, "A YANG model to manage the optical interface parameters for an external transponder in a WDM network", Work in Progress, Internet-Draft, draft-ietf-ccamp-dwdm-if-param-yang-06, 12 July 2021, <<https://>

www.ietf.org/archive/id/draft-ietf-ccamp-dwdm-if-param-yang-06.txt>.

[ITU-T_G.694.1] ITU-T Recommendation G.694.1, "Spectral grids for WDM applications: DWDM frequency grid", ITU-T G.694.1 , October 2020.

[ITU-T_G.694.2] ITU-T Recommendation G.694.2, "Spectral grids for WDM applications: CWDM wavelength grid", ITU-T G.694.2 , December 2003.

[RFC3688] Mealling, M., "The IETF XML Registry", BCP 81, RFC 3688, DOI 10.17487/RFC3688, January 2004, <<https://www.rfc-editor.org/info/rfc3688>>.

[RFC7446] Lee, Y., Ed., Bernstein, G., Ed., Li, D., and W. Imajuku, "Routing and Wavelength Assignment Information Model for Wavelength Switched Optical Networks", RFC 7446, DOI 10.17487/RFC7446, February 2015, <<https://www.rfc-editor.org/info/rfc7446>>.

[RFC7581] Bernstein, G., Ed., Lee, Y., Ed., Li, D., Imajuku, W., and J. Han, "Routing and Wavelength Assignment Information Encoding for Wavelength Switched Optical Networks", RFC 7581, DOI 10.17487/RFC7581, June 2015, <<https://www.rfc-editor.org/info/rfc7581>>.

[RFC9093] Zheng, H., Lee, Y., Guo, A., Lopez, V., and D. King, "A YANG Data Model for Layer 0 Types", RFC 9093, DOI 10.17487/RFC9093, August 2021, <<https://www.rfc-editor.org/info/rfc9093>>.

Appendix A. Changes from RFC 9093

To be added in a future revision of this draft.

Acknowledgments

The authors and the working group give their sincere thanks to Robert Wilton for the YANG doctor review and Tom Petch for his comments during the model and document development.

This document was prepared using kramdown.

Contributors

Dhruv Dhody
Huawei

Email: dhruv.ietf@gmail.com

Bin Yeong Yoon
ETRI

Email: byyun@etri.re.kr

Ricard Vilalta
CTTC

Email: ricard.vilalta@cttc.es

Authors' Addresses

Haomian Zheng
Huawei

Email: zhenghaomian@huawei.com

Young Lee
Samsung

Email: younglee.tx@gmail.com

Aihua Guo
Futurewei Technologies

Email: aihuaguo.ietf@gmail.com

Victor Lopez
Nokia

Email: victor.lopez@nokia.com

Daniel King
University of Lancaster

Email: d.king@lancaster.ac.uk

Dieter Beller
Nokia

Email: dieter.beller@nokia.com

Sergio Belotti
Nokia

Email: sergio.belotti@nokia.com

Italo Busi
Huawei

Email: italo.busi@huawei.com

Esther Le Rouzic
Orange

Email: esther.lerouzic@orange.com