

Entity MIB
<[draft-ietf-entmib-entmib-00.txt](#)>

17 November 1995

Keith McCloghrie
Cisco Systems Inc.
kzm@cisco.com

Andy Bierman
Bierman Consulting
abierman@west.net

Status of this Memo

This document is an Internet-Draft. Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as ``work in progress.''

To learn the current status of any Internet-Draft, please check the ``1id-abstracts.txt' listing contained in the Internet-Drafts Shadow Directories on ds.internic.net (US East Coast), nic.nordu.net (Europe), ftp.isi.edu (US West Coast), or munnari.oz.au (Pacific Rim).

1. Introduction

This memo defines an experimental portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it describes managed objects used for managing multiple logical entities managed by a single SNMP agent.

2. The SNMPv2 Network Management Framework

The SNMPv2 Network Management Framework consists of four major components. They are:

- o [RFC 1442](#) [1] which defines the SMI, the mechanisms used for describing and naming objects for the purpose of management.
- o STD 17, [RFC 1213](#) [2] defines MIB-II, the core set of managed objects for the Internet suite of protocols.
- o [RFC 1445](#) [3] which defines the administrative and other architectural aspects of the framework.
- o [RFC 1448](#) [4] which defines the protocol used for network access to managed objects.

The Framework permits new objects to be defined for the purpose of experimentation and evaluation.

2.1. Object Definitions

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. Objects in the MIB are defined using the subset of Abstract Syntax Notation One (ASN.1) defined in the SMI. In particular, each object type is named by an OBJECT IDENTIFIER, an administratively assigned name. The object type together with an object instance serves to uniquely identify a specific instantiation of the object. For human convenience, we often use a textual string, termed the descriptor, to refer to the object type.

3. Overview

There is a need for a standardized way of representing a single agent which supports multiple instances of one MIB. This is already true for at least 3 standard MIBs, and is likely to become true for more and more MIBs as time passes. For example:

- multiple instances of a bridge supported within a single device having a single agent;
- multiple repeaters supported by a single agent;
- multiple OSPF backbone areas, each one operating as part of its own Autonomous System, and each identified by the same area-id (e.g., 0.0.0.0), supported inside a single router with one agent.

The fact that it is a single agent in each of these cases implies there is some relationship which binds all of these entities together. Effectively, there is some "overall" physical entity which houses the sum of the things managed by that one agent, i.e., there are multiple "logical" entities within a single physical entity. Sometimes, the overall physical entity contains multiple (smaller) physical entities and each logical entity is associated with a particular such physical entity. Sometimes, the overall physical entity is a "compound" of multiple physical entities (e.g., a stack of stackable hubs).

What is needed is a way to determine exactly what logical entities are managed by the agent (either by SNMPv1 or SNMPv2), and thereby to be able to communicate with the agent about a particular logical entity. When different logical entities are associated with different physical entities within the overall physical entity, it is also useful to be able to use this information to distinguish between logical entities.

In these situations, there is no need for varbinds for multiple logical entities to be referenced in the same SNMP message (although that might be useful in the future). Rather, it is sufficient, and in some situations preferable, to have the context/community in the message identify the logical entity to which the varbinds apply.

3.1. Relationship to Contexts

For SNMPv2, in simple scenarios, a SNMPv2 context [\[5\]](#) will correspond directly to a logical entity. However, in the general case, there is a

many-to-many correspondence between an entry in the contextTable and an entry in the entLogicalTable.

On the one hand, each logical entity is associated with exactly one value of contextLocalEntity. However, it is possible to have multiple logical entities associated with the same value of contextLocalEntity. For example, the logical entities, 'bridge1' and 'repeater1', may be represented in an agent's main context, even though different contexts may be used to represent logical entities 'bridge2' and 'repeater2'.

On the other hand, a single value of contextLocalEntity can be associated with multiple contexts (multiple entries in the contextTable) when each has the same value of contextLocalEntity, but a different value of contextLocalTime.

3.2. Relationship to Community Strings

For SNMPv1, distinguishing between different logical entities is one (but not the only) purpose of the community string [6]. This is accommodated by representing each community string as a logical entity.

3.3. Relationship to a Chassis MIB

Some readers may recall that a previous IETF working group attempted to define a Chassis MIB. No consensus was reached by that working group, possibly because its scope was too broad. As such, it is not the purpose of this MIB to be a "Chassis MIB replacement", nor is it within the scope of this MIB to contain all the information which might be necessary to manage a "chassis". On the other hand, the entities represented by an implementation of this MIB might well be contained in a chassis.

3.4. Relationship to the Interfaces MIB

The Entity MIB contains a mapping table identifying physical components that have 'external values' (e.g. ifIndex) associated with them within a given context. This table can be used to identify the physical location of each interface in the ifTable. Since ifIndex values in different contexts are not related to one another, the interface to physical component associations are relative to a specific logical entity within

the agent.

3.5. Relationship to the Other MIBs

The Entity MIB contains a mapping table identifying physical components that have identifiers from other standard MIBs associated with them. For example, this table can be used along with the physical mapping table to identify the physical location of each repeater port in the `rpTrPortTable`, each bridge port in the `dot1dBasePortTable`, or each `ifIndex` in the `ifTable`.

3.6. Re-Configuration of Entities

All the MIB objects defined in this MIB have at most a read-only MAX-ACCESS clause, i.e., none are write-able. This is another conscious decision by the authors to limit this MIB's scope. It is possible that this restriction could be lifted after implementation experience.

3.7. MIB Structure

This MIB contains four tables: the `entPhysicalTable` and the `entLogicalTable` each provide a list of entities. The `entLPMappingTable` provides mappings between logical and physical entities. The `entAliasMappingTable` provides mappings between physical components and associated identifiers from other MIBs. For example, a physical repeater port may be associated with an instance of `'rpTrPortGroupIndex.1.5'`, or `'ifIndex.12'`, or both.

The `entPhysicalTable` contains one row per physical entity, and should always contain at least one row for an "overall" physical entity. Each row is indexed by an arbitrary, small integer, and contains a description and type of the physical entity. It also optionally contains the index number of another row in the same table indicating a containment relationship between the two.

The `entLogicalTable` contains one row per logical entity. Each row is indexed by an arbitrary, small integer and contains a name, description, and type of the logical entity. It also contains information to allow SNMPv2 and/or SNMPv1 access to the MIB information for the logical

entity.

The entLPMappingTable contains mappings between entLogicalIndex values (logical entities) and entPhysicalIndex values (the physical components supporting that entity). A logical entity can map to more than one physical component, and more than one logical entity can map to (share) the same physical component.

The entAliasMappingTable contains mappings between entPhysicalIndex, entLogicalIndex pairs and 'alias' object identifier values. This allows resources managed with other MIBs (e.g. repeater ports, bridge ports, physical and logical interfaces) to be identified in the physical entity hierarchy.

3.8. Multiple Agents

Even though a primary motivation for this MIB is to represent the multiple logical entities supported by a single agent, it is also possible to use it to represent multiple logical entities supported by multiple agents (in the same "overall" physical entity). Indeed, it is implicit in the SNMP architecture, that the number of agents is transparent to a network management station.

4. Definitions

ENTITY-MIB DEFINITIONS ::= BEGIN

IMPORTS

MODULE-IDENTITY, OBJECT-TYPE, experimental,
IpAddress

FROM SNMPv2-SMI

DisplayString, AutonomousType, TruthValue

FROM SNMPv2-TC

Context

FROM SNMPv2-PARTY-MIB

MODULE-COMPLIANCE, OBJECT-GROUP

FROM SNMPv2-CONF;

entityMIB MODULE-IDENTITY

LAST-UPDATED "9511170000Z"

ORGANIZATION "IETF ENTMIB Working Group"

CONTACT-INFO

" Keith McCloghrie
Cisco Systems Inc.
170 West Tasman Drive
San Jose, CA 95134
408-526-5260
kzm@cisco.com

Andy Bierman
Bierman Consulting
1200 Sagamore Lane
Ventura, CA 93001
805-648-2028
abierman@west.net"

DESCRIPTION

"The MIB module for representing multiple logical
entities supported by a single SNMP agent."

::= { experimental xx }

entityMIBObjects OBJECT IDENTIFIER ::= { entityMIB 1 }

-- The Physical Entity Table

entPhysicalTable OBJECT-TYPE

SYNTAX SEQUENCE OF EntPhysicalEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

 "This table contains one row per physical entity. There is
 always at least one row for an 'overall' physical entity."

::= { entityMIBObjects 1 }

entPhysicalEntry OBJECT-TYPE

SYNTAX EntPhysicalEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

 "Information about a particular physical entity. An agent
 is expected to represent physical components in as much
 detail as possible. If more than one agent within a chassis
 implements the Entity MIB, the information retrieved from
 each agent must be consistent, but not necessarily
 identical."

INDEX { entPhysicalIndex }

::= { entPhysicalTable 1 }

EntPhysicalEntry ::= SEQUENCE {

entPhysicalIndex	INTEGER,
entPhysicalDescr	DisplayString,
entPhysicalVendorType	AutonomousType,
entPhysicalContainedIn	INTEGER,
entPhysicalIsRemovable	TruthValue,
entPhysicalClass	AutonomousType

}

entPhysicalIndex OBJECT-TYPE

SYNTAX INTEGER (1..2147483647)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

 "The value of this object uniquely identifies the physical
 entity. The value is a small positive integer; index values
 for different physical entities are not necessarily
 contiguous."

::= { entPhysicalEntry 1 }

entPhysicalDescr OBJECT-TYPE

SYNTAX DisplayString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A textual description of physical entity."

::= { entPhysicalEntry 2 }

entPhysicalVendorType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An indication of the vendor-specific hardware type of the physical entity. Note that this is different from the definition of MIB-II's sysObjectID.

An agent should set this object to a enterprise-specific registration identifier value indicating the specific equipment type in detail. The associated instance of the entPhysicalClass object should be used to indicate the general type of hardware device.

If no vendor-specific registration identifier exists for this physical entity, then the value { 0 0 } is returned. If the value is unknown by this agent, then the special value 'entPClassUnknown' is returned."

::= { entPhysicalEntry 3 }

entPhysicalContainedIn OBJECT-TYPE

SYNTAX INTEGER (0..2147483647)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of entPhysicalIndex for the physical entity which 'contains' this physical entity. A value of zero indicates this physical entity is not contained in any other physical entity. Note that the set of 'containment' relationships define a strict hierarchy; that is, recursion is not allowed."

::= { entPhysicalEntry 4 }

entPhysicalIsRemovable OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An indication of the physical characteristics of specified component. A value of 'true(1)' indicates that this entPhysicalEntry represents a field-replaceable unit. A value of 'false(2)' indicates a physical component that cannot be replaced by a user or equipment installer."

::= { entPhysicalEntry 5 }

entPhysicalClass OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An indication of the general hardware type of the physical entity.

An agent should set this object to a standard registration identifier value (from the entPClassTypes sub-tree) which most accurately indicates the general class of the physical entity.

If no appropriate standard registration identifier exists for this physical entity, then the value { 0 0 } is returned. If the value is unknown by this agent, then the special value 'entPClassUnknown' is returned."

::= { entPhysicalEntry 6 }


```
--          The Logical Entity Table
entLogicalTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF EntLogicalEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "This table contains one row per logical entity."
    ::= { entityMIBObjects 2 }

entLogicalEntry      OBJECT-TYPE
    SYNTAX      EntLogicalEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "Information about a particular logical entity.  Entities
         may be managed by this agent or other SNMP agents (possibly)
         in the same chassis."
    INDEX       { entLogicalIndex }
    ::= { entLogicalTable 1 }

EntLogicalEntry ::= SEQUENCE {
    entLogicalIndex      INTEGER,
    entLogicalDescr      DisplayString,
    entLogicalType        AutonomousType,
    entLogicalLocalEntityName OCTET STRING,
    entLogicalContext     Context,
    entLogicalCommunity   OCTET STRING,
    entLogicalIpAddress    IPAddress
}

entLogicalIndex OBJECT-TYPE
    SYNTAX      INTEGER (1..2147483647)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "The value of this object uniquely identifies the logical
         entity.  The value is a small positive integer; index values
         for different logical entities are are not necessarily
         contiguous."
    ::= { entLogicalEntry 1 }
```


entLogicalDescr OBJECT-TYPE

SYNTAX DisplayString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A textual description of logical entity."

::= { entLogicalEntry 2 }

entLogicalType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An indication of the type of logical entity. This will typically be the OBJECT IDENTIFIER name of the node in the SMI's naming hierarchy which represents the major MIB module, or the majority of the MIB modules, supported by the logical entity. For example:

a logical entity of a regular host/router -> mib-2

a logical entity of a 802.1d bridge -> dot1dBridge

a logical entity of a 802.3 repeater ->

snmpDot3RptrMgmt"

::= { entLogicalEntry 3 }

entLogicalLocalEntityName OBJECT-TYPE

SYNTAX OCTET STRING (SIZE(0..255))

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A name associated with the logical entity. This name and the SNMPv2 contextLocalEntity [[RFC-1447](#)] for the corresponding local context have the same value. Note that multiple contexts may have the same value of contextLocalEntity, each having a different value of contextLocalTime.

A conformant SNMPv2 agent may wish to conserve contexts by representing multiple logical entities in a single 'main' context. This is possible when the logical entities represented by the same value of contextLocalEntity have no object instances in common. For example, 'bridge1' and 'repeater1' may be part of the main context, but two additional entries are needed to represent 'bridge2' and 'repeater2'.

Logical entities 'bridge1' and 'repeater1' would be represented by sysOREntries associated with the 'main' context.

For agents not accessible via SNMPv2, the value of this object is the empty string."

```
::= { entLogicalEntry 4 }
```

entLogicalContext OBJECT-TYPE

SYNTAX Context
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"An SNMPv2 context containing detailed management information for this logical entity. If more than one context is associated with this logical entity, then the agent should choose a 'primary' context for the logical entity; e.g. the context whose associated value of contextLocalTime is equal to 'currentTime'.

Other contexts (for different values of contextLocalTime) may be derived from the entLogicalLocalEntityName according to whatever conventions are used for context naming.

For agents not accessible via SNMPv2, this object would have the value 0.0.

[TBD 1: the issue of which Parties to use along with this context is considered beyond the scope of the Entity MIB.

TBD 2: this part of the entLogicalTable will change to reflect the new SNMPv2 administrative model.] "

```
::= { entLogicalEntry 5 }
```

entLogicalCommunity OBJECT-TYPE

SYNTAX OCTET STRING
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"A SNMPv1 community-string which can be used to access detailed management information for this logical entity. The agent should allow read access with this community string (to an appropriate subset of all managed objects) and may also choose to return a community string based on the privileges of the request used to read this object (e.g. only return a string having read-write privileges when

accessed with read-write privileges).

For agents not accessible via SNMPv1, the value of this object is the empty-string."

::= { entLogicalEntry 6 }

entLogicalIpAddress OBJECT-TYPE

SYNTAX IpAddress

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The IP-address of the SNMPv1 agent from which detailed management information for this logical entity can be obtained. For agents not accessible via SNMPv1, the value of this object is 0.0.0.0."

::= { entLogicalEntry 7 }

```
--  entLPMappingTable: for each entity index, there are N
--      rows, each representing a physical component
--      that is associated with the indicated entity
--
-- entity to component table
entLPMappingTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF EntLPMappingEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "This table contains zero or more rows of logical entity to
        physical equipment associations."
    ::= { entityMIBObjects 3 }

entLPMappingEntry      OBJECT-TYPE
    SYNTAX      EntLPMappingEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "Information about a particular logical entity to physical
        equipment binding."
    INDEX      { entLogicalIndex, entLPPhysicalIndex }
    ::= { entLPMappingTable 1 }

EntLPMappingEntry ::= SEQUENCE {
    entLPPhysicalIndex      INTEGER
}

entLPPhysicalIndex OBJECT-TYPE
    SYNTAX      INTEGER (1..2147483647)
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The value of this object identifies a particular
        entPhysicalEntry associated with the indicated
        entLogicalEntity."
    ::= { entLPMappingEntry 1 }
```



```
-- logical entity/component to alias table
entAliasMappingTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF EntAliasMappingEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "This table contains zero or more rows of logical entity,
        and physical component to external identifier associations."
    ::= { entityMIBObjects 4 }

entAliasMappingEntry      OBJECT-TYPE
    SYNTAX      EntAliasMappingEntry
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "Information about a particular physical equipment, logical
        entity to external identifier binding. Note that the same
        physical component-logical entity pair may have an arbitrary
        number of external identifier (alias) bindings."
    INDEX { entPhysicalIndex, entLogicalIndex, entAliasMappingIndex }
    ::= { entAliasMappingTable 1 }

EntAliasMappingEntry ::= SEQUENCE {
    entAliasMappingIndex      INTEGER,
    entAliasIdentifier        OBJECT IDENTIFIER
}

entAliasMappingIndex OBJECT-TYPE
    SYNTAX      INTEGER (1..2147483647)
    MAX-ACCESS  not-accessible
    STATUS      current
    DESCRIPTION
        "The value of this object uniquely identifies the particular
        binding for a specific logical entity on a particular
        physical component. The value is a small positive integer;
        index values for different entAlias mappings are not
        necessarily contiguous."
    ::= { entAliasMappingEntry 1 }

entAliasIdentifier OBJECT-TYPE
    SYNTAX      OBJECT IDENTIFIER
    MAX-ACCESS  read-only
    STATUS      current
    DESCRIPTION
        "The value of this object identifies a particular MIB
```


instance associated with the indicated entPhysicalEntry and entLogicalEntry pair.

For example, suppose a physical port was represented by entPhysicalEntry.3, and entLogicalEntry.1 existed for a repeater, entLogicalEntry.2 existed for a bridge, and the bridge port was also represented in the ifTable. Then there might be three associated instances of entAliasIdentifier:

entAliasIdentifier.3.1.1 == rptrPortGroupIndex.5.2

entAliasIdentifier.3.2.1 == dot1dBasePort.2

entAliasIdentifier.3.2.2 == ifIndex.2 "

::= { entAliasMappingEntry 2 }


```
-- standard OBJECT IDENTIFIER values for entPhysicalClass
--
-- this section needs a lot of work
-- the following identifiers are intended to be a
-- starting point for WG discussion, and should not be
-- considered complete
--
entPClassTypes OBJECT IDENTIFIER ::= { entityMIBObjects 5 }

entPClassUnknown OBJECT IDENTIFIER ::= { entPClassTypes 1 }

entPClassChassis OBJECT IDENTIFIER ::= { entPClassTypes 2 }

entPClassBackplanes OBJECT IDENTIFIER ::= { entPClassTypes 3 }

entPClassNetBackplane OBJECT IDENTIFIER ::= { entPClassBackplanes 1 }

entPClassPowerBackplane OBJECT IDENTIFIER ::= { entPClassBackplanes 2 }

entPClassSlot OBJECT IDENTIFIER ::= { entPClassTypes 4 }

entPClassPowerSupply OBJECT IDENTIFIER ::= { entPClassTypes 5 }

entPClassFan OBJECT IDENTIFIER ::= { entPClassTypes 6 }

entPClassSensors OBJECT IDENTIFIER ::= { entPClassTypes 7 }

entPClassTempSensor OBJECT IDENTIFIER ::= { entPClassSensors 1 }

entPClassGenModules OBJECT IDENTIFIER ::= { entPClassTypes 8 }

entPClassNetModules OBJECT IDENTIFIER ::= { entPClassTypes 9 }

entPClassNetRepeater OBJECT IDENTIFIER ::= { entPClassNetModules 1 }

entPClassNetRouter OBJECT IDENTIFIER ::= { entPClassNetModules 2 }

entPClassNetBridge OBJECT IDENTIFIER ::= { entPClassNetModules 3 }

entPClassTermServer OBJECT IDENTIFIER ::= { entPClassNetModules 4 }

entPClassPort OBJECT IDENTIFIER ::= { entPClassTypes 10 }
```



```
-- conformance information

entityConformance OBJECT IDENTIFIER ::= { entityMIB 2 }

entityCompliances OBJECT IDENTIFIER ::= { entityConformance 1 }
entityGroups      OBJECT IDENTIFIER ::= { entityConformance 2 }

-- compliance statements

entityCompliance MODULE-COMPLIANCE
    STATUS current
    DESCRIPTION
        "The compliance statement for SNMPv2 entities
        which implement the Entity MIB."
    MODULE -- this module
        MANDATORY-GROUPS { entityGroup }
    ::= { entityCompliances 1 }

-- units of conformance

entityGroup OBJECT-GROUP
    OBJECTS { entPhysicalDescr, entPhysicalVendorType,
               entPhysicalContainedIn, entPhysicalIsRemovable,
               entPhysicalClass,
               entLogicalDescr, entLogicalType,
               entLogicalLocalEntityName, entLogicalContext,
               entLogicalCommunity, entLogicalIpAddress,
               entLPPPhysicalIndex, entAliasIdentifier
             }
    STATUS current
    DESCRIPTION
        "The collection of objects which are used to
        represent the multiple logical entities,
        physical components, interfaces, and port
        alias identifiers for which a single agent
        provides MIB information."
    ::= { entityGroups 1 }

END
```


5. Usage Examples

5.1. Router/Bridge

A bi-lingual (SNMPv1 and SNMPv2) router containing two slots. Each slot contains a 3 port router/bridge module. Each port is represented in the ifTable. There are two logical instances of OSPF running and two logical bridges:

Physical entities -- entPhysicalTable:

1 Field-replaceable physical chassis:

```
entPhysicalDescr.1 == "Acme Chassis Model 100"
entPhysicalVendorType.1 == acmeProducts.chassisTypes.1
entPhysicalContainedIn.1 == 0
entPhysicalIsRemovable.1 == true(1)
entPhysicalClass.1 == entPClassChassis
```

2 slots within the chassis:

```
entPhysicalDescr.2 == "Acme Router Chassis Slot 1"
entPhysicalVendorType.2 == acmeProducts.slotTypes.1
entPhysicalContainedIn.2 == 1
entPhysicalIsRemovable.2 == false(2)
entPhysicalClass.2 == entPClassSlot
```

```
entPhysicalDescr.3 == "Acme Router Chassis Slot 2"
entPhysicalVendorType.3 == acmeProducts.slotTypes.1
entPhysicalContainedIn.3 == 1
entPhysicalIsRemovable.3 == false(2)
entPhysicalClass.3 == entPClassSlot
```

2 Field-replaceable modules:

Slot 1 contains a module with 3 ports:

```
entPhysicalDescr.4 == "Acme Router Module Model 10"
entPhysicalVendorType.4 == acmeProducts.moduleTypes.14
entPhysicalContainedIn.4 == 2
entPhysicalIsRemovable.4 == true(1)
entPhysicalClass.4 == entPClassNetRouter
```

```
entPhysicalDescr.5 == "Acme Router Ethernet Port 1"
entPhysicalVendorType.5 == acmeProducts.portTypes.2
entPhysicalContainedIn.5 == 4
entPhysicalIsRemovable.5 == false(2)
entPhysicalClass.5 == entPClassPort
```



```
entPhysicalDescr.6 ==      "Acme Router Ethernet Port 2"
entPhysicalVendorType.6 == acmeProducts.portTypes.2
entPhysicalContainedIn.6 == 4
entPhysicalIsRemovable.6 == false(2)
entPhysicalClass.6 ==      entPClassPort
```

```
entPhysicalDescr.7 ==      "Acme Router Fddi Port 3"
entPhysicalVendorType.7 ==  acmeProducts.portTypes.3
entPhysicalContainedIn.7 ==  4
entPhysicalIsRemovable.7 == false(2)
entPhysicalClass.7 ==      entPClassPort
```

Slot 2 contains another 3-port module:

```
entPhysicalDescr.8 ==      "Acme Router Module Model 11"
entPhysicalVendorType.8 ==  acmeProducts.moduleTypes.15
entPhysicalContainedIn.8 ==  3
entPhysicalIsRemovable.8 == true(1)
entPhysicalClass.8 ==      entPClassNetRouter
```

```
entPhysicalDescr.9 ==      "Acme Router Fddi Port 1"
entPhysicalVendorType.9 ==  acmeProducts.portTypes.3
entPhysicalContainedIn.9 ==  8
entPhysicalIsRemovable.9 == false(2)
entPhysicalClass.9 ==      entPClassPort
```

```
entPhysicalDescr.10 ==     "Acme Router Ethernet Port 2"
entPhysicalVendorType.10 == acmeProducts.portTypes.2
entPhysicalContainedIn.10 == 8
entPhysicalIsRemovable.10 == false(2)
entPhysicalClass.10 ==     entPClassPort
```

```
entPhysicalDescr.11 ==     "Acme Router Ethernet Port 3"
entPhysicalVendorType.11 == acmeProducts.portTypes.2
entPhysicalContainedIn.11 == 8
entPhysicalIsRemovable.11 == false(2)
entPhysicalClass.11 ==     entPClassPort
```

Logical entities -- entLogicalTable

2 OSPF instances:

```
entLogicalDescr.1 ==      "ospf-1"
entLogicalType.1 ==        ospf
entLogicalLocalEntityName.1 == "wan-gwty"
entLogicalContext.1 ==     { initialContextId
                             124 125 126 127 10 }
entLogicalCommunity.1 ==   "public-ospf1"
```



```
entLogicalIpAddress.1 ==      124.125.126.127

entLogicalDescr.2 ==          "ospf-2"
entLogicalType.2 ==           ospf
entLogicalLocalEntityName.2 == "wan-gwty-ospf2"
entLogicalContext.2 ==        { initialContextId
                                124 125 126 127 11 }

entLogicalCommunity.2 ==      "public-ospf2"
entLogicalIpAddress.2 ==      124.125.126.127
```

2 logical bridges:

```
entLogicalDescr.3 ==          "bridge1"
entLogicalType.3 ==           dod1dBridge
entLogicalLocalEntityName.3 == "wan-gwty-bridge1"
entLogicalContext.3 ==        { initialContextId
                                124 125 126 127 101 }

entLogicalCommunity.3 ==      "public-bridge1"
entLogicalIpAddress.3 ==      124.125.126.127

entLogicalDescr.4 ==          "bridge2"
entLogicalType.4 ==           dod1dBridge
entLogicalLocalEntityName.4 == "wan-gwty-bridge2"
entLogicalContext.4 ==        { initialContextId
                                124 125 126 127 102 }

entLogicalCommunity.4 ==      "public-bridge2"
entLogicalIpAddress.4 ==      124.125.126.127
```

Logical to Physical Mappings:

```
1st OSPF instance: uses module 1-port 1
entLPPhysicalIndex.1.5 ==      5
```

```
2nd OSPF instance: uses module 2-port 1
entLPPhysicalIndex.2.9 ==      9
```

```
1st bridge group: uses module 1, all ports
entLPPhysicalIndex.3.5 ==      5
entLPPhysicalIndex.3.6 ==      6
entLPPhysicalIndex.3.7 ==      7
```

```
2nd bridge group: uses module 2, all ports
entLPPhysicalIndex.4.9 ==      9
entLPPhysicalIndex.4.10 ==     10
entLPPhysicalIndex.4.11 ==     11
```

Physical/Logical to Alias Mappings -- entAliasMappingTable:

Bridge 1 uses Ports 1..3 on Slot 1

```
entAliasIdentifier.5.3.1 == dot1dBasePort.1
entAliasIdentifier.5.3.2 == ifIndex.1
entAliasIdentifier.6.3.1 == dot1dBasePort.2
entAliasIdentifier.6.3.2 == ifIndex.2
entAliasIdentifier.7.3.1 == dot1dBasePort.3
entAliasIdentifier.7.3.2 == ifIndex.3
```

Bridge 2 uses Ports 1..3 on Slot 2; uses same Bridge MIB and ifIndex values as Bridge 1, but in a different context, and representing different physical ports:

```
entAliasIdentifier.9.4.1 == dot1dBasePort.1
entAliasIdentifier.9.4.2 == ifIndex.1
entAliasIdentifier.10.4.1 == dot1dBasePort.2
entAliasIdentifier.10.4.2 == ifIndex.2
entAliasIdentifier.11.4.1 == dot1dBasePort.3
entAliasIdentifier.11.4.2 == ifIndex.3
```

5.2. Repeaters

An SNMPv1 only, 3-slot Hub with 2 backplane ethernet segments. Slot three is empty, and the remaining slots contain ethernet repeater modules.

Physical entities -- entPhysicalTable:

1 Field-replaceable physical chassis:

```
entPhysicalDescr.1 == "Acme Repeater Chassis Model 110"
entPhysicalVendorType.1 == acmeProducts.chassisTypes.2
entPhysicalContainedIn.1 == 0
entPhysicalIsRemovable.1 == true(1)
entPhysicalClass.1 == entPClassChassis
```

2 Chassis Ethernet Backplanes:

```
entPhysicalDescr.2 == "Ethernet Backplane 1"
entPhysicalVendorType.2 == acmeProducts.backplaneTypes.1
entPhysicalContainedIn.2 == 1
entPhysicalIsRemovable.2 == false(2)
entPhysicalClass.2 == entPClassNetBackplane
```

```
entPhysicalDescr.3 == "Ethernet Backplane 2"
entPhysicalVendorType.3 == acmeProducts.backplaneTypes.1
entPhysicalContainedIn.3 == 1
entPhysicalIsRemovable.3 == false(2)
entPhysicalClass.3 == entPClassNetBackplane
```


3 slots within the chassis:

```
entPhysicalDescr.4 == "Acme Hub Slot 1"
entPhysicalVendorType.4 == acmeProducts.slotTypes.5
entPhysicalContainedIn.4 == 1
entPhysicalIsRemovable.4 == false(2)
entPhysicalClass.4 == entPClassSlot
```

```
entPhysicalDescr.5 == "Acme Hub Slot 2"
entPhysicalVendorType.5 == acmeProducts.slotTypes.5
entPhysicalContainedIn.5 == 1
entPhysicalIsRemovable.5 == false(2)
entPhysicalClass.5 == entPClassSlot
```

```
entPhysicalDescr.6 == "Acme Hub Slot 3"
entPhysicalVendorType.6 == acmeProducts.slotTypes.5
entPhysicalContainedIn.6 == 1
entPhysicalIsRemovable.6 == false(2)
entPhysicalClass.6 == entPClassSlot
```

Slot 1 contains a plug-in module with 4 10-BaseT ports:

```
entPhysicalDescr.7 == "10Base-T Module Model 14"
entPhysicalVendorType.7 == acmeProducts.moduleTypes.32
entPhysicalContainedIn.7 == 4
entPhysicalIsRemovable.7 == true(1)
entPhysicalClass.7 == entPClassNetRepeater
```

```
entPhysicalDescr.8 == "10Base-T Port 1"
entPhysicalVendorType.8 == acmeProducts.portTypes.10
entPhysicalContainedIn.8 == 7
entPhysicalIsRemovable.8 == false(2)
entPhysicalClass.8 == entPClassPort
```

```
entPhysicalDescr.9 == "10Base-T Port 2"
entPhysicalVendorType.9 == acmeProducts.portTypes.10
entPhysicalContainedIn.9 == 7
entPhysicalIsRemovable.9 == false(2)
entPhysicalClass.9 == entPClassPort
```

```
entPhysicalDescr.10 == "10Base-T Port 3"
entPhysicalVendorType.10 == acmeProducts.portTypes.10
entPhysicalContainedIn.10 == 7
entPhysicalIsRemovable.10 == false(2)
entPhysicalClass.10 == entPClassPort
```

```
entPhysicalDescr.11 == "10Base-T Port 4"
```



```

entPhysicalVendorType.11 == acmeProducts.portTypes.10
entPhysicalContainedIn.11 == 7
entPhysicalIsRemovable.11 == false(2)
entPhysicalClass.11 == entPClassPort

```

Slot 2 contains another ethernet module with 2 ports.

```

entPhysicalDescr.12 == "Acme 10Base-T Module Model 4"
entPhysicalVendorType.12 == acmeProducts.moduleTypes.30
entPhysicalContainedIn.12 == 5
entPhysicalIsRemovable.12 == true(1)
entPhysicalClass.12 == entPClassNetRepeater

```

```

entPhysicalDescr.13 == "802.3 AUI Port 1"
entPhysicalVendorType.13 == acmeProducts.portTypes.11
entPhysicalContainedIn.13 == 5
entPhysicalIsRemovable.13 == false(2)
entPhysicalClass.13 == entPClassPort

```

```

entPhysicalDescr.14 == "10Base-T Port 2"
entPhysicalVendorType.14 == acmeProducts.portTypes.10
entPhysicalContainedIn.14 == 5
entPhysicalIsRemovable.14 == false(2)
entPhysicalClass.14 == entPClassPort

```

Logical entities -- entLogicalTable

Repeater 1--comprised of any ports attached to backplane 1

```

entLogicalDescr.1 == "repeater1"
entLogicalType.1 == snmpDot3RptrMgt
entLogicalLocalEntityName.1 == ""
entLogicalContext.1 == { 0.0 }
entLogicalCommunity.1 == "public-repeater1"
entLogicalIpAddress.1 == 124.125.126.128

```

Repeater 2--comprised of any ports attached to backplane 2:

```

entLogicalDescr.2 == "repeater2"
entLogicalType.2 == snmpDot3RptrMgt
entLogicalLocalEntityName.2 == ""
entLogicalContext.2 == { 0.0 }
entLogicalCommunity.2 == "public-repeater2"
entLogicalIpAddress.2 == 124.125.126.128

```

Logical to Physical Mappings -- entLPMappingTable:

```

repeater1 uses backplane 1, slot 1-ports 1 & 2, slot 2-port 1
entLPPhysicalIndex.1.2 == 2

```



```
entLPPhysicalIndex.1.8 ==      8
entLPPhysicalIndex.1.9 ==      9
entLPPhysicalIndex.1.13 ==     13
```

repeater2 uses backplane 2, slot 1-ports 3 & 4, slot 2-port 2

```
entLPPhysicalIndex.2.3 ==      3
entLPPhysicalIndex.2.10 ==     10
entLPPhysicalIndex.2.11 ==     11
entLPPhysicalIndex.2.14 ==     14
```

Physical/Logical to Alias Mappings -- entAliasMappingTable:

repeater1 uses slot 1-ports 1 & 2, slot 2-port 1

```
entAliasIdentifier.8.1.1 ==    rptrPortGroupIndex.1.1
entAliasIdentifier.9.1.1 ==    rptrPortGroupIndex.1.2
entAliasIdentifier.13.1.1 ==   rptrPortGroupIndex.2.1
```

repeater2 uses slot 1-ports 3 & 4, slot 2-port 2

```
entAliasIdentifier.10.2.1 ==   rptrPortGroupIndex.1.3
entAliasIdentifier.11.2.1 ==   rptrPortGroupIndex.1.4
entAliasIdentifier.14.2.1 ==   rptrPortGroupIndex.2.2
```

6. Acknowledgements

This document was produced by the IETF Entity MIB Working Group.

7. References

- [1] Case, J., McCloghrie, K., Rose, M., and S. Waldbusser, "Structure of Management Information for version 2 of the Simple Network Management Protocol (SNMPv2)", [RFC 1442](#), SNMP Research, Inc., Hughes LAN Systems, Dover Beach Consulting, Inc., Carnegie Mellon University, April 1993.
- [2] McCloghrie, K., and M. Rose, Editors, "Management Information Base for Network Management of TCP/IP-based internets: MIB-II", STD 17, [RFC 1213](#), Hughes LAN Systems, Performance Systems International, March 1991.
- [3] Galvin, J., and K. McCloghrie, "Administrative Model for version 2 of the Simple Network Management Protocol (SNMPv2)", [RFC 1445](#), Trusted Information Systems, Hughes LAN Systems, April 1993.
- [4] Case, J., McCloghrie, K., Rose, M., and S. Waldbusser, "Protocol Operations for version 2 of the Simple Network Management Protocol (SNMPv2)", [RFC 1448](#), SNMP Research, Inc., Hughes LAN Systems, Dover Beach Consulting, Inc., Carnegie Mellon University, April 1993.
- [5] McCloghrie, K., and J. Galvin, "Party MIB for Version 2 of the Simple Network Management Protocol (SNMPv2)", [RFC 1447](#), Hughes LAN Systems, Trusted Information Systems, April 1993.
- [6] Case, J., M. Fedor, M. Schoffstall, J. Davin, "Simple Network Management Protocol", [RFC 1157](#), SNMP Research, Performance Systems International, MIT Laboratory for Computer Science, May 1990.
- [7] McCloghrie, K., and Kastenholz, F., "Interfaces Group Evolution", [RFC 1573](#), Hughes LAN Systems, FTP Software, January 1994.

8. Security Considerations

Security issues are not discussed in this memo.

9. Authors' Addresses

Keith McCloghrie
cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134
Phone: 408-526-5260
Email: kzm@cisco.com

Andy Bierman
Bierman Consulting
1200 Sagamore Lane
Ventura, CA 93001
Phone: 805-648-2028
Email: abierman@west.net

Table of Contents

1	Introduction	2
2	The SNMPv2 Network Management Framework	3
2.1	Object Definitions	3
3	Overview	4
3.1	Relationship to Contexts	4
3.2	Relationship to Community Strings	5
3.3	Relationship to a Chassis MIB	5
3.4	Relationship to the Interfaces MIB	5
3.5	Relationship to the Other MIBs	6
3.6	Re-Configuration of Entities	6
3.7	MIB Structure	6
3.8	Multiple Agents	7
4	Definitions	8
5	Usage Examples	21
5.1	Router/Bridge	21
5.2	Repeaters	24
6	Acknowledgements	28
7	References	29
8	Security Considerations	30
9	Authors' Addresses	30

