

**Definitions of Managed Objects for
IEEE 802.3 Medium Attachment Units (MAUs)**

[<draft-ietf-hubmib-mau-mib-v3-03.txt>](mailto:draft-ietf-hubmib-mau-mib-v3-03.txt)

Status of this Memo

This document is an Internet-Draft and is in full conformance with all provisions of [Section 10 of RFC2026](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/1id-abstracts.txt>

To view the list Internet-Draft Shadow Directories, see <http://www.ietf.org/shadow.html>.

Copyright Notice

Copyright (C) The Internet Society (2002). All Rights Reserved.

Abstract

This memo defines a portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it defines objects for managing IEEE 802.3 Medium Attachment Units (MAUs).

This memo obsoletes [RFC 2668](#). This memo extends that specification by including management information useful for the management of 10 gigabit per second (Gb/s) MAUs. This memo also obsoletes [RFC 1515](#).

Distribution of this memo is unlimited. Please forward comments to

hubmib@ietf.org.

Table of Contents

1.	Introduction	2
2.	The Internet-Standard Management Framework	3
3.	Overview	3
3.1.	Relationship to RFC 2668	3
3.2.	Relationship to RFC 2239	4
3.3.	Relationship to RFC 1515	4
3.4.	Relationship to Other MIBs	4
3.4.1.	Relationship to the Interfaces MIB	4
3.4.2.	Relationship to the 802.3 Repeater MIB	5
3.5.	Management of Internal MAUs	5
3.6.	Mapping of IEEE 802.3 Managed Objects	6
4.	Definitions	7
5.	Intellectual Property	56
6.	Acknowledgements	56
7.	Normative References	57
8.	Informative References	58
9.	Security Considerations	58
10.	Authors' Addresses	59
A.	Change Log	60
A.1.	Changes since RFC 2668	60
A.2.	Changes between RFC 2239 and RFC 2668	60
B.	Full Copyright Statement	62

[1.](#) Introduction

This memo defines a portion of the Management Information Base (MIB) for use with network management protocols in the Internet community. In particular, it defines objects for managing IEEE 802.3 Medium Attachment Units (MAUs).

This memo also includes a MIB module. This MIB module extends the list of managed objects specified in the earlier version of this MIB module, [RFC 2668](#) [[RFC2668](#)].

Ethernet technology, as defined by the 802.3 Working Group of the IEEE, continues to evolve, with scalable increases in speed, new types of cabling and interfaces, and new features. This evolution may require changes in the managed objects in order to reflect this new functionality. This document, as with other documents issued by this working group, reflects a certain stage in the evolution of Ethernet technology. In the future, this document might be revised, or new documents might be issued by the Ethernet Interfaces and Hub

Flick

Expires September 2003

[Page 2]

MIB Working Group, in order to reflect the evolution of Ethernet technology.

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [[RFC2119](#)].

[2.](#) The Internet-Standard Management Framework

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to [section 7 of RFC 3410](#) [[RFC3410](#)].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIV2, which is described in STD 58, [RFC 2578](#) [[RFC2578](#)], STD 58, [RFC 2579](#) [[RFC2579](#)] and STD 58, [RFC 2580](#) [[RFC2580](#)].

[3.](#) Overview

Instances of these object types represent attributes of an IEEE 802.3 MAU. Several types of MAUs are defined in the IEEE 802.3 CSMA/CD standard [[IEEE802.3](#)]. These MAUs may be connected to IEEE 802.3 repeaters or to 802.3 (Ethernet-like) interfaces. For convenience this document refers to these devices as "repeater MAUs" and "interface MAUs."

The definitions presented here are based on [Section 30.5](#), "Layer Management for 10 Mb/s, 100 Mb/s, 1000 Mb/s and 10 Gb/s Medium Attachment Units (MAUs)", [Section 30.6](#), "Management for link Auto-Negotiation", and Annex 30A, "GDMO Specifications for 802.3 managed object classes" of IEEE Std. 802.3, 2002 edition [[IEEE802.3](#)], as amended by IEEE Std. 802.3ae-2002 [[IEEE802.3ae](#)]. That specification includes definitions for 10 Mb/s, 100 Mb/s, 1000 Mb/s and 10 Gb/s devices. This specification is intended to serve the same purpose: to provide for management of all types of Ethernet/802.3 MAUs.

[3.1.](#) Relationship to [RFC 2668](#)

This MIB is intended to be a superset of that defined by [RFC 2668](#) [[RFC2668](#)]. This MIB includes all of the objects contained in that MIB, with new and updated definitions which provide support for

additional capabilities. Implementors are encouraged to support all applicable conformance groups in order to make the best use of the new functionality provided by this MIB. The new and updated definitions provide management support for 10 Gb/s devices.

3.2. Relationship to [RFC 2239](#)

[RFC 2668](#) was a replacement for [RFC 2239](#) [[RFC2239](#)]. [RFC 2668](#) defined a superset of that defined by [RFC 2239](#), which contained all of the objects defined in [RFC 2239](#), plus several new ones which provide additional capabilities. The new objects provided management support for:

- o management of 1000 Mb/s devices
- o management of PAUSE negotiation
- o management of remote fault status

3.3. Relationship to [RFC 1515](#)

[RFC 2239](#) was a replacement for [RFC 1515](#) [[RFC1515](#)]. [RFC 2239](#) defined a superset of [RFC 1515](#) which contained all of the objects defined in [RFC 1515](#), plus several new ones which provided additional capabilities. The new objects in [RFC 2239](#) provided management support for:

- o management of 100 Mb/s devices
- o auto-negotiation on interface MAUs
- o jack management

3.4. Relationship to Other MIBs

It is assumed that an agent implementing this MIB will also implement (at least) the 'system' group defined in the SNMPv2 MIB [[RFC3418](#)]. The following sections identify other MIBs that such an agent should implement.

3.4.1. Relationship to the Interfaces MIB.

The sections of this document that define interface MAU-related objects specify an extension to the Interfaces MIB [[RFC2863](#)]. An agent implementing these interface-MAU related objects MUST also implement the relevant groups of the ifCompliance3 MODULE-COMPLIANCE statement of the Interface MIB. The value of the object ifMauIfIndex

is the same as the value of 'ifIndex' used to instantiate the interface to which the given MAU is connected.

It is REQUIRED that an agent implementing the interface-MAU related objects in this MIB will also fully comply with the dot3Compliance2 MODULE-COMPLIANCE statement of the Ethernet-like Interfaces MIB, [ETHERIF]. Furthermore, when the interface-MAU related objects are used to manage a 10GBASE-W PHY -- i.e., when ifMauType is equal to dot3MauType10GigBaseW or any other 10GBASE-W variant -- then the agent MUST also support the Ethernet WAN Interface Sublayer (WIS) MIB [ETHERWIS] and must follow the interface layering model specified therein. In that case the value of the object ifMauIfIndex is the same as the value of 'ifIndex' for the layer at the top of the stack, i.e., for the ifTable entry that has 'ifType' equal to ethernetCsmacd(6). If the interface-MAU related objects are used to manage a PHY that allows the MAU type to be changed dynamically, then the agent SHALL create ifTable, ifStackTable, and ifInvStackTable entries that pertain to the WIS when ifMauDefaultType is changed to a 10GBASEW variant (i.e., one of dot3MauType10GigBaseW, dot3MauType10GigBaseEW, dot3MauType10GigBaseLW, or dot3MauType10GigBaseSW) from any other type, and shall destroy the WIS-related entries when ifMauDefaultType is changed to a non-10GBASE-W type. The agent SHALL also change the values of 'ifConnectorPresent' and 'ifHighSpeed' in the ifTable entry indexed by ifMauIfIndex as specified in [ETHERIF] and [ETHERWIS] when ifMauDefaultType is manipulated in this way but SHALL NOT otherwise alter that entry.

(Note that repeater ports are not represented as interfaces in the Interface MIB.)

3.4.2. Relationship to the 802.3 Repeater MIB

The section of this document that defines repeater MAU-related objects specifies an extension to the 802.3 Repeater MIB defined in [RFC2108]. An agent implementing these repeater-MAU related objects MUST also comply with the snmpRptrModCompl compliance statement of the 802.3 Repeater MIB.

The values of 'rpMauGroupIndex' and 'rpMauPortIndex' used to instantiate a repeater MAU variable SHALL be the same as the values of 'rptrPortGroupIndex' and 'rptrPortIndex' used to instantiate the port to which the given MAU is connected.

3.5. Management of Internal MAUs

In some situations, a MAU can be "internal" -- i.e., its functionality is implemented entirely within a device. For example,

a managed repeater may contain an internal repeater-MAU and/or an internal interface-MAU through which management communications originating on one of the repeater's external ports pass in order to reach the management agent associated with the repeater. Such internal MAUs may or may not be managed. If they are managed, objects describing their attributes should appear in the appropriate MIB subtree: dot3RpMauBasicGroup for internal repeater-MAUs and dot3IfMauBasicGroup for internal interface-MAUs.

3.6. Mapping of IEEE 802.3 Managed Objects

IEEE 802.3 Managed Object	Corresponding SNMP Object
oMAU	
.aMAUID	rpMauIndex or ifMauIndex or broadMauIndex
.aMAUType	rpMauType or ifMauType
.aMAUTypeList	ifMauTypeListBits
.aMediaAvailable	rpMauMediaAvailable or ifMauMediaAvailable
.aLoseMediaCounter	rpMauMediaAvailableStateExits or ifMauMediaAvailableStateExits
.aJabber	rpMauJabberState and rpMauJabberingStateEnters or ifMauJabberState and ifMauJabberingStateEnters
.aMAUAdminState	rpMauStatus or ifMauStatus
.aBbMAUXmitRcvSplitType	broadMauXmtRcvSplitType
.aBroadbandFrequencies	broadMauXmtCarrierFreq and broadMauTranslationFreq
.aFalseCarriers	rpMauFalseCarriers or ifMauFalseCarriers
.acResetMAU	rpMauStatus or ifMauStatus
.acMAUAdminControl	rpMauStatus or ifMauStatus
.nJabber	rpMauJabberTrap or ifMauJabberTrap
oAutoNegotiation	
.aAutoNegID	ifMauIndex
.aAutoNegAdminState	ifMauAutoNegAdminStatus
.aAutoNegRemoteSignalling	ifMauAutoNegRemoteSignalling

Flick

Expires September 2003

[Page 6]

.aAutoNegAutoConfig	ifMauAutoNegConfig
.aAutoNegLocalTechnologyAbility	ifMauAutoNegCapabilityBits
.aAutoNegAdvertisedTechnologyAbility	ifMauAutoNegAdvertisedBits and ifMauAutoNegRemoteFaultAdvertised
.aAutoNegReceivedTechnologyAbility	ifMauAutoNegReceivedBits and ifMauAutoNegRemoteFaultReceived
.acAutoNegRestartAutoConfig	ifMauAutoNegRestart
.acAutoNegAdminControl	ifMauAutoNegAdminStatus

The following IEEE 802.3 managed objects have not been included in this MIB for the following reasons.

IEEE 802.3 Managed Object	Corresponding SNMP Object
oMAU	
.aIdleErrorCount	Only useful for 100BaseT2, which is not widely implemented.
oAutoNegotiation	
.aAutoNegLocalSelectorAbility	Only needed for support of
.aAutoNegAdvertisedSelectorAbility	isoethernet (802.9a), which is
.aAutoNegReceivedSelectorAbility	not supported by this MIB.

4. Definitions

MAU-MIB DEFINITIONS ::= BEGIN

IMPORTS

Counter32, Integer32, Counter64,
 OBJECT-TYPE, MODULE-IDENTITY, NOTIFICATION-TYPE,
 OBJECT-IDENTITY, mib-2
 FROM SNMPv2-SMI
 TruthValue, AutonomousType, TEXTUAL-CONVENTION
 FROM SNMPv2-TC
 OBJECT-GROUP, MODULE-COMPLIANCE, NOTIFICATION-GROUP
 FROM SNMPv2-CONF
 InterfaceIndex
 FROM IF-MIB;

mauMod MODULE-IDENTITY

LAST-UPDATED "200302280000Z" -- February 28, 2003
 ORGANIZATION "IETF Ethernet Interfaces and Hub MIB
 Working Group"

CONTACT-INFO

"WG E-mail: hubmib@ietf.org
 To subscribe: hubmib-request@ietf.org"

Chair: Dan Romascanu
Postal: Avaya Inc.
Atidim Technology Park, Bldg. 3
Tel Aviv 61131
Israel
Tel: +972 3 645 8414
E-mail: dromasca@avaya.com

Editor: John Flick
Postal: Hewlett-Packard Company
8000 Foothills Blvd. M/S 5557
Roseville, CA 95747-5557
USA
Tel: +1 916 785 4018
Fax: +1 916 785 1199
E-mail: johnf@rose.hp.com"

DESCRIPTION "Management information for 802.3 MAUs.

The following reference is used throughout
this MIB module:

[IEEE 802.3 Std] refers to:
IEEE Std 802.3, 2002 Edition: 'IEEE Standard
for Information technology -
Telecommunications and information exchange
between systems - Local and metropolitan
area networks - Specific requirements -
Part 3: Carrier sense multiple access with
collision detection (CSMA/CD) access method
and physical layer specifications', as
amended by IEEE Std 802.3ae-2002:
'Amendment: Media Access Control (MAC)
Parameters, Physical Layer, and Management
Parameters for 10 Gb/s Operation', August,
2002.

Of particular interest is Clause 30, '10Mb/s,
100Mb/s, 1000Mb/s and 10 Gb/s Management'.

Copyright (C) The Internet Society (2003). This
version of this MIB module is part of RFC XXXX;
see the RFC itself for full legal notices."

-- RFC Ed.: Replace XXXX with the actual RFC number & remove
-- this note

REVISION "200302280000Z" -- February 28, 2003
DESCRIPTION "Updated to include support for 10 Gb/s MAUs.
This resulted in the following revisions:

Flick

Expires September 2003

[Page 8]

- Added OBJECT-IDENTITY definitions for 10 gigabit MAU types
- Added fiberLC jack type to JackType TC
- Extended ifMauTypeListBits with bits for the 10 gigabit MAU types
- Added enumerations to ifMauMediaAvailable, and updated its DESCRIPTION to reflect behaviour at 10 Gb/s
- Added 64-bit version of ifMauFalseCarriers and added mauIfGrpHCStats object group to contain the new object
- Deprecated mauModIfCompl2 and replaced it with mauModIfCompl3, which includes the new object group

This version published as RFC XXXX."

-- RFC Ed.: Replace XXXX with the actual RFC number & remove
-- this note

REVISION "199908240400Z" -- August 24, 1999
DESCRIPTION "This version published as [RFC 2668](#). Updated
to include support for 1000 Mb/sec
MAUs and flow control negotiation."

REVISION "199710310000Z" -- October 31, 1997
DESCRIPTION "Version published as [RFC 2239](#)."

REVISION "199309300000Z" -- September 30, 1993
DESCRIPTION "Initial version, published as [RFC 1515](#)."

::= { snmpDot3MauMgt 6 }

snmpDot3MauMgt OBJECT IDENTIFIER ::= { mib-2 26 }

-- textual conventions

JackType ::= TEXTUAL-CONVENTION

STATUS current

DESCRIPTION "Common enumeration values for repeater
and interface MAU jack types."

SYNTAX INTEGER {
 other(1),
 rj45(2),
 rj45S(3), -- rj45 shielded
 db9(4),
 bnc(5),
 fAUI(6), -- female aui


```
        mAUI(7), -- male aui
        fiberSC(8),
        fiberMIC(9),
        fiberST(10),
        telco(11),
        mtrj(12), -- fiber MT-RJ
        hssdc(13), -- fiber channel style-2
        fiberLC(14)
    }

dot3RpMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 1 }
dot3IfMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 2 }
dot3BroadMauBasicGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 3 }

dot3IfMauAutoNegGroup
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 5 }

-- object identities for MAU types
-- (see rpMauType and ifMauType for usage)

dot3MauType
    OBJECT IDENTIFIER ::= { snmpDot3MauMgt 4 }

dot3MauTypeAUI OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "no internal MAU, view from AUI"
    REFERENCE   "[IEEE 802.3 Std.], Section 7"
    ::= { dot3MauType 1 }

dot3MauType10Base5 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "thick coax MAU"
    REFERENCE   "[IEEE 802.3 Std.], Section 7"
    ::= { dot3MauType 2 }

dot3MauTypeFoir1 OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "FOIRL MAU"
    REFERENCE   "[IEEE 802.3 Std.], Section 9.9"
    ::= { dot3MauType 3 }

dot3MauType10Base2 OBJECT-IDENTITY
```


STATUS current
DESCRIPTION "thin coax MAU"
REFERENCE "[IEEE 802.3 Std.], [Section 10](#)"
::= { dot3MauType 4 }

dot3MauType10BaseT OBJECT-IDENTITY

STATUS current
DESCRIPTION "UTP MAU.
Note that it is strongly recommended that agents return either dot3MauType10BaseTHD or dot3MauType10BaseTFD if the duplex mode is known. However, management applications should be prepared to receive this MAU type value from older agent implementations."
REFERENCE "[IEEE 802.3 Std.], [Section 14](#)"
::= { dot3MauType 5 }

dot3MauType10BaseFP OBJECT-IDENTITY

STATUS current
DESCRIPTION "passive fiber MAU"
REFERENCE "[IEEE 802.3 Std.], [Section 16](#)"
::= { dot3MauType 6 }

dot3MauType10BaseFB OBJECT-IDENTITY

STATUS current
DESCRIPTION "sync fiber MAU"
REFERENCE "[IEEE 802.3 Std.], [Section 17](#)"
::= { dot3MauType 7 }

dot3MauType10BaseFL OBJECT-IDENTITY

STATUS current
DESCRIPTION "async fiber MAU.
Note that it is strongly recommended that agents return either dot3MauType10BaseFLHD or dot3MauType10BaseFLFD if the duplex mode is known. However, management applications should be prepared to receive this MAU type value from older agent implementations."
REFERENCE "[IEEE 802.3 Std.], [Section 18](#)"
::= { dot3MauType 8 }

dot3MauType10Broad36 OBJECT-IDENTITY

STATUS current
DESCRIPTION "broadband DTE MAU.
Note that 10BROAD36 MAUs can be attached to interfaces but not to repeaters."
REFERENCE "[IEEE 802.3 Std.], [Section 11](#)"
::= { dot3MauType 9 }

Flick

Expires September 2003

[Page 11]

----- new since [RFC 1515](#):

dot3MauType10BaseTHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "UTP MAU, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 14](#)"
::= { dot3MauType 10 }

dot3MauType10BaseTFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "UTP MAU, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 14](#)"
::= { dot3MauType 11 }

dot3MauType10BaseFLHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "async fiber MAU, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 18](#)"
::= { dot3MauType 12 }

dot3MauType10BaseFLFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "async fiber MAU, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 18](#)"
::= { dot3MauType 13 }

dot3MauType100BaseT4 OBJECT-IDENTITY

STATUS current
DESCRIPTION "4 pair category 3 UTP"
REFERENCE "[IEEE 802.3 Std.], [Section 23](#)"
::= { dot3MauType 14 }

dot3MauType100BaseTXHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "2 pair category 5 UTP, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 25](#)"
::= { dot3MauType 15 }

dot3MauType100BaseTXFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "2 pair category 5 UTP, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 25](#)"
::= { dot3MauType 16 }

dot3MauType100BaseFXHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "X fiber over PMT, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 26](#)"


```
 ::= { dot3MauType 17 }

dot3MauType100BaseFXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "X fiber over PMT, full duplex mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 26"
    ::= { dot3MauType 18 }

dot3MauType100BaseT2HD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "2 pair category 3 UTP, half duplex mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 32"
    ::= { dot3MauType 19 }

dot3MauType100BaseT2FD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "2 pair category 3 UTP, full duplex mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 32"
    ::= { dot3MauType 20 }

----- new since RFC 2239:

dot3MauType1000BaseXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "PCS/PMA, unknown PMD, half duplex mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 36"
    ::= { dot3MauType 21 }

dot3MauType1000BaseXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "PCS/PMA, unknown PMD, full duplex mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 36"
    ::= { dot3MauType 22 }

dot3MauType1000BaseLXHD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "Fiber over long-wavelength laser, half duplex
                mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 38"
    ::= { dot3MauType 23 }

dot3MauType1000BaseLXFD OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION "Fiber over long-wavelength laser, full duplex
                mode"
    REFERENCE   "[IEEE 802.3 Std.], Section 38"
    ::= { dot3MauType 24 }
```


dot3MauType1000BaseSXHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Fiber over short-wavelength laser, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 38](#)"
::= { dot3MauType 25 }

dot3MauType1000BaseSXFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Fiber over short-wavelength laser, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 38](#)"
::= { dot3MauType 26 }

dot3MauType1000BaseCXHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Copper over 150-Ohm balanced cable, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 39](#)"
::= { dot3MauType 27 }

dot3MauType1000BaseCXFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Copper over 150-Ohm balanced cable, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 39](#)"
::= { dot3MauType 28 }

dot3MauType1000BaseTHD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Four-pair Category 5 UTP, half duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 40](#)"
::= { dot3MauType 29 }

dot3MauType1000BaseTFD OBJECT-IDENTITY

STATUS current
DESCRIPTION "Four-pair Category 5 UTP, full duplex mode"
REFERENCE "[IEEE 802.3 Std.], [Section 40](#)"
::= { dot3MauType 30 }

----- new since [RFC 2668](#):

dot3MauType10GigBaseX OBJECT-IDENTITY

STATUS current
DESCRIPTION "X PCS/PMA, unknown PMD."
REFERENCE "[IEEE 802.3 Std.], [Section 48](#)"
::= { dot3MauType 31 }

dot3MauType10GigBaseLX4 OBJECT-IDENTITY

STATUS current
DESCRIPTION "X fiber over WDM optics"
REFERENCE "[IEEE 802.3 Std.], [Section 53](#)"
::= { dot3MauType 32 }

dot3MauType10GigBaseR OBJECT-IDENTITY

STATUS current
DESCRIPTION "R PCS/PMA, unknown PMD."
REFERENCE "[IEEE 802.3 Std.], [Section 49](#)"
::= { dot3MauType 33 }

dot3MauType10GigBaseER OBJECT-IDENTITY

STATUS current
DESCRIPTION "R fiber over 1550 nm optics"
REFERENCE "[IEEE 802.3 Std.], [Section 52](#)"
::= { dot3MauType 34 }

dot3MauType10GigBaseLR OBJECT-IDENTITY

STATUS current
DESCRIPTION "R fiber over 1310 nm optics"
REFERENCE "[IEEE 802.3 Std.], [Section 52](#)"
::= { dot3MauType 35 }

dot3MauType10GigBaseSR OBJECT-IDENTITY

STATUS current
DESCRIPTION "R fiber over 850 nm optics"
REFERENCE "[IEEE 802.3 Std.], [Section 52](#)"
::= { dot3MauType 36 }

dot3MauType10GigBaseW OBJECT-IDENTITY

STATUS current
DESCRIPTION "W PCS/PMA, unknown PMD."
REFERENCE "[IEEE 802.3 Std.], [Section 49](#) and 50"
::= { dot3MauType 37 }

dot3MauType10GigBaseEW OBJECT-IDENTITY

STATUS current
DESCRIPTION "W fiber over 1550 nm optics"
REFERENCE "[IEEE 802.3 Std.], [Section 52](#)"
::= { dot3MauType 38 }

dot3MauType10GigBaseLW OBJECT-IDENTITY

STATUS current
DESCRIPTION "W fiber over 1310 nm optics"
REFERENCE "[IEEE 802.3 Std.], [Section 52](#)"
::= { dot3MauType 39 }


```
dot3MauType10GigBaseSW OBJECT-IDENTITY
    STATUS      current
    DESCRIPTION  "W fiber over 850 nm optics"
    REFERENCE    "[IEEE 802.3 Std.], Section 52"
    ::= { dot3MauType 40 }

--
-- The Basic Repeater MAU Table
--

rpMauTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF RpMauEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION  "Table of descriptive and status information
                  about the MAU(s) attached to the ports of a
                  repeater."
    ::= { dot3RpMauBasicGroup 1 }

rpMauEntry OBJECT-TYPE
    SYNTAX      RpMauEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION  "An entry in the table, containing information
                  about a single MAU."
    INDEX        { rpMauGroupIndex,
                  rpMauPortIndex,
                  rpMauIndex
                }
    ::= { rpMauTable 1 }

RpMauEntry ::=
    SEQUENCE {
        rpMauGroupIndex      Integer32,
        rpMauPortIndex       Integer32,
        rpMauIndex           Integer32,
        rpMauType            AutonomousType,
        rpMauStatus          INTEGER,
        rpMauMediaAvailable  INTEGER,
        rpMauMediaAvailableStateExits Counter32,
        rpMauJabberState     INTEGER,
        rpMauJabberingStateEnters Counter32,
        rpMauFalseCarriers   Counter32
    }

rpMauGroupIndex OBJECT-TYPE
    SYNTAX      Integer32 (1..2147483647)
```

Flick

Expires September 2003

[Page 16]

MAX-ACCESS read-only -- read-only since originally an
-- SMIV1 index

STATUS current

DESCRIPTION "This variable uniquely identifies the group
containing the port to which the MAU described
by this entry is connected.

Note: In practice, a group will generally be
a field-replaceable unit (i.e., module, card,
or board) that can fit in the physical system
enclosure, and the group number will correspond
to a number marked on the physical enclosure.

The group denoted by a particular value of this
object is the same as the group denoted by the
same value of rpMauGroupIndex."

REFERENCE "Reference [RFC 2108](#), rpMauGroupIndex."
::= { rpMauEntry 1 }

rpMauPortIndex OBJECT-TYPE

SYNTAX Integer32 (1..2147483647)

MAX-ACCESS read-only -- read-only since originally an
-- SMIV1 index

STATUS current

DESCRIPTION "This variable uniquely identifies the repeater
port within group rpMauGroupIndex to which the
MAU described by this entry is connected."

REFERENCE "Reference [RFC 2108](#), rpMauPortIndex."
::= { rpMauEntry 2 }

rpMauIndex OBJECT-TYPE

SYNTAX Integer32 (1..2147483647)

MAX-ACCESS read-only -- read-only since originally an
-- SMIV1 index

STATUS current

DESCRIPTION "This variable uniquely identifies the MAU
described by this entry from among other
MAUs connected to the same port
(rpMauPortIndex)."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.1, aMAUID."
::= { rpMauEntry 3 }

rpMauType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION "This object identifies the MAU type. An
initial set of MAU types are defined above. The

Flick

Expires September 2003

[Page 17]

assignment of OBJECT IDENTIFIERS to new types of MAUs is managed by the IANA. If the MAU type is unknown, the object identifier

unknownMauType OBJECT IDENTIFIER ::= { 0 0 }

is returned. Note that unknownMauType is a syntactically valid object identifier, and any conformant implementation of ASN.1 and the BER must be able to generate and recognize this value."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.2, aMAUType."
::= { rpMauEntry 4 }

rpMauStatus OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 operational(3),
 standby(4),
 shutdown(5),
 reset(6)
}

MAX-ACCESS read-write

STATUS current

DESCRIPTION "The current state of the MAU. This object MAY be implemented as a read-only object by those agents and MAUs that do not implement software control of the MAU state. Some agents may not support setting the value of this object to some of the enumerated values.

The value other(1) is returned if the MAU is in a state other than one of the states 2 through 6.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

A MAU in the operational(3) state is fully functional, operates, and passes signals to its attached DTE or repeater port in accordance to its specification.

A MAU in standby(4) state forces DI and CI to idle and the media transmitter to idle or fault, if supported. Standby(4) mode only applies to

link type MAUs. The state of rpMauMediaAvailable is unaffected.

A MAU in shutdown(5) state assumes the same condition on DI, CI, and the media transmitter as though it were powered down or not connected. The MAU MAY return other(1) value for the rpMauJabberState and rpMauMediaAvailable objects when it is in this state. For an AUI, this state will remove power from the AUI.

Setting this variable to the value reset(6) resets the MAU in the same manner as a power-off, power-on cycle of at least one-half second would. The agent is not required to return the value reset (6).

Setting this variable to the value operational(3), standby(4), or shutdown(5) causes the MAU to assume the respective state except that setting a mixing-type MAU or an AUI to standby(4) will cause the MAU to enter the shutdown state."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.7, aMAUAdminState, 30.5.1.2.2, acMAUAdminControl, and 30.5.1.2.1, acResetMAU."

::= { rpMauEntry 5 }

rpMauMediaAvailable OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 available(3),
 notAvailable(4),
 remoteFault(5),
 invalidSignal(6),
 remoteJabber(7),
 remoteLinkLoss(8),
 remoteTest(9),
 offline(10),
 autoNegError(11)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION "If the MAU is a link or fiber type (FOIRL, 10BASE-T, 10BASE-F) then this is equivalent to the link test fail state/low light function. For an AUI or a coax (including broadband) MAU

this indicates whether or not loopback is detected on the DI circuit. The value of this attribute persists between packets for MAU types AUI, 10BASE5, 10BASE2, 10BROAD36, and 10BASE-FP.

The value other(1) is returned if the mediaAvailable state is not one of 2 through 11.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized. At power-up or following a reset, the value of this attribute will be unknown for AUI, coax, and 10BASE-FP MAUs. For these MAUs loopback will be tested on each transmission during which no collision is detected. If DI is receiving input when DO returns to IDL after a transmission and there has been no collision during the transmission then loopback will be detected. The value of this attribute will only change during non-collided transmissions for AUI, coax, and 10BASE-FP MAUs.

For 100Mbps and 1000Mbps MAUs, the enumerations match the states within the respective link integrity state diagrams, fig 32-16, 23-12 and 24-15 of sections [32](#), [23](#) and [24](#) of [[IEEE802.3](#)]. Any MAU which implements management of auto-negotiation will map remote fault indication to remote fault.

The value available(3) indicates that the link, light, or loopback is normal. The value notAvailable(4) indicates link loss, low light, or no loopback.

The value remoteFault(5) indicates that a fault has been detected at the remote end of the link. This value applies to 10BASE-FB, 100BASE-T4 Far End Fault Indication and non-specified remote faults from a system running auto-negotiation. The values remoteJabber(7), remoteLinkLoss(8), and remoteTest(9) SHOULD be used instead of remoteFault(5) where the reason for remote fault is identified in the remote signaling protocol.

The value invalidSignal(6) indicates that an invalid signal has been received from the other

Flick

Expires September 2003

[Page 20]

end of the link. invalidSignal(6) applies only to MAUs of type 10BASE-FB.

Where an IEEE Std 802.3-2002 clause 22 MII is present, a logic one in the remote fault bit (reference [section 22.2.4.2.8](#) of that document) maps to the value remoteFault(5), and a logic zero in the link status bit (reference [section 22.2.4.2.10](#) of that document) maps to the value notAvailable(4). The value notAvailable(4) takes precedence over the value remoteFault(5).

Any MAU that implements management of clause 37 Auto-Negotiation will map the received Remote Fault (RF1 and RF2) bit values for Offline to offline(10), Link Failure to remoteFault(5) and Auto-Negotiation Error to autoNegError(11)."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.4, aMediaAvailable."
::= { rpMauEntry 6 }

rpMauMediaAvailableStateExits OBJECT-TYPE

SYNTAX Counter32
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A count of the number of times that
rpMauMediaAvailable for this MAU instance leaves
the state available(3).

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.5,
aLoseMediaCounter.
[RFC 2108](#), rpPtrMonitorPortLastChange"
::= { rpMauEntry 7 }

rpMauJabberState OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 noJabber(3),
 jabbering(4)
}
MAX-ACCESS read-only
STATUS current
DESCRIPTION "The value other(1) is returned if the jabber

state is not 2, 3, or 4. The agent MUST always return other(1) for MAU type dot3MauTypeAUI.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

If the MAU is not jabbering the agent returns noJabber(3). This is the 'normal' state.

If the MAU is in jabber state the agent returns the jabbering(4) value."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.6,
aJabber.jabberFlag."
::= { rpMauEntry 8 }

rpMauJabberingStateEnters OBJECT-TYPE

SYNTAX Counter32
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A count of the number of times that mauJabberState for this MAU instance enters the state jabbering(4). For MAUs of type dot3MauTypeAUI, dot3MauType100BaseT4, dot3MauType100BaseTX, dot3MauType100BaseFX and all 1000Mbps types, this counter will always indicate zero.

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.6,
aJabber.jabberCounter.
[RFC 2108](#), rpPtrMonitorPortLastChange"
::= { rpMauEntry 9 }

rpMauFalseCarriers OBJECT-TYPE

SYNTAX Counter32
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A count of the number of false carrier events during IDLE in 100BASE-X links. This counter does not increment at the symbol rate. It can increment after a valid carrier completion at a maximum rate of once per 100 ms until the next carrier event.

This counter increments only for MAUs of type dot3MauType100BaseT4, dot3MauType100BaseTX, and dot3MauType100BaseFX and all 1000Mbps types. For all other MAU types, this counter will always indicate zero.

The approximate minimum time for rollover of this counter is 7.4 hours.

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of rpPtrMonitorPortLastChange."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.10, aFalseCarriers.
[RFC 2108](#), rpPtrMonitorPortLastChange"
 ::= { rpMauEntry 10 }

-- The rpJackTable applies to MAUs attached to repeaters
 -- which have one or more external jacks (connectors).

rpJackTable OBJECT-TYPE

SYNTAX SEQUENCE OF RpJackEntry
 MAX-ACCESS not-accessible
 STATUS current
 DESCRIPTION "Information about the external jacks attached
 to MAUs attached to the ports of a repeater."
 ::= { dot3RpMauBasicGroup 2 }

rpJackEntry OBJECT-TYPE

SYNTAX RpJackEntry
 MAX-ACCESS not-accessible
 STATUS current
 DESCRIPTION "An entry in the table, containing information
 about a particular jack."
 INDEX { rpMauGroupIndex,
 rpMauPortIndex,
 rpMauIndex,
 rpJackIndex
 }
 ::= { rpJackTable 1 }

RpJackEntry ::=

SEQUENCE {
 rpJackIndex Integer32,
 rpJackType JackType
 }

rpJackIndex OBJECT-TYPE

```
SYNTAX      Integer32 (1..2147483647)
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION "This variable uniquely identifies the jack
            described by this entry from among other jacks
            attached to the same MAU (rpMauIndex)."
 ::= { rpJackEntry 1 }
```

rpJackType OBJECT-TYPE

```
SYNTAX      JackType
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION "The jack connector type, as it appears on the
            outside of the system."
 ::= { rpJackEntry 2 }
```

--

-- The Basic Interface MAU Table

--

ifMauTable OBJECT-TYPE

```
SYNTAX      SEQUENCE OF IfMauEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION "Table of descriptive and status information
            about MAU(s) attached to an interface."
 ::= { dot3IfMauBasicGroup 1 }
```

ifMauEntry OBJECT-TYPE

```
SYNTAX      IfMauEntry
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION "An entry in the table, containing information
            about a single MAU."
INDEX       { ifMauIfIndex,
              ifMauIndex
            }
 ::= { ifMauTable 1 }
```

IfMauEntry ::=

```
SEQUENCE {
    ifMauIfIndex      InterfaceIndex,
    ifMauIndex        Integer32,
    ifMauType         AutonomousType,
    ifMauStatus        INTEGER,
    ifMauMediaAvailable INTEGER,
```

Flick

Expires September 2003

[Page 24]

```

        ifMauMediaAvailableStateExits      Counter32,
        ifMauJabberState                    INTEGER,
        ifMauJabberingStateEnters           Counter32,
        ifMauFalseCarriers                  Counter32,
        ifMauTypeList                       Integer32,
        ifMauDefaultType                    AutonomousType,
        ifMauAutoNegSupported                TruthValue,
        ifMauTypeListBits                   BITS,
        ifMauHCFALSECarriers                 Counter64
    }

```

ifMauIfIndex OBJECT-TYPE

```

SYNTAX      InterfaceIndex
MAX-ACCESS  read-only  -- read-only since originally an
                        -- SMIV1 index

STATUS      current
DESCRIPTION "This variable uniquely identifies the interface
            to which the MAU described by this entry is
            connected."
REFERENCE   "RFC 2863, ifIndex"
 ::= { ifMauEntry 1 }

```

ifMauIndex OBJECT-TYPE

```

SYNTAX      Integer32 (1..2147483647)
MAX-ACCESS  read-only  -- read-only since originally an
                        -- SMIV1 index

STATUS      current
DESCRIPTION "This variable uniquely identifies the MAU
            described by this entry from among other MAUs
            connected to the same interface (ifMauIfIndex)."
REFERENCE   "[IEEE 802.3 Std], 30.5.1.1.1, aMAUID."
 ::= { ifMauEntry 2 }

```

ifMauType OBJECT-TYPE

```

SYNTAX      AutonomousType
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION "This object identifies the MAU type.  An
            initial set of MAU types are defined above.  The
            assignment of OBJECT IDENTIFIERS to new types of
            MAUs is managed by the IANA.  If the MAU type is
            unknown, the object identifier

```

unknownMauType OBJECT IDENTIFIER ::= { 0 0 }

is returned. Note that unknownMauType is a syntactically valid object identifier, and any conformant implementation of ASN.1 and the BER

Flick

Expires September 2003

[Page 25]

must be able to generate and recognize this value.

This object represents the operational type of the MAU, as determined by either (1) the result of the auto-negotiation function or (2) if auto-negotiation is not enabled or is not implemented for this MAU, by the value of the object ifMauDefaultType. In case (2), a set to the object ifMauDefaultType will force the MAU into the new operating mode."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.2, aMAUType."
::= { ifMauEntry 3 }

ifMauStatus OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 operational(3),
 standby(4),
 shutdown(5),
 reset(6)
}

MAX-ACCESS read-write

STATUS current

DESCRIPTION "The current state of the MAU. This object MAY be implemented as a read-only object by those agents and MAUs that do not implement software control of the MAU state. Some agents may not support setting the value of this object to some of the enumerated values.

The value other(1) is returned if the MAU is in a state other than one of the states 2 through 6.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized.

A MAU in the operational(3) state is fully functional, operates, and passes signals to its attached DTE or repeater port in accordance to its specification.

A MAU in standby(4) state forces DI and CI to idle and the media transmitter to idle or fault, if supported. Standby(4) mode only applies to

Flick

Expires September 2003

[Page 26]

link type MAUs. The state of ifMauMediaAvailable is unaffected.

A MAU in shutdown(5) state assumes the same condition on DI, CI, and the media transmitter as though it were powered down or not connected. The MAU MAY return other(1) value for the ifMauJabberState and ifMauMediaAvailable objects when it is in this state. For an AUI, this state will remove power from the AUI.

Setting this variable to the value reset(6) resets the MAU in the same manner as a power-off, power-on cycle of at least one-half second would. The agent is not required to return the value reset (6).

Setting this variable to the value operational(3), standby(4), or shutdown(5) causes the MAU to assume the respective state except that setting a mixing-type MAU or an AUI to standby(4) will cause the MAU to enter the shutdown state."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.7, aMAUAdminState, 30.5.1.2.2, acMAUAdminControl, and 30.5.1.2.1, acResetMAU."

::= { ifMauEntry 4 }

ifMauMediaAvailable OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 available(3),
 notAvailable(4),
 remoteFault(5),
 invalidSignal(6),
 remoteJabber(7),
 remoteLinkLoss(8),
 remoteTest(9),
 offline(10),
 autoNegError(11),
 pmdLinkFault(12),
 wisFrameLoss(13),
 wisSignalLoss(14),
 pcsLinkFault(15),
 excessiveBER(16),
 dxsLinkFault(17),
 pxsLinkFault(18)


```
    }
MAX-ACCESS      read-only
STATUS          current
DESCRIPTION     "If the MAU is a link or fiber type (FOIRL,
                10BASE-T, 10BASE-F) then this is equivalent to
                the link test fail state/low light function.
                For an AUI or a coax (including broadband) MAU
                this indicates whether or not loopback is
                detected on the DI circuit. The value of this
                attribute persists between packets for MAU types
                AUI, 10BASE5, 10BASE2, 10BROAD36, and 10BASE-FP.
```

The value other(1) is returned if the mediaAvailable state is not one of 2 through 18.

The value unknown(2) is returned when the MAU's true state is unknown; for example, when it is being initialized. At power-up or following a reset, the value of this attribute will be unknown for AUI, coax, and 10BASE-FP MAUs. For these MAUs loopback will be tested on each transmission during which no collision is detected. If DI is receiving input when D0 returns to IDL after a transmission and there has been no collision during the transmission then loopback will be detected. The value of this attribute will only change during non-collided transmissions for AUI, coax, and 10BASE-FP MAUs.

For 100Mbps and 1000Mbps MAUs, the enumerations match the states within the respective link integrity state diagrams, fig 32-16, 23-12 and 24-15 of sections [32](#), [23](#) and [24](#) of [[IEEE802.3](#)]. Any MAU which implements management of auto-negotiation will map remote fault indication to remote fault.

The value available(3) indicates that the link, light, or loopback is normal. The value notAvailable(4) indicates link loss, low light, or no loopback.

The value remoteFault(5) indicates that a fault has been detected at the remote end of the link. This value applies to 10BASE-FB, 100BASE-T4 Far End Fault Indication and non-specified remote faults from a system running auto-negotiation.

The values remoteJabber(7), remoteLinkLoss(8), and remoteTest(9) SHOULD be used instead of remoteFault(5) where the reason for remote fault is identified in the remote signaling protocol.

The value invalidSignal(6) indicates that an invalid signal has been received from the other end of the link. invalidSignal(6) applies only to MAUs of type 10BASE-FB.

Where an IEEE Std 802.3-2002 clause 22 MII is present, a logic one in the remote fault bit (reference [section 22.2.4.2.8](#) of that document) maps to the value remoteFault(5), and a logic zero in the link status bit (reference [section 22.2.4.2.10](#) of that document) maps to the value notAvailable(4). The value notAvailable(4) takes precedence over the value remoteFault(5).

Any MAU that implements management of clause 37 Auto-Negotiation will map the received RF1 and RF2 bit values for Offline to offline(10), Link Failure to remoteFault(5) and Auto-Negotiation Error to autoNegError(11).

For 10 Gb/s, the enumerations map to the states within the Reconciliation Sublayer state diagram as follows:

- NoFault maps to the enumeration 'available(3)'
- LocalFault maps to the enumeration 'notAvailable(4)'
- RemoteFault maps to the enumeration 'remoteFault(5)'

The enumerations 'pmdLinkFault(12)', 'wisFrameLoss(13)', 'wisSignalLoss(14)', 'pcsLinkFault(15)', 'excessiveBER(16)', and 'dxsLinkFault(17)' and 'pxsLinkFault(18)' should be used instead of the enumeration 'notAvailable(4)' where the reason for the local fault can be identified through the use of the MDIO Interface. Where multiple reasons for the local fault state can be identified only the highest precedence error should be reported. The precedence in descending order is as follows:

- pxsLinkFault
- pmdLinkFault
- wisFrameLoss

wisSignalLoss
pcsLinkFault
excessiveBER
dxsLinkFault"

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.4, aMediaAvailable."
::= { ifMauEntry 5 }

ifMauMediaAvailableStateExits OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of times that
ifMauMediaAvailable for this MAU instance leaves
the state available(3).

Discontinuities in the value of this counter can
occur at re-initialization of the management
system, and at other times as indicated by the
value of ifCounterDiscontinuityTime."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.5,
aLoseMediaCounter.
[RFC 2863](#), ifCounterDiscontinuityTime."

::= { ifMauEntry 6 }

ifMauJabberState OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 unknown(2),
 noJabber(3),
 jabbering(4)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION "The value other(1) is returned if the jabber
state is not 2, 3, or 4. The agent MUST always
return other(1) for MAU type dot3MauTypeAUI.

The value unknown(2) is returned when the MAU's
true state is unknown; for example, when it is
being initialized.

If the MAU is not jabbering the agent returns
noJabber(3). This is the 'normal' state.

If the MAU is in jabber state the agent returns
the jabbering(4) value."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.6,
aJabber.jabberFlag."

::= { ifMauEntry 7 }

ifMauJabberingStateEnters OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of times that mauJabberState for this MAU instance enters the state jabbering(4). This counter will always indicate zero for MAUs of type dot3MauTypeAUI and those of speeds above 10Mbps.

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of ifCounterDiscontinuityTime."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.6, aJabber.jabberCounter.
[RFC 2863](#), ifCounterDiscontinuityTime."

::= { ifMauEntry 8 }

ifMauFalseCarriers OBJECT-TYPE

SYNTAX Counter32

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A count of the number of false carrier events during IDLE in 100BASE-X and 1000BASE-X links.

For all other MAU types, this counter will always indicate zero. This counter does not increment at the symbol rate.

It can increment after a valid carrier completion at a maximum rate of once per 100 ms for 100BASE-X and once per 10us for 1000BASE-X until the next CarrierEvent.

This counter can roll over very quickly. A management station is advised to poll the ifMauHCFALSECarriers instead of this counter in order to avoid loss of information.

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of ifCounterDiscontinuityTime."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.10, aFalseCarriers.
[RFC 2863](#), ifCounterDiscontinuityTime."


```
::= { ifMauEntry 9 }
```

```
ifMauTypeList OBJECT-TYPE
```

```
SYNTAX      Integer32
```

```
MAX-ACCESS  read-only
```

```
STATUS      deprecated
```

```
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"
```

This object has been deprecated in favour of ifMauTypeListBits.

A value that uniquely identifies the set of possible IEEE 802.3 types that the MAU could be. The value is a sum which initially takes the value zero. Then, for each type capability of this MAU, 2 raised to the power noted below is added to the sum. For example, a MAU which has the capability to be only 10BASE-T would have a value of 512 (2^{*9}). In contrast, a MAU which supports both 10Base-T (full duplex) and 100BASE-TX (full duplex) would have a value of $((2^{*11}) + (2^{*16}))$ or 67584.

The powers of 2 assigned to the capabilities are these:

Power	Capability
0	other or unknown
1	AUI
2	10BASE-5
3	FOIRL
4	10BASE-2
5	10BASE-T duplex mode unknown
6	10BASE-FP
7	10BASE-FB
8	10BASE-FL duplex mode unknown
9	10BROAD36
10	10BASE-T half duplex mode
11	10BASE-T full duplex mode
12	10BASE-FL half duplex mode
13	10BASE-FL full duplex mode
14	100BASE-T4
15	100BASE-TX half duplex mode
16	100BASE-TX full duplex mode
17	100BASE-FX half duplex mode
18	100BASE-FX full duplex mode
19	100BASE-T2 half duplex mode
20	100BASE-T2 full duplex mode

Flick

Expires September 2003

[Page 32]

If auto-negotiation is present on this MAU, this object will map to ifMauAutoNegCapability."
 ::= { ifMauEntry 10 }

ifMauDefaultType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-write

STATUS current

DESCRIPTION "This object identifies the default administrative baseband MAU type, to be used in conjunction with the operational MAU type denoted by ifMauType.

The set of possible values for this object is the same as the set defined for the ifMauType object.

This object represents the administratively-configured type of the MAU. If auto-negotiation is not enabled or is not implemented for this MAU, the value of this object determines the operational type of the MAU. In this case, a set to this object will force the MAU into the specified operating mode.

If auto-negotiation is implemented and enabled for this MAU, the operational type of the MAU is determined by auto-negotiation, and the value of this object denotes the type to which the MAU will automatically revert if/when auto-negotiation is later disabled.

NOTE TO IMPLEMENTORS: It may be necessary to provide for underlying hardware implementations which do not follow the exact behavior specified above. In particular, when ifMauAutoNegAdminStatus transitions from enabled to disabled, the agent implementation MUST ensure that the operational type of the MAU (as reported by ifMauType) correctly transitions to the value specified by this object, rather than continuing to operate at the value earlier determined by the auto-negotiation function."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.1, aMAUID, and 22.2.4.1.4."

::= { ifMauEntry 11 }

ifMauAutoNegSupported OBJECT-TYPE

Flick

Expires September 2003

[Page 33]

```

SYNTAX      TruthValue
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION "This object indicates whether or not
            auto-negotiation is supported on this MAU."
 ::= { ifMauEntry 12 }

```

ifMauTypeListBits OBJECT-TYPE

```

SYNTAX      BITS {
    bOther(0),          -- other or unknown
    bAUI(1),            -- AUI
    b10base5(2),        -- 10BASE-5
    bFoirl(3),          -- FOIRL

    b10base2(4),        -- 10BASE-2
    b10baseT(5),        -- 10BASE-T duplex mode unknown
    b10baseFP(6),       -- 10BASE-FP
    b10baseFB(7),       -- 10BASE-FB
    b10baseFL(8),       -- 10BASE-FL duplex mode unknown
    b10broad36(9),      -- 10BROAD36
    b10baseTHD(10),     -- 10BASE-T half duplex mode
    b10baseTFD(11),     -- 10BASE-T full duplex mode
    b10baseFLHD(12),    -- 10BASE-FL half duplex mode
    b10baseFLFD(13),    -- 10BASE-FL full duplex mode

    b100baseT4(14),     -- 100BASE-T4
    b100baseTXHD(15),   -- 100BASE-TX half duplex mode
    b100baseTXFD(16),   -- 100BASE-TX full duplex mode
    b100baseFXHD(17),   -- 100BASE-FX half duplex mode
    b100baseFXFD(18),   -- 100BASE-FX full duplex mode
    b100baseT2HD(19),   -- 100BASE-T2 half duplex mode
    b100baseT2FD(20),   -- 100BASE-T2 full duplex mode

    b1000baseXHD(21),   -- 1000BASE-X half duplex mode
    b1000baseXFD(22),   -- 1000BASE-X full duplex mode
    b1000baseLXHD(23),  -- 1000BASE-LX half duplex mode
    b1000baseLXFD(24),  -- 1000BASE-LX full duplex mode
    b1000baseSXHD(25),  -- 1000BASE-SX half duplex mode
    b1000baseSXFD(26),  -- 1000BASE-SX full duplex mode
    b1000baseCXHD(27),  -- 1000BASE-CX half duplex mode
    b1000baseCXFD(28),  -- 1000BASE-CX full duplex mode
    b1000baseTHD(29),   -- 1000BASE-T half duplex mode
    b1000baseTFD(30),   -- 1000BASE-T full duplex mode

    b10GbaseX(31),      -- 10GBASE-X
    b10GbaseLX4(32),    -- 10GBASE-LX4
    b10GbaseR(33),      -- 10GBASE-R
    b10GbaseER(34),     -- 10GBASE-ER

```



```
    b10GbaseLR(35),    -- 10GBASE-LR
    b10GbaseSR(36),    -- 10GBASE-SR
    b10GbaseW(37),     -- 10GBASE-W
    b10GbaseEW(38),    -- 10GBASE-EW
    b10GbaseLW(39),    -- 10GBASE-LW
    b10GbaseSW(40)     -- 10GBASE-SW
}
MAX-ACCESS    read-only
STATUS        current
DESCRIPTION   "A value that uniquely identifies the set of
               possible IEEE 802.3 types that the MAU could be.
               If auto-negotiation is present on this MAU, this
               object will map to ifMauAutoNegCapabilityBits.
```

Note that this MAU may be capable of operating as a MAU type that is beyond the scope of this MIB. This is indicated by returning the bit value bOther in addition to any bit values for capabilities that are listed above."

```
::= { ifMauEntry 13 }
```

ifMauHCFALSECarriers OBJECT-TYPE

```
SYNTAX        Counter64
MAX-ACCESS    read-only
STATUS        current
DESCRIPTION   "A count of the number of false carrier events
               during IDLE in 100BASE-X and 1000BASE-X links.
```

For all other MAU types, this counter will always indicate zero. This counter does not increment at the symbol rate.

This counter is a 64 bit version of ifMauFalseCarriers. Since the 32 bit version of this counter can roll over very quickly, management stations are advised to poll the 64 bit version instead in order to avoid loss of information.

Discontinuities in the value of this counter can occur at re-initialization of the management system, and at other times as indicated by the value of ifCounterDiscontinuityTime."

```
REFERENCE     "[IEEE 802.3 Std], 30.5.1.1.10, aFalseCarriers.
               RFC 2863, ifCounterDiscontinuityTime."
```

```
::= { ifMauEntry 14 }
```


-- The ifJackTable applies to MAUs attached to interfaces
-- which have one or more external jacks (connectors).

ifJackTable OBJECT-TYPE

SYNTAX SEQUENCE OF IfJackEntry
MAX-ACCESS not-accessible
STATUS current
DESCRIPTION "Information about the external jacks attached
to MAUs attached to an interface."
::= { dot3IfMauBasicGroup 2 }

ifJackEntry OBJECT-TYPE

SYNTAX IfJackEntry
MAX-ACCESS not-accessible
STATUS current
DESCRIPTION "An entry in the table, containing information
about a particular jack."
INDEX { ifMauIfIndex,
ifMauIndex,
ifJackIndex
}
::= { ifJackTable 1 }

IfJackEntry ::=

SEQUENCE {
ifJackIndex Integer32,
ifJackType JackType
}

ifJackIndex OBJECT-TYPE

SYNTAX Integer32 (1..2147483647)
MAX-ACCESS not-accessible
STATUS current
DESCRIPTION "This variable uniquely identifies the jack
described by this entry from among other jacks
attached to the same MAU."
::= { ifJackEntry 1 }

ifJackType OBJECT-TYPE

SYNTAX JackType
MAX-ACCESS read-only
STATUS current
DESCRIPTION "The jack connector type, as it appears on the
outside of the system."
::= { ifJackEntry 2 }

--


```
-- The MAU Auto-Negotiation Table
--
```

```
ifMauAutoNegTable OBJECT-TYPE
```

```
    SYNTAX      SEQUENCE OF IfMauAutoNegEntry
```

```
    MAX-ACCESS  not-accessible
```

```
    STATUS      current
```

```
    DESCRIPTION "Configuration and status objects for the
                  auto-negotiation function of MAUs attached to
                  interfaces.
```

```
                  The ifMauAutoNegTable applies to systems in
                  which auto-negotiation is supported on one or
                  more MAUs attached to interfaces. Note that if
                  auto-negotiation is present and enabled, the
                  ifMauType object reflects the result of the
                  auto-negotiation function."
```

```
 ::= { dot3IfMauAutoNegGroup 1 }
```

```
ifMauAutoNegEntry OBJECT-TYPE
```

```
    SYNTAX      IfMauAutoNegEntry
```

```
    MAX-ACCESS  not-accessible
```

```
    STATUS      current
```

```
    DESCRIPTION "An entry in the table, containing configuration
                  and status information for the auto-negotiation
                  function of a particular MAU."
```

```
    INDEX      { ifMauIfIndex,
                  ifMauIndex
                }
```

```
 ::= { ifMauAutoNegTable 1 }
```

```
IfMauAutoNegEntry ::=
```

```
    SEQUENCE {
```

```
        ifMauAutoNegAdminStatus      INTEGER,
```

```
        ifMauAutoNegRemoteSignaling  INTEGER,
```

```
        ifMauAutoNegConfig            INTEGER,
```

```
        ifMauAutoNegCapability        Integer32,
```

```
        ifMauAutoNegCapAdvertised     Integer32,
```

```
        ifMauAutoNegCapReceived       Integer32,
```

```
        ifMauAutoNegRestart           INTEGER,
```

```
        ifMauAutoNegCapabilityBits    BITS,
```

```
        ifMauAutoNegCapAdvertisedBits BITS,
```

```
        ifMauAutoNegCapReceivedBits  BITS,
```

```
        ifMauAutoNegRemoteFaultAdvertised  INTEGER,
```

```
        ifMauAutoNegRemoteFaultReceived  INTEGER
```

```
    }
```


ifMauAutoNegAdminStatus OBJECT-TYPE

SYNTAX INTEGER {
 enabled(1),
 disabled(2)
 }

MAX-ACCESS read-write

STATUS current

DESCRIPTION "Setting this object to enabled(1) will cause
 the interface which has the auto-negotiation
 signaling ability to be enabled.

If the value of this object is disabled(2) then
the interface will act as it would if it had no
auto-negotiation signaling. Under these
conditions, an IEEE 802.3 MAU will immediately
be forced to the state indicated by the value of
the object ifMauDefaultType.

NOTE TO IMPLEMENTORS: When
ifMauAutoNegAdminStatus transitions from enabled
to disabled, the agent implementation MUST
ensure that the operational type of the MAU (as
reported by ifMauType) correctly transitions to
the value specified by the ifMauDefaultType
object, rather than continuing to operate at the
value earlier determined by the auto-negotiation
function."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.2,
 aAutoNegAdminState and 30.6.1.2.2,
 acAutoNegAdminControl."

::= { ifMauAutoNegEntry 1 }

ifMauAutoNegRemoteSignaling OBJECT-TYPE

SYNTAX INTEGER {
 detected(1),
 notdetected(2)
 }

MAX-ACCESS read-only

STATUS current

DESCRIPTION "A value indicating whether the remote end of
 the link is using auto-negotiation signaling. It
 takes the value detected(1) if and only if,
 during the previous link negotiation, FLP Bursts
 were received."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.3,
 aAutoNegRemoteSignaling."

::= { ifMauAutoNegEntry 2 }

Flick

Expires September 2003

[Page 38]

ifMauAutoNegConfig OBJECT-TYPE

```
SYNTAX      INTEGER {
                other(1),
                configuring(2),
                complete(3),
                disabled(4),
                parallelDetectFail(5)
            }
MAX-ACCESS   read-only
STATUS       current
DESCRIPTION  "A value indicating the current status of the
              auto-negotiation process.  The enumeration
              parallelDetectFail(5) maps to a failure in
              parallel detection as defined in 28.2.3.1 of
              [IEEE 802.3 Std]."
```

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.4,
 aAutoNegAutoConfig."

::= { ifMauAutoNegEntry 4 }

ifMauAutoNegCapability OBJECT-TYPE

```
SYNTAX      Integer32
MAX-ACCESS   read-only
STATUS       deprecated
DESCRIPTION  "***** THIS OBJECT IS DEPRECATED *****"
```

This object has been deprecated in favour of
ifMauAutoNegCapabilityBits.

A value that uniquely identifies the set of capabilities of the local auto-negotiation entity. The value is a sum which initially takes the value zero. Then, for each capability of this interface, 2 raised to the power noted below is added to the sum. For example, an interface which has the capability to support only 100Base-TX half duplex would have a value of 32768 (2^{15}). In contrast, an interface which supports both 100Base-TX half duplex and 100Base-TX full duplex would have a value of 98304 ($((2^{15}) + (2^{16}))$).

The powers of 2 assigned to the capabilities are these:

Power	Capability
0	other or unknown
(1-9)	(reserved)
10	10BASE-T half duplex mode

11	10BASE-T full duplex mode
12	(reserved)
13	(reserved)
14	100BASE-T4
15	100BASE-TX half duplex mode
16	100BASE-TX full duplex mode
17	(reserved)
18	(reserved)
19	100BASE-T2 half duplex mode
20	100BASE-T2 full duplex mode

Note that interfaces that support this MIB may have capabilities that extend beyond the scope of this MIB."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.5,
aAutoNegLocalTechnologyAbility."
::= { ifMauAutoNegEntry 5 }

ifMauAutoNegCapAdvertised OBJECT-TYPE

SYNTAX Integer32
MAX-ACCESS read-write
STATUS deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This object has been deprecated in favour of ifMauAutoNegCapAdvertisedBits.

A value that uniquely identifies the set of capabilities advertised by the local auto-negotiation entity. Refer to ifMauAutoNegCapability for a description of the possible values of this object.

Capabilities in this object that are not available in ifMauAutoNegCapability cannot be enabled."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.6,
aAutoNegAdvertisedTechnologyAbility."
::= { ifMauAutoNegEntry 6 }

ifMauAutoNegCapReceived OBJECT-TYPE

SYNTAX Integer32
MAX-ACCESS read-only
STATUS deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This object has been deprecated in favour of ifMauAutoNegCapReceivedBits.

A value that uniquely identifies the set of capabilities received from the remote auto-negotiation entity. Refer to ifMauAutoNegCapability for a description of the possible values of this object.

Note that interfaces that support this MIB may be attached to remote auto-negotiation entities which have capabilities beyond the scope of this MIB."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
::= { ifMauAutoNegEntry 7 }

ifMauAutoNegRestart OBJECT-TYPE

SYNTAX INTEGER {
 restart(1),
 norestart(2)
}

MAX-ACCESS read-write

STATUS current

DESCRIPTION "If the value of this object is set to restart(1) then this will force auto-negotiation to begin link renegotiation. If auto-negotiation signaling is disabled, a write to this object has no effect.

Setting the value of this object to norestart(2) has no effect."

REFERENCE "[IEEE 802.3 Std], 30.6.1.2.1,
acAutoNegRestartAutoConfig."
::= { ifMauAutoNegEntry 8 }

ifMauAutoNegCapabilityBits OBJECT-TYPE

SYNTAX BITS {
 bOther(0), -- other or unknown
 b10baseT(1), -- 10BASE-T half duplex mode
 b10baseTFD(2), -- 10BASE-T full duplex mode
 b100baseT4(3), -- 100BASE-T4
 b100baseTX(4), -- 100BASE-TX half duplex mode
 b100baseTXFD(5), -- 100BASE-TX full duplex mode
 b100baseT2(6), -- 100BASE-T2 half duplex mode
 b100baseT2FD(7), -- 100BASE-T2 full duplex mode
 bfdxPause(8), -- PAUSE for full-duplex links
 bfdxAPause(9), -- Asymmetric PAUSE for full-duplex
 -- links
 bfdxSPause(10), -- Symmetric PAUSE for full-duplex
 -- links

Flick

Expires September 2003

[Page 41]

```

    bFdxBPAUSE(11),    -- Asymmetric and Symmetric PAUSE for
                        --      full-duplex links
    b1000baseX(12),    -- 1000BASE-X, -LX, -SX, -CX half
                        --      duplex mode
    b1000baseXFD(13),  -- 1000BASE-X, -LX, -SX, -CX full
                        --      duplex mode
    b1000baseT(14),    -- 1000BASE-T half duplex mode
    b1000baseTFD(15)   -- 1000BASE-T full duplex mode
}
MAX-ACCESS    read-only
STATUS        current
DESCRIPTION   "A value that uniquely identifies the set of
              capabilities of the local auto-negotiation
              entity. Note that interfaces that support this
              MIB may have capabilities that extend beyond the
              scope of this MIB.

              Note that the local auto-negotiation entity may
              support some capabilities beyond the scope of
              this MIB. This is indicated by returning the
              bit value bOther in addition to any bit values
              for capabilities that are listed above."
REFERENCE    "[IEEE 802.3 Std], 30.6.1.1.5,
              aAutoNegLocalTechnologyAbility."
 ::= { ifMauAutoNegEntry 9 }

```

ifMauAutoNegCapAdvertisedBits OBJECT-TYPE

```

SYNTAX      BITS {
    bOther(0),          -- other or unknown
    b10baseT(1),        -- 10BASE-T half duplex mode
    b10baseTFD(2),      -- 10BASE-T full duplex mode
    b100baseT4(3),      -- 100BASE-T4
    b100baseTX(4),      -- 100BASE-TX half duplex mode
    b100baseTXFD(5),    -- 100BASE-TX full duplex mode
    b100baseT2(6),      -- 100BASE-T2 half duplex mode
    b100baseT2FD(7),    -- 100BASE-T2 full duplex mode
    bFdxPause(8),       -- PAUSE for full-duplex links
    bFdxAPause(9),      -- Asymmetric PAUSE for full-duplex
                        --      links
    bFdxSPause(10),     -- Symmetric PAUSE for full-duplex
                        --      links
    bFdxBPAUSE(11),     -- Asymmetric and Symmetric PAUSE for
                        --      full-duplex links
    b1000baseX(12),     -- 1000BASE-X, -LX, -SX, -CX half
                        --      duplex mode
    b1000baseXFD(13),   -- 1000BASE-X, -LX, -SX, -CX full
                        --      duplex mode
    b1000baseT(14),     -- 1000BASE-T half duplex mode

```



```

        b1000baseTFD(15) -- 1000BASE-T full duplex mode
    }
    MAX-ACCESS    read-write
    STATUS        current
    DESCRIPTION    "A value that uniquely identifies the set of
                   capabilities advertised by the local
                   auto-negotiation entity."

```

Capabilities in this object that are not available in ifMauAutoNegCapabilityBits cannot be enabled.

Note that the local auto-negotiation entity may advertise some capabilities beyond the scope of this MIB. This is indicated by returning the bit value b0ther in addition to any bit values for capabilities that are listed above."

```

REFERENCE    "[IEEE 802.3 Std], 30.6.1.1.6,
              aAutoNegAdvertisedTechnologyAbility."
::= { ifMauAutoNegEntry 10 }

```

ifMauAutoNegCapReceivedBits OBJECT-TYPE

```

SYNTAX      BITS {
    b0ther(0),          -- other or unknown
    b10baseT(1),        -- 10BASE-T half duplex mode
    b10baseTFD(2),      -- 10BASE-T full duplex mode
    b100baseT4(3),      -- 100BASE-T4
    b100baseTX(4),      -- 100BASE-TX half duplex mode
    b100baseTXFD(5),    -- 100BASE-TX full duplex mode
    b100baseT2(6),      -- 100BASE-T2 half duplex mode
    b100baseT2FD(7),    -- 100BASE-T2 full duplex mode
    bFdxPause(8),       -- PAUSE for full-duplex links
    bFdxAPause(9),      -- Asymmetric PAUSE for full-duplex
                        -- links
    bFdxSPause(10),     -- Symmetric PAUSE for full-duplex
                        -- links
    bFdxBPAuse(11),     -- Asymmetric and Symmetric PAUSE for
                        -- full-duplex links
    b1000baseX(12),     -- 1000BASE-X, -LX, -SX, -CX half
                        -- duplex mode
    b1000baseXFD(13),   -- 1000BASE-X, -LX, -SX, -CX full
                        -- duplex mode
    b1000baseT(14),     -- 1000BASE-T half duplex mode
    b1000baseTFD(15)    -- 1000BASE-T full duplex mode
}
    MAX-ACCESS    read-only
    STATUS        current
    DESCRIPTION    "A value that uniquely identifies the set of

```


capabilities received from the remote auto-negotiation entity.

Note that interfaces that support this MIB may be attached to remote auto-negotiation entities which have capabilities beyond the scope of this MIB. This is indicated by returning the bit value bOther in addition to any bit values for capabilities that are listed above."

REFERENCE "[IEEE 802.3 Std], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
::= { ifMauAutoNegEntry 11 }

ifMauAutoNegRemoteFaultAdvertised OBJECT-TYPE

SYNTAX INTEGER {
noError(1),
offline(2),
linkFailure(3),
autoNegError(4)
}
MAX-ACCESS read-write
STATUS current
DESCRIPTION "A value that identifies any local fault indications that this MAU has detected and will advertise at the next auto-negotiation interaction for 1000Mbps MAUs."
REFERENCE "[IEEE 802.3 Std], 30.6.1.1.6,
aAutoNegAdvertisedTechnologyAbility."
::= { ifMauAutoNegEntry 12 }

ifMauAutoNegRemoteFaultReceived OBJECT-TYPE

SYNTAX INTEGER {
noError(1),
offline(2),
linkFailure(3),
autoNegError(4)
}
MAX-ACCESS read-only
STATUS current
DESCRIPTION "A value that identifies any fault indications received from the far end of a link by the local auto-negotiation entity for 1000Mbps MAUs."
REFERENCE "[IEEE 802.3 Std], 30.6.1.1.7,
aAutoNegReceivedTechnologyAbility."
::= { ifMauAutoNegEntry 13 }

Flick

Expires September 2003

[Page 44]

--

-- The Basic Broadband MAU Table

--

broadMauBasicTable OBJECT-TYPE

SYNTAX SEQUENCE OF BroadMauBasicEntry

MAX-ACCESS not-accessible

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This entire table has been deprecated. There have been no reported implementations of this table, and it is unlikely that there ever will be. IEEE recommends that broadband MAU types should not be used for new installations.

Table of descriptive and status information about the broadband MAUs connected to interfaces."

::= { dot3BroadMauBasicGroup 1 }

broadMauBasicEntry OBJECT-TYPE

SYNTAX BroadMauBasicEntry

MAX-ACCESS not-accessible

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

An entry in the table, containing information about a single broadband MAU."

INDEX { broadMauIfIndex,
broadMauIndex
}

::= { broadMauBasicTable 1 }

BroadMauBasicEntry ::=

SEQUENCE {

broadMauIfIndex	InterfaceIndex,
broadMauIndex	Integer32,
broadMauXmtRcvSplitType	INTEGER,
broadMauXmtCarrierFreq	Integer32,
broadMauTranslationFreq	Integer32

}

broadMauIfIndex OBJECT-TYPE

SYNTAX InterfaceIndex

MAX-ACCESS read-only -- read-only since originally an
-- SMIV1 index

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This variable uniquely identifies the interface to which the MAU described by this entry is connected."

REFERENCE "Reference [RFC 2863](#), ifIndex."

::= { broadMauBasicEntry 1 }

broadMauIndex OBJECT-TYPE

SYNTAX Integer32 (1..2147483647)

MAX-ACCESS read-only -- read-only since originally an
-- SMiv1 index

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This variable uniquely identifies the MAU connected to interface broadMauIfIndex that is described by this entry."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.1, aMAUID."

::= { broadMauBasicEntry 2 }

broadMauXmtRcvSplitType OBJECT-TYPE

SYNTAX INTEGER {
 other(1),
 single(2),
 dual(3)
}

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****

This object indicates the type of frequency multiplexing/cabling system used to separate the transmit and receive paths for the 10BROAD36 MAU.

The value other(1) is returned if the split type is not either single or dual.

The value single(2) indicates a single cable system. The value dual(3) indicates a dual cable system, offset normally zero."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.8,
aBbMAUXmitRcvSplitType."

::= { broadMauBasicEntry 3 }

broadMauXmtCarrierFreq OBJECT-TYPE

SYNTAX Integer32

MAX-ACCESS read-only
STATUS deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This variable indicates the transmit carrier frequency of the 10BROAD36 MAU in MHz/4; that is, in units of 250 kHz."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.9, aBroadbandFrequencies.xmitCarrierFrequency."
::= { broadMauBasicEntry 4 }

broadMauTranslationFreq OBJECT-TYPE

SYNTAX Integer32
MAX-ACCESS read-only
STATUS deprecated
DESCRIPTION "***** THIS OBJECT IS DEPRECATED *****"

This variable indicates the translation offset frequency of the 10BROAD36 MAU in MHz/4; that is, in units of 250 kHz."

REFERENCE "[IEEE 802.3 Std], 30.5.1.1.9, aBroadbandFrequencies.translationFrequency."
::= { broadMauBasicEntry 5 }

-- Notifications for use by 802.3 MAUs

snmpDot3MauTraps OBJECT IDENTIFIER ::= { snmpDot3MauMgt 0 }

rpMauJabberTrap NOTIFICATION-TYPE

OBJECTS { rpMauJabberState }
STATUS current
DESCRIPTION "This trap is sent whenever a managed repeater MAU enters the jabber state."

The agent MUST throttle the generation of consecutive rpMauJabberTraps so that there is at least a five-second gap between them."

REFERENCE "[IEEE 802.3 Mgt], 30.5.1.3.1, nJabber notification."
::= { snmpDot3MauTraps 1 }

ifMauJabberTrap NOTIFICATION-TYPE

OBJECTS { ifMauJabberState }
STATUS current
DESCRIPTION "This trap is sent whenever a managed interface MAU enters the jabber state."


```

        The agent MUST throttle the generation of
        consecutive ifMauJabberTraps so that there is at
        least a five-second gap between them."
REFERENCE  "[IEEE 802.3 Mgt], 30.5.1.3.1, nJabber
            notification."
 ::= { snmpDot3MauTraps 2 }

-- Conformance information

mauModConf
    OBJECT IDENTIFIER ::= { mauMod 1 }
mauModCompls
    OBJECT IDENTIFIER ::= { mauModConf 1 }
mauModObjGrps
    OBJECT IDENTIFIER ::= { mauModConf 2 }
mauModNotGrps
    OBJECT IDENTIFIER ::= { mauModConf 3 }

-- Object groups

mauRpGrpBasic OBJECT-GROUP
    OBJECTS      { rpMauGroupIndex,
                  rpMauPortIndex,
                  rpMauIndex,
                  rpMauType,
                  rpMauStatus,
                  rpMauMediaAvailable,
                  rpMauMediaAvailableStateExits,
                  rpMauJabberState,
                  rpMauJabberingStateEnters
                }
    STATUS      current
    DESCRIPTION "Basic conformance group for MAUs attached to
                repeater ports. This group is also the
                conformance specification for RFC 1515
                implementations."
    ::= { mauModObjGrps 1 }

mauRpGrp100Mbs OBJECT-GROUP
    OBJECTS      { rpMauFalseCarriers }
    STATUS      current
    DESCRIPTION "Conformance group for MAUs attached to
                repeater ports with 100 Mb/s or greater
                capability."
    ::= { mauModObjGrps 2 }
```



```
mauRpGrpJack OBJECT-GROUP
    OBJECTS      { rpJackType }
    STATUS       current
    DESCRIPTION   "Conformance group for MAUs attached to
                    repeater ports with managed jacks."
    ::= { mauModObjGrps 3 }

mauIfGrpBasic OBJECT-GROUP
    OBJECTS      { ifMauIfIndex,
                    ifMauIndex,
                    ifMauType,
                    ifMauStatus,
                    ifMauMediaAvailable,
                    ifMauMediaAvailableStateExits,
                    ifMauJabberState,
                    ifMauJabberingStateEnters
                  }
    STATUS       current
    DESCRIPTION   "Basic conformance group for MAUs attached to
                    interfaces. This group also provides a
                    conformance specification for RFC 1515
                    implementations."
    ::= { mauModObjGrps 4 }

mauIfGrp100Mbs OBJECT-GROUP
    OBJECTS      { ifMauFalseCarriers,
                    ifMauTypeList,
                    ifMauDefaultType,
                    ifMauAutoNegSupported
                  }
    STATUS       deprecated
    DESCRIPTION   "***** THIS GROUP IS DEPRECATED *****

                    Conformance group for MAUs attached to
                    interfaces with 100 Mb/s capability.

                    This object group has been deprecated in favor
                    of mauIfGrpHighCapacity."
    ::= { mauModObjGrps 5 }

mauIfGrpJack OBJECT-GROUP
    OBJECTS      { ifJackType }
    STATUS       current
    DESCRIPTION   "Conformance group for MAUs attached to
                    interfaces with managed jacks."
    ::= { mauModObjGrps 6 }

mauIfGrpAutoNeg OBJECT-GROUP
```



```
OBJECTS      { ifMauAutoNegAdminStatus,
                ifMauAutoNegRemoteSignaling,
                ifMauAutoNegConfig,
                ifMauAutoNegCapability,
                ifMauAutoNegCapAdvertised,
                ifMauAutoNegCapReceived,
                ifMauAutoNegRestart
              }
STATUS       deprecated
DESCRIPTION  "***** THIS GROUP IS DEPRECATED *****"
```

Conformance group for MAUs attached to
interfaces with managed auto-negotiation.

This object group has been deprecated in favor
of mauIfGrpAutoNeg2."

```
::= { mauModObjGrps 7 }
```

mauBroadBasic OBJECT-GROUP

```
OBJECTS      { broadMauIfIndex,
                broadMauIndex,
                broadMauXmtRcvSplitType,
                broadMauXmtCarrierFreq,
                broadMauTranslationFreq
              }
STATUS       deprecated
DESCRIPTION  "***** THIS GROUP IS DEPRECATED *****"
```

Conformance group for broadband MAUs attached
to interfaces.

This object group is deprecated. There have
been no reported implementations of this group,
and it was felt to be unlikely that there will
be any future implementations."

```
::= { mauModObjGrps 8 }
```

mauIfGrpHighCapacity OBJECT-GROUP

```
OBJECTS      { ifMauFalseCarriers,
                ifMauTypeListBits,
                ifMauDefaultType,
                ifMauAutoNegSupported
              }
STATUS       current
DESCRIPTION  "Conformance group for MAUs attached to
              interfaces with 100 Mb/s or greater capability."
::= { mauModObjGrps 9 }
```



```
mauIfGrpAutoNeg2 OBJECT-GROUP
    OBJECTS      { ifMauAutoNegAdminStatus,
                    ifMauAutoNegRemoteSignaling,
                    ifMauAutoNegConfig,
                    ifMauAutoNegCapabilityBits,
                    ifMauAutoNegCapAdvertisedBits,
                    ifMauAutoNegCapReceivedBits,
                    ifMauAutoNegRestart
                  }
    STATUS       current
    DESCRIPTION   "Conformance group for MAUs attached to
                  interfaces with managed auto-negotiation."
    ::= { mauModObjGrps 10 }

mauIfGrpAutoNeg1000Mbps OBJECT-GROUP
    OBJECTS      { ifMauAutoNegRemoteFaultAdvertised,
                    ifMauAutoNegRemoteFaultReceived
                  }
    STATUS       current
    DESCRIPTION   "Conformance group for 1000Mbps MAUs attached to
                  interfaces with managed auto-negotiation."
    ::= { mauModObjGrps 11 }

mauIfGrpHCStats OBJECT-GROUP
    OBJECTS      { ifMauHCFALSECarriers }
    STATUS       current
    DESCRIPTION   "Conformance for high capacity statistics for
                  MAUs attached to interfaces"
    ::= { mauModObjGrps 12 }

-- Notification groups

rpMauNotifications NOTIFICATION-GROUP
    NOTIFICATIONS { rpMauJabberTrap }
    STATUS       current
    DESCRIPTION   "Notifications for repeater MAUs."
    ::= { mauModNotGrps 1 }

ifMauNotifications NOTIFICATION-GROUP
    NOTIFICATIONS { ifMauJabberTrap }
    STATUS       current
    DESCRIPTION   "Notifications for interface MAUs."
    ::= { mauModNotGrps 2 }

-- Compliances
```


mauModRpCompl MODULE-COMPLIANCE

STATUS deprecated

DESCRIPTION "***** THIS COMPLIANCE IS DEPRECATED *****"

Compliance for MAUs attached to repeater ports.

This compliance is deprecated and replaced by mauModRpCompl2, which corrects an oversight by allowing rpMauStatus to be implemented read-only."

MODULE -- this module

MANDATORY-GROUPS { mauRpGrpBasic }

GROUP mauRpGrp100Mbps

DESCRIPTION "Implementation of this optional group is recommended for MAUs which have 100Mb/s or greater capability."

GROUP mauRpGrpJack

DESCRIPTION "Implementation of this optional group is recommended for MAUs which have one or more external jacks."

GROUP rpMauNotifications

DESCRIPTION "Implementation of this group is recommended for MAUs attached to repeater ports."

::= { mauModCompls 1 }

mauModIfCompl MODULE-COMPLIANCE

STATUS deprecated

DESCRIPTION "***** THIS COMPLIANCE IS DEPRECATED *****"

Compliance for MAUs attached to interfaces.

This compliance is deprecated and replaced by mauModIfCompl2."

MODULE -- this module

MANDATORY-GROUPS { mauIfGrpBasic }

GROUP mauIfGrp100Mbps

DESCRIPTION "Implementation of this optional group is recommended for MAUs which have 100Mb/s capability."


```
GROUP      mauIfGrpJack
DESCRIPTION "Implementation of this optional group is
            recommended for MAUs which have one or more
            external jacks."

GROUP      mauIfGrpAutoNeg
DESCRIPTION "Implementation of this group is mandatory
            for MAUs which support managed
            auto-negotiation."

GROUP      mauBroadBasic
DESCRIPTION "Implementation of this group is mandatory
            for broadband MAUs."

GROUP      ifMauNotifications
DESCRIPTION "Implementation of this group is recommended
            for MAUs attached to interfaces."
::= { mauModCompls 2 }

mauModIfCompl2 MODULE-COMPLIANCE
STATUS      deprecated
DESCRIPTION "***** THIS COMPLIANCE IS DEPRECATED *****

            Compliance for MAUs attached to interfaces.

            This compliance is deprecated and replaced by
            mauModIfCompl3."

MODULE -- this module
MANDATORY-GROUPS { mauIfGrpBasic }

GROUP      mauIfGrpHighCapacity
DESCRIPTION "Implementation of this optional group is
            recommended for MAUs which have 100Mb/s
            or greater capability."

GROUP      mauIfGrpJack
DESCRIPTION "Implementation of this optional group is
            recommended for MAUs which have one or more
            external jacks."

GROUP      mauIfGrpAutoNeg2
DESCRIPTION "Implementation of this group is mandatory
            for MAUs which support managed
            auto-negotiation."

GROUP      mauIfGrpAutoNeg1000Mbps
DESCRIPTION "Implementation of this group is mandatory
```


for MAUs which have 1000Mb/s or greater capability and support managed auto-negotiation."

GROUP ifMauNotifications
DESCRIPTION "Implementation of this group is recommended for MAUs attached to interfaces."

OBJECT ifMauStatus
MIN-ACCESS read-only
DESCRIPTION "Write access is not required."
::= { mauModCompls 3 }

mauModRpCompl2 MODULE-COMPLIANCE

STATUS current
DESCRIPTION "Compliance for MAUs attached to repeater ports."

Note that compliance with this compliance statement requires compliance with the snmpRptrModCompl MODULE-COMPLIANCE statement of the SNMP-REPEATER-MIB [[RFC2108](#)]."

MODULE -- this module

MANDATORY-GROUPS { mauRpGrpBasic }

GROUP mauRpGrp100Mbs
DESCRIPTION "Implementation of this optional group is recommended for MAUs which have 100Mb/s or greater capability."

GROUP mauRpGrpJack
DESCRIPTION "Implementation of this optional group is recommended for MAUs which have one or more external jacks."

GROUP rpMauNotifications
DESCRIPTION "Implementation of this group is recommended for MAUs attached to repeater ports."

OBJECT rpMauStatus
MIN-ACCESS read-only
DESCRIPTION "Write access is not required."
::= { mauModCompls 4 }

mauModIfCompl3 MODULE-COMPLIANCE

STATUS current
DESCRIPTION "Compliance for MAUs attached to interfaces."

Note that compliance with this compliance statement requires compliance with the ifCompliance3 MODULE-COMPLIANCE statement of the IF-MIB [[RFC2863](#)] and the dot3Compliance2 MODULE-COMPLIANCE statement of the EtherLike-MIB [[ETHERIF](#)]."

```
MODULE -- this module
  MANDATORY-GROUPS { mauIfGrpBasic }

  GROUP      mauIfGrpHighCapacity
  DESCRIPTION "Implementation of this optional group is
               recommended for MAUs which have 100Mb/s
               or greater capability."

  GROUP      mauIfGrpHCStats
  DESCRIPTION "Implementation of this group is mandatory
               for MAUs which have 1000Mb/s capacity, and
               is recommended for MAUs which have 100Mb/s
               capacity."

  GROUP      mauIfGrpJack
  DESCRIPTION "Implementation of this optional group is
               recommended for MAUs which have one or more
               external jacks."

  GROUP      mauIfGrpAutoNeg2
  DESCRIPTION "Implementation of this group is mandatory
               for MAUs which support managed
               auto-negotiation."

  GROUP      mauIfGrpAutoNeg1000Mbps
  DESCRIPTION "Implementation of this group is mandatory
               for MAUs which have 1000Mb/s or greater
               capability and support managed
               auto-negotiation."

  GROUP      ifMauNotifications
  DESCRIPTION "Implementation of this group is recommended
               for MAUs attached to interfaces."

  OBJECT      ifMauStatus
  MIN-ACCESS  read-only
  DESCRIPTION "Write access is not required."
 ::= { mauModCompls 5 }
```

END

5. Intellectual Property

The IETF takes no position regarding the validity or scope of any intellectual property or other rights that might be claimed to pertain to the implementation or use of the technology described in this document or the extent to which any license under such rights might or might not be available; neither does it represent that it has made any effort to identify any such rights. Information on the IETF's procedures with respect to rights in standards-track and standards-related documentation can be found in [BCP-11](#). Copies of claims of rights made available for publication and any assurances of licenses to be made available, or the result of an attempt made to obtain a general license or permission for the use of such proprietary rights by implementors or users of this specification can be obtained from the IETF Secretariat.

The IETF invites any interested party to bring to its attention any copyrights, patents or patent applications, or other proprietary rights which may cover technology that may be required to practice this standard. Please address the information to the IETF Executive Director.

6. Acknowledgements

This document was produced by the IETF Ethernet Interfaces and Hub MIB Working Group, whose efforts were greatly advanced by the contributions of the following people:

Mike Ayers
Mike Heard
Chuck Black
John Flick
Jeff Johnson
Kam Lam
Leon Leong
Mike Lui
Kerry McDonald
K.C. Norseth
Dave Perkins
Dan Romascanu
Andrew Smith
Kaj Tesink
Geoff Thompson
Maurice Turcotte
Paul Woodruff

This document is based on the Proposed Standard MAU MIB, [RFC 2668](#)

[[RFC2668](#)], edited by John Flick of Hewlett-Packard and Andrew Smith, then of Extreme Networks, and produced by the Ethernet Interfaces and Hub MIB Working Group. It extends that document by providing support for 10 Gb/s MAUs as defined in [[IEEE802.3ae](#)].

[RFC 2668](#), in turn, was based on the Proposed Standard MAU MIB, [RFC 2239](#) [[RFC2239](#)], edited by Kathryn de Graaf, then of 3Com, and Dan Romascanu, then of Madge Networks, and produced by the Ethernet Interfaces and Hub MIB Working Group. It extended that document by providing support for 1000 Mb/sec MAUs as defined in [[IEEE802.3](#)].

[RFC 2239](#), in turn, was based on the Proposed Standard MAU MIB, [RFC 1515](#) [[RFC1515](#)], edited by Donna McMaster, then of SynOptics Communications, Keith McCloghrie, then of Hughes LAN Systems, and Sam Roberts, then of Farallon Computing, and produced by the Hub MIB Working Group. It extends that document by providing support for 100 Mb/sec MAUs, full duplex MAUs, and auto-negotiation, as defined in [[IEEE802.3](#)].

7. Normative References

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirements Levels", [BCP 14](#), [RFC 2119](#), March 1997.
- [RFC2578] McCloghrie, K., Perkins, D., Schoenwaelder, J., Case, J., Rose, M. and S. Waldbusser, "Structure of Management Information Version 2 (SMIV2)", STD 58, [RFC 2578](#), April 1999.
- [RFC2579] McCloghrie, K., Perkins, D., Schoenwaelder, J., Case, J., Rose, M. and S. Waldbusser, "Textual Conventions for SMIV2", STD 58, [RFC 2579](#), April 1999.
- [RFC2580] McCloghrie, K., Perkins, D., Schoenwaelder, J., Case, J., Rose, M. and S. Waldbusser, "Conformance Statements for SMIV2", STD 58, [RFC 2580](#), April 1999.
- [IEEE802.3] IEEE, IEEE Std 802.3, 2002 Edition: "Carrier Sense Multiple Access with Collision Detection (CSMA/CD) Access Method and Physical Layer Specifications", March 2002.
- [IEEE802.3ae] IEEE, IEEE Std 802.3ae-2002, "Amendment: Media Access Control (MAC) Parameters, Physical Layers, and Management Parameters for 10 Gb/s Operation", August, 2002.

- [RFC2863] McCloghrie, K. and F. Kastenholz, "The Interfaces Group MIB using SMIV2", [RFC 2863](#), June 2000.
- [RFC2108] de Graaf, K., D. Romascanu, D. McMaster, and K. McCloghrie, "Definitions of Managed Objects for IEEE 802.3 Repeater Devices using SMIV2", [RFC 2108](#), February 1997.
- [ETHERIF] Flick, J., "Definitions of Managed Objects for the Ethernet-like Interface Types", work in progress, [draft-ietf-hubmib-etherif-mib-v3-02.txt](#), March, 2003.

8. Informative References

- [RFC3410] Case, J., Mundy, R., Partain, D. and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Network Management Framework", [RFC 3410](#), December 2002.
- [RFC3418] Presuhn, R., Case, J., McCloghrie, K., Rose, M. and S. Waldbusser, "Management Information Base (MIB) for the Simple Network Management Protocol (SNMP)", [RFC 3418](#), December 2002.
- [RFC2668] Smith, A., Flick, J., deGraaf, K., Romascanu, D., McMaster, D., McCloghrie, K. and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)", [RFC 2668](#), August 1999.
- [RFC2239] de Graaf, K., Romascanu, D., McMaster, D., McCloghrie, K. and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs) using SMIV2", [RFC 2239](#), November 1997.
- [RFC1515] McMaster, D., McCloghrie, K. and S. Roberts, "Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)", [RFC 1515](#), September 1993.
- [ETHERWIS] Ayers, M., Flick, J., Heard, C. M., Lam, K., McDonald, K., Norseth, K. C., and K. Tesink, "Definitions of Managed Objects for the Ethernet WAN Interface Sublayer", work in progress, [draft-ietf-hubmib-wis-mib-04.txt](#), May 2002.

9. Security Considerations

There are a number of management objects defined in this MIB that

have a MAX-ACCESS clause of read-write. Setting these objects can have a serious effect on the operation of the network, including:

- enabling or disabling a MAU
- changing a MAU's default type
- enabling, disabling or restarting autonegotiation
- modifying the capabilities that a MAU advertizes during autonegotiation.

Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. In some environments it may be undesirable to allow unauthorized parties to access statistics or status information about individual links in a network. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP.

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example by using IPSec), even then, there is no control as to who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in this MIB module.

It is recommended that the implementors consider the security features as provided by the SNMPv3 framework (see [[RFC3410](#)], [section 8](#)), including full support for the SNMPv3 cryptographic mechanisms (for authentication and privacy).

Furthermore, deployment of SNMP versions prior to SNMPv3 is NOT RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of this MIB module is properly configured to give access to the objects only to those principals (users) that have legitimate rights to indeed GET or SET (change/create/delete) them.

[10.](#) Authors' Addresses

John Flick
Hewlett-Packard Company
8000 Foothills Blvd. M/S 5557

Roseville, CA 95747-5557
Phone: +1 916 785 4018
E-mail: johnf@rose.hp.com

A. Change Log

A.1. Changes since [RFC 2668](#)

This section enumerates changes made to [RFC 2668](#) to produce this document.

- (1) Updated references to the IEEE 802.3 standard to refer to the 2000 edition.
- (2) Added reference to 802.3ae.
- (3) Updated WG e-mail address.
- (4) The following DESCRIPTION clauses have been updated to reflect behaviour on 10 Gb/s interfaces:
ifMauMediaAvailable.
- (5) OBJECT-IDENTITY definitions have been added for 10 gigabit MAU types.
- (6) Enumerations for 'pmdLinkFault', 'wisFrameLoss', 'wisSignalLoss', pcsLinkFault', excessiveBER', 'dxsLinkFault' and 'pxsLinkFault' have been added for the ifMauMediaAvailable object.
- (7) ifMauTypeListBits has been extended with bits for the 10 Gb/s MAU types.
- (8) The MODULE-IDENTITY clause has been updated to reflect the changes in the MIB module.
- (9) MIB boilerplate in [section 2](#) has been updated to the latest approved text.
- (10) Added 64-bit version of ifMauFalseCarriers, and updated compliances accordingly.
- (11) Added section on mapping of IEEE managed objects to the objects in this MIB module.

A.2. Changes between [RFC 2239](#) and [RFC 2668](#)

This section enumerates the changes made to [RFC 2239](#) to produce [RFC 2668](#).

- (1) The MODULE-IDENTITY has been updated to reflect the changes in the MIB.
- (2) OBJECT-IDENTITY definitions have been added for gigabit MAU types.
- (3) The ifMauTypeList, ifMauAutoNegCapability, ifMauAutoNegCapAdvertised and ifMauAutoNegCapReceived objects have been deprecated and replaced by ifMauTypeListBits, ifMauAutoNegCapabilityBits, ifMauAutoNegCapAdvertisedBits and ifMauAutoNegCapReceivedBits.
- (4) Two new objects, ifMauAutoNegRemoteFaultAdvertised and ifMauAutoNegRemoteFaultReceived have been added.
- (5) Enumerations for 'offline' and 'autoNegError' have been added for the rpMauMediaAvailable and ifMauMediaAvailable objects.
- (6) The broadMauBasicTable and mauBroadBasic object group have been deprecated.
- (7) The mauIfGrp100Mbs and mauIfGrpAutoNeg object groups have been deprecated and replaced by mauIfGrpHighCapacity and mauIfGrpAutoNeg2.
- (8) A new object group, mauIfGrpAutoNeg1000Mbps, has been added.
- (9) The mauModIfCompl and mauModRpCompl compliances have been deprecated and replaced by mauModIfCompl2 and mauModRpCompl2.
- (10) Added section on relationship to [RFC 2239](#).
- (11) Updated the SNMP Network Management Framework boilerplate.
- (12) Refer to the Interfaces MIB, rather than the interfaces group of MIB-II.
- (13) Updated references to refer to latest edition of IEEE 802.3.
- (14) An intellectual property notice was added, as required by [RFC 2026](#).

B. Full Copyright Statement

Copyright (C) The Internet Society (2002). All Rights Reserved.

This document and translations of it may be copied and furnished to others, and derivative works that comment on or otherwise explain it or assist in its implementation may be prepared, copied, published and distributed, in whole or in part, without restriction of any kind, provided that the above copyright notice and this paragraph are included on all such copies and derivative works. However, this document itself may not be modified in any way, such as by removing the copyright notice or references to the Internet Society or other Internet organizations, except as needed for the purpose of developing Internet standards in which case the procedures for copyrights defined in the Internet Standards process must be followed, or as required to translate it into languages other than English.

The limited permissions granted above are perpetual and will not be revoked by the Internet Society or its successors or assigns.

This document and the information contained herein is provided on an "AS IS" basis and THE INTERNET SOCIETY AND THE INTERNET ENGINEERING TASK FORCE DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

