

Network Working Group  
Internet Draft  
Expiration Date: July 2004

M. Shand  
L. Ginsberg  
Cisco Systems  
January 2004

**Restart signaling for IS-IS**  
**draft-ietf-isis-restart-05.txt**

Status of this Memo

This document is an Internet-Draft and is in full conformance with all provisions of [Section 10 of RFC 2026](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts. Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/1id-abstracts.txt>.

The list of Internet-Draft Shadow Directories can be accessed at <http://www.ietf.org/shadow.html>.

Copyright Notice Copyright (C) The Internet Society (2003). All Rights Reserved.

Abstract

The IS-IS routing protocol ([RFC 1195](#), ISO/IEC 10589) is a link state intra-domain routing protocol. Normally, when an IS-IS router is restarted, temporary disruption of routing occurs due to events in both the restarting router and the neighbors of the restarting router.

The router which has been restarted computes its own routes before achieving database synchronization with its neighbors. The results



of this computation are likely to be non-convergent with the routes computed by other routers in the area/domain.

Neighbors of the restarting router detect the restart event and cycle their adjacencies with the restarting router through the down state. The cycling of the adjacency state causes the neighbors to regenerate their LSPs describing the adjacency concerned. This in turn causes temporary disruption of routes passing through the restarting router.

In certain scenarios the temporary disruption of the routes is highly undesirable. This draft describes mechanisms to avoid or minimize the disruption due to both of these causes.

## Table of Contents

<a href="#">1.</a>	<a href="#">Conventions used in this document.....</a>	<a href="#">3</a>
<a href="#">2.</a>	<a href="#">Overview.....</a>	<a href="#">3</a>
<a href="#">3.</a>	<a href="#">Approach.....</a>	<a href="#">4</a>
<a href="#">3.1</a>	<a href="#">Timers.....</a>	<a href="#">4</a>
<a href="#">3.2</a>	<a href="#">Restart TLV.....</a>	<a href="#">4</a>
<a href="#">3.2.1</a>	<a href="#">Use of RR and RA bits.....</a>	<a href="#">5</a>
<a href="#">3.2.2</a>	<a href="#">Use of SA bit.....</a>	<a href="#">7</a>
<a href="#">3.3</a>	<a href="#">Adjacency (re)acquisition.....</a>	<a href="#">8</a>
<a href="#">3.3.1</a>	<a href="#">Adjacency reacquisition during restart.....</a>	<a href="#">8</a>
<a href="#">3.3.2</a>	<a href="#">Adjacency acquisition during start.....</a>	<a href="#">10</a>
<a href="#">3.3.3</a>	<a href="#">Multiple levels.....</a>	<a href="#">11</a>
<a href="#">3.4</a>	<a href="#">Database synchronization.....</a>	<a href="#">12</a>
<a href="#">3.4.1</a>	<a href="#">LSP generation and flooding and SPF computation.....</a>	<a href="#">12</a>
<a href="#">3.4.1.1</a>	<a href="#">Restarting.....</a>	<a href="#">13</a>
<a href="#">3.4.1.2</a>	<a href="#">Starting.....</a>	<a href="#">14</a>
<a href="#">4.</a>	<a href="#">State Tables.....</a>	<a href="#">16</a>
<a href="#">4.1</a>	<a href="#">Running Router.....</a>	<a href="#">16</a>
<a href="#">4.2</a>	<a href="#">Restarting Router.....</a>	<a href="#">17</a>
<a href="#">4.3</a>	<a href="#">Starting Router.....</a>	<a href="#">18</a>
<a href="#">5.</a>	<a href="#">Security Considerations.....</a>	<a href="#">19</a>
<a href="#">6.</a>	<a href="#">IANA Considerations.....</a>	<a href="#">19</a>
<a href="#">7.</a>	<a href="#">Normative References.....</a>	<a href="#">20</a>
<a href="#">8.</a>	<a href="#">Acknowledgments.....</a>	<a href="#">20</a>
<a href="#">9.</a>	<a href="#">Authors' Addresses.....</a>	<a href="#">20</a>
<a href="#">10.</a>	<a href="#">Full Copyright Statement.....</a>	<a href="#">21</a>

## **1. Conventions used in this document**

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [RFC-2119](#) [4].

If the control and forwarding functions in a router can be maintained independently, it is possible for the forwarding function state to be maintained across a control function restart. This functionality is assumed when the terms "restart/restarting" are used in this document.

The terms "start/starting" are used to refer to a router in which the control function has either been started for the first time or has been restarted but the forwarding functions have not been maintained in a prior state.

The terms "(re)start/(re)starting" are used when the text is applicable to both a "starting" and a "restarting" router.

## **2. Overview**

When an adjacency is reinitialized as a result of a neighbor restarting, a router does three things:

1. It causes its own LSP(s) to be regenerated, thus triggering SPF runs throughout the area (or in the case of Level 2, throughout the domain).
2. It sets SRMflags on its own LSP database on the adjacency concerned.
3. In the case of a Point-to-Point link it transmits a (set of) CSNP(s) over the adjacency.

In the case of a restarting router process, the first of these is highly undesirable, but the second is essential in order to ensure synchronization of the LSP database.

The third action above minimizes the number of LSPs which must be exchanged and, if made reliable, provides a means of determining when the LSP databases of the neighboring routers have been synchronized. This is desirable whether the router is being restarted or not (so that the overload bit can be cleared in the router's own LSP, for example).

This draft describes a mechanism for a restarting router to signal that it is restarting to its neighbors, and allow them to reestablish their adjacencies without cycling through the down

state, while still correctly initiating database synchronization.

This draft additionally describes a mechanism for a restarting router to determine when it has achieved LSP database synchronization with its neighbors and a mechanism to optimize LSP database synchronization and minimize transient routing disruption when a router starts.

It is assumed that the three-way handshake [5] is being used on Point-to-Point circuits.

### **3. Approach**

#### **3.1 Timers**

Three additional timers, T1, T2 and T3 are required to support the functionality defined in this document.

An instance of the timer T1 is maintained per interface, and indicates the time after which an unacknowledged (re)start attempt will be repeated. A typical value might be 3 seconds.

An instance of the timer T2 is maintained for each LSP database present in the system i.e. for a Level1/2 system, there will be an instance of the timer T2 for Level 1 and an instance for Level 2. This is the maximum time that the system will wait for LSPDB synchronization. A typical value might be 60 seconds.

A single instance of the timer T3 is maintained for the entire system. It indicates the time after which the router will declare that it has failed to achieve database synchronization (by setting the overload bit in its own LSP). This is initialized to 65535 seconds, but is set to the minimum of the remaining times of received IIHs containing a restart TLV with RA set and an indication that the neighbor has an adjacency in the UP state to the restarting router.

NOTE: The timer T3 is only used by a restarting router.

#### **3.2 Restart TLV**

A new TLV is defined to be included in IIH PDUs. The presence of this TLV indicates that the sender supports the functionality defined in this document and it carries flags that are used to convey information during a (re)start. All IIHs transmitted by a router that supports this capability MUST include this TLV.



Type 211

Length # of octets in the value field (1 to (3 + ID Length))

Value

	No. of octets
+-----+   Flags	1
+-----+   Remaining Time	2
+-----+   Restarting Neighbor ID	ID Length
+-----+	

Flags (1 octet)

0	1	2	3	4	5	6	7
+--+	+--+	+--+	+--+	+--+	+--+	+--+	+--+
	Reserved			SA	RA	RR	
+--+	+--+	+--+	+--+	+--+	+--+	+--+	+--+

RR - Restart Request

RA - Restart Acknowledgment

SA - Suppress adjacency advertisement

(Note: Remaining fields are required when RA bit is set)

Remaining Time (2 octets)

Remaining holding time (in seconds)

Restarting Neighbor System ID (ID Length octets)

The system ID of the neighbor to which an RA refers. Note: Implementations based on earlier versions of this document may not include this field in the TLV when RA is set. In this case a router which is expecting an RA on a LAN circuit SHOULD assume that the acknowledgement is directed at the local system.

### [3.2.1](#) Use of RR and RA bits

The RR bit is used by a (re)starting router to signal to its neighbors that a (re)start is in progress, that an existing





adjacency SHOULD be maintained even under circumstances when the normal operation of the adjacency state machine would require the adjacency to be reinitialized, to request a set of CSNPs, and to request setting of SRMflags.

The RA bit is sent by the neighbor of a (re)starting router to acknowledge the receipt of a restart TLV with the RR bit set.

When the neighbor of a (re)starting router receives an IIH with the restart TLV having the RR bit set, if there exists on this interface an adjacency in state "Up" with the same System ID, and in the case of a LAN circuit, with the same source LAN address, then, irrespective of the other contents of the "Intermediate System Neighbors" option (LAN circuits), or the "Point-to-Point Three-Way Adjacency" option (Point-to-Point circuits):

- a) The state of the adjacency is not changed. If this is the first IIH with the RR bit set that this system has received associated with this adjacency then the adjacency is marked as being in "Restart mode" and the adjacency holding time is refreshed - otherwise the holding time is not refreshed. The "remaining time" transmitted according to (b) below MUST reflect the actual time after which the adjacency will now expire. Receipt of a normal IIH with RR bit reset will clear the "Restart mode" state. This procedure allows the restarting router to cause the neighbor to maintain the adjacency long enough for restart to successfully complete while also preventing repetitive restarts from maintaining an adjacency indefinitely. Whether an adjacency is marked as being in "Restart mode" or not has no effect on adjacency state transitions.
- b) immediately (i.e. without waiting for any currently running timer interval to expire, but with a small random delay of a few 10s of milliseconds on LANs to avoid "storms"), transmit over the corresponding interface an IIH including the restart TLV with the RR bit clear and the RA bit set, in the case of Point-to-Point adjacencies having updated the "Point-to-Point Three-Way Adjacency" option to reflect any new values received from the (re)starting router. (This allows a restarting router to quickly acquire the correct information to place in its hellos.) The "Remaining Time" MUST be set to the current time (in seconds) before the holding timer on this adjacency is due to expire. If the corresponding interface is a LAN interface, then the Restarting Neighbor System ID SHOULD be set to the System ID of the router from whom the IIH with RR bit set was received. This is required to correctly associate the acknowledgement and holding time in the case where multiple systems on a LAN restart at approximately the same time. This IIH SHOULD be transmitted

before any LSPs or SNPs transmitted as a result of the receipt of the original IIH.

Shand, Ginsberg

Expires Jul 2004

[Page 6]

- c) if the corresponding interface is a Point-to-Point interface, or if the receiving router has the highest LnRouterPriority (with highest source MAC address breaking ties) among those routers to which the receiving router has an adjacency in state "Up" on this interface whose IIHs contain the restart TLV, excluding adjacencies to all routers which are considered in "Restart mode" (note the actual DIS is NOT changed by this process), initiate the transmission over the corresponding interface of a complete set of CSNPs, and set SRMflags on the corresponding interface for all LSPs in the local LSP database.

Otherwise (i.e. if there was no adjacency in the "UP" state to the system ID in question), process the IIH as normal by reinitializing the adjacency, and setting the RA bit in the returned IIH.

### **3.2.2      Use of SA bit**

The SA bit is used by a starting router to request that its neighbor suppress advertisement of the adjacency to the starting router in the neighbor's LSPs.

A router which is starting has no maintained forwarding function state. This may or may not be the first time the router has started. If this is not the first time the router has started, copies of LSPs generated by this router in its previous incarnation may exist in the LSP databases of other routers in the network. These copies are likely to appear "newer" than LSPs initially generated by the starting router due to the reinitialization of LSP fragment sequence numbers by the starting router. This may cause temporary blackholes to occur until the normal operation of the update process causes the starting router to regenerate and flood copies of its own LSPs with higher sequence numbers. The temporary blackholes can be avoided if the starting router's neighbors suppress advertising an adjacency to the starting router until the starting router has been able to propagate newer versions of LSPs generated by previous incarnations.

When a router receives an IIH with the restart TLV having the SA bit set, if there exists on this interface an adjacency in state "Up" with the same System ID, and in the case of a LAN circuit, with the same source LAN address, then the router MUST suppress advertisement of the adjacency to the neighbor in its own LSPs. Until an IIH with the SA bit clear has been received, the neighbor advertisement MUST continue to be suppressed. If the adjacency transitions to the UP state, the new adjacency MUST NOT be advertised until an IIH with the SA bit clear has been received.

Note that a router which suppresses advertisement of an adjacency MUST NOT use this adjacency when performing its SPF calculation. In

particular, if an implementation follows the example guidelines  
presented in [3] Annex C.2.5 Step 0:b) "pre-load TENT with the local

adjacency database", the suppressed adjacency MUST NOT be loaded into TENT.

### **3.3 Adjacency (re)acquisition**

Adjacency (re)acquisition is the first step in (re)initialization. Restarting and starting routers will make use of the RR bit in the restart TLV, though each will use it at different stages of the (re)start procedure.

#### **3.3.1 Adjacency reacquisition during restart**

The restarting router explicitly notifies its neighbor that the adjacency is being reacquired, and hence that it SHOULD NOT reinitialize the adjacency. This is achieved by setting the RR bit in the restart TLV. When the neighbor of a restarting router receives an IIH with the restart TLV having the RR bit set, if there exists on this interface an adjacency in state "Up" with the same System ID, and in the case of a LAN circuit, with the same source LAN address, then the procedures described in 4.2.1 are followed.

A router that does not support the restart capability will ignore the restart TLV and reinitialize the adjacency as normal, returning an IIH without the restart TLV.

On restarting, a router initializes the timer T3, starts the timer T2 for each LSPDB and for each interface (and in the case of a LAN circuit, for each level) starts the timer T1 and transmits an IIH containing the restart TLV with the RR bit set.

On a Point-to-Point circuit the restarting router SHOULD set the "Adjacency Three-Way State" to "Init", because the receipt of the acknowledging IIH (with RA set) MUST cause the adjacency to enter "Up" state immediately.

On a LAN circuit the LAN-ID assigned to the circuit SHOULD be the same as that used prior to the restart. In particular, for any circuits for which the restarting router was previously DIS, the use of a different LAN-ID would necessitate the generation of a new set of pseudonode LSPs, and corresponding changes in all the LSPs referencing them from other routers on the LAN. By preserving the LAN-ID across the restart, this churn can be prevented. To enable a restarting router to learn the LAN-ID used prior to restart, the LAN-ID specified in an IIH with RR set MUST be ignored.

Transmission of "normal" IIHs is inhibited until the conditions described below are met (in order to avoid causing an unnecessary adjacency initialization). On expiry of the timer T1, it is restarted and the IIH is retransmitted as above.



When a restarting router receives an IIH a local adjacency is established as usual, and if the IIH contains a restart TLV with the RA bit set (and on LAN circuits with a Restart Neighbor System ID which matches that of the local system), the receipt of the acknowledgement over that interface is noted. When the RA bit is set and the state of the remote adjacency is UP then the timer T3 is set to the minimum of its current value and the value of the "Remaining Time" field in the received IIH.

On a Point-to-Point link, receipt of an IIH not containing the restart TLV is also treated as an acknowledgement, since it indicates that the neighbor is not restart capable. However, since no CSNP is guaranteed to be received over this interface, the timer T1 is cancelled immediately without waiting for a complete set of CSNP(s). Synchronization may therefore be deemed complete even though there are some LSPs which are held (only) by this neighbor (see [section 4.4](#)). In this case we also want to be certain that the neighbor will reinitialize the adjacency in order to guarantee that SRMflags have been set on its database, thus ensuring eventual LSPDB synchronization. This is guaranteed to happen except in the case where the Adjacency Three-Way State in the received IIH is UP and the Neighbor Extended Local Circuit ID matches the extended local circuit ID assigned by the restarting router. In this case the restarting router MUST force the adjacency to reinitialize by setting the local Adjacency Three-Way State to DOWN and sending a normal IIH.

In the case of a LAN interface, receipt of an IIH not containing the restart TLV is unremarkable since synchronization can still occur so long as at least one of the non-restarting neighboring routers on the LAN supports restart. Therefore T1 continues to run in this case. If none of the neighbors on the LAN are restart capable, T1 will eventually expire after the locally defined number of retries.

In the case of a Point-to-Point circuit, the "LocalCircuitID" and "Extended Local Circuit ID" information contained in the IIH can be used immediately to generate an IIH containing the correct 3-way handshake information. The presence of "Neighbor Extended Local Circuit ID" information which does not match the value currently in use by the local system is ignored (since the IIH may have been transmitted before the neighbor had received the new value from the restarting router), but the adjacency remains in the initializing state until the correct information is received.

In the case of a LAN circuit the source neighbor information (e.g. SNPAAddress) is recorded and used for adjacency establishment and maintenance as normal.





When BOTH a complete set of CSNP(s) (for each active level, in the case of a pt-pt circuit) and an acknowledgement have been received over the interface, the timer T1 is cancelled.

Once the timer T3 has expired or been cancelled, subsequent IIHs are transmitted according to the normal algorithms, but including the restart TLV with both RR and RA clear.

If a LAN contains a mixture of systems, only some of which support the new algorithm, database synchronization is still guaranteed, but the "old" systems will have reinitialized their adjacencies.

If an interface is active, but does not have any neighboring router reachable over that interface the timer T1 would never be cancelled, and according to clause 3.4.1.1 the SPF would never be run. Therefore timer T1 is cancelled after some pre-determined number of expirations (which MAY be 1).

### **3.3.2 Adjacency acquisition during start**

The starting router wants to ensure that in the event a neighboring router has an adjacency to the starting router in the UP state (from a previous incarnation of the starting router) that this adjacency is reinitialized. The starting router also wants neighboring routers to suppress advertisement of an adjacency to the starting router until LSP database synchronization is achieved. This is achieved by sending IIHs with the RR bit clear and the SA bit set in the restart TLV. The RR bit remains clear and the SA bit remains set in subsequent transmissions of IIHs until the adjacency has reached the UP state and the initial T1 timer interval (see below) has expired.

Receipt of an IIH with RR bit clear will result in the neighboring router utilizing normal operation of the adjacency state machine. This will ensure that any old adjacency on the neighboring router will be reinitialized.

On receipt of an IIH with SA bit set the behavior described in 3.2.2 is followed.

On starting, a router starts timer T2 for each LSPDB.

For each interface (and in the case of a LAN circuit, for each level), when an adjacency reaches the UP state, the starting router starts a timer T1 and transmits an IIH containing the restart TLV with the RR bit clear and SA bit set. On expiry of the timer T1, it is restarted and the IIH is retransmitted with both RR and SA bits set (only the RR bit has changed state from earlier IIHs).

On receipt of an IIH with RR bit set (regardless of whether SA is

set or not) the behavior described in 3.2.1 is followed.

When an IIH is received by the starting router and the IIH contains a restart TLV with the RA bit set (and on LAN circuits with a Restart Neighbor System ID which matches that of the local system), the receipt of the acknowledgement over that interface is noted.

On a Point-to-Point link, receipt of an IIH not containing the restart TLV is also treated as an acknowledgement, since it indicates that the neighbor is not restart capable. Since the neighbor will have reinitialized the adjacency this guarantees that SRMflags have been set on its database, thus ensuring eventual LSPDB synchronization. However, since no CSNP is guaranteed to be received over this interface, the timer T1 is cancelled immediately without waiting for a complete set of CSNP(s). Synchronization may therefore be deemed complete even though there are some LSPs which are held (only) by this neighbor (see [section 4.4](#)).

In the case of a LAN interface, receipt of an IIH not containing the restart TLV is unremarkable since synchronization can still occur so long as at least one of the non-restarting neighboring routers on the LAN supports restart. Therefore T1 continues to run in this case. If none of the neighbors on the LAN are restart capable, T1 will eventually expire after the locally defined number of retries. The usual operation of the update process will ensure that synchronization is eventually achieved.

When BOTH a complete set of CSNP(s) (for each active level, in the case of a pt-pt circuit) and an acknowledgement have been received over the interface, the timer T1 is cancelled. Subsequent IIHs sent by the starting router have the RR and RA bits clear and the SA bit set in the restart TLV.

Timer T1 is cancelled after some pre-determined number of expirations (which MAY be 1).

When the T2 timer(s) are cancelled or expire transmission of "normal" IIHs (with RR, RA, and SA bits clear) will begin.

### **[3.3.3](#) Multiple levels**

A router which is operating as both a Level 1 and a Level 2 router on a particular interface MUST perform the above operations for each level.

On a LAN interface, it MUST send and receive both Level 1 and Level 2 IIHs and perform the CSNP synchronizations independently for each level.

On a pt-pt interface, only a single IIH (indicating support for both levels) is required, but it MUST perform the CSNP synchronizations

independently for each level.

Shand, Ginsberg

Expires Jul 2004

[Page 11]

### **3.4 Database synchronization**

When a router is started or restarted it can expect to receive a (set of) CSNP(s) over each interface. The arrival of the CSNP(s) is now guaranteed, since an IIH with RR bit set will be retransmitted until the CSNP(s) are correctly received.

The CSNPs describe the set of LSPs that are currently held by each neighbor. Synchronization will be complete when all these LSPs have been received.

When (re)starting, a router starts an instance of timer T2 for each LSPDB as described in 4.3.1 or 4.3.2. In addition to normal processing of the CSNPs, the set of LSPIDs contained in the first complete set of CSNP(s) received over each interface is recorded, together with their remaining lifetime. In the case of a LAN interface, a complete set of CSNPs MUST consist of CSNPs received from neighbor(s) which are not restarting. If there are multiple interfaces on the (re)starting router, the recorded set of LSPIDs is the union of those received over each interface. LSPs with a remaining lifetime of zero are NOT so recorded.

As LSPs are received (by the normal operation of the update process) over any interface, the corresponding LSPID entry is removed (it is also removed if the LSP had arrived before the CSNP containing the reference). When an LSPID has been held in the list for its indicated remaining lifetime, it is removed from the list. When the list of LSPIDs is empty and the timer T1 has been cancelled for all the interfaces that have an adjacency at this level, the timer T2 is cancelled.

At this point the local database is guaranteed to contain all the LSP(s) (either the same sequence number, or a more recent sequence number) which were present in the neighbors' databases at the time of (re)starting. LSPs that arrived in a neighbor's database after the time of (re)starting may or may not be present, but the normal operation of the update process will guarantee that they will eventually be received. At this point the local database is deemed to be "synchronized".

Since LSPs mentioned in the CSNP(s) with a zero remaining lifetime are not recorded, and those with a short remaining lifetime are deleted from the list when the lifetime expires, cancellation of the timer T2 will not be prevented by waiting for an LSP that will never arrive.

#### **3.4.1 LSP generation and flooding and SPF computation**

The operation of a router starting, as opposed to restarting is

somewhat different. These two cases are dealt with separately below.

Shand, Ginsberg

Expires Jul 2004

[Page 12]

#### **3.4.1.1. Restarting**

In order to avoid causing unnecessary routing churn in other routers, it is highly desirable that the own LSPs generated by the restarting system are the same as those previously present in the network (assuming no other changes have taken place). It is important therefore not to regenerate and flood the LSPs until all the adjacencies have been re-established and any information required for propagation into the local LSPs is fully available. Ideally, the information is loaded into the LSPs in a deterministic way, such that the same information occurs in the same place in the same LSP (and hence the LSPs are identical to their previous versions). If this can be achieved, the new versions may not even cause SPF to be run in other systems. However, provided the same information is included in the set of LSPs (albeit in a different order, and possibly different LSPs), the result of running the SPF will be the same and will not cause churn to the forwarding tables.

In the case of a restarting router, none of the router's own LSPs are transmitted, nor are the router's own forwarding tables updated while the timer T3 is running.

Redistribution of inter-level information MUST be regenerated before this router's LSP is flooded to other nodes. Therefore the Level-n non-pseudonode LSP(s) MUST NOT be flooded until the other level's T2 timer has expired and its SPF has been run. This ensures that any inter-level information which is to be propagated can be included in the Level-n LSP(s).

During this period, if one of the router's own (including pseudonodes) LSPs is received, which the local router does not currently have in its own database, it is NOT purged. Under normal operation, such an LSP would be purged, since the LSP clearly should not be present in the global LSP database. However, in the present circumstances, this would be highly undesirable, because it could cause premature removal of an own LSP - and hence churn in remote routers. Even if the local system has one or more own LSPs (which it has generated, but not yet transmitted) it is still not valid to compare the received LSP against this set, since it may be that as a result of propagation between Level 1 and Level 2 (or vice versa) a further own LSP will need to be generated when the LSP databases have synchronized.

During this period a restarting router SHOULD send CSNPs as it normally would. Information about the router's own LSPs MAY be included, but if it is included it MUST be based on LSPs which have



been received, not on versions which have been generated (but not

yet transmitted). This restriction is necessary to prevent premature removal of an LSP from the global LSP database.

When the timer T2 expires or is cancelled indicating that synchronization for that level is complete, the SPF for that level is run in order to derive any information which is required to be propagated to another level, but the forwarding tables are not yet updated.

Once the other level's SPF has run and any inter-level propagation has been resolved, the own LSPs can be generated and flooded. Any own LSPs which were previously ignored, but which are not part of the current set of own LSPs (including pseudonodes) MUST then be purged. Note that it is possible that a Designated Router change may have taken place, and consequently the router SHOULD purge those pseudonode LSPs which it previously owned, but which are now no longer part of its set of pseudonode LSPs.

When all the T2 timers have expired or been cancelled, the timer T3 is cancelled and the local forwarding tables are updated.

If the timer T3 expires before all the T2 timers have expired or been cancelled, this indicates that the synchronization process is taking longer than minimum holding time of the neighbors. The router's own LSP(s) for levels which have not yet completed their first SPF computation are then flooded with the overload bit set to indicate that the router's LSPDB is not yet synchronized (and therefore other routers MUST NOT compute routes through this router). Normal operation of the update process resumes and the local forwarding tables are updated. In order to prevent the neighbor's adjacencies from expiring, IIHs with the normal interface value for the holding time are transmitted over all interfaces with neither RR nor RA set in the restart TLV. This will cause the neighbors to refresh their adjacencies. The own LSP(s) will continue to have the overload bit set until timer T2 has expired or been cancelled.

#### **3.4.1.2. Starting**

In the case of a starting router, as soon as each adjacency is established, and before any CSNP exchanges, the router's own zeroth LSP is transmitted with the overload bit set. This prevents other routers from computing routes through the router until it has reliably acquired the complete set of LSPs. The overload bit remains set in subsequent transmissions of the zeroth LSP (such as will occur if a previous copy of the routers LSP is still present in the network) while any timer T2 is running.

When all the T2 timers have been cancelled, the own LSP(s) MAY be regenerated with the overload bit clear (assuming the router isn't

in fact overloaded, and there is no other reason, such as incomplete BGP convergence, to keep the overload bit set), and flooded as normal.

Other own LSPs (including pseudonodes) are generated and flooded as normal, irrespective of the timer T2. The SPF is also run as normal and the RIB and FIB updated as routes become available.

To avoid the possible formation of temporary blackholes the starting router sets the SA bit in the restart TLV (as described in 4.3.2) in all IIHs that it sends.

When all T2 timers have been cancelled the starting router **MUST** transmit IIHs with the SA bit clear.



#### 4. State Tables

This section presents state tables which summarize the behaviors described in this document. Other behaviors, in particular adjacency state transitions and LSP database update operation, are NOT included in the state tables except where this document modifies the behaviors described in [3] and [5].

The states named in the columns of the tables below are a mixture of states that are specific to a single adjacency (ADJ suppressed, ADJ Seen RA, ADJ Seen CSNP) and states which are indicative of the state of the protocol instance (Running, Restarting, Starting, SPF Wait).

Three state tables are presented from the point of view of a running router, a restarting router, and a starting router.

##### 4.1 Running Router

Event	Running	ADJ suppressed
RX RR	Maintain ADJ State Send RA Set SRM, send CSNP (Note 1) Update Hold Time, set Restart Mode (Note 2)	
RX RR clr	Clr Restart mode	
RX SA	Suppress IS neighbor TLV in LSP(s) Goto ADJ Suppressed	
RX SA clr		Unsuppress IS neighbor TLV in LSP(s) Goto Running

Note 1: CSNPs are sent by routers in accordance with [Section 3.2.1c](#)

Note 2: If Restart Mode clear



**4.2 Restarting Router**

Event	Restarting	ADJ Seen RA	ADJ Seen CSNP	SPF Wait
=====				
Router restarts	Send IIH/RR ADJ Init Start T1,T2,T3			
-----+-----+-----+-----				
RX RR	Send RA			
-----+-----+-----+-----				
RX RA	Adjust T3 Goto ADJ Seen RA		Cancel T1 Adjust T3	
-----+-----+-----+-----				
RX CSNP set	Goto ADJ Seen CSNP	Cancel T1		
-----+-----+-----+-----				
RX IIH w/o Restart TLV	Cancel T1 (Point-to-point only)			
-----+-----+-----+-----				
T1 Expires	Send IIH/RR Restart T1	Send IIH/RR Restart T1	Send IIH/RR Restart T1	
-----+-----+-----+-----				
T1 Expires nth time	Send IIH/ normal	Send IIH/ normal	Send IIH/ normal	
-----+-----+-----+-----				
T2 expires	Trigger SPF Goto SPF Wait			
-----+-----+-----+-----				
T3 expires	Set OL Flood local LSPs Update fwd plane			
-----+-----+-----+-----				
LSP DB Sync	Cancel T2, and T3 Trigger SPF Goto SPF wait			
-----+-----+-----+-----				
All SPF done				Clear OL Update fwd plane Flood local LSPs Goto Runing
=====				



**4.3 Starting Router**

Event	Starting	ADJ Seen RA	ADJ Seen CSNP
Router starts	Send IIH/SA Start T1,T2		
RX RR	Send RA		
RX RA	Goto ADJ Seen RA		Cancel T1
RX CSNP Set	Goto ADJ Seen CSNP	Cancel T1	
RX IIH w no Restart TLV	Cancel T1 (Point-to-Point only)		
ADJ UP	Start T1 Send local LSPs w OL		
T1 Expires	Send IIH/RR and SA Restart T1	Send IIH/RR and SA Restart T1	Send IIH/RR and SA Restart T1
T1 Expires nth time	Send IIH/SA	Send IIH/SA	Send IIH/SA
T2 expires	Clear OL Send IIH normal Goto Running		
LSP DB Sync	Cancel T2 Clear OL Send IIH normal		

## 5. Security Considerations

Any new security issues raised by the procedures in this document depend upon the ability of an attacker to inject a false but apparently valid IIH, the ease/difficulty of which has not been altered.

If the RR bit is set in a false IIH, neighbors who receive such an IIH will continue to maintain an existing adjacency in the UP state and may (re)send a complete set of CSNPs. While the latter action is wasteful, neither action causes any disruption in correct protocol operation.

If the RA bit is set in a false IIH, a (re)starting router which receives such an IIH may falsely believe that there is a neighbor on the corresponding interface which supports the procedures described in this document. In the absence of receipt of a complete set of CSNPs on that interface, this could delay the completion of (re)start procedures by requiring the timer T1 to time out the locally defined maximum number of retries. This behavior is the same as would occur on a LAN where none of the (re)starting router's neighbors support the procedures in this document and is covered in Sections [3.3.1](#) and [3.3.2](#).

If an SA bit is set in a false IIH, this could cause suppression of the advertisement of an IS neighbor which could either continue for an indefinite period or occur intermittently with the result being possible loss of reachability to some destinations in the network and/or increased frequency of LSP flooding and SPF calculation.

The possibility of IS-IS PDU spoofing can be reduced by the use of authentication as described in [2] and [3], and especially the use of cryptographic authentication as described in [6].

## 6. IANA Considerations

This document defines the following new ISIS TLV that needs to be reflected in the ISIS TLV code-point registry:

Type	Description	IIH	LSP	SNP
----	-----	---	---	---
211	Restart TLV	y	n	n



## **7. Normative References**

- 1 Bradner, S., "The Internet Standards Process -- Revision 3", [BCP 9](#), [RFC 2026](#), October 1996.
- 2 Callon, R., "OSI IS-IS for IP and Dual Environment," [RFC 1195](#), December 1990.
- 3 ISO, "Intermediate system to Intermediate system routing information exchange protocol for use in conjunction with the Protocol for providing the Connectionless-mode Network Service (ISO 8473)," ISO/IEC 10589:2002, Second Edition.
- 4 Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", [BCP 14](#), [RFC 2119](#), March 1997
- 5 Katz, D., and Saluja, R., "Three-Way Handshake for IS-IS Point-to-Point Adjacencies", [RFC 3373](#), September 2002
- 6 Li, T., and Atkinson, R., "Intermediate System to Intermediate System (IS-IS) Cryptographic Authentication", [RFC 3567](#), July 2003
- 7 Narten, T. and Alvestrand, H., "Guidelines for Writing an IANA Considerations Section in RFCs", [BCP 26](#) , [RFC 2434](#), October 1998

## **8. Acknowledgments**

The authors would like to acknowledge contributions made by Jeff Parker, Radia Perlman, Mark Schaefer, Naiming Shen, Nischal Sheth, Russ White, and Rena Yang.

## **9. Authors' Addresses**

Mike Shand  
Cisco Systems  
250 Longwater Avenue,  
Reading,  
Berkshire,  
RG2 6GB  
UK  
Phone: +44 208 824 8690  
Email: mshand@cisco.com

Les Ginsberg  
Cisco Systems  
510 McCarthy Blvd.  
Milpitas, Ca. 95035 USA

Email: ginsberg@cisco.com

Shand, Ginsberg

Expires Jul 2004

[Page 20]

**10. Full Copyright Statement**

Copyright (C) The Internet Society (2003). All Rights Reserved.

This document and translations of it may be copied and furnished to others, and derivative works that comment on or otherwise explain it or assist in its implementation may be prepared, copied, published and distributed, in whole or in part, without restriction of any kind, provided that the above copyright notice and this paragraph are included on all such copies and derivative works. However, this document itself may not be modified in any way, such as by removing the copyright notice or references to the Internet Society or other Internet organizations, except as needed for the purpose of developing Internet standards in which case the procedures for copyrights defined in the Internet Standards process must be followed, or as required to translate it into languages other than English.

The limited permissions granted above are perpetual and will not be revoked by the Internet Society or its successors or assigns.

This document and the information contained herein is provided on an "AS IS" basis and THE INTERNET SOCIETY AND THE INTERNET ENGINEERING TASK FORCE DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY WARRANTY THAT THE USE OF THE INFORMATION HEREIN WILL NOT INFRINGE ANY RIGHTS OR ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

