

NETMOD Working Group
Internet-Draft
Intended status: Standards Track
Expires: August 15, 2020

Q. Wu
Huawei
B. Lengyel
Ericsson Hungary
Y. Niu
Huawei
February 12, 2020

Factory Default Setting
draft-ietf-netmod-factory-default-11

Abstract

This document defines a method to reset a server to its factory default content. The reset operation may be used, e.g., when the existing configuration has major errors so re-starting the configuration process from scratch is the best option.

A new "factory-reset" RPC is defined. When resetting a device, all previous configuration settings will be lost and replaced by the factory default content.

A new optional "factory-default" read-only datastore is defined, that contains the factory default configuration for the device.

Status of This Memo

This Internet-Draft is submitted in full conformance with the provisions of [BCP 78](#) and [BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF). Note that other groups may also distribute working documents as Internet-Drafts. The list of current Internet-Drafts is at <https://datatracker.ietf.org/drafts/current/>.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

This Internet-Draft will expire on August 15, 2020.

Copyright Notice

Copyright (c) 2020 IETF Trust and the persons identified as the document authors. All rights reserved.

Internet-Draft

Factory Default Setting

February 2020

This document is subject to [BCP 78](https://trustee.ietf.org/license-info) and the IETF Trust's Legal Provisions Relating to IETF Documents (<https://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

Table of Contents

1.	Introduction	2
1.1.	Terminology	3
2.	Factory-Reset RPC	3
3.	Factory-Default Datastore	4
4.	YANG Module	5
5.	IANA Considerations	7
6.	Security Considerations	7
7.	Acknowledgements	7
8.	Contributors	8
9.	Normative References	8
Appendix A.	Changes between revisions	9
	Authors' Addresses	11

[1.](#) Introduction

This document defines a method to reset a server to its factory default content. The reset operation may be used, e.g., when the existing configuration has major errors so re-starting the configuration process from scratch is the best option.

A "factory-reset" RPC is defined. When resetting a device, all previous configuration settings will be lost and replaced by the factory default content.

A "factory-default" read-only datastore is defined, that contains the data to replace the contents of implemented read-write conventional configuration datastores at reset. This datastore can also be used in the <get-data> operation.

The YANG data model in this document conforms to the Network Management Datastore Architecture defined in [[RFC8342](#)].

[1.1.](#) Terminology

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "NOT RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [BCP 14](#) [[RFC2119](#)] [[RFC8174](#)] when, and only when, they appear in all capitals, as shown here.

The following terms are defined in [[RFC8342](#)] [[RFC7950](#)] and are not redefined here:

- o server
- o startup configuration datastore
- o candidate configuration datastore
- o running configuration datastore
- o intended configuration datastore
- o operational state datastore
- o conventional configuration datastore
- o RPC operation

The following terms are defined in this document as follows:

- o factory-default datastore: A read-only configuration datastore holding a preconfigured initial configuration that is used to initialize the configuration of a server.

[2.](#) Factory-Reset RPC

A new "factory-reset" RPC is introduced. Upon receiving the RPC

- o All supported conventional read-write configuration datastores (i.e. <running>, <startup>, and <candidate>) are all reset to the contents of <factory-default>.
- o Read-only datastores receive their content from other datastores(e.g. <intended> gets its content from <running>).
- o All data in any ephemeral datastores MUST be discarded.

- o The contents of the <operational> datastore MUST reflect the operational state of the device after applying the factory default configuration.

In addition, the "factory-reset" RPC MUST restore non-volatile storage to factory condition. Depending on the system, this may entail deleting dynamically generated files, such as those containing keys (e.g., /etc/ssl/private), certificates (e.g., /etc/ssl), logs (e.g., /var/log), and temporary files (e.g., /tmp/*). All security sensitive data (i.e., private keys, passwords, etc.) SHOULD be overwritten with zeros or a pattern before deletion. The "factory-reset" RPC MAY also be used to trigger some other resetting tasks such as restarting the node or some of the software processes.

Note that operators should be aware that since all read-write datastores are immediately reset to factory default, the device may become unreachable on the network. It is important to understand how a given vendor's device will behave after the RPC is executed. Implementors SHOULD reboot the device or otherwise restart processes needed to bootstrap it.

3. Factory-Default Datastore

Following the guidelines for defining Datastores in the [appendix A of \[RFC8342\]](#), this document introduces a new optional datastore resource named "factory-default" that represents a preconfigured minimal initial configuration that can be used to initialize the configuration of a server. A device MAY implement the "factory-reset" RPC without implementing the "factory-default" datastore,

which would only eliminate the ability to programmatically determine the factory default configuration.

- o Name: "factory-default"
- o YANG modules: all
- o YANG nodes: all "config true" data nodes
- o Management operations: The content of the datastore is set by the server in an implementation dependent manner. The content can not be changed by management operations via NETCONF, RESTCONF, the CLI etc. unless specialized, dedicated operations are provided. The datastore can be read using the standard NETCONF/RESTCONF protocol operations. The "factory-reset" operation copies the factory default content to <running> and, if present, <startup> and/or <candidate> and then the content of these datastores is propagated automatically to any other read only datastores, e.g., <intended> and <operational>.

- o Origin: This document does not define a new origin identity as it does not interact with <operational> datastore.
- o Protocols: RESTCONF, NETCONF and other management protocol.
- o Defining YANG module: "ietf-factory-default".

The contents of <factory-default> is defined by the device vendor and MUST persist across device restarts.

4. YANG Module

This module imports typedefs from [[RFC8342](#)], and it references "default-deny-all" extension statement from [[RFC8341](#)].

```
<CODE BEGINS> file "ietf-factory-default@2019-11-27.yang"
module ietf-factory-default {
  yang-version 1.1;
  namespace "urn:ietf:params:xml:ns:yang:ietf-factory-default";
  prefix fd;

  import ietf-datastores {
```

```
prefix ds;
reference
  "RFC 8342: Network Management Datastore Architecture (NMDA)";
}
import ietf-netconf-acm {
  prefix nacm;
  reference
    "RFC8341: Network Configuration Access Control Model";
}

organization
  "IETF NETMOD (Network Modeling) Working Group";
contact
  "WG Web:  <https://tools.ietf.org/wg/netconf/>
  WG List: <mailto:netconf@ietf.org>

  Editor:  Qin Wu
           <mailto:bill.wu@huawei.com>
  Editor:  Balazs Lengyel
           <mailto:balazs.lengyel@ericsson.com>
  Editor:  Ye Niu
           <mailto:niuye@huawei.com>";
description
  "This module defines an RPC called 'factory-reset', and a
  datastore identity called 'factory-default'.
```

It provides functionality to reset a server to its factory default configuration and, when supported, to discover the factory default configuration contents independent of resetting the server.

Copyright (c) 2019 IETF Trust and the persons identified as authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, is permitted pursuant to, and subject to the license terms contained in, the Simplified BSD License set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX;
see the RFC itself for full legal notices.";

```
revision 2019-11-27 {
  description
    "Initial revision.";
  reference
    "RFC XXXX: Factory default Setting";
}

feature factory-default-datastore {
  description
    "Indicates that the factory default configuration is
    available as a datastore.";
}

rpc factory-reset {
  nacm:default-deny-all;
  description
    "The server resets the content of all read-write
    configuration datastores (i.e., <running>, <startup>,
    and <candidate>) to their factory default content.";
}

identity factory-default {
  if-feature "factory-default-datastore";
  base ds:datastore;
  description
    "This read-only datastore contains the factory default
    configuration for the device used to replace the contents
    of the read-write conventional configuration datastores
    during a 'factory-reset' RPC operation.";
}
```

```
}
<CODE ENDS>
```

5. IANA Considerations

This document registers one URI in the IETF XML Registry [[RFC3688](#)].
The following registration has been made:

URI: urn:ietf:params:xml:ns:yang:ietf-factory-default
Registrant Contact: The IESG.
XML: N/A, the requested URI is an XML namespace.

This document registers one YANG module in the YANG Module Names Registry [[RFC6020](#)]. The following registration has been made:

name: ietf-factory-default
namespace: urn:ietf:params:xml:ns:yang:ietf-factory-default
prefix: fd
RFC: xxxx

6. Security Considerations

The YANG module defined in this document extends the base operations for NETCONF [[RFC6241](#)] and RESTCONF [[RFC8040](#)]. The lowest NETCONF layer is the secure transport layer, and the mandatory-to-implement secure transport is Secure Shell (SSH) [[RFC6242](#)]. The lowest RESTCONF layer is HTTPS, and the mandatory-to-implement secure transport is TLS [[RFC8446](#)].

Access to the "factory-reset" RPC operation is considered sensitive and therefore has been restricted using the "default-deny-all" access control defined in [[RFC8341](#)].

The "factory-reset" RPC can prevent any further management of the device if the session and client config is included in the factory default contents.

The operational disruption caused by setting the config to factory default contents varies greatly depending on the implementation and current config.

7. Acknowledgements

Thanks to Juergen Schoenwaelder, Ladislav Lhotka, Alex Campbell, Joe Clarke, Robert Wilton, Kent Watsen, Joel Jaeggli, Lou Berger, Andy Bierman, Susan Hares to review this draft and provide important input to this document.

8. Contributors

Rohit R Ranade
Huawei
Email: rohitrranade@huawei.com

9. Normative References

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", [BCP 14](#), [RFC 2119](#), DOI 10.17487/RFC2119, March 1997, <<https://www.rfc-editor.org/info/rfc2119>>.
- [RFC3688] Mealling, M., "The IETF XML Registry", [BCP 81](#), [RFC 3688](#), DOI 10.17487/RFC3688, January 2004, <<https://www.rfc-editor.org/info/rfc3688>>.
- [RFC6020] Bjorklund, M., Ed., "YANG - A Data Modeling Language for the Network Configuration Protocol (NETCONF)", [RFC 6020](#), DOI 10.17487/RFC6020, October 2010, <<https://www.rfc-editor.org/info/rfc6020>>.
- [RFC6241] Enns, R., Ed., Bjorklund, M., Ed., Schoenwaelder, J., Ed., and A. Bierman, Ed., "Network Configuration Protocol (NETCONF)", [RFC 6241](#), DOI 10.17487/RFC6241, June 2011, <<https://www.rfc-editor.org/info/rfc6241>>.
- [RFC6242] Wasserman, M., "Using the NETCONF Protocol over Secure Shell (SSH)", [RFC 6242](#), DOI 10.17487/RFC6242, June 2011, <<https://www.rfc-editor.org/info/rfc6242>>.
- [RFC7950] Bjorklund, M., Ed., "The YANG 1.1 Data Modeling Language", [RFC 7950](#), DOI 10.17487/RFC7950, August 2016, <<https://www.rfc-editor.org/info/rfc7950>>.
- [RFC8040] Bierman, A., Bjorklund, M., and K. Watsen, "RESTCONF Protocol", [RFC 8040](#), DOI 10.17487/RFC8040, January 2017, <<https://www.rfc-editor.org/info/rfc8040>>.
- [RFC8174] Leiba, B., "Ambiguity of Uppercase vs Lowercase in [RFC 2119](#) Key Words", [BCP 14](#), [RFC 8174](#), DOI 10.17487/RFC8174, May 2017, <<https://www.rfc-editor.org/info/rfc8174>>.
- [RFC8341] Bierman, A. and M. Bjorklund, "Network Configuration Access Control Model", STD 91, [RFC 8341](#), DOI 10.17487/RFC8341, March 2018, <<https://www.rfc-editor.org/info/rfc8341>>.

- [RFC8342] Bjorklund, M., Schoenwaelder, J., Shafer, P., Watsen, K., and R. Wilton, "Network Management Datastore Architecture (NMDA)", [RFC 8342](#), DOI 10.17487/RFC8342, March 2018, <<https://www.rfc-editor.org/info/rfc8342>>.
- [RFC8446] Rescorla, E., "The Transport Layer Security (TLS) Protocol Version 1.3", [RFC 8446](#), DOI 10.17487/RFC8446, August 2018, <<https://www.rfc-editor.org/info/rfc8446>>.

[Appendix A](#). Changes between revisions

Editorial Note (To be removed by RFC Editor)

v10 - 11

- o Incorporate additional Shepherd review's comments.

v09 - 10

- o Incorporate Shepherd review's comments.

v08 - 09

- o Provide some guideline for operators and implementor who implement factory default method.

v07 - 08

- o Provide clarification and recommendation on the relationship between factory-reset RPC and reboot.
- o Nits fixed based on YANG Doctor Review.

v06 - 07

- o Remove Factory default content specification;
- o Remove reference to YANG instance data file format and zero touch provision [[RFC8573](#)];
- o Remove copy-config operation extension on factory-default datastore

v05 - 06

- o Additional text to enhance security section.

- o Add nacm:default-deny-all on "factory-reset" RPC.

- o A few clarification on Factory default content specification.

v03 - 04

- o Additional text to clarify factory-reset RPC usage.

v02 - 03

- o Update security consideration section.

v01 - v02

- o Address security issue in the security consideration section.

- o Remove an extension to the NETCONF <copy-config> operation which allows it to operate on the factory-default datastore.

- o Add an extension to the NETCONF <get-config> operation which allows it to operate on the factory-default datastore.

v00 - v01

- o Change YANG server into server defined in NMDA architecture based on discussion.

- o Allow reset the content of all read-write configuraton datastores to its factory default content except <candidate>.

- o Add clarification text on factory-reset protocol operation behavior.

v03 - v00

- o Change draft name from [draft-wu](#) to [draft-ietf-netmod-factory-default-00](#) without content changes.

v02 - v03

- o Change reset-datastore RPC into factory-reset RPC to allow reset

the whole device with factory default content.

- o Remove target datastore parameter from factory-reset RPC.

- o Other editorial changes.

v01 - v02

- o Add copy-config based on Rob's comment.

Wu, et al.

Expires August 15, 2020

[Page 10]

Internet-Draft

Factory Default Setting

February 2020

- o Reference Update.

v03 - v00 - v01

- o Changed name from [draft-wu-netconf-restconf-factory-restore](#) to [draft-wu-netmod-factory-default](#)

- o Removed copy-config ; reset-datastore is enough

v02 - v03

- o Restructured
- o Made new datastore optional
- o Removed Netconf capability
- o Listed Open issues

v01 - v02

- o -

v00 - v01

- o -

Authors' Addresses

Qin Wu
Huawei
101 Software Avenue, Yuhua District

Nanjing, Jiangsu 210012
China

Email: bill.wu@huawei.com

Balazs Lengyel
Ericsson Hungary
Magyar Tudosok korutja 11
1117 Budapest
Hungary

Phone: +36-70-330-7909

Email: balazs.lengyel@ericsson.com

Wu, et al.

Expires August 15, 2020

[Page 11]

Internet-Draft

Factory Default Setting

February 2020

Ye Niu
Huawei

Email: niuye@huawei.com

