

Softwire Working Group
Internet-Draft
Intended status: Standards Track
Expires: June 15, 2019

Y. Cui
Tsinghua University
I. Farrer, Ed.
Deutsche Telekom AG
M. Boucadair, Ed.
Orange
Q. Sun
L. Sun
Tsinghua University
S. Zechlin
Deutsche Telekom AG
R. Asati
Cisco Systems, Inc.
December 12, 2018

**YANG Modules for IPv4-in-IPv6 Address plus Port (A+P) Softwires
draft-ietf-softwire-yang-13**

Abstract

This document defines YANG modules for the configuration and operation of IPv4-in-IPv6 softwire Border Relays and Customer Premises Equipment for the Lightweight 4over6, Mapping of Address and Port with Encapsulation (MAP-E), and Mapping of Address and Port using Translation (MAP-T) softwire mechanisms.

Editorial Note (To be removed by RFC Editor)

Please update these statements within this document with the RFC number to be assigned to this document:

- o "This version of this YANG module is part of RFC XXXX;"
- o "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port Softwires";
- o "reference: RFC XXXX"

Please update the "revision" date of the YANG modules.

Status of This Memo

This Internet-Draft is submitted in full conformance with the provisions of [BCP 78](#) and [BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF). Note that other groups may also distribute

working documents as Internet-Drafts. The list of current Internet-Drafts is at <https://datatracker.ietf.org/drafts/current/>.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

This Internet-Draft will expire on June 15, 2019.

Copyright Notice

Copyright (c) 2018 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to [BCP 78](#) and the IETF Trust's Legal Provisions Relating to IETF Documents (<https://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

Table of Contents

1.	Introduction	3
2.	Terminology	3
3.	Overview of the Modules	4
3.1.	Overall Structure	4
3.2.	Additional Components Configuration	5
4.	Softwire CE YANG Tree Diagram	6
4.1.	CE Tree Diagram	6
4.2.	Softwire CE Tree Diagram Description	8
5.	Softwire BR YANG Tree Diagram	9
5.1.	BR Tree Diagram	9
5.2.	Softwire BR Tree Diagram Description	13
6.	Softwire CE YANG Module	13
7.	BR Softwire YANG Module	19
8.	Common Softwire Element Groups YANG Module	31
9.	Security Considerations	40
10.	IANA Considerations	40
11.	Acknowledgements	41
12.	Contributors	41
13.	References	41
13.1.	Normative References	41
13.2.	Informative References	43

Appendix A . Configuration Examples	44
A.1 . Configuration Example for a lw4o6 BR Binding-Table	44
A.2 . Configuration Example for a MAP-E BR	45
A.3 . lw4o6 CE Configuration Example	47
Authors' Addresses	51

[1](#). Introduction

The IETF Softwire working group has developed several IPv4-in-IPv6 softwire mechanisms to address various deployment contexts and constraints. As a companion to the architectural specification documents, this document focuses on the provisioning of address plus port (A+P) softwire functional elements: Border Routers (BRs) and Customer Premises Equipment (CEs, a.k.a., CPE). The softwire mechanisms covered in this document are Lightweight 4 over 6 (lw4o6) [[RFC7596](#)], Mapping of Address and Port with Encapsulation (MAP-E) [[RFC7597](#)], and Mapping of Address and Port using Translation (MAP-T) [[RFC7599](#)].

This document focuses on A+P mechanisms [[RFC6346](#)]; the reader can refer to [[I-D.ietf-softwire-dslite-yang](#)] for a YANG module for DS-Lite [[RFC6333](#)].

This document defines YANG modules [[RFC7950](#)] that can be used to configure and manage A+P softwire elements using the NETCONF protocol [[RFC6241](#)] for:

- o Configuration
- o Operational State
- o Notifications

[2](#). Terminology

The reader should be familiar with the concepts and terms defined in [[RFC7596](#)], [[RFC7597](#)], [[RFC7599](#)], and the YANG data modelling language defined in [[RFC7950](#)].

The adopts the Network Management Datastore Architecture (NMDA) [[RFC8342](#)]. The meaning of the symbols in tree diagrams is defined in [[RFC8340](#)].

The document uses the abbreviation 'BR' as a general term for softwire tunnel concentrators, including both MAP Border Routers [[RFC7597](#)] and Lightweight 4over6 LWAFTRs [[RFC7596](#)].

For brevity, "algorithm" is used to refer to the "mapping algorithm"

defined in [[RFC7597](#)].

A network element may support one or multiple instances of a software mechanism; each of these instances (i.e., binding instances, MAP-E instances, or MAP-T instances) may have its own configuration and parameters. The term 'algo-instance' is used to denote both MAP-E and MAP-T instances.

3. Overview of the Modules

3.1. Overall Structure

The document defines the following two YANG modules for the configuration and monitoring of software functional elements:

ietf-software-ce	Provides configuration and monitoring for software CE element. This module is defined as augments to the interface YANG module [RFC8343].
ietf-software-br	Provides configuration and monitoring for software BR element.

In addition, the following module is defined:

ietf-software-common	Contains groups of common functions that are imported into the CE and BR modules.
----------------------	---

This approach has been taken so that the various modules can be easily extended to support additional software mechanisms, if required.

Within the BR and CE modules, the YANG "feature" statement is used to distinguish which of the different software mechanism(s) is relevant for a specific element's configuration. For each module, a choice statement 'ce-type' is included for either 'binding' or 'algorithm'. 'Binding' is used for configuring Lightweight 4over6, whereas 'algorithm' is used for configuring MAP-T or MAP-E.

In the 'algo-instances' container, a choice statement 'data-plane' is included to specify MAP-E (encapsulation) or MAP-T (translation). Table 1 shows how these choices are used to indicate the desired software mechanism:

+-----+-----+-----+			
S46 Mechanism	ce-type?	data-plane?	
+-----+-----+-----+			
Lightweight 4over6	binding	n/a	
MAP-E	algorithm	encapsulation	
MAP-T	algorithm	translation	
+-----+-----+-----+			

Table 1: Softwire Mechanism Choice Statement Enumeration

NETCONF notifications are also included.

Note: Earlier versions of this specification combined the software mechanisms by their associated technologies rather than their function in the architecture. As the document was revised, it became apparent that dividing the modules by their role in the architecture (CE or BR) was a better approach as this follows the intended function and existing implementation approaches more closely.

3.2. Additional Components Configuration

The software modules only aim to provide configuration relevant for softwires. In order to fully provision a CE element, the following may also be necessary:

- o IPv6 forwarding and routing configuration, enabling the CE to obtain one or more IPv6 prefixes for software usage. A YANG module for routing management is described in [[RFC8349](#)].
- o IPv4 routing configuration, to add one or more IPv4 destination prefix(es) reachable via the configured software. A YANG module for routing management is described in [[RFC8349](#)].
- o Stateful NAT44/NAPT management, to optionally specify a port set (Port Set Identifier (PSID)) along with its length. A YANG module for NAT management is described in [[I-D.ietf-opsawg-nat-yang](#)].
- o Stateless NAT46 management, required by software translation based mechanisms (i.e., the assignment of a Network-Specific Prefix to use for IPv4/IPv6 translation). A YANG module for NAT management is described in [[I-D.ietf-opsawg-nat-yang](#)].

As YANG modules for the above functions are already defined in other documents, their functionality is not duplicated here and they should be referred to, as needed. [Appendix A.3](#) provides XML examples of how these modules can be used together.

The CE must already have minimal IPv6 configuration in place so it is reachable by the NETCONF client to obtain software configuration. If additional IPv6 specific configuration is necessary, the YANG modules defined in [RFC8344] and [RFC8349] may be used.

4. Software CE YANG Tree Diagram

4.1. CE Tree Diagram

The CE module provides configuration and monitoring for all of the software mechanisms covered in this document (i.e., Lightweight 4over6, MAP-E, and MAP-T).

This module augments "ietf-interfaces", defined in [RFC8343] with an entry for the software. This entry can be referenced to configure IPv4 forwarding features for the element. This entry is added only if tunnel type ([Section 10](#)) is set to 'aplus'.

Figure 1 shows the tree structure of the software CE YANG module:

```

module: ietf-software-ce
  augment /if:interfaces/if:interface:
    +--rw software-payload-mtu?   uint16
    +--rw software-path-mru?      uint16
    +--rw (ce-type)?
      +--:(binding) {binding-mode}?
        | +--rw binding-ipv6info?   union
        | | +--rw br-ipv6-addr      inet:ipv6-address
        +--:(algo) {map-e or map-t}?
          +--rw algo-instances
            +--rw algo-instance* [name]
              +--rw name              string
              +--rw enable?           boolean
              +--rw algo-versioning
                | +--rw version?     uint64
                | +--rw date?        yang:date-and-time
              +--rw (data-plane)?
                | +--:(encapsulation) {map-e}?
                | | +--rw br-ipv6-addr  inet:ipv6-address
                | +--:(translation) {map-t}?
                | | +--rw dmr-ipv6-prefix?  inet:ipv6-prefix
              +--rw ea-len            uint8
              +--rw rule-ipv6-prefix  inet:ipv6-prefix
              +--rw rule-ipv4-prefix  inet:ipv4-prefix
              +--rw forwarding        boolean
  augment /if:interfaces/if:interface/if:statistics:
    +--ro sent-ipv4-packets?
      | yang:zero-based-counter64

```



```

+--ro sent-ipv4-bytes?
|   yang:zero-based-counter64
+--ro sent-ipv6-packets?
|   yang:zero-based-counter64
+--ro sent-ipv6-bytes?
|   yang:zero-based-counter64
+--ro rcvd-ipv4-packets?
|   yang:zero-based-counter64
+--ro rcvd-ipv4-bytes?
|   yang:zero-based-counter64
+--ro rcvd-ipv6-packets?
|   yang:zero-based-counter64
+--ro rcvd-ipv6-bytes?
|   yang:zero-based-counter64
+--ro dropped-ipv4-packets?
|   yang:zero-based-counter64
+--ro dropped-ipv4-bytes?
|   yang:zero-based-counter64
+--ro dropped-ipv6-packets?
|   yang:zero-based-counter64
+--ro dropped-ipv6-bytes?
|   yang:zero-based-counter64
+--ro dropped-ipv4-fragments?
|   yang:zero-based-counter64
+--ro dropped-ipv4-fragment-bytes?
|   yang:zero-based-counter64
+--ro ipv6-fragments-reassembled?
|   yang:zero-based-counter64
+--ro ipv6-fragments-bytes-reassembled?
|   yang:zero-based-counter64
+--ro out-icmpv4-error-packets?
|   yang:zero-based-counter64
+--ro out-icmpv4-error-bytes?
|   yang:zero-based-counter64
+--ro out-icmpv6-error-packets?
|   yang:zero-based-counter64
+--ro out-icmpv6-error-bytes?
    yang:zero-based-counter64

```

notifications:

```

+---n softwire-ce-event {binding-mode}?
  +--ro ce-binding-ipv6-addr-change    inet:ipv6-address

```

Figure 1: Softwire CE YANG Tree Diagram

4.2. Software CE Tree Diagram Description

Additional information related to the operation of a CE element is provided below:

- o software-payload-mtu: optionally used to set the IPv4 MTU for the software. Needed if the software implementation is unable to correctly calculate the correct IPv4 Maximum Transit Unit (MTU) size automatically.
- o software-path-mru: optionally used to set the maximum IPv6 software packet size that can be received, including the encapsulation/translation overhead. Needed if the software implementation is unable to correctly calculate the correct IPv4 Maximum Receive Unit (MRU) size automatically [[RFC4213](#)].
- o ce-type: provides a choice statement allowing the binding or algorithmic software mechanisms to be selected.

Further details relevant to binding software elements are:

- o binding-ipv6info: used to set the IPv6 binding prefix type to identify which IPv6 address to use as the tunnel source. It can be 'ipv6-prefix' or 'ipv6-address'.
- o br-ipv6-addr: sets the IPv6 address of the remote BR.

Additional details relevant to some of the important algorithmic elements are provided below:

- o algo-versioning: optionally used to associate a version number and/or timestamp to the algorithm. This can be used for logging/data retention purposes [[RFC7422](#)]. The version number is selected to uniquely identify the algorithm configuration and a new value written whenever a change is made to the algorithm or a new algo-instance is created.
- o forwarding: specifies whether the rule can be used as a Forward Mapping Rule (FMR). If not set, this rule is a Basic Mapping Rule (BMR) only and must not be used for forwarding. Refer to [Section 4.1 of \[RFC7598\]](#).
- o ea-len: used to set the length of the Embedded-Address (EA), which is defined in the mapping rule for a MAP domain.
- o data-plane: provides a choice statement for either encapsulation (MAP-E) or translation (MAP-T).

- o br-ipv6-addr: defines the IPv6 address of the BR. This information is valid for MAP-E.
- o dmr-ipv6-prefix: defines the Default Mapping Rule (DMR) IPv6 prefix of the BR. This information is valid for MAP-T.

Additional information on the notification node is listed below:

- o ce-binding-ipv6-addr-change: if the CE's binding IPv6 address changes for any reason, the NETCONF client will be notified.

5. Softwire BR YANG Tree Diagram

5.1. BR Tree Diagram

The BR YANG module provides configuration and monitoring for all of the softwire mechanisms covered in this document (i.e., Lightweight 4over6, MAP-E, and MAP-T).

Figure 2 provides the tree structure of this module:

```

module: ietf-softwire-br
  +--rw br-instances
    +--rw (br-type)?
      +--:(binding) {binding-mode}?
        | +--rw binding
        |   +--rw bind-instance* [name]
        |     +--rw name string
        |     +--rw binding-table-versioning
        |       | +--rw version? uint64
        |       | +--rw date? yang:date-and-time
        |     +--rw softwire-num-max uint32
        |     +--rw softwire-payload-mtu uint16
        |     +--rw softwire-path-mru uint16
        |     +--rw enable-hairpinning? boolean
        |     +--rw binding-table
        |       | +--rw binding-entry* [binding-ipv6info]
        |       |   +--rw binding-ipv6info union
        |       |   +--rw binding-ipv4-addr?
        |       |     | inet:ipv4-address
        |       |   +--rw port-set
        |       |     | +--rw psid-offset? uint8
        |       |     | +--rw psid-len uint8
        |       |     | +--rw psid uint16
        |       |   +--rw br-ipv6-addr?
        |       |     inet:ipv6-address
        |     +--rw icmp-policy
        |     +--rw icmpv4-errors

```



```

|         | | +-rw allow-incoming-icmpv4?    boolean
|         | | +-rw icmpv4-rate?              uint32
|         | | +-rw generate-icmpv4-errors?    boolean
|         | +-rw icmpv6-errors
|         |     +-rw generate-icmpv6-errors?    boolean
|         |     +-rw icmpv6-rate?              uint32
| +-ro traffic-stat
|     +-ro discontinuity-time                yang:date-and-time
|     +-ro sent-ipv4-packets?
|         | yang:zero-based-counter64
|     +-ro sent-ipv4-bytes?
|         | yang:zero-based-counter64
|     +-ro sent-ipv6-packets?
|         | yang:zero-based-counter64
|     +-ro sent-ipv6-bytes?
|         | yang:zero-based-counter64
|     +-ro rcvd-ipv4-packets?
|         | yang:zero-based-counter64
|     +-ro rcvd-ipv4-bytes?
|         | yang:zero-based-counter64
|     +-ro rcvd-ipv6-packets?
|         | yang:zero-based-counter64
|     +-ro rcvd-ipv6-bytes?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv4-packets?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv4-bytes?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv6-packets?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv6-bytes?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv4-fragments?
|         | yang:zero-based-counter64
|     +-ro dropped-ipv4-fragment-bytes?
|         | yang:zero-based-counter64
|     +-ro ipv6-fragments-reassembled?
|         | yang:zero-based-counter64
|     +-ro ipv6-fragments-bytes-reassembled?
|         | yang:zero-based-counter64
|     +-ro out-icmpv4-error-packets?
|         | yang:zero-based-counter64
|     +-ro out-icmpv4-error-bytes?
|         | yang:zero-based-counter64
|     +-ro out-icmpv6-error-packets?
|         | yang:zero-based-counter64
|     +-ro out-icmpv6-error-bytes?
|         | yang:zero-based-counter64

```



```

|         +--ro dropped-icmpv4-packets?
|         |         yang:zero-based-counter64
|         +--ro dropped-icmpv4-bytes?
|         |         yang:zero-based-counter64
|         +--ro hairpin-ipv4-packets?
|         |         yang:zero-based-counter64
|         +--ro hairpin-ipv4-bytes?
|         |         yang:zero-based-counter64
|         +--ro active-softwire-num?
|         |         uint32
+--:(algo) {map-e or map-t}?
  +--rw algorithm
    +--rw algo-instance* [name]
      +--rw name                string
      +--rw enable?             boolean
      +--rw algo-versioning
        | +--rw version?        uint64
        | +--rw date?           yang:date-and-time
      +--rw (data-plane)?
        | +--:(encapsulation) {map-e}?
        | | +--rw br-ipv6-addr    inet:ipv6-address
        | +--:(translation) {map-t}?
        | | +--rw dmr-ipv6-prefix? inet:ipv6-prefix
      +--rw ea-len                uint8
      +--rw rule-ipv6-prefix      inet:ipv6-prefix
      +--rw rule-ipv4-prefix      inet:ipv4-prefix
      +--rw forwarding            boolean
      +--rw port-set
        | +--rw psid-offset?      uint8
        | +--rw psid-len          uint8
        | +--rw psid              uint16
      +--ro traffic-stat
        +--ro discontinuity-time    yang:date-and-time
        +--ro sent-ipv4-packets?
        |         yang:zero-based-counter64
        +--ro sent-ipv4-bytes?
        |         yang:zero-based-counter64
        +--ro sent-ipv6-packets?
        |         yang:zero-based-counter64
        +--ro sent-ipv6-bytes?
        |         yang:zero-based-counter64
        +--ro rcvd-ipv4-packets?
        |         yang:zero-based-counter64
        +--ro rcvd-ipv4-bytes?
        |         yang:zero-based-counter64
        +--ro rcvd-ipv6-packets?
        |         yang:zero-based-counter64
        +--ro rcvd-ipv6-bytes?

```



```

|      yang:zero-based-counter64
+--ro dropped-ipv4-packets?
|      yang:zero-based-counter64
+--ro dropped-ipv4-bytes?
|      yang:zero-based-counter64
+--ro dropped-ipv6-packets?
|      yang:zero-based-counter64
+--ro dropped-ipv6-bytes?
|      yang:zero-based-counter64
+--ro dropped-ipv4-fragments?
|      yang:zero-based-counter64
+--ro dropped-ipv4-fragment-bytes?
|      yang:zero-based-counter64
+--ro ipv6-fragments-reassembled?
|      yang:zero-based-counter64
+--ro ipv6-fragments-bytes-reassembled?
|      yang:zero-based-counter64
+--ro out-icmpv4-error-packets?
|      yang:zero-based-counter64
+--ro out-icmpv4-error-bytes?
|      yang:zero-based-counter64
+--ro out-icmpv6-error-packets?
|      yang:zero-based-counter64
+--ro out-icmpv6-error-bytes?
      yang:zero-based-counter64

```

notifications:

```

+---n software-binding-instance-event {binding-mode}?
| +--ro bind-name?
| |      -> /br-instances/binding/bind-instance/name
| +--ro invalid-entry*      leafref
| +--ro added-entry*        inet:ipv6-address
| +--ro modified-entry*     leafref
+---n software-algorithm-instance-event {map-e, map-t}?
+--ro algo-name
|      -> /br-instances/algorithm/algo-instance/name
+--ro invalid-entry-id*
|      -> /br-instances/algorithm/algo-instance/name
+--ro added-entry*
|      -> /br-instances/algorithm/algo-instance/name
+--ro modified-entry*
      -> /br-instances/algorithm/algo-instance/name

```

Figure 2: Software BR YANG Tree

5.2. Software BR Tree Diagram Description

The descriptions for leaves which are common with the CE module are provided in [Section 4.2](#). Descriptions for additional elements are provided below:

- o binding-table-versioning: optionally used to associate a version number and/or timestamp to the binding table. This can be used for logging or data retention purposes [[RFC7422](#)]. The version number is selected to uniquely identify the binding table configuration and a new timestamp value written whenever a change is made to the contents of the binding table or a new binding table list is created.
- o binding-entry: used to define the binding relationship between 3-tuples {lwB4's IPv6 address/prefix, the allocated IPv4 address, restricted port-set}. For detail information, please refer to [[RFC7596](#)].
- o software-num-max: used to set the maximum number of software binding rules that can be created on the lw4o6 element simultaneously. This paramter must not be set to zero because this is equivalent to disabling the BR instance.
- o active-software-num: holds the number of softwires currently provisioned on the BR element.

Additional information on some of the important notification nodes is listed below:

- o invalid-entry, added-entry, modified-entry: used to notify the NETCONF client that a specific binding entry or MAP rule has expired, been invalidated, added, or modified.

6. Software CE YANG Module

This module imports the modules defined in [[RFC6991](#)], [[RFC8343](#)], and [[RFC7224](#)]. It also imports the 'ietf-software-common' and 'iana-tunnel-type' modules [[I-D.ietf-software-iftunnel](#)].

```
<CODE BEGINS>file "ietf-software-ce@2018-11-30.yang"
```

```
module ietf-software-ce {  
  yang-version 1.1;  
  namespace "urn:ietf:params:xml:ns:yang:ietf-software-ce";  
  prefix software-ce;  
  
  import ietf-inet-types {
```



```
    prefix inet;
    reference "Section 4 of RFC 6991";
}
import ietf-interfaces {
    prefix if;
    reference "RFC 8343: A YANG Data Model for Interface Management";
}
import ietf-softwire-common {
    prefix softwire-common;
    reference
        "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port
        Softwires";
}
import iana-tunnel-type {
    prefix iana-tunnel-type;
    reference
        "RFC YYYY: Tunnel Interface Types YANG Module";
}
```

organization

"IETF Softwire Working Group";

contact

"WG Web: <<https://datatracker.ietf.org/wg/softwire/>>

WG List: <<mailto:softwire@ietf.org>>

Author: Qi Sun
<<mailto:sunqi.ietf@gmail.com>>

Author: Linhui Sun
<<mailto:lh.sunlinh@gmail.com>>

Author: Yong Cui
<<mailto:yong@csnet1.cs.tsinghua.edu.cn>>

Editor: Ian Farrer
<<mailto:ian.farrer@telekom.de>>

Author: Sladjana Zoric
<<mailto:sladjana.zoric@telekom.de>>

Editor: Mohamed Boucadair
<<mailto:mohamed.boucadair@orange.com>>

Author: Rajiv Asati
<<mailto:rajiva@cisco.com>>";

description

"This document defines a YANG module for the configuration and management of A+P Softwire Customer Premises Equipment (CEs). It

covers Lightweight 4over6, MAP-E, and MAP-T mechanisms.

Copyright (c) 2018 IETF Trust and the persons identified as authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, is permitted pursuant to, and subject to the license terms contained in, the Simplified BSD License set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see the RFC itself for full legal notices.";

```
revision 2018-10-23 {
  description
    "Initial revision.";
  reference
    "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port
      Softwires";
}

/*
 * Features
 */

feature binding-mode {
  description
    "Binding is used for configuring the Lightweight 4over6 mechanism.

    Binding based softwire mechanisms are IPv4-over-IPv6 tunnelling
    transition mechanisms specifically intended for complete
    independence between the IPv6 subnet prefix (and IPv6 address)
    and IPv4 address, with or without IPv4 address sharing.

    This is accomplished by maintaining state for each softwire
    (per-subscriber state) in the central Border Relay (BR) and using
    a hub-and-spoke forwarding architecture. In order to delegate the
    NAT function and achieve IPv4 address sharing, port-restricted
    IPv4 addresses needs to be allocated to CEs.

    This feature indicates that the network element can function as
    one or more binding based softwire instances.";
  reference
    "RFC7596: Lightweight 4over6: An Extension to the Dual-Stack Lite
      Architecture
    RFC7597: Mapping of Address and Port with Encapsulation (MAP-E)
```



```
    RFC7599: Mapping of Address and Port using Translation (MAP-T)";
}

feature map-e {
  description
    "MAP-E is an IPv6 transition mechanism for transporting IPv4
    packets across an IPv6 network using IP encapsulation. MAP-E
    allows for a reduction of the amount of centralized state using
    rules to express IPv4/IPv6 address mappings. This introduces an
    algorithmic relationship between the IPv6 subnet and IPv4
    address.

    This feature indicates that the network element can function as
    one or more MAP-E software instances.";
  reference
    "RFC7597: Mapping of Address and Port with Encapsulation (MAP-E)";
}

feature map-t {
  description
    "MAP-T is an IPv6 transition mechanism for transporting IPv4
    packets across an IPv6 network using IP translation. It leverages
    a double stateless NAT64 based solution as well as the stateless
    algorithmic address & transport layer port mapping algorithm
    defined for MAP-E.

    This feature indicates that the network element can function as
    one or more MAP-T software instances.";
  reference
    "RFC7599: Mapping of Address and Port using Translation (MAP-T)";
}

// Binding Entry

grouping binding-entry {
  description
    "The binding BR (Border Relay) maintains an address binding table
    that contains the binding between the CE's IPv6 address,
    the allocated IPv4 address and restricted port-set.";
  leaf binding-ipv6info {
    type union {
      type inet:ipv6-address;
      type inet:ipv6-prefix;
    }
  }
  description
    "The IPv6 information for a binding entry.

    When the IPv6 prefix type is used,
```



```
    the IPv6 source address of the CE is constructed
    according to the description in RFC7596.

    If the IPv6 address type is used, the CE can use
    any valid /128 address from a prefix assigned to
    the CE.";
    reference "Section 5.1 of RFC7596";
}
leaf br-ipv6-addr {
    type inet:ipv6-address;
    mandatory true;
    description
        "The IPv6 address of the binding BR.";
}
}

// configuration and stateful parameters for softwire CE interface

augment "/if:interfaces/if:interface" {
    when "derived-from(if:type, 'iana-tunnel-type:aplus')";
    description
        "Softwire CE interface configuration";
    leaf softwire-payload-mtu {
        type uint16;
        units "bytes";
        description
            "The payload IPv4 MTU for the softwire tunnel.";
    }
    leaf softwire-path-mru {
        type uint16;
        units "bytes";
        description
            "The path MRU for the softwire (payload + encapsulation
            overhead).";
        reference
            "RFC 4213: Basic Transition Mechanisms for IPv6 Hosts and
            Routers";
    }
}
choice ce-type {
    description
        "Sets the softwire CE mechanism";
    case binding {
        if-feature "binding-mode";
        description
            "CE binding configuration";
        uses binding-entry;
    }
}
case algo {
```



```
    if-feature "map-e or map-t";
    description
      "CE algorithm configuration";
    container algo-instances {
      description
        "Collection of MAP-E/MAP-T parameters";
      list algo-instance {
        key "name";
        description
          "MAP forwarding rule instance for
            MAP-E/MAP-T";
        leaf name {
          type string;
          mandatory true;
          description
            "The name is used to uniquely identify an algorithm
              instance.

              This name can be automatically assigned
              or explicitly configured.";
        }
        uses software-common:algorithm-instance;
      }
    }
  }
}

augment "/if:interfaces/if:interface/if:statistics" {
  when "derived-from(..if:type, 'iana-tunnel-type:aplus')";
  description
    "Software CE interface statistics.";
  uses software-common:traffic-stat;
}

/*
 * Notifications
 */

notification software-ce-event {
  if-feature "binding-mode";
  description
    "CE notification";
  leaf ce-binding-ipv6-addr-change {
    type inet:ipv6-address;
    mandatory true;
    description
      "This notification is generated whenever the CE's binding IPv6
        address changes for any reason.";
  }
}
```



```
    }  
  }  
}  
<CODE ENDS>
```

7. BR Software YANG Module

This module imports typedefs from [[RFC6991](#)]. It also imports the 'ietf-software-common' module.

```
<CODE BEGINS>file "ietf-software-br@2018-10-23.yang"  
  
module ietf-software-br {  
  yang-version 1.1;  
  namespace "urn:ietf:params:xml:ns:yang:ietf-software-br";  
  prefix software-br;  
  
  import ietf-inet-types {  
    prefix inet;  
    reference "Section 4 of RFC 6991";  
  }  
  import ietf-yang-types {  
    prefix yang;  
    reference "Section 3 of RFC 6991";  
  }  
  import ietf-software-common {  
    prefix software-common;  
    reference  
      "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port  
        Softwires";  
  }  
  
  organization  
    "IETF Software Working Group";  
  contact  
    "WG Web:  <https://datatracker.ietf.org/wg/software/>  
    WG List:  <mailto:software@ietf.org>  
  
    Author: Qi Sun  
            <mailto:sunqi.ietf@gmail.com>  
  
    Author: Linhui Sun  
            <mailto:lh.sunlinh@gmail.com>  
  
    Author: Yong Cui  
            <mailto:yong@csnet1.cs.tsinghua.edu.cn>  
  
    Editor: Ian Farrer
```


<mailto:ian.farrer@telekom.de>

Author: Sladjana Zoric
<mailto:sladjana.zoric@telekom.de>

Editor: Mohamed Boucadair
<mailto:mohamed.boucadair@orange.com>

Author: Rajiv Asati
<mailto:rajiva@cisco.com>;

description

"This document defines a YANG module for the configuration and management of A+P Softwire Border Routers. It covers Lightweight 4over6, MAP-E, and MAP-T mechanisms.

Copyright (c) 2018 IETF Trust and the persons identified as authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, is permitted pursuant to, and subject to the license terms contained in, the Simplified BSD License set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see the RFC itself for full legal notices.";

```
revision 2018-10-23 {
  description
    "Initial revision.";
  reference
    "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port
      Softwires";
}
```

```
/*
 * Groupings
 */
```

```
grouping port-set {
  description
    "Describes a set of layer 4 port numbers.
```

```

    This may be a simple port range, or use the Port Set
    Identifier (PSID) algorithm to represent a range of transport
    layer ports which will be used by a NAT.";
```



```
leaf psid-offset {
  type uint8 {
    range "0..16";
  }
  description
    "The number of offset bits. In Lightweight 4over6,
    the default value is 0 for assigning one contiguous
    port range. In MAP-E/T, the default value is 6,
    which means the system ports (0-1023) are excluded by
    default and the assigned port ranges are distributed across
    the entire port space, depending on either psid-len or the
    number of contiguous ports.";
}
leaf psid-len {
  type uint8 {
    range "0..15";
  }
  mandatory true;
  description
    "The length of PSID, representing the sharing
    ratio for an IPv4 address. This, along with ea-len, can
    be used to calculate the number of contiguous ports per
    port range";
}
leaf psid {
  type uint16;
  mandatory true;
  description
    "Port Set Identifier (PSID) value, which
    identifies a set of ports algorithmically.";
}
}

grouping binding-entry {
  description
    "The binding BR maintains an address binding table that
    contains the binding between the CE's IPv6 address,
    the allocated IPv4 address and restricted port-set.";
  leaf binding-ipv6info {
    type union {
      type inet:ipv6-address;
      type inet:ipv6-prefix;
    }
    description
      "The IPv6 information for a CE binding entry.
      When the IPv6 prefix type is used,
      the IPv6 source address of the CE is constructed
      according to the description in RFC7596;
```



```
        if the IPv6 address type is used, the CE can use
        any valid /128 address from a prefix assigned to
        the CE.";
    reference
        "RFC7596: Lightweight 4over6: An Extension to the Dual-Stack
        Lite Architecture";
}
leaf binding-ipv4-addr {
    type inet:ipv4-address;
    description
        "The IPv4 address assigned to the binding CE,
        which is used as the IPv4 external address
        for binding CE local NAPT44.";
}
container port-set {
    description
        "For Lightweight 4over6, the default value
        for offset should be 0, to configure one contiguous
        port range.";
    uses port-set {
        refine "psid-offset" {
            default "0";
        }
    }
}
leaf br-ipv6-addr {
    type inet:ipv6-address;
    description
        "The IPv6 address for binding BR.";
}
}

/*
 * Features
 */

feature binding-mode {
    description
        "Binding is used for configuring the Lightweight 4over6 mechanism.

        Binding based softwire mechanisms are IPv4-over-IPv6 tunnelling
        transition mechanisms specifically intended for complete
        independence between the IPv6 subnet prefix (and IPv6 address)
        and IPv4 address, with or without IPv4 address sharing.

        This is accomplished by maintaining state for each softwire
        (per-subscriber state) in the central Border Relay (BR) and using
        a hub-and-spoke forwarding architecture. In order to delegate the
```


NAPT function and achieve IPv4 address sharing, port-restricted IPv4 addresses needs to be allocated to CEs.

This feature indicates that the network element can function as one or more binding based softwire instances.";

reference

"[RFC7596](#): Lightweight 4over6: An Extension to the Dual-Stack Lite Architecture

[RFC7597](#): Mapping of Address and Port with Encapsulation (MAP-E)

[RFC7599](#): Mapping of Address and Port using Translation (MAP-T)";

}

feature map-e {

description

"MAP-E is an IPv6 transition mechanism for transporting IPv4 packets across an IPv6 network using IP encapsulation. MAP-E allows for a reduction of the amount of centralized state using rules to express IPv4/IPv6 address mappings. This introduces an algorithmic relationship between the IPv6 subnet and IPv4 address.

This feature indicates that the network element can function as one or more MAP-E softwire instances.";

reference

"[RFC7597](#): Mapping of Address and Port with Encapsulation (MAP-E)";

}

feature map-t {

description

"MAP-T is an IPv6 transition mechanism for transporting IPv4 packets across an IPv6 network using IP translation. It leverages a double stateless NAT64 based solution as well as the stateless algorithmic address & transport layer port mapping algorithm defined for MAP-E.

This feature indicates that the network element can function as one or more MAP-T softwire instances.";

reference

"[RFC7599](#): Mapping of Address and Port using Translation (MAP-T)";

}

container br-instances {

description

"BR instances enabled in a network element.";

choice br-type {

description

"Select binding or algorithmic BR functionality.";

case binding {


```
if-feature "binding-mode";
container binding {
  description
    "binding mechanism (binding table) configuration.";
  list bind-instance {
    key "name";
    description
      "A set of binding instances to be configured.";
    leaf name {
      type string;
      mandatory true;
      description
        "The name for the binding BR. It is used to uniquely
        distinguish a binding instance by its name.";
    }
  }
  container binding-table-versioning {
    description
      "binding table's version";
    leaf version {
      type uint64;
      description
        "Timestamp when the binding table was activated.

        A binding instance may be provided with binding
        entries that may change in time (e.g., increase
        the size of the port set). When an abuse party
        presents an external IP address/port, the version
        of the binding table is important because, depending
        on the version, a distinct customer may be
        identified.

        The timestamp is used as a key to find the
        appropriate binding table that was put into effect
        when an abuse occurred. ";
    }
    leaf date {
      type yang:date-and-time;
      description
        "Timestamp of the binding table";
      reference
        "RFC7422: Deterministic Address Mapping to Reduce
        Logging in Carrier-Grade NAT Deployments";
    }
  }
}
leaf softwire-num-max {
  type uint32 {
    range "1..max";
  }
}
```



```
    mandatory true;
    description
      "The maximum number of softwires that can be created
       on the binding BR.";
  }
  leaf softwire-payload-mtu {
    type uint16;
    units "bytes";
    mandatory true;
    description
      "The payload IPv4 MTU for binding softwire.";
  }
  leaf softwire-path-mru {
    type uint16;
    units "bytes";
    mandatory true;
    description
      "The path MRU for binding softwire.";
    reference
      "RFC4213: Basic Transition Mechanisms for IPv6 Hosts
       and Routers";
  }
  leaf enable-hairpinning {
    type boolean;
    default "true";
    description
      "Enables/disables support for locally forwarding
       (hairpinning) traffic between two CEs.";
    reference "Section 6.2 of RFC7596";
  }
  container binding-table {
    description
      "binding table";
    list binding-entry {
      key "binding-ipv6info";
      description
        "binding entry";
      uses binding-entry;
    }
  }
  container icmp-policy {
    description
      "The binding BR can be configured to process or drop
       incoming ICMP messages, and to generate outgoing ICMP
       error messages.";
    container icmpv4-errors {
      description
        "ICMPv4 error processing configuration";
```



```
leaf allow-incoming-icmpv4 {
    type boolean;
    default "true";
    description
        "Enables the processing of incoming ICMPv4
        packets.";
    reference
        "RFC7596: Lightweight 4over6: An Extension to
        the Dual-Stack Lite Architecture";
}
leaf icmpv4-rate {
    type uint32;
    description
        "Rate limit threshold in messages per-second
        for processing incoming ICMPv4 errors messages";
}
leaf generate-icmpv4-errors {
    type boolean;
    default "true";
    description
        "Enables the generation of outgoing ICMPv4 error
        messages on receipt of an inbound IPv4 packet
        with no matching binding table entry.";
    reference "Section 5.2 of RFC7596.";
}
}
container icmpv6-errors {
    description
        "ICMPv6 error processing configuration";
    leaf generate-icmpv6-errors {
        type boolean;
        default "true";
        description
            "Enables the generation of ICMPv6 error messages if
            no matching binding table entry is found for a
            received packet.";
        reference "Section 6.2 of RFC7596.";
    }
    leaf icmpv6-rate {
        type uint32;
        description
            "Rate limit threshold in messages per-second
            for sending ICMPv6 errors messages";
        reference "Section 9 of RFC7596.";
    }
}
}
container traffic-stat {
```



```
config false;
description
  "Traffic statistics information for the BR.";
leaf discontinuity-time {
  type yang:date-and-time;
  mandatory true;
  description
    "The time of the most recent occasion on which the BR
    instance suffered a discontinuity. This must be
    initialized when the BR instance is configured
    or rebooted.";
}
uses software-common:traffic-stat;
leaf dropped-icmpv4-packets {
  type yang:zero-based-counter64;
  description
    "ICMPv4 packets that are dropped as a result
    of the ICMP policy. Typically, this can be any
    incoming ICMPv4 packets if ICMPv4 processing is
    disabled or incoming ICMPv4 packets that exceed
    the ICMPv4 rate-limit threshold.

    Discontinuities in the value of this counter can
    occur at re-initialization of the management
    system, and at other times as indicated by
    the value of 'discontinuity-time'.";
}
leaf dropped-icmpv4-bytes {
  type yang:zero-based-counter64;
  description
    "ICMPv4 messages, in bytes, that are dropped as
    a result of the ICMP policy. Typically, it
    can be any incoming ICMPv4 packets if ICMPv4
    processing is disabled or incoming ICMPv4
    packets that exceed the ICMPv4 rate-limit
    threshold.

    Discontinuities in the value of this counter can
    occur at re-initialization of the management
    system, and at other times as indicated by
    the value of 'discontinuity-time'.";
}
leaf hairpin-ipv4-packets {
  type yang:zero-based-counter64;
  description
    "IPv4 packets locally routed between two CEs
    (hairpinned)."
```



```
        Discontinuities in the value of this counter can
        occur at re-initialization of the management
        system, and at other times as indicated by
        the value of 'discontinuity-time'.";
    }
    leaf hairpin-ipv4-bytes {
        type yang:zero-based-counter64;
        description
            "IPv4 bytes locally routed between two CEs
            (hairpinned).

            Discontinuities in the value of this counter can
            occur at re-initialization of the management
            system, and at other times as indicated by
            the value of 'discontinuity-time'.";
    }
    leaf active-softwire-num {
        type uint32;
        config false;
        description
            "The number of currently active softwires on the
            binding instance.

            Discontinuities in the value of this counter can
            occur at re-initialization of the management
            system, and at other times as indicated by
            the value of 'discontinuity-time'.";
    }
}
}
}
}
}
case algo {
    if-feature "map-e or map-t";
    container algorithm {
        description
            " A set of parameters used for MAP-E/MAP-T.";
        list algo-instance {
            key "name";
            description
                "Instances of algorithm";
            leaf name {
                type string;
                mandatory true;
                description
                    "The name is used to uniquely identify an algorithm
                    instance.
```



```

        This name can be automatically assigned
        or explicitly configured.";
    }
    uses software-common:algorithm-instance;
    container port-set {
        description
            "Indicates a set of ports.";
        uses port-set;
    }
    container traffic-stat {
        config false;
        description
            "Traffic statistics information for the BR.";
        leaf discontinuity-time {
            type yang:date-and-time;
            mandatory true;
            description
                "The time of the most recent occasion on which the BR
                instance suffered a discontinuity. This must be
                reset to the current date-and-time when the BR
                instance is configured or rebooted.";
        }
        uses software-common:traffic-stat;
    }
}

}
}
}
}
}
}

/*
 * Notifications
 */

notification software-binding-instance-event {
    if-feature "binding-mode";
    description
        "Notifications for binding instance when an entry is
        added, modified, or is not valid anymore.";
    leaf bind-name {
        type leafref {
            path "/br-instances/binding/bind-instance/name";
        }
        description
            "The name of the binding-instance that
            generated the notification.";
    }
    leaf-list invalid-entry {

```



```
    type leafref {
      path
        "/br-instances/binding/"
        + "bind-instance[name=current()/../bind-name]/"
        + "binding-table/binding-entry/binding-ipv6info";
    }
    description
      "Notify the client that a specific binding entry has
      expired or is invalid. The binding-ipv6info identifies
      an entry.";
  }
  leaf-list added-entry {
    type inet:ipv6-address;
    description
      "Notify the client that a binding entry has been added.
      The ipv6 address of that entry is the index. The client
      gets other information from the binding BR about the entry
      indexed by that ipv6 address.";
  }
  leaf-list modified-entry {
    type leafref {
      path
        "/br-instances/binding/"
        + "bind-instance[name=current()/../bind-name]/"
        + "binding-table/binding-entry/binding-ipv6info";
    }
    description
      "The binding-table entry that has been modified.";
  }
}

notification softwire-algorithm-instance-event {
  if-feature "map-e or map-t";
  description
    "Notifications for algorithm instance when an entry is
    added, modified, or is not valid anymore.";
  leaf algo-name {
    type leafref {
      path "/br-instances/algorithm/algo-instance/name";
    }
    mandatory true;
    description
      "algorithmic instance event.";
  }
  leaf-list invalid-entry {
    type leafref {
      path "/br-instances/algorithm/algo-instance/name";
    }
    description
```



```
        "Invalid entry event.";
    }
    leaf-list added-entry {
        type leafref {
            path "/br-instances/algorithm/algo-instance/name";
        }
        description
            "Added entry.";
    }
    leaf-list modified-entry {
        type leafref {
            path "/br-instances/algorithm/algo-instance/name";
        }
        description
            "Modified entry.";
    }
}
}
}
<CODE ENDS>
```

8. Common Software Element Groups YANG Module

This module imports typedefs from [[RFC6991](#)].

The following YANG module contains definitions that are used by both the software CE and software BR YANG modules.

```
<CODE BEGINS>file "ietf-software-common@2018-10-23.yang"

module ietf-software-common {
    yang-version 1.1;
    namespace "urn:ietf:params:xml:ns:yang:ietf-software-common";
    prefix software-common;

    import ietf-inet-types {
        prefix inet;
        reference "Section 4 of RFC 6991";
    }
    import ietf-yang-types {
        prefix yang;
        reference "Section 3 of RFC 6991";
    }

    organization
        "IETF Software Working Group";
    contact
        "WG Web:  <https://datatracker.ietf.org/wg/software/>
        WG List:  <mailto:software@ietf.org>
```


Author: Qi Sun
<mailto:sunqi.ietf@gmail.com>

Author: Linhui Sun
<mailto:lh.sunlinh@gmail.com>

Author: Yong Cui
<mailto:yong@csnet1.cs.tsinghua.edu.cn>

Editor: Ian Farrer
<mailto:ian.farrer@telekom.de>

Author: Sladjana Zoric
<mailto:sladjana.zoric@telekom.de>

Editor: Mohamed Boucadair
<mailto:mohamed.boucadair@orange.com>

Author: Rajiv Asati
<mailto:rajiva@cisco.com>;

description

"This document defines a YANG module defining types
common to all A+P modules.

Copyright (c) 2018 IETF Trust and the persons identified as
authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or
without modification, is permitted pursuant to, and subject
to the license terms contained in, the Simplified BSD License
set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions
Relating to IETF Documents
(<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see
the RFC itself for full legal notices."

```
revision 2018-10-23 {
  description
    "Initial revision.";
  reference
    "RFC XXXX: YANG Modules for IPv4-in-IPv6 Address plus Port
      Softwires";
}

feature map-e {
  description
    "MAP-E is an IPv6 transition mechanism for transporting IPv4
```


packets across an IPv6 network using IP encapsulation. MAP-E allows for a reduction of the amount of centralized state using rules to express IPv4/IPv6 address mappings. This introduces an algorithmic relationship between the IPv6 subnet and IPv4 address.

This feature indicates that the network element can function as one or more MAP-E softwire instances.";

reference

"[RFC7597](#): Mapping of Address and Port with Encapsulation (MAP-E)";

}

feature map-t {

description

"MAP-T is an IPv6 transition mechanism for transporting IPv4 packets across an IPv6 network using IP translation. It leverages a double stateless NAT64 based solution as well as the stateless algorithmic address & transport layer port mapping algorithm defined for MAP-E.

This feature indicates that the network element can function as one or more MAP-T softwire instances.";

reference

"[RFC7599](#): Mapping of Address and Port using Translation (MAP-T)";

}

/*

* Groupings

*/

grouping algorithm-instance {

description

"A collection of parameters that is used fro MAP-E/MAP-T.";

leaf enable {

type boolean;

description

"Enable/disable an individual MAP-E or MAP-T rule.";

}

container algo-versioning {

description

"Version number for this algorithm instance";

leaf version {

type uint64;

description

"A version number for the mapping algorithm rules provided to the algorithm instance";

}

leaf date {


```
type yang:date-and-time;
description
  "Timestamp when the algorithm instance was activated.

  An algorithm instance may be provided with mapping
  rules that may change in time (for example, increase
  the size of the port set). When an abuse party
  presents an external IP address/port, the version
  of the algorithm is important because depending on
  the version, a distinct customer may be identified.

  The timestamp is used as a key to find the appropriate
  algorithm that was put into effect when an abuse
  occurred. ";
reference
  "RFC7422: Deterministic Address Mapping to Reduce
  Logging in Carrier-Grade NAT Deployments";
}
}
choice data-plane {
  description
    "Selects MAP-E (encapsulation) or MAP-T
    (translation)";
  case encapsulation {
    if-feature "map-e";
    description
      "encapsulation for MAP-E";
    leaf br-ipv6-addr {
      type inet:ipv6-address;
      mandatory true;
      description
        "The IPv6 address of the MAP-E BR.";
    }
  }
  case translation {
    if-feature "map-t";
    description
      "translation for MAP-T";
    leaf dmr-ipv6-prefix {
      type inet:ipv6-prefix;
      description
        "The IPv6 prefix of the MAP-T BR.";
    }
  }
}
leaf ea-len {
  type uint8;
  mandatory true;
```



```
    description
      "Embedded Address (EA) bits are the IPv4 EA-bits in the IPv6
      address identifying an IPv4 prefix/address (or part thereof)
      or a shared IPv4 address (or part thereof) and a port-set
      identifier. The length of the EA-bits is defined as part of
      a MAP rule for a MAP domain.";
  }
  leaf rule-ipv6-prefix {
    type inet:ipv6-prefix;
    mandatory true;
    description
      "The Rule IPv6 prefix defined in the mapping rule.";
  }
  leaf rule-ipv4-prefix {
    type inet:ipv4-prefix;
    mandatory true;
    description
      "The Rule IPv4 prefix defined in the mapping rule.";
  }
  leaf forwarding {
    type boolean;
    mandatory true;
    description
      "This parameter specifies whether the rule may be used for
      forwarding (FMR). If set, this rule is used as an FMR;
      if not set, this rule is a Basic Mapping Rule (BMR) only
      and must not be used for forwarding.";
  }
}

grouping traffic-stat {
  description
    "Traffic statistics";
  leaf sent-ipv4-packets {
    type yang:zero-based-counter64;
    description
      "Number of decapsulated and forwarded IPv4 packets.

      Discontinuities in the value of this counter can occur
      at re-initialization of the management system, and at
      other times as indicated by the value of
      'discontinuity-time'.";
  }
  leaf sent-ipv4-bytes {
    type yang:zero-based-counter64;
    description
      "Decapsulated/translated IPv4 traffic sent, in bytes
```



```
        Discontinuities in the value of this counter can occur
        at re-initialization of the management system, and at
        other times as indicated by the value of
        'discontinuity-time'. ";
    }
    leaf sent-ipv6-packets {
        type yang:zero-based-counter64;
        description
            "Number of encapsulated IPv6 packets sent.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf sent-ipv6-bytes {
        type yang:zero-based-counter64;
        description
            "Encapsulated IPv6 traffic sent, in bytes

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf rcvd-ipv4-packets {
        type yang:zero-based-counter64;
        description
            "Number of incoming IPv4 packets at the
            Internet-facing interface.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf rcvd-ipv4-bytes {
        type yang:zero-based-counter64;
        description
            "IPv4 traffic received for processing, in bytes.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf rcvd-ipv6-packets {
        type yang:zero-based-counter64;
```



```
description
  "Number of IPv4-in-IPv6 packets received.

  Discontinuities in the value of this counter can occur
  at re-initialization of the management system, and at
  other times as indicated by the value of
  'discontinuity-time'.";
}
leaf rcvd-ipv6-bytes {
  type yang:zero-based-counter64;
  description
    "IPv4-in-IPv6 traffic received, in bytes.

    Discontinuities in the value of this counter can occur
    at re-initialization of the management system, and at
    other times as indicated by the value of
    'discontinuity-time'.";
}
leaf dropped-ipv4-packets {
  type yang:zero-based-counter64;
  description
    "Number of IPv4 packets dropped at the
    Internet-facing interface.

    Discontinuities in the value of this counter can occur
    at re-initialization of the management system, and at
    other times as indicated by the value of
    'discontinuity-time'.";
}
leaf dropped-ipv4-bytes {
  type yang:zero-based-counter64;
  description
    "IPv4 traffic dropped at the Internet-facing
    interface, in bytes.

    Discontinuities in the value of this counter can occur
    at re-initialization of the management system, and at
    other times as indicated by the value of
    'discontinuity-time'.";
}
leaf dropped-ipv6-packets {
  type yang:zero-based-counter64;
  description
    "Number of IPv4-in-IPv6 packets dropped.

    Discontinuities in the value of this counter can occur
    at re-initialization of the management system, and at
    other times as indicated by the value of
```



```
        'discontinuity-time'.");
    }
    leaf dropped-ipv6-bytes {
        type yang:zero-based-counter64;
        description
            "IPv4-in-IPv6 traffic dropped, in bytes.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'.");
    }
    leaf dropped-ipv4-fragments {
        type yang:zero-based-counter64;
        description
            "Number of fragmented IPv4 packets dropped.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'.");
    }
    leaf dropped-ipv4-fragment-bytes {
        type yang:zero-based-counter64;
        description
            "Fragmented IPv4 traffic dropped, in bytes.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'.");
    }
    leaf ipv6-fragments-reassembled {
        type yang:zero-based-counter64;
        description
            "Number of IPv6 fragments successfully reassembled.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'.");
    }
    leaf ipv6-fragments-bytes-reassembled {
        type yang:zero-based-counter64;
        description
            "IPv6 fragments successfully reassembled, in bytes.

            Discontinuities in the value of this counter can occur
```



```
        at re-initialization of the management system, and at
        other times as indicated by the value of
        'discontinuity-time'. ";
    }
    leaf out-icmpv4-error-packets {
        type yang:zero-based-counter64;
        description
            "Internally generated ICMPv4 error packets.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf out-icmpv4-error-bytes {
        type yang:zero-based-counter64;
        description
            "Internally generated ICMPv4 error messages, in bytes.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf out-icmpv6-error-packets {
        type yang:zero-based-counter64;
        description
            "Internally generated ICMPv6 error packets.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
    leaf out-icmpv6-error-bytes {
        type yang:zero-based-counter64;
        description
            "Internally generated ICMPv6 error messages, in bytes.

            Discontinuities in the value of this counter can occur
            at re-initialization of the management system, and at
            other times as indicated by the value of
            'discontinuity-time'. ";
    }
}
}
}
<CODE ENDS>
```


9. Security Considerations

The YANG modules defined in this document is designed to be accessed via network management protocols such as NETCONF [[RFC6241](#)] or RESTCONF [[RFC8040](#)]. The lowest NETCONF layer is the secure transport layer, and the mandatory-to-implement secure transport is Secure Shell (SSH) [[RFC6242](#)]. The lowest RESTCONF layer is HTTPS, and the mandatory-to-implement secure transport is TLS [[RFC8446](#)].

The NETCONF access control model [[RFC8341](#)] provides the means to restrict access for particular NETCONF or RESTCONF users to a preconfigured subset of all available NETCONF or RESTCONF protocol operations and content.

All data nodes defined in the YANG modules which can be created, modified, and deleted (i.e., config true, which is the default) are considered sensitive. Write operations (e.g., edit-config) applied to these data nodes without proper protection can negatively affect network operations.

10. IANA Considerations

This document requests IANA to assign a new tunnel type under the "tunnelType" sub-registry of the "ifType definitions" registry maintained at [[TUNNELTYPE-IANA-REGISTRY](#)] and use the following data for the new entry:

Decimal:	TDB1
Name:	aplusp
Description:	A+P encapsulation
Reference:	[RFC6346]

This document requests IANA to register the following URIs in the "IETF XML Registry" [[RFC3688](#)]:

URI: urn:ietf:params:xml:ns:yang:ietf-softwire-ce
Registrant Contact: The IESG.
XML: N/A; the requested URI is an XML namespace.

URI: urn:ietf:params:xml:ns:yang:ietf-softwire-br
Registrant Contact: The IESG.
XML: N/A; the requested URI is an XML namespace.

URI: urn:ietf:params:xml:ns:yang:ietf-softwire-common
Registrant Contact: The IESG.
XML: N/A; the requested URI is an XML namespace.

This document requests that IANA registers the following YANG modules

in the "YANG Module Names" registry [[RFC6020](#)]:

```
name: ietf-softwire-ce
namespace: urn:ietf:params:xml:ns:yang:ietf-softwire-ce
prefix: softwire-ce
reference: RFC XXXX

name: ietf-softwire-br
namespace: urn:ietf:params:xml:ns:yang:ietf-softwire-br
prefix: softwire-br
reference: RFC XXXX

name: ietf-softwire-common
namespace: urn:ietf:params:xml:ns:yang:ietf-softwire-common
prefix: softwire-common
reference: RFC XXXX
```

11. Acknowledgements

The authors would like to thank Lishan Li, Bert Wijnen, Giles Heron, Ole Troan, Andy Wingo and Leo Tietz for their contributions to this work.

Thanks to Sheng Jiang for the review.

Special thanks to Tom Petch and Martin Bjorklund for the detailed review and suggestions.

12. Contributors

The following individual contributed to this document:

```
Hao Wang
Tsinghua University
Beijing 100084
P.R.China
Phone: +86-10-6278-5822
Email: wangh13@mails.tsinghua.edu.cn
```

13. References

13.1. Normative References

```
[I-D.ietf-softwire-iftunnel]
    Boucadair, M., Ed. and I. Farrer, "Tunnel Interface Types
    YANG Module", <https://datatracker.ietf.org/doc/
    draft-ietf-softwire-iftunnel/>.
```


- [RFC3688] Mealling, M., "The IETF XML Registry", [BCP 81](#), [RFC 3688](#), DOI 10.17487/RFC3688, January 2004, <<https://www.rfc-editor.org/info/rfc3688>>.
- [RFC6020] Bjorklund, M., Ed., "YANG - A Data Modeling Language for the Network Configuration Protocol (NETCONF)", [RFC 6020](#), DOI 10.17487/RFC6020, October 2010, <<https://www.rfc-editor.org/info/rfc6020>>.
- [RFC6241] Enns, R., Ed., Bjorklund, M., Ed., Schoenwaelder, J., Ed., and A. Bierman, Ed., "Network Configuration Protocol (NETCONF)", [RFC 6241](#), DOI 10.17487/RFC6241, June 2011, <<https://www.rfc-editor.org/info/rfc6241>>.
- [RFC6242] Wasserman, M., "Using the NETCONF Protocol over Secure Shell (SSH)", [RFC 6242](#), DOI 10.17487/RFC6242, June 2011, <<https://www.rfc-editor.org/info/rfc6242>>.
- [RFC6991] Schoenwaelder, J., Ed., "Common YANG Data Types", [RFC 6991](#), DOI 10.17487/RFC6991, July 2013, <<https://www.rfc-editor.org/info/rfc6991>>.
- [RFC7224] Bjorklund, M., "IANA Interface Type YANG Module", [RFC 7224](#), DOI 10.17487/RFC7224, May 2014, <<https://www.rfc-editor.org/info/rfc7224>>.
- [RFC7596] Cui, Y., Sun, Q., Boucadair, M., Tsou, T., Lee, Y., and I. Farrer, "Lightweight 4over6: An Extension to the Dual-Stack Lite Architecture", [RFC 7596](#), DOI 10.17487/RFC7596, July 2015, <<https://www.rfc-editor.org/info/rfc7596>>.
- [RFC7597] Troan, O., Ed., Dec, W., Li, X., Bao, C., Matsushima, S., Murakami, T., and T. Taylor, Ed., "Mapping of Address and Port with Encapsulation (MAP-E)", [RFC 7597](#), DOI 10.17487/RFC7597, July 2015, <<https://www.rfc-editor.org/info/rfc7597>>.
- [RFC7598] Mrugalski, T., Troan, O., Farrer, I., Perreault, S., Dec, W., Bao, C., Yeh, L., and X. Deng, "DHCPv6 Options for Configuration of Software Address and Port-Mapped Clients", [RFC 7598](#), DOI 10.17487/RFC7598, July 2015, <<https://www.rfc-editor.org/info/rfc7598>>.
- [RFC7599] Li, X., Bao, C., Dec, W., Ed., Troan, O., Matsushima, S., and T. Murakami, "Mapping of Address and Port using Translation (MAP-T)", [RFC 7599](#), DOI 10.17487/RFC7599, July 2015, <<https://www.rfc-editor.org/info/rfc7599>>.

- [RFC7950] Bjorklund, M., Ed., "The YANG 1.1 Data Modeling Language", [RFC 7950](#), DOI 10.17487/RFC7950, August 2016, <<https://www.rfc-editor.org/info/rfc7950>>.
- [RFC8040] Bierman, A., Bjorklund, M., and K. Watsen, "RESTCONF Protocol", [RFC 8040](#), DOI 10.17487/RFC8040, January 2017, <<https://www.rfc-editor.org/info/rfc8040>>.
- [RFC8341] Bierman, A. and M. Bjorklund, "Network Configuration Access Control Model", STD 91, [RFC 8341](#), DOI 10.17487/RFC8341, March 2018, <<https://www.rfc-editor.org/info/rfc8341>>.
- [RFC8343] Bjorklund, M., "A YANG Data Model for Interface Management", [RFC 8343](#), DOI 10.17487/RFC8343, March 2018, <<https://www.rfc-editor.org/info/rfc8343>>.
- [RFC8446] Rescorla, E., "The Transport Layer Security (TLS) Protocol Version 1.3", [RFC 8446](#), DOI 10.17487/RFC8446, August 2018, <<https://www.rfc-editor.org/info/rfc8446>>.
- [TUNNELTYPE-IANA-REGISTRY]
Internet Assigned Numbers Authority, "tunnelType Definitions", <<https://www.iana.org/assignments/smi-numbers/smi-numbers.xhtml#smi-numbers-6>>.

13.2. Informative References

- [I-D.ietf-opsawg-nat-yang]
Boucadair, M., Sivakumar, S., Jacquenet, C., Vinapamula, S., and Q. Wu, "A YANG Module for Network Address Translation (NAT) and Network Prefix Translation (NPT)", [draft-ietf-opsawg-nat-yang-17](#) (work in progress), September 2018.
- [I-D.ietf-softwire-dslite-yang]
Boucadair, M., Jacquenet, C., and S. Sivakumar, "A YANG Data Model for Dual-Stack Lite (DS-Lite)", [draft-ietf-softwire-dslite-yang-17](#) (work in progress), May 2018.
- [RFC4213] Nordmark, E. and R. Gilligan, "Basic Transition Mechanisms for IPv6 Hosts and Routers", [RFC 4213](#), DOI 10.17487/RFC4213, October 2005, <<https://www.rfc-editor.org/info/rfc4213>>.

- [RFC6333] Durand, A., Droms, R., Woodyatt, J., and Y. Lee, "Dual-Stack Lite Broadband Deployments Following IPv4 Exhaustion", [RFC 6333](#), DOI 10.17487/RFC6333, August 2011, <<https://www.rfc-editor.org/info/rfc6333>>.
- [RFC6346] Bush, R., Ed., "The Address plus Port (A+P) Approach to the IPv4 Address Shortage", [RFC 6346](#), DOI 10.17487/RFC6346, August 2011, <<https://www.rfc-editor.org/info/rfc6346>>.
- [RFC7422] Donley, C., Grundemann, C., Sarawat, V., Sundaresan, K., and O. Vautrin, "Deterministic Address Mapping to Reduce Logging in Carrier-Grade NAT Deployments", [RFC 7422](#), DOI 10.17487/RFC7422, December 2014, <<https://www.rfc-editor.org/info/rfc7422>>.
- [RFC8340] Bjorklund, M. and L. Berger, Ed., "YANG Tree Diagrams", [BCP 215](#), [RFC 8340](#), DOI 10.17487/RFC8340, March 2018, <<https://www.rfc-editor.org/info/rfc8340>>.
- [RFC8342] Bjorklund, M., Schoenwaelder, J., Shafer, P., Watsen, K., and R. Wilton, "Network Management Datastore Architecture (NMDA)", [RFC 8342](#), DOI 10.17487/RFC8342, March 2018, <<https://www.rfc-editor.org/info/rfc8342>>.
- [RFC8344] Bjorklund, M., "A YANG Data Model for IP Management", [RFC 8344](#), DOI 10.17487/RFC8344, March 2018, <<https://www.rfc-editor.org/info/rfc8344>>.
- [RFC8349] Lhotka, L., Lindem, A., and Y. Qu, "A YANG Data Model for Routing Management (NMDA Version)", [RFC 8349](#), DOI 10.17487/RFC8349, March 2018, <<https://www.rfc-editor.org/info/rfc8349>>.

[Appendix A](#). Configuration Examples

The following sections provide examples of how the software YANG modules can be used for configuring software elements.

[A.1](#). Configuration Example for a lw4o6 BR Binding-Table

The lwAFTR maintains an address binding table which contains the following 3-tuples:

- o IPv6 Address for a single lwB4
- o Public IPv4 Address

- o Restricted port-set

The entry has two functions: the IPv6 encapsulation of inbound IPv4 packets destined to the lwB4 and the validation of outbound IPv4-in-IPv6 packets received from the lwB4 for de-capsulation.

Consider an example for the following lw4o6 binding table entry:

lwB4 Binding IPv6 Address: 2001:db8::1

lwB4 Binding IPv4 Address: 192.0.2.1

lwB4 PSID: 0x34

lwB4 PSID Length 8

BR IPv6 Address: 2001:db8:1::2

```
<br-instances>
  <binding>
    <bind-instance>
      <name>mybinding-instance</name>
      <binding-table>
        <binding-entry>
          <binding-ipv6info>2001:db8::1</binding-ipv6info>
          <binding-ipv4-addr>192.0.2.1</binding-ipv4-addr>
          <port-set>
            <psid>52</psid>
            <psid-len>8</psid-len>
          </port-set>
          <br-ipv6-addr>2001:db8:1::2</br-ipv6-addr>
        </binding-entry>
      </binding-table>
      <software-num-max>1024</software-num-max>
      <software-path-mru>1540</software-path-mru>
      <software-payload-mtu>1500</software-payload-mtu>
    </bind-instance>
  </binding>
</br-instances>
```

Figure 3: lw4o6 Binding-Table Configuration XML

A.2. Configuration Example for a MAP-E BR

A MAP-E BR is configured with forward mapping rules for the CEs it is serving. In this example (taken from [\[RFC7597\]](#), [Appendix A](#), Example 2), the following parameters are required:

- o Rule IPv6 Prefix
- o Rule IPv4 Prefix
- o Rule EA-bit bit length
- o IPv6 Address of MAP-BR

The mapping rule has two functions: identifying the destination CE IPv6 address for encapsulating inbound IPv4 packets and the validation of outbound IPv4-in-IPv6 packets received from the CE for de-capsulation.

The transport type for the data plane also needs to be configured for encapsulation to enable MAP-E and forwarding needs to be enabled.

Consider an example for the following MAP-E Forwarding Mapping Rule:

Data plane: encapsulation

Rule IPv6 Prefix: 2001:db8::/40

Rule IPv4 Prefix: 192.0.2.0/24

Rule EA-bit Length: 16

BR IPv6 Address: 2001:db8:ffff::1

Figure 4 provides the example MAP-E BR configuration xml.


```

<br-instances>
  <algorithm>
    <algo-instance>
      <name>myalgo-instance</name>
      <encapsulation>
        <br-ipv6-addr>2001:db8:ffff::1</br-ipv6-addr>
      </encapsulation>
      <ea-len>16</ea-len>
      <rule-ipv4-prefix>192.0.2.0/24</rule-ipv4-prefix>
      <rule-ipv6-prefix>2001:db8::/40</rule-ipv6-prefix>
      <forwarding>true</forwarding>
      <port-set>
        <psid-offset>6</psid-offset>
        <psid-len>8</psid-len>
      </port-set>
    </algo-instance>
  </algorithm>
</br-instances>

```

Figure 4: MAP-E FMR Configuration XML

[A.3.](#) lw4o6 CE Configuration Example

This section provides XML examples for configuring a lw4o6 CE. Examples for routing and NAT44 are also provided for convenience.

Consider an example for the following lw4o6 CE configuration:

```

lwB4 Binding IPv6 Address:  2001:db8::1

lwB4 Binding IPv4 Address:  192.0.2.1

lwB4 PSID:                  0x34

lwB4 PSID Length            8

BR IPv6 Address:            2001:db8:1::2

```



```
<config xmlns="urn:ietf:params:xml:ns:netconf:base:1.0">
  <interfaces xmlns="urn:ietf:params:xml:ns:yang:ietf-interfaces">
    <interface>
      <name>lw4o6-wan</name>
      <type>iana-tunnel-type:aplus</type>
      <br-ipv6-addr
        xmlns="urn:ietf:params:xml:ns:yang:ietf-softwire-ce">
        2001:db8:1::2
      </br-ipv6-addr>
      <binding-ipv6info
        xmlns="urn:ietf:params:xml:ns:yang:ietf-softwire-ce">
        2001:db8::1
      </binding-ipv6info>
    </interface>
  </interfaces>
</config>
```

Figure 5: lw4o6 CE Configuration XML

In the example depicted in Figure 5, the interface name is defined for the softwire tunnel. This name is then referenced by the routing configuration for the IPv4 route. Figure 6 provides an example configuration for the CE's IPv4 routing, using the YANG module described in [[RFC8349](#)].


```
<config xmlns="urn:ietf:params:xml:ns:netconf:base:1.0">
  <routing xmlns="urn:ietf:params:xml:ns:yang:ietf-routing">
    <control-plane-protocols>
      <control-plane-protocol>
        <type>static</type>
        <name>v4</name>
        <static-routes>
          <ipv4
            xmlns="urn:ietf:params:xml:ns:yang:ietf-ipv4-unicast-routing">
            <route>
              <destination-prefix>0.0.0.0/0</destination-prefix>
              <next-hop>
                <outgoing-interface>lw4o6-wan</outgoing-interface>
              </next-hop>
            </route>
          </ipv4>
        </static-routes>
      </control-plane-protocol>
    </control-plane-protocols>
  </routing>
</config>
```

Figure 6: lw4o6 CE Routing Configuration XML

Figure 7 provides an example configuration for the CE's NAT44 function, using the YANG module described in [\[I-D.ietf-opsawg-nat-yang\]](#).

```
<config xmlns="urn:ietf:params:xml:ns:netconf:base:1.0">
  <nat xmlns="urn:ietf:params:xml:ns:yang:ietf-nat">
    <instances>
      <instance>
        <id>1</id>
        <policy>
          <policy-id>1</policy-id>
          <external-ip-address-pool>
            <pool-id>1</pool-id>
            <external-ip-pool>192.0.2.1</external-ip-pool>
          </external-ip-address-pool>
          <port-set-restrict>
            <port-set-algo>
              <psid-offset>6</psid-offset>
              <psid-len>8</psid-len>
              <psid>52</psid>
            </port-set-algo>
          </port-set-restrict>
          <notify-pool-usage>
            <pool-id>1</pool-id>
```



```
    <high-threshold>80</high-threshold>
  </notify-pool-usage>
</policy>
<mapping-limits>
  <limit-per-protocol>
    <protocol-id>1</protocol-id>
    <limit>8</limit>
  </limit-per-protocol>
  <limit-per-protocol>
    <protocol-id>6</protocol-id>
    <limit>32</limit>
  </limit-per-protocol>
  <limit-per-protocol>
    <protocol-id>17</protocol-id>
    <limit>16</limit>
  </limit-per-protocol>
</mapping-limits>
<mapping-table>
  <mapping-entry>
    <index>1</index>
    <external-src-address>192.0.2.1/32</external-src-address>
    <internal-src-address>192.168.1.0/24</internal-src-address>
    <transport-protocol>6</transport-protocol>
  </mapping-entry>
  <mapping-entry>
    <index>2</index>
    <external-src-address>192.0.2.1/32</external-src-address>
    <internal-src-address>192.168.1.0/24</internal-src-address>
    <transport-protocol>17</transport-protocol>
  </mapping-entry>
  <mapping-entry>
    <index>3</index>
    <external-src-address>192.0.2.1/32</external-src-address>
    <internal-src-address>192.168.1.0/24</internal-src-address>
    <transport-protocol>1</transport-protocol>
  </mapping-entry>
</mapping-table>
</instance>
</instances>
</nat>
</config>
```

Figure 7: lw4o6 NAT Configuration XML

Authors' Addresses

Yong Cui
Tsinghua University
Beijing 100084
P.R. China

Phone: +86-10-6260-3059
Email: cuiyong@tsinghua.edu.cn

Ian Farrer (editor)
Deutsche Telekom AG
CTO-ATI, Landgrabenweg 151
Bonn, NRW 53227
Germany

Email: ian.farrer@telekom.de

Mohamed Boucadair (editor)
Orange
Rennes 35000
France

Email: mohamed.boucadair@orange.com

Qi Sun
Tsinghua University
Beijing 100084
P.R. China

Phone: +86-10-6278-5822
Email: sunqi.ietf@gmail.com

Linhui Sun
Tsinghua University
Beijing 100084
P.R. China

Phone: +86-10-6278-5822
Email: lh.sunlinh@gmail.com

Sladjana Zechlin
Deutsche Telekom AG
Landgrabenweg 151
Bonn, NRW 53227
Germany

Email: sladjana.zechlin@telekom.de

Rajiv Asati
Cisco Systems, Inc.
7025 Kit Creek Rd.
RTP, NC 27709
USA

Email: Rajiva@cisco.com

