

INTERNET-DRAFT
STORM Working Group
Intended status: Proposed Standard
Expires: January 2012
Obsoletes: [4544](#)

Mark Bakke
Cisco Systems
Prakash Venkatesen
HCL Technologies
July 4, 2011

**Definitions of Managed Objects for Internet Small Computer System
Interface (iSCSI)
draft-ietf-storm-iscsimib-00.txt**

Status of this Memo

This Internet-Draft is submitted to IETF in full conformance with the provisions of [BCP 78](#) and [BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF), its areas, and its working groups. Note that other groups may also distribute working documents as Internet-Drafts.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

The list of current Internet-Drafts can be accessed at <http://www.ietf.org/ietf/1id-abstracts.txt>

The list of Internet-Draft Shadow Directories can be accessed at <http://www.ietf.org/shadow.html>

This Internet-Draft will expire on January 4, 2012.

Copyright Notice

Copyright (c) 2011 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to [BCP 78](#) and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must include Simplified BSD License text as described in [Section 4.e](#) of

the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

This document may contain material from IETF Documents or IETF Contributions published or made publicly available before November 10, 2008. The person(s) controlling the copyright in some of this material may not have granted the IETF Trust the right to allow modifications of such material outside the IETF Standards Process. Without obtaining an adequate license from the person(s) controlling the copyright in such materials, this document may not be modified outside the IETF Standards Process, and derivative works of it may not be created outside the IETF Standards Process, except to format it for publication as an RFC or to translate it into languages other than English.

Abstract

This document defines a portion of the Management Information Base (MIB) for use with network management protocols. In particular, it defines objects for managing a client using the Internet Small Computer System Interface (iSCSI) protocol (SCSI over TCP).

This document obsoletes [RFC4544](#).

Table of Contents

1. The Internet-Standard Management Framework.....	3
2. Introduction.....	3
3. Relationship to Other MIB Modules.....	3
4. Relationship to SNMP Contexts.....	4
5. Differences from RFC 4544.....	4
6. Discussion.....	5
6.1. iSCSI MIB Object Model.....	5
6.2. iSCSI MIB Table Structure.....	6
6.3. iscsiInstance.....	7
6.4. iscsiPortal.....	8
6.5. iscsiTargetPortal.....	9
6.6. iscsiInitiatorPortal.....	9
6.7. iscsiNode.....	10
6.8. iscsiTarget.....	10
6.9. iscsiTgtAuthorization.....	11
6.10. iscsiInitiator.....	11
6.11. iscsiIntrAuthorization.....	11
6.12. iscsiSession.....	11
6.13. iscsiConnection.....	12
6.14. IP Addresses and TCP Port Numbers.....	12

6.15. Descriptors: Using OIDs in Place of Enumerated Types....	13
6.16. Notifications.....	13
7. MIB Definition.....	14
8. Security Considerations.....	82
9. IANA Considerations.....	83
10. References.....	83
10.1. Normative References.....	83
10.2. Informative References.....	84
11. Acknowledgments.....	84

[1. The Internet-Standard Management Framework](#)

For a detailed overview of the documents that describe the current Internet-Standard Management Framework, please refer to [section 7 of RFC 3410](#) [[RFC3410](#)].

Managed objects are accessed via a virtual information store, termed the Management Information Base or MIB. MIB objects are generally accessed through the Simple Network Management Protocol (SNMP). Objects in the MIB are defined using the mechanisms defined in the Structure of Management Information (SMI). This memo specifies a MIB module that is compliant to the SMIV2, which is described in STD 58, [RFC 2578](#) [[RFC2578](#)], STD 58, [RFC 2579](#) [[RFC2579](#)] and STD 58, [RFC 2580](#) [[RFC2580](#)].

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "NOT RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [[RFC2119](#)].

[2. Introduction](#)

This document defines a MIB module for iSCSI [[RFC3720](#)], used to manage devices that implement the iSCSI protocol. It obsoletes [RFC 4544](#) [[RFC4544](#)].

[3. Relationship to Other MIB Modules](#)

The iSCSI MIB module is normally layered between the SCSI MIB module [[RFC4455](#)] and the TCP MIB module [[RFC4022](#)], and makes use of the IP Storage (IPS) Identity Authentication MIB module [[RFC4545](#)]. Here is how these modules are related:

SCSI MIB Within systems where a SCSI layer is present, each iscsiNode, whether it has an initiator role, target role, or both, is related to one SCSI device within the SCSI MIB module. In this case, the iscsiNodeTransportType attribute points to the SCSI transport object within the SCSI MIB

module, which in turn contains an attribute that points back to the `iscsiNode`. In this way, a management station can navigate between the two MIB modules. In systems where a SCSI layer is not present, such as within an iSCSI proxy device, the `iscsiNodeTransportType` attribute points to the appropriate corresponding object within the appropriate MIB, or is left blank.

- TCP MIB Each iSCSI connection is related to one transport-level connection. Currently, iSCSI uses only TCP; the iSCSI connection is related to a TCP connection using its normal (protocol, source address, source port, destination address, destination port) 5-tuple.
- AUTH MIB Each iSCSI node that serves a target role can have a list of authorized initiators. Each of the entries in this list points to an identity within the IPS Identity Authentication MIB module that will be allowed to access the target. iSCSI nodes that serve in an initiator role can also have a list of authorized targets. Each of the entries in this list points to an identity within the Auth MIB module to which the initiator should attempt to establish sessions. The Auth MIB module includes information used to identify initiators and targets by their iSCSI name, IP address, and/or credentials.

This MIB module imports objects from RFCs 2578 [[RFC2578](#)], 2579 [[RFC2579](#)], 2580 [[RFC2580](#)], and 3411 [[RFC3411](#)]. It also imports textual conventions from the INET-ADDRESS-MIB [[RFC4001](#)].

4. Relationship to SNMP Contexts

Each non-scalar object in the iSCSI MIB module is indexed first by an iSCSI Instance. Each instance is a collection of nodes, portals, sessions, etc., that can define a physical or virtual partitioning of an iSCSI-capable device. The use of an instance works well with partitionable or hierarchical storage devices and fits in logically with other management schemes. Instances do not replace SNMP contexts, however they do provide a very simple way to assign a virtual or physical partition of a device to one or more SNMP contexts, without having to do so for each individual node, portal, and session row.

5. Differences from [RFC 4544](#)

[iSCSI-CONS] updates several RFCs, including [[RFC3720](#)]. This document updates the iSCSI MIB correspondingly. It obsoletes [[RFC4544](#)]. Below is a brief description of the changes:

- . Added `iscsiInstXNodeArchitecture` to `InstanceAttributes`
- . Added `iscsiSsnTaskReporting` of type BITS to `SessionAttributes`
- . Added `iscsiSsnProtocolLevel` to `SessionAttributes`
- . Deprecated the marker objects
- . Changed the conformance statements to match the above
- . Fixed the errata to [\[RFC4544\]](#)

6. Discussion

This MIB module structure supplies configuration, fault, and statistics information for iSCSI devices [\[RFC3720\]](#). It is structured around the well-known iSCSI objects, such as targets, initiators, sessions, connections, and the like.

This MIB module may also be used to configure access to iSCSI targets, by creating iSCSI Portals and authorization list entries.

It is worthwhile to note that this is an iSCSI MIB module and as such reflects only iSCSI objects. This module does not contain information about the SCSI-layer attributes of a device. If a SCSI layer is present, the SCSI MIB module [\[RFC4455\]](#) may be used to manage SCSI information for a device.

The iSCSI MIB module consists of several "objects", each of which is represented by one or more tables. This section contains a brief description of the "object" hierarchy and a description of each object, followed by a discussion of the actual table structure within the objects.

6.1. iSCSI MIB Object Model

The top-level object in this structure is the iSCSI instance, which "contains" all of the other objects.

`iscsiInstance`

-- A distinct iSCSI entity within the managed system.

`iscsiPortal`

-- An IP address used by this instance

`iscsiTargetPortal`

-- Contains portal information relevant when the portal

-- is used to listen for connections to its targets.

`iscsiInitiatorPortal`

-- Contains portal information relevant when the portal

-- is used to initiate connections to other targets.

`iscsiNode`

-- An iSCSI node can act as an initiator, a target, or both.

-- Contains generic (non-role-specific) information.


```
iscsiTarget
-- Target-specific iSCSI node information.
iscsiTgtAuth
-- A list of initiator identities that are allowed
-- access to this target.
iscsiInitiator
-- Initiator-specific iSCSI node information.
iscsiIntrAuth
-- A list of target identities to which this initiator
-- is configured to establish sessions.
iscsiSession
-- An active iSCSI session between an initiator and target.
-- The session's direction may be Inbound (outside
-- initiator to our target) or Outbound (our initiator to
-- an outside target).
iscsiConnection
-- An active TCP connection within an iSCSI session.
```

An iSCSI node can be an initiator, a target, or both. The iSCSI node's portals may be used to initiate connections (initiator) or listen for connections (target), depending on whether the iSCSI node is acting as an initiator or target. The iSCSI MIB module assumes that any target may be accessed via any portal that can take on a target role, although other access controls not reflected in the module might limit this.

6.2. iSCSI MIB Table Structure

Each iSCSI object exports one or more tables: an attributes table, and zero or more statistics tables, which augment the attributes table. Since iSCSI is an evolving standard, it is much cleaner to provide statistics and attributes as separate tables, allowing attributes and statistics to be added independently. In a few cases, there are multiple categories of statistics that will likely grow; in this case, an object will contain multiple statistics tables.

```
iscsiObjects
  iscsiDescriptors
  iscsiInstance
    iscsiInstanceAttributesTable
    iscsiInstanceSsnErrorStatsTable
    -- Counts abnormal session terminations
  iscsiPortal
    iscsiPortalAttributesTable
  iscsiTargetPortal
    iscsiTgtPortalAttributesTable
  iscsiInitiatorPortal
    iscsiIntrPortalAttributesTable
```

iscsiNode

Bakke, et al.

Expires January 4, 2012

[Page 6]

```
    iscsiNodeAttributesTable
iscsiTarget
    iscsiTargetAttributesTable
    iscsiTargetLoginStatsTable
        -- Counts successful and unsuccessful logins
    iscsiTargetLogoutStatsTable
        -- Counts normal and abnormal logouts
iscsiTgtAuthorization
    iscsiTgtAuthAttributesTable
iscsiInitiator
    iscsiInitiatorAttributesTable
    iscsiInitiatorLoginStatsTable
        -- Counts successful and unsuccessful logins
    iscsiInitiatorLogoutStatsTable
        -- Counts normal and abnormal logouts
iscsiIntrAuthorization
    iscsiIntrAuthAttributesTable
iscsiSession
    iscsiSessionAttributesTable
    iscsiSessionStatsTable
        -- Performance-related counts (requests, responses, bytes)
    iscsiSessionCxnErrorStatsTable
        -- Counts digest errors, connection errors, etc.
iscsiConnection
    iscsiConnectionAttributesTable
```

Note that this module does not attempt to count everything that could be counted; it is designed to include only those counters that would be useful for identifying performance, security, and fault problems from a management station.

6.3. iscsiInstance

The `iscsiInstanceAttributesTable` is the primary table of the iSCSI MIB module. Every table entry in this module is "owned" by exactly one iSCSI instance; all other table entries in the module include this table's index as their primary index.

Most implementations will include just one iSCSI instance row in this table. However, this table exists to allow for multiple virtual instances. For example, many IP routing products now allow multiple virtual routers. The iSCSI MIB module has the same premise; a large system could be "partitioned" into multiple, distinct virtual systems.

This also allows a single SNMP agent to proxy for multiple subsystems, perhaps a set of stackable devices, each of which has one or even more instances.

The instance attributes include the iSCSI vendor and version, as well as information on the last target or initiator at the other end of a session that caused a session failure.

The `iscsiInstanceSsnErrorStatsTable` augments the attributes table and provides statistics on session failures due to digest, connection, or iSCSI format errors.

6.4. `iscsiPortal`

The `iscsiPortalAttributesTable` lists iSCSI portals that can be used to listen for connections to targets, to initiate connections to other targets, or to do both.

Each row in the table includes an IP address (either v4 or v6), and a transport protocol (currently only TCP is defined). Each portal may have additional attributes, depending on whether it is an initiator portal, a target portal, or both. Initiator portals also have portal tags; these are placed in corresponding rows in the `iscsiIntrPortalAttributesTable`. Target portals have both portal tags and ports (e.g., TCP listen ports if the transport protocol is TCP); these are placed in rows in the `iscsiTgtPortalAttributesTable`.

Portal rows, along with their initiator and target portal counterparts, may be created and destroyed through this MIB module by a management station. Rows in the initiator and target portal tables are created and destroyed automatically by the agent, whenever a row is created or destroyed in the `iscsiPortalAttributesTable`, or if the value of `iscsiPortalRoles` changes. Attributes in these tables may then be modified by the management station if the agent implementation allows.

When created by a management station, the `iscsiPortalRoles` attribute is used to control row creation in the initiator and target portal tables. Creating a row with the `targetTypePortal` bit set in `iscsiPortalRoles` will cause the implementation to start listening for iSCSI connections on the portal. Creating a row with the `initiatorTypePortal` bit set in `iscsiPortalRoles` will not necessarily cause connections to be established; it is left to the implementation whether and when to make use of the portal. Both bits may be set if the portal is to be used by both initiator and target nodes.

When deleting a row in the `iscsiPortalAttributesTable`, all connections associated with that row are terminated. The implementation may either terminate the connection immediately or request a clean shutdown as specified in [\[RFC3720\]](#). An outbound connection (when an `iscsiInitiatorPortal` is deleted) matches the portal if its `iscsiCxnLocalAddr` matches the `iscsiPortalAddr`. An inbound connection

(when an `iscsiTargetPortal` is deleted) matches the portal if its

`iscsiCxnLocalAddr` matches the `iscsiPortalAddr`, and its `iscsiCxnLocalPort` matches the `iscsiTargetPortalPort`.

Individual objects within a row in this table may not be modified while the row is active. For instance, changing the IP address of a portal requires that the rows associated with the old IP address be deleted, and new rows be created (in either order).

6.5. `iscsiTargetPortal`

The `iscsiTgtPortalAttributesTable` contains target-specific attributes for iSCSI portals. Rows in this table use the same indices as their corresponding rows in the `iscsiPortalAttributesTable`, with the addition of `iscsiNodeIndex`.

Rows in this table are created when the `targetTypePortal` bit is set in the `iscsiPortalRoles` attribute of the corresponding `iscsiPortalAttributesEntry`; they are destroyed when this bit is cleared.

This table contains the TCP (or other protocol) port on which the socket is listening for incoming connections. It also includes a portal group aggregation tag; iSCSI target portals within this instance sharing the same tag can contain connections within the same session.

This table will be empty for iSCSI instances that contain only initiators (such as iSCSI host driver implementations).

Many implementations use the same target portal tag and protocol port for all nodes accessed via a portal. These implementations will create a single row in the `iscsiTgtPortalAttributeTable`, with an `iscsiNodeIndex` of zero.

Other implementations do not use the same tag and/or port for all nodes; these implementations will create a row in this table for each (portal, node) tuple, using `iscsiNodeIndex` to designate the node for this portal tag and port.

6.6. `iscsiInitiatorPortal`

The `iscsiIntrPortalAttributesTable` contains initiator-specific objects for iSCSI portals. Rows in this table use the same indices as their corresponding entries in the `iscsiPortalAttributesTable`. A row in this table is created when the `initiatorTypePortal` bit is set in the `iscsiPortalRoles` attribute; it is destroyed when this bit is cleared.

Each row in this table contains a portal group aggregation tag,

indicating which portals an initiator may use together within a multiple-connection session.

This table will be empty for iSCSI instances that contain only targets (such as most iSCSI devices).

Many implementations use the same initiator tag for all nodes accessing targets via a given portal. These implementations will create a single row in `iscsiIntrPortalAttributeTable`, with an `iscsiNodeIndex` of zero.

Other implementations do not use the same tag and/or port for all nodes; these implementations will create a row in this table for each (portal, node) tuple, using `iscsiNodeIndex` to designate the node for this portal tag and port.

6.7. iscsiNode

The `iscsiNodeAttributesTable` contains a list of iSCSI nodes, each of which may have an initiator role, a target role, or both.

This table contains the node's attributes that are common to both roles, such as its iSCSI name and alias string. Attributes specific to initiators or targets are available in the `iscsiTarget` and `iscsiInitiator` objects. Each row in this table that can fulfill a target role has a corresponding row in the `iscsiTarget` table; each entry that fulfills an initiator role has a row in the `iscsiInitiator` table. Nodes such as copy managers that can take on both roles have a corresponding row in each table.

This table also contains the login negotiations preferences for this node. These objects indicate the values this node will offer or prefer in the operational negotiation phase of the login process.

For most implementations, each entry in the table also contains a `RowPointer` to the transport table entry in the SCSI MIB module that this iSCSI node represents. For implementations without a standard SCSI layer above iSCSI, such as an iSCSI proxy or gateway, this `RowPointer` can point to a row in an implementation-specific table that this iSCSI node represents.

6.8. iscsiTarget

The `iscsiTargetAttributesTable` contains target-specific attributes for iSCSI nodes. Each entry in this table uses the same index values as its corresponding `iscsiNode` entry.

This table contains attributes used to indicate the last failure that was (or should have been) sent as a notification.

This table is augmented by the `iscsiTargetLoginStatsTable` and the `iscsiTargetLogoutStatsTable`, which count the numbers of normal and abnormal logins and logouts to this target.

6.9. iscsiTgtAuthorization

The `iscsiTgtAuthAttributesTable` contains an entry for each initiator identifier that will be allowed to access the target under which it appears. Each entry contains a `RowPointer` to a user identity in the IPS Authorization MIB module, which contains the name, address, and credential information necessary to authenticate the initiator.

6.10. iscsiInitiator

The `iscsiInitiatorAttributesTable` contains a list of initiator-specific attributes for iSCSI nodes. Each entry in this table uses the same index values as its corresponding `iscsiNode` entry.

Most implementations will include a single entry in this table, regardless of the number of physical interfaces the initiator may use.

This table is augmented by the `iscsiInitiatorLoginStatsTable` and the `iscsiInitiatorLogoutStatsTable`, which count the numbers of normal and abnormal logins and logouts from this initiator.

6.11. iscsiIntrAuthorization

The `iscsiIntrAuthAttributesTable` contains an entry for each target identifier to which the initiator is configured to establish a session.

Each entry contains a `RowPointer` to a user identity in the IPS Authorization MIB module, which contains the name, address, and credential information necessary to identify (for discovery purposes) and authenticate the target.

6.12. iscsiSession

The `iscsiSessionAttributesTable` contains a set of rows that list the sessions known to be existing locally for each node in each iSCSI instance.

The session type for each session indicates whether the session is used for normal SCSI commands or for discovery using the `SendTargets` text command. Discovery sessions that do not belong to any particular node have a node index attribute of zero.

The session direction for each session indicates whether it is an Inbound session or an Outbound session. Inbound sessions are from some other initiator to the target node under which the session appears. Outbound sessions are from the initiator node under which the session appears to a target outside this iSCSI instance.

Many attributes may be negotiated when starting an iSCSI session. Most of these attributes are included in the session object.

Some attributes, such as the integrity and authentication schemes, have some standard values that can be extended by vendors to include their own schemes. These contain an object identifier, rather than the expected enumerated type, to allow these values to be extended by other MIB modules, such as an enterprise MIB module.

The `iscsiSessionStatsTable` includes statistics related to performance; it counts iSCSI data bytes and PDUs.

For implementations that support error recovery without terminating a session, the `iscsiSessionCxnErrorStatsTable` contains counters for the numbers of digest and connection errors that have occurred within the session.

6.13. `iscsiConnection`

The `iscsiConnectionAttributesTable` contains a list of active connections within each session. It contains the IP addresses and TCP (or other protocol) ports of both the local and remote sides of the connection. These may be used to locate other connection-related information and statistics in the TCP MIB module [[RFC4022](#)].

The attributes table also contains a connection state. This state is not meant to directly map to the state tables included within the iSCSI specification; they are meant to be simplified, higher-level definitions of connection state that provide information more useful to a user or network manager.

No statistics are kept for connections.

6.14. IP Addresses and TCP Port Numbers

The IP addresses in this module are represented by two attributes, one of type `InetAddressType`, and the other of type `InetAddress`. These are taken from [[RFC4001](#)], which specifies how to support addresses that may be either IPv4 or IPv6.

The TCP port numbers that appear in a few of the structures are described as simply port numbers, with a protocol attribute indicating whether they are TCP ports or something else. This will

allow the module to be compatible with iSCSI over transports other than TCP in the future.

6.15. Descriptors: Using OIDs in Place of Enumerated Types

The iSCSI MIB module has a few attributes, namely, the digest method attributes, where an enumerated type would work well, except that an implementation may need to extend the attribute and add types of its own. To make this work, this MIB module defines a set of object identities within the `iscsiDescriptors` subtree. Each of these object identities is basically an enumerated type.

Attributes that make use of these object identities have a value that is an Object Identifier (OID) instead of an enumerated type. These OIDs can indicate either the object identities defined in this module or object identities defined elsewhere, such as in an enterprise MIB module. Those implementations that add their own digest methods should also define a corresponding object identity for each of these methods within their own enterprise MIB module, and return its OID whenever one of these attributes is using that method.

6.16. Notifications

Three notifications are provided. One is sent by an initiator detecting a critical login failure, another is sent by a target detecting a critical login failure, and the third is sent upon a session being terminated due to an abnormal connection or digest failure. Critical failures are defined as those that may expose security-related problems that may require immediate action, such as failures due to authentication, authorization, or negotiation problems. Attributes in the initiator, target, and instance objects provide the information necessary to send in the notification, such as the initiator or target name and IP address at the other end that may have caused the failure.

To avoid sending an excessive number of notifications due to multiple errors counted, an SNMP agent implementing the iSCSI MIB module SHOULD NOT send more than three iSCSI notifications in any 10-second period.

The 3-in-10 rule was chosen because one notification every three seconds was deemed often enough, but should two or three different notifications happen at the same time, it would not be desirable to suppress them. Three notifications in 10 seconds is a happy medium, where a short burst of notifications is allowed, without inundating the network and/or notification host with a large number of notifications.

7. MIB Definition

```
ISCSI-MIB DEFINITIONS ::= BEGIN

    IMPORTS
        MODULE-IDENTITY, OBJECT-TYPE, OBJECT-IDENTITY, NOTIFICATION-TYPE,
        Unsigned32, Counter32, Counter64, Gauge32,
        mib-2
        FROM SNMPv2-SMI

        TEXTUAL-CONVENTION, TruthValue, RowPointer, TimeStamp, RowStatus,
        AutonomousType, StorageType
        FROM SNMPv2-TC

        MODULE-COMPLIANCE, OBJECT-GROUP, NOTIFICATION-GROUP
        FROM SNMPv2-CONF

        SnmpAdminString
        FROM SNMP-FRAMEWORK-MIB -- RFC 3411

        InetAddressType, InetAddress, InetPortNumber
        FROM INET-ADDRESS-MIB -- RFC 4001
    ;

iscsiMibModule MODULE-IDENTITY
    LAST-UPDATED "201107040000Z" -- Jul 04, 2011
    ORGANIZATION "IETF STORage Maintenance (STORM) Working Group"
    CONTACT-INFO "
        Working Group Email : storm@ietf.org
        Attn: Mark Bakke
            Cisco Systems, Inc
            Email: mbakke@cisco.com

        Prakash Venkatesen
        HCL Technologies
        Email: prakashvn@hcl.com"

    DESCRIPTION
        "This module defines management information specific
        to the iSCSI protocol.

        Copyright (C) The IETF Trust (2011). This
        version of this MIB module is part of RFC xxxx;
        see the RFC itself for full legal notices."
-- RFC Editor: replace xxxx with actual RFC number & remove this note.
    REVISION      "201107040000Z"
    DESCRIPTION
        "Second version of the iSCSI Protocol MIB Module.
        [iSCSI-CONS] makes several updates to [RFC3720]. This
```



```
        version makes corresponding updates to the MIB module.
        This MIB module published as RFC xxxx."
-- RFC Editor: replace xxxx with actual RFC number & remove this note.
REVISION "200605220000Z"
DESCRIPTION
    "Initial version of the iSCSI Protocol MIB module.
    This MIB module published as RFC 4544."

 ::= { mib-2 142 }

iscsiNotifications OBJECT IDENTIFIER ::= { iscsiMibModule 0 }
iscsiObjects        OBJECT IDENTIFIER ::= { iscsiMibModule 1 }
iscsiConformance    OBJECT IDENTIFIER ::= { iscsiMibModule 2 }
iscsiAdmin           OBJECT IDENTIFIER ::= { iscsiMibModule 3 }

-- Textual Conventions

IscsiTransportProtocol ::= TEXTUAL-CONVENTION
    DISPLAY-HINT "d"
    STATUS      current
    DESCRIPTION
        "This data type is used to define the transport
        protocols that will carry iSCSI PDUs."
    REFERENCE
        "RFC791, RFC1700"

        The presently known, officially delegated numbers
        can be found at:
        http://www.iana.org/assignments/protocol-numbers"

    SYNTAX      Unsigned32 (0..255)

IscsiDigestMethod ::= TEXTUAL-CONVENTION
    STATUS      current
    DESCRIPTION
        "This data type represents the methods possible
        for digest negotiation.
        none      - a placeholder for a secondary digest method
                    that means only the primary method can be
                    used.
        other      - a digest method other than those defined below.
        noDigest   - does not support digests (will operate without
                    a digest (Note: implementations must support
                    digests to be compliant with the RFC3720).
        CRC32c     - require a CRC32C digest."
    REFERENCE
        "RFC 3720, Section 12.1, HeaderDigest and DataDigest"
    SYNTAX      INTEGER {
```

none(1),

Bakke, et al.

Expires January 4, 2012

[Page 15]

```

        other(2),
        noDigest(3),
        crc32c(4)
    }

```

IscsiName ::= TEXTUAL-CONVENTION

DISPLAY-HINT "223t"

STATUS current

DESCRIPTION

"This data type is used for objects whose value is an iSCSI name with the properties described in [RFC 3720 section 3.2.6.1](#), and encoded as specified in [RFC 3720 section 3.2.6.2](#). A zero-length string indicates the absence of an iSCSI name."

REFERENCE

"[RFC 3720, Section 3.2.6](#), iSCSI Names."

SYNTAX OCTET STRING (SIZE(0 | 16..223))

__*****

iscsiDescriptors OBJECT IDENTIFIER ::= { iscsiAdmin 1 }

iscsiHeaderIntegrityTypes OBJECT IDENTIFIER ::= { iscsiDescriptors 1 }

iscsiHdrIntegrityNone OBJECT-IDENTITY

STATUS current

DESCRIPTION

"The authoritative identifier when no integrity scheme for the header is being used."

REFERENCE

"[RFC 3720, Section 12.1](#), HeaderDigest and DataDigest"

::= { iscsiHeaderIntegrityTypes 1 }

iscsiHdrIntegrityCrc32c OBJECT-IDENTITY

STATUS current

DESCRIPTION

"The authoritative identifier when the integrity scheme for the header is CRC32c."

REFERENCE

"[RFC 3720, Section 12.1](#), HeaderDigest and DataDigest"

::= { iscsiHeaderIntegrityTypes 2 }

iscsiDataIntegrityTypes OBJECT IDENTIFIER ::= { iscsiDescriptors 2 }

iscsiDataIntegrityNone OBJECT-IDENTITY

STATUS current

DESCRIPTION

"The authoritative identifier when no integrity scheme for the data is being used."

REFERENCE

"[RFC 3720, Section 12.1](#), HeaderDigest and DataDigest"

::= { iscsiDataIntegrityTypes 1 }

iscsiDataIntegrityCrc32c OBJECT-IDENTITY

STATUS current

DESCRIPTION

"The authoritative identifier when the integrity scheme for the data is CRC32c."

REFERENCE

"[RFC 3720, Section 12.1](#), HeaderDigest and DataDigest"

::= { iscsiDataIntegrityTypes 2 }

-- *****

iscsiInstance OBJECT IDENTIFIER ::= { iscsiObjects 1 }

-- Instance Attributes Table

iscsiInstanceAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiInstanceAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of iSCSI instances present on the system."

::= { iscsiInstance 1 }

iscsiInstanceAttributesEntry OBJECT-TYPE

SYNTAX IscsiInstanceAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular iSCSI instance."

INDEX { iscsiInstIndex }

::= { iscsiInstanceAttributesTable 1 }

IscsiInstanceAttributesEntry ::= SEQUENCE {

iscsiInstIndex	Unsigned32,
iscsiInstDescr	SnmpAdminString,
iscsiInstVersionMin	Unsigned32,
iscsiInstVersionMax	Unsigned32,
iscsiInstVendorID	SnmpAdminString,
iscsiInstVendorVersion	SnmpAdminString,
iscsiInstPortalNumber	Unsigned32,
iscsiInstNodeNumber	Unsigned32,
iscsiInstSessionNumber	Unsigned32,
iscsiInstSsnFailures	Counter32,

iscsiInstLastSsnFailureType AutonomousType,

Bakke, et al.

Expires January 4, 2012

[Page 17]

```
    iscsiInstLastSsnRmtNodeName      IscsiName,  
    iscsiInstDiscontinuityTime       TimeStamp,  
    iscsiInstXNodeArchitecture       SnmpAdminString  
}
```

iscsiInstIndex OBJECT-TYPE

```
SYNTAX      Unsigned32 (1..4294967295)  
MAX-ACCESS  not-accessible  
STATUS      current
```

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular iSCSI instance. This index value must not be modified or reused by an agent unless a reboot has occurred. An agent should attempt to keep this value persistent across reboots."

```
::= { iscsiInstanceAttributesEntry 1 }
```

iscsiInstDescr OBJECT-TYPE

```
SYNTAX      SnmpAdminString  
MAX-ACCESS  read-only  
STATUS      current
```

DESCRIPTION

"A UTF-8 string, determined by the implementation to describe the iSCSI instance. When only a single instance is present, this object may be set to the zero-length string; with multiple iSCSI instances, it may be used in an implementation-dependent manner to describe the purpose of the respective instance."

```
::= { iscsiInstanceAttributesEntry 2 }
```

iscsiInstVersionMin OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..255)  
MAX-ACCESS  read-only  
STATUS      current
```

DESCRIPTION

"The minimum version number of the iSCSI specification such that this iSCSI instance supports this minimum value, the maximum value indicated by the corresponding instance in iscsiInstVersionMax, and all versions in between."

REFERENCE

"[RFC 3720, Section 10.12](#), Login Request"

```
::= { iscsiInstanceAttributesEntry 3 }
```

iscsiInstVersionMax OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..255)  
MAX-ACCESS  read-only  
STATUS      current
```

DESCRIPTION

Bakke, et al.

Expires January 4, 2012

[Page 18]

"The maximum version number of the iSCSI specification such that this iSCSI instance supports this maximum value, the minimum value indicated by the corresponding instance in iscsiInstVersionMin, and all versions in between."

REFERENCE

"[RFC 3720, Section 10.12](#), Login Request"

::= { iscsiInstanceAttributesEntry 4 }

iscsiInstVendorID OBJECT-TYPE

SYNTAX SnmpAdminString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A UTF-8 string describing the manufacturer of the implementation of this instance."

::= { iscsiInstanceAttributesEntry 5 }

iscsiInstVendorVersion OBJECT-TYPE

SYNTAX SnmpAdminString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A UTF-8 string set by the manufacturer describing the version of the implementation of this instance. The format of this string is determined solely by the manufacturer, and is for informational purposes only.

It is unrelated to the iSCSI specification version numbers."

::= { iscsiInstanceAttributesEntry 6 }

iscsiInstPortalNumber OBJECT-TYPE

SYNTAX Unsigned32

UNITS "transport endpoints"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of rows in the iscsiPortalAttributesTable that are currently associated with this iSCSI instance."

::= { iscsiInstanceAttributesEntry 7 }

iscsiInstNodeNumber OBJECT-TYPE

SYNTAX Unsigned32

UNITS "iSCSI nodes"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of rows in the iscsiNodeAttributesTable that are currently associated with this iSCSI instance."

```
::= { iscsiInstanceAttributesEntry 8 }
```

iscsiInstSessionNumber OBJECT-TYPE

SYNTAX Unsigned32

UNITS "sessions"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of rows in the iscsiSessionAttributesTable that are currently associated with this iSCSI instance."

::= { iscsiInstanceAttributesEntry 9 }

iscsiInstSsnFailures OBJECT-TYPE

SYNTAX Counter32

UNITS "sessions"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object counts the number of times a session belonging to this instance has failed. If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiInstDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 12.1](#), HeaderDigest and DataDigest"

::= { iscsiInstanceAttributesEntry 10 }

iscsiInstLastSsnFailureType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The counter object in the iscsiInstSsnErrorStatsTable that was incremented when the last session failure occurred."

If the reason for failure is not found in the iscsiInstSsnErrorStatsTable, the value { 0.0 } is used instead."

::= { iscsiInstanceAttributesEntry 11 }

iscsiInstLastSsnRmtNodeName OBJECT-TYPE

SYNTAX IscsiName

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The iSCSI name of the remote node from the failed session."

::= { iscsiInstanceAttributesEntry 12 }

iscsiInstDiscontinuityTime OBJECT-TYPE

SYNTAX

TimeStamp

Bakke, et al.

Expires January 4, 2012

[Page 20]

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of SysUpTime on the most recent occasion at which any one or more of this instance's counters suffered a discontinuity.

If no such discontinuities have occurred since the last re-initialization of the local management subsystem, then this object contains a zero value."

::= { iscsiInstanceAttributesEntry 13 }

iscsiInstXNodeArchitecture OBJECT-TYPE

SYNTAX SnmpAdminString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A UTF-8 string set by the manufacturer declaring the details of its iSCSI node architecture to the remote endpoint. These details may include, but are not limited to, iSCSI vendor software, firmware, or hardware versions, the OS version, or hardware architecture.

The format of this string is determined solely by the manufacturer, and is for informational purposes only.

It is unrelated to the iSCSI specification version numbers."

REFERENCE

"[[iSCSI-CONS](#)], Section 13.26, X#NodeArchitecture"

::= { iscsiInstanceAttributesEntry 14 }

-- Instance Session Failure Stats Table

iscsiInstanceSsnErrorStatsTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiInstanceSsnErrorStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"Statistics regarding the occurrences of error types that result in a session failure."

::= { iscsiInstance 2 }

iscsiInstanceSsnErrorStatsEntry OBJECT-TYPE

SYNTAX IscsiInstanceSsnErrorStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular iSCSI instance."

AUGMENTS { iscsiInstanceAttributesEntry }

::= { iscsiInstanceSsnErrorStatsTable 1 }

```
IscsiInstanceSsnErrorStatsEntry ::= SEQUENCE {  
    iscsiInstSsnDigestErrors      Counter32,  
    iscsiInstSsnCxnTimeoutErrors Counter32,  
    iscsiInstSsnFormatErrors      Counter32  
}
```

iscsiInstSsnDigestErrors OBJECT-TYPE

SYNTAX Counter32
UNITS "sessions"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The count of sessions that failed due to receipt of a PDU containing header or data digest errors. If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiInstDiscontinuityTime."

REFERENCE

["RFC 3720, Section 6.7, Digest Errors"](#)

```
::= { iscsiInstanceSsnErrorStatsEntry 1 }
```

iscsiInstSsnCxnTimeoutErrors OBJECT-TYPE

SYNTAX Counter32
UNITS "sessions"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The count of sessions that failed due to a sequence exceeding a time limit. If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiInstDiscontinuityTime."

REFERENCE

["RFC 3720, Section 6.4, Connection Timeout Management"](#)

```
::= { iscsiInstanceSsnErrorStatsEntry 2 }
```

iscsiInstSsnFormatErrors OBJECT-TYPE

SYNTAX Counter32
UNITS "sessions"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The count of sessions that failed due to receipt of a PDU that contained a format error. If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiInstDiscontinuityTime."

REFERENCE

["RFC 3720, Section 6.6, Format Errors"](#)

```
::= { iscsiInstanceSsnErrorStatsEntry 3 }
```


_ _*****

iscsiPortal OBJECT IDENTIFIER ::= { iscsiObjects 2 }

-- Portal Attributes Table

iscsiPortalAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of transport endpoints (using TCP or another transport protocol) used by this iSCSI instance. An iSCSI instance may use a portal to listen for incoming connections to its targets, to initiate connections to other targets, or both."

::= { iscsiPortal 1 }

iscsiPortalAttributesEntry OBJECT-TYPE

SYNTAX IscsiPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular portal instance."

INDEX { iscsiInstIndex, iscsiPortalIndex }

::= { iscsiPortalAttributesTable 1 }

IscsiPortalAttributesEntry ::= SEQUENCE {

iscsiPortalIndex	Unsigned32,
iscsiPortalRowStatus	RowStatus,
iscsiPortalRoles	BITS,
iscsiPortalAddrType	InetAddressType,
iscsiPortalAddr	InetAddress,
iscsiPortalProtocol	IscsiTransportProtocol,
iscsiPortalMaxRecvDataSegLength	Unsigned32,
iscsiPortalPrimaryHdrDigest	IscsiDigestMethod,
iscsiPortalPrimaryDataDigest	IscsiDigestMethod,
iscsiPortalSecondaryHdrDigest	IscsiDigestMethod,
iscsiPortalSecondaryDataDigest	IscsiDigestMethod,
iscsiPortalRecvMarker	TruthValue,
iscsiPortalStorageType	StorageType

}

iscsiPortalIndex OBJECT-TYPE

SYNTAX Unsigned32 (1..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular

transport endpoint within this iSCSI instance. This index value must not be modified or reused by an agent unless a reboot has occurred. An agent should attempt to keep this value persistent across reboots."

::= { iscsiPortalAttributesEntry 1 }

iscsiPortalRowStatus OBJECT-TYPE

SYNTAX RowStatus
MAX-ACCESS read-create
STATUS current

DESCRIPTION

"This field allows entries to be dynamically added and removed from this table via SNMP. When adding a row to this table, all non-Index/RowStatus objects must be set. When the value of this object is 'active', the values of the other objects in this table cannot be changed. Rows may be discarded using RowStatus.

Note that creating a row in this table will typically cause the agent to create one or more rows in iscsiTgtPortalAttributesTable and/or iscsiIntrPortalAttributesTable."

::= { iscsiPortalAttributesEntry 2 }

iscsiPortalRoles OBJECT-TYPE

SYNTAX BITS {
targetTypePortal(0),
initiatorTypePortal(1)
}
MAX-ACCESS read-create
STATUS current

DESCRIPTION

"A portal can operate in one or both of two roles: as a target portal and/or an initiator portal. If the portal will operate in both roles, both bits must be set.

This object will define a corresponding row that will exist or must be created in the iscsiTgtPortalAttributesTable, the iscsiIntrPortalAttributesTable or both. If the targetTypePortal bit is set, one or more corresponding iscsiTgtPortalAttributesEntry rows will be found or created. If the initiatorTypePortal bit is set, one or more corresponding iscsiIntrPortalAttributesEntry rows will be found or created. If both bits are set, one or more corresponding rows will be found or created in one of the above tables."

```
::= { iscsiPortalAttributesEntry 3 }
```

iscsiPortalAddrType OBJECT-TYPE

SYNTAX InetAddressType

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The type of Internet Network Address contained in the corresponding instance of the iscsiPortalAddr."

DEFVAL { ipv4 }

::= { iscsiPortalAttributesEntry 4 }

iscsiPortalAddr OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The portal's Internet Network Address, of the type specified by the object iscsiPortalAddrType. If iscsiPortalAddrType has the value 'dns', this address gets resolved to an IP address whenever a new iSCSI connection is established using this portal."

::= { iscsiPortalAttributesEntry 5 }

iscsiPortalProtocol OBJECT-TYPE

SYNTAX IscsiTransportProtocol

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The portal's transport protocol."

DEFVAL { 6 } -- TCP

::= { iscsiPortalAttributesEntry 6 }

iscsiPortalMaxRecvDataSegLength OBJECT-TYPE

SYNTAX Unsigned32 (512..16777215)

UNITS "bytes"

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"The maximum PDU length this portal can receive. This may be constrained by hardware characteristics and individual implementations may choose not to allow this object to be changed."

REFERENCE

"[RFC 3720, Section 12.12](#), MaxRecvDataSegmentLength"

DEFVAL { 8192 }

::= { iscsiPortalAttributesEntry 7 }

iscsiPortalPrimaryHdrDigest OBJECT-TYPE

SYNTAX

IscsiDigestMethod

Bakke, et al.

Expires January 4, 2012

[Page 25]

```
MAX-ACCESS      read-create
STATUS          current
DESCRIPTION
    "The preferred header digest for this portal."
DEFVAL          { crc32c }
::= { iscsiPortalAttributesEntry 8 }
```

```
iscsiPortalPrimaryDataDigest OBJECT-TYPE
    SYNTAX      IscsiDigestMethod
    MAX-ACCESS   read-create
    STATUS      current
    DESCRIPTION
        "The preferred data digest method for this portal."
    DEFVAL      { crc32c }
    ::= { iscsiPortalAttributesEntry 9 }
```

```
iscsiPortalSecondaryHdrDigest OBJECT-TYPE
    SYNTAX      IscsiDigestMethod
    MAX-ACCESS   read-create
    STATUS      current
    DESCRIPTION
        "An alternate header digest preference for this portal."
    DEFVAL      { noDigest }
    ::= { iscsiPortalAttributesEntry 10 }
```

```
iscsiPortalSecondaryDataDigest OBJECT-TYPE
    SYNTAX      IscsiDigestMethod
    MAX-ACCESS   read-create
    STATUS      current
    DESCRIPTION
        "An alternate data digest preference for this portal."
    DEFVAL      { noDigest }
    ::= { iscsiPortalAttributesEntry 11 }
```

```
iscsiPortalRecvMarker OBJECT-TYPE
    SYNTAX      TruthValue
    MAX-ACCESS   read-create
    STATUS      deprecated
    DESCRIPTION
        "This object indicates whether or not this portal will
        request markers in its incoming data stream."
    REFERENCE
        "[iSCSI-CONS], 13.25 Obsoleted Keys."
    DEFVAL      { false }
    ::= { iscsiPortalAttributesEntry 12 }
```

```
iscsiPortalStorageType OBJECT-TYPE
    SYNTAX      StorageType
```

MAX-ACCESS read-create

Bakke, et al.

Expires January 4, 2012

[Page 26]

STATUS current

DESCRIPTION

"The storage type for this row. Rows in this table that were created through an external process (e.g. not created via this MIB) may have a storage type of readOnly or permanent.

Conceptual rows having the value 'permanent' need not allow write access to any columnar objects in the row."

DEFVAL { nonVolatile }

::= { iscsiPortalAttributesEntry 13 }

_ _*****

iscsiTargetPortal OBJECT IDENTIFIER ::= { iscsiObjects 3 }

-- Target Portal Attributes Table

iscsiTgtPortalAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiTgtPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of transport endpoints (using TCP or another transport protocol) on which this iSCSI instance listens for incoming connections to its targets."

::= { iscsiTargetPortal 1 }

iscsiTgtPortalAttributesEntry OBJECT-TYPE

SYNTAX IscsiTgtPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular portal instance that is used to listen for incoming connections to local targets. One or more rows in this table is populated by the agent for each iscsiPortalAttributesEntry row that has the bit targetTypePortal set in its iscsiPortalRoles column."

INDEX { iscsiInstIndex, iscsiPortalIndex,
iscsiTgtPortalNodeIndexOrZero }

::= { iscsiTgtPortalAttributesTable 1 }

```
IscliTgtPortalAttributesEntry ::= SEQUENCE {
    iscsiTgtPortalNodeIndexOrZero  Unsigned32,
    iscsiTgtPortalPort              InetPortNumber,
    iscsiTgtPortalTag                Unsigned32
}
```

iscsiTgtPortalNodeIndexOrZero OBJECT-TYPE

SYNTAX

Unsigned32 (0..4294967295)

Bakke, et al.

Expires January 4, 2012

[Page 27]

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular node within an iSCSI instance present on the local system.

For implementations where each {portal, node} tuple can have a different portal tag, this value will map to the iscsiNodeIndex.

For implementations where the portal tag is the same for a given portal regardless of which node is using the portal, the value 0 (zero) is used."

::= { iscsiTgtPortalAttributesEntry 1 }

iscsiTgtPortalPort OBJECT-TYPE

SYNTAX InetPortNumber (1..65535)

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The portal's transport protocol port number on which the portal listens for incoming iSCSI connections when the portal is used as a target portal. This object's storage type is specified in iscsiPortalStorageType."

::= { iscsiTgtPortalAttributesEntry 2 }

iscsiTgtPortalTag OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The portal's aggregation tag when the portal is used as a target portal. Multiple-connection sessions may be aggregated over portals sharing an identical aggregation tag. This object's storage type is specified in iscsiPortalStorageType."

REFERENCE

"[RFC 3720, Section 3.4.1](#), iSCSI Architectural Model"

::= { iscsiTgtPortalAttributesEntry 3 }

-- *****

iscsiInitiatorPortal OBJECT IDENTIFIER ::= { iscsiObjects 4 }

-- Initiator Portal Attributes Table

iscsiIntrPortalAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiIntrPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of Internet Network Addresses (using TCP or another transport protocol) from which this iSCSI instance may initiate connections to other targets."

::= { iscsiInitiatorPortal 1 }

iscsiIntrPortalAttributesEntry OBJECT-TYPE

SYNTAX IscsiIntrPortalAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular portal instance that is used to initiate connections to iSCSI targets. One or more rows in this table is populated by the agent for each iscsiPortalAttributesEntry row that has the bit initiatorTypePortal set in its iscsiPortalRoles column."

INDEX { iscsiInstIndex, iscsiPortalIndex,
iscsiIntrPortalNodeIndexOrZero }

::= { iscsiIntrPortalAttributesTable 1 }

IscsiIntrPortalAttributesEntry ::= SEQUENCE {
iscsiIntrPortalNodeIndexOrZero Unsigned32,
iscsiIntrPortalTag Unsigned32
}

iscsiIntrPortalNodeIndexOrZero OBJECT-TYPE

SYNTAX Unsigned32 (0..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular node within an iSCSI instance present on the local system.

For implementations where each {portal, node} tuple can have a different portal tag, this value will map to the iscsiNodeIndex.

For implementations where the portal tag is the same for a given portal regardless of which node is using the portal, the value 0 (zero) is used."

::= { iscsiIntrPortalAttributesEntry 1 }

iscsiIntrPortalTag OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

MAX-ACCESS read-write

Bakke, et al.

Expires January 4, 2012

[Page 29]

STATUS current

DESCRIPTION

"The portal's aggregation tag when the portal is used as an initiator portal. Multiple-connection sessions may be aggregated over portals sharing an identical aggregation tag. This object's storage type is specified in iscsiPortalStorageType."

REFERENCE

"[RFC 3720, Section 3.4.1](#), iSCSI Architectural Model"

::= { iscsiIntrPortalAttributesEntry 2 }

_
_*****

iscsiNode OBJECT IDENTIFIER ::= { iscsiObjects 5 }

-- Node Attributes Table

iscsiNodeAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiNodeAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of iSCSI nodes belonging to each iSCSI instance present on the local system. An iSCSI node can act as an initiator, a target, or both."

::= { iscsiNode 1 }

iscsiNodeAttributesEntry OBJECT-TYPE

SYNTAX IscsiNodeAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular iSCSI node."

INDEX { iscsiInstIndex, iscsiNodeIndex }

::= { iscsiNodeAttributesTable 1 }

IscsiNodeAttributesEntry ::= SEQUENCE {

iscsiNodeIndex Unsigned32,

iscsiNodeName IscsiName,

iscsiNodeAlias SnmpAdminString,

iscsiNodeRoles BITS,

iscsiNodeTransportType RowPointer,

iscsiNodeInitialR2T TruthValue,

iscsiNodeImmediateData TruthValue,

iscsiNodeMaxOutstandingR2T Unsigned32,

iscsiNodeFirstBurstLength Unsigned32,

iscsiNodeMaxBurstLength Unsigned32,

iscsiNodeMaxConnections

Unsigned32,

Bakke, et al.

Expires January 4, 2012

[Page 30]

```
    iscsiNodeDataSequenceInOrder    TruthValue,
    iscsiNodeDataPDUInOrder         TruthValue,
    iscsiNodeDefaultTime2Wait       Unsigned32,
    iscsiNodeDefaultTime2Retain     Unsigned32,
    iscsiNodeErrorRecoveryLevel     Unsigned32,
    iscsiNodeDiscontinuityTime      TimeStamp,
    iscsiNodeStorageType            StorageType
}
```

iscsiNodeIndex OBJECT-TYPE

```
SYNTAX      Unsigned32 (1..4294967295)
MAX-ACCESS  not-accessible
STATUS      current
DESCRIPTION
```

"An arbitrary integer used to uniquely identify a particular node within an iSCSI instance. This index value must not be modified or reused by an agent unless a reboot has occurred. An agent should attempt to keep this value persistent across reboots."

```
::= { iscsiNodeAttributesEntry 1 }
```

iscsiNodeName OBJECT-TYPE

```
SYNTAX      IscsiName
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
```

"This node's iSCSI name, which is independent of the location of the node, and can be resolved into a set of addresses through various discovery services."

```
::= { iscsiNodeAttributesEntry 2 }
```

iscsiNodeAlias OBJECT-TYPE

```
SYNTAX      SnmpAdminString
MAX-ACCESS  read-only
STATUS      current
DESCRIPTION
```

"A character string that is a human-readable name or description of the iSCSI node. If configured, this alias may be communicated to the initiator or target node at the remote end of the connection during a Login Request or Response message. This string is not used as an identifier, but can be displayed by the system's user interface in a list of initiators and/or targets to which it is connected.

If no alias exists, the value is a zero-length string."

REFERENCE

[RFC 3720, Section 12.6](#), TargetAlias, 12.7, InitiatorAlias"

`::= { iscsiNodeAttributesEntry 3 }`

iscsiNodeRoles OBJECT-TYPE

SYNTAX BITS {
 targetTypeNode(0),
 initiatorTypeNode(1)
 }

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A node can operate in one or both of two roles:
a target role and/or an initiator role. If the node
will operate in both roles, both bits must be set.

This object will also define the corresponding rows that
will exist in the iscsiTargetAttributesTable, the
iscsiInitiatorAttributesTable or both. If the
targetTypeNode bit is set, there will be a corresponding
iscsiTargetAttributesEntry. If the initiatorTypeNode bit
is set, there will be a corresponding
iscsiInitiatorAttributesEntry. If both bits are set,
there will be a corresponding iscsiTgtPortalAttributesEntry
and iscsiPortalAttributesEntry."

::= { iscsiNodeAttributesEntry 4 }

iscsiNodeTransportType OBJECT-TYPE

SYNTAX RowPointer

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A pointer to the corresponding row in the appropriate
table for this SCSI transport, thereby allowing management
stations to locate the SCSI-level device that is represented
by this iscsiNode. For example, it will usually point to the
corresponding scsiTrnspt object in the SCSI MIB module.
If no corresponding row exists, the value 0.0 must be
used to indicate this."

REFERENCE

"SCSI-MIB"

::= { iscsiNodeAttributesEntry 5 }

iscsiNodeInitialR2T OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object indicates the InitialR2T preference for this
node:
true = YES,

false = will try to negotiate NO, will accept YES "

REFERENCE

"[RFC 3720, Section 12.10](#), InitialR2T"

::= { iscsiNodeAttributesEntry 6 }

iscsiNodeImmediateData OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"This object indicates ImmediateData preference for this node:

true = YES (but will accept NO),

false = NO "

REFERENCE

"[RFC 3720, Section 12.11](#), ImmediateData"

DEFVAL { true }

::= { iscsiNodeAttributesEntry 7 }

iscsiNodeMaxOutstandingR2T OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

UNITS "R2Ts"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"Maximum number of outstanding requests-to-transmit (R2Ts) allowed per iSCSI task."

REFERENCE

"[RFC 3720, Section 12.17](#), MaxOutstandingR2T"

DEFVAL { 1 }

::= { iscsiNodeAttributesEntry 8 }

iscsiNodeFirstBurstLength OBJECT-TYPE

SYNTAX Unsigned32 (512..16777215)

UNITS "bytes"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The maximum length (bytes) supported for unsolicited data to/from this node."

REFERENCE

"[RFC 3720, Section 12.14](#), FirstBurstLength"

DEFVAL { 65536 }

::= { iscsiNodeAttributesEntry 9 }

iscsiNodeMaxBurstLength OBJECT-TYPE

SYNTAX Unsigned32 (512..16777215)

UNITS "bytes"

MAX-ACCESS read-write

STATUS

current

Bakke, et al.

Expires January 4, 2012

[Page 33]

DESCRIPTION

"The maximum number of bytes that can be sent within a single sequence of Data-In or Data-Out PDUs."

REFERENCE

["RFC 3720, Section 12.13, MaxBurstLength"](#)

DEFVAL { 262144 }

::= { iscsiNodeAttributesEntry 10 }

iscsiNodeMaxConnections OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

UNITS "connections"

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The maximum number of connections allowed in each session to and/or from this node."

REFERENCE

["RFC 3720, Section 12.2, MaxConnections"](#)

DEFVAL { 1 }

::= { iscsiNodeAttributesEntry 11 }

iscsiNodeDataSequenceInOrder OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The DataSequenceInOrder preference of this node.

False (=No) indicates that iSCSI data PDU sequences may be transferred in any order. True (=Yes) indicates that data PDU sequences must be transferred using continuously increasing offsets, except during error recovery."

REFERENCE

["RFC 3720, Section 12.19, DataSequenceInOrder"](#)

DEFVAL { true }

::= { iscsiNodeAttributesEntry 12 }

iscsiNodeDataPDUInOrder OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The DataPDUInOrder preference of this node.

False (=No) indicates that iSCSI data PDUs within sequences may be in any order. True (=Yes) indicates that data PDUs within sequences must be at continuously increasing addresses, with no gaps or overlay between PDUs."

REFERENCE

"[RFC 3720, Section 12.18](#), DataPDUInOrder"

```
    DEFVAL          { true }
 ::= { iscsiNodeAttributesEntry 13 }
```

iscsiNodeDefaultTime2Wait OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..3600)
UNITS       "seconds"
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The DefaultTime2Wait preference of this node. This is the minimum time, in seconds, to wait before attempting an explicit/implicit logout or active iSCSI task reassignment after an unexpected connection termination or a connection reset."

REFERENCE

"[RFC 3720, Section 12.15](#), DefaultTime2Wait"

```
    DEFVAL          { 2 }
 ::= { iscsiNodeAttributesEntry 14 }
```

iscsiNodeDefaultTime2Retain OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..3600)
UNITS       "seconds"
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The DefaultTime2Retain preference of this node. This is the maximum time, in seconds after an initial wait (Time2Wait), before which an active iSCSI task reassignment is still possible after an unexpected connection termination or a connection reset."

REFERENCE

"[RFC 3720, Section 12.16](#), DefaultTime2Retain"

```
    DEFVAL          { 20 }
 ::= { iscsiNodeAttributesEntry 15 }
```

iscsiNodeErrorRecoveryLevel OBJECT-TYPE

```
SYNTAX      Unsigned32 (0..255)
MAX-ACCESS  read-write
STATUS      current
```

DESCRIPTION

"The ErrorRecoveryLevel preference of this node. Currently, only 0-2 are valid.

This object is designed to accommodate future error recovery levels.

Higher error recovery levels imply support in addition to support for the lower error level functions. In other words,

error level 2 implies support for levels 0-1, since those

functions are subsets of error level 2."

REFERENCE

"[RFC 3720, Section 12.20](#), ErrorRecoveryLevel"

DEFVAL { 0 }

::= { iscsiNodeAttributesEntry 16 }

iscsiNodeDiscontinuityTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The value of SysUpTime on the most recent occasion at which any one or more of this node's counters suffered a discontinuity.

If no such discontinuities have occurred since the last re-initialization of the local management subsystem, then this object contains a zero value."

::= { iscsiNodeAttributesEntry 17 }

iscsiNodeStorageType OBJECT-TYPE

SYNTAX StorageType

MAX-ACCESS read-write

STATUS current

DESCRIPTION

"The storage type for all read-write objects within this row. Rows in this table are always created via an external process (e.g. not created via this MIB), and may have a storage type of readOnly or permanent. Conceptual rows having the value 'permanent' need not allow write access to any columnar objects in the row.

If this object has the value 'volatile', modifications to read-write objects in this row are not persistent across reboots. If this object has the value 'nonVolatile', modifications to objects in this row are persistent.

An implementation may choose to allow this object to be set to either 'nonVolatile' or 'volatile', allowing the management application to choose this behavior."

DEFVAL { volatile }

::= { iscsiNodeAttributesEntry 18 }

_ _*****

iscsiTarget OBJECT IDENTIFIER ::= { iscsiObjects 6 }

-- Target Attributes Table

iscsiTargetAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiTargetAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of iSCSI nodes that can take on a target role,
belonging to each iSCSI instance present on the local
system."

::= { iscsiTarget 1 }

iscsiTargetAttributesEntry OBJECT-TYPE

SYNTAX IscsiTargetAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable
to a particular node that can take on a target role."

INDEX { iscsiInstIndex, iscsiNodeIndex }

::= { iscsiTargetAttributesTable 1 }

IscsiTargetAttributesEntry ::= SEQUENCE {

iscsiTgtLoginFailures Counter32,

iscsiTgtLastFailureTime TimeStamp,

iscsiTgtLastFailureType AutonomousType,

iscsiTgtLastIntrFailureName IscsiName,

iscsiTgtLastIntrFailureAddrType InetAddressType,

iscsiTgtLastIntrFailureAddr InetAddress

}

iscsiTgtLoginFailures OBJECT-TYPE

SYNTAX Counter32

UNITS "failed login attempts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object counts the number of times a login attempt to this
local target has failed.

If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiTargetAttributesEntry 1 }

iscsiTgtLastFailureTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS

current

Bakke, et al.

Expires January 4, 2012

[Page 37]

DESCRIPTION

"The timestamp of the most recent failure of a login attempt to this target. A value of zero indicates that no such failures have occurred since the last system boot."

::= { iscsiTargetAttributesEntry 2 }

iscsiTgtLastFailureType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The type of the most recent failure of a login attempt to this target, represented as the OID of the counter object in iscsiTargetLoginStatsTable for which the relevant instance was incremented. If no such failures have occurred since the last system boot, this attribute will have the value 0.0. A value of 0.0 may also be used to indicate a type that is not represented by any of the counters in iscsiTargetLoginStatsTable."

::= { iscsiTargetAttributesEntry 3 }

iscsiTgtLastIntrFailureName OBJECT-TYPE

SYNTAX IscsiName

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The iSCSI name of the initiator that failed the last login attempt. If no such failures have occurred since the last system boot, this value is a zero-length string."

::= { iscsiTargetAttributesEntry 4 }

iscsiTgtLastIntrFailureAddrType OBJECT-TYPE

SYNTAX InetAddressType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The type of Internet Network Address contained in the corresponding instance of the iscsiTgtLastIntrFailureAddr. The value 'dns' is not allowed. If no such failures have occurred since the last system boot, this value is zero."

::= { iscsiTargetAttributesEntry 5 }

iscsiTgtLastIntrFailureAddr OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An Internet Network Address, of the type specified by

the object `iscsiTgtLastIntrFailureAddrType`, giving the

```
        host address of the initiator that failed the last login
        attempt. If no such failures have occurred since the last
        system boot, this value is a zero-length string."
 ::= { iscsiTargetAttributesEntry 6 }

-- Target Login Stats Table

iscsiTargetLoginStatsTable OBJECT-TYPE
    SYNTAX      SEQUENCE OF IscsiTargetLoginStatsEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION
        "A table of counters that keep a record of the results
        of initiators' login attempts to this target."
 ::= { iscsiTarget 2 }

iscsiTargetLoginStatsEntry OBJECT-TYPE
    SYNTAX      IscsiTargetLoginStatsEntry
    MAX-ACCESS   not-accessible
    STATUS      current
    DESCRIPTION
        "An entry (row) containing counters for each result of
        a login attempt to this target."
    AUGMENTS { iscsiTargetAttributesEntry }
 ::= { iscsiTargetLoginStatsTable 1 }

IscsiTargetLoginStatsEntry ::= SEQUENCE {
    iscsiTgtLoginAccepts      Counter32,
    iscsiTgtLoginOtherFails   Counter32,
    iscsiTgtLoginRedirects    Counter32,
    iscsiTgtLoginAuthorizeFails Counter32,
    iscsiTgtLoginAuthenticateFails Counter32,
    iscsiTgtLoginNegotiateFails Counter32
}

iscsiTgtLoginAccepts OBJECT-TYPE
    SYNTAX      Counter32
    UNITS        "successful logins"
    MAX-ACCESS   read-only
    STATUS      current
    DESCRIPTION
        "The count of Login Response PDUs with status
        0x0000, Accept Login, transmitted by this
        target.
        If this counter has suffered a discontinuity, the time of the
        last discontinuity is indicated in iscsiNodeDiscontinuityTime."
    REFERENCE
        "RFC 3720, Section 10.13.5, Status-Class and Status-Detail"
```

```
::= { iscsiTargetLoginStatsEntry 1 }
```

iscsiTgtLoginOtherFails OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of Login Response PDUs that were transmitted by this target and that were not counted by any other object in the row.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiTargetLoginStatsEntry 2 }**iscsiTgtLoginRedirects OBJECT-TYPE**

SYNTAX Counter32

UNITS "redirected logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status class 0x01, Redirection, transmitted by this target.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiTargetLoginStatsEntry 3 }**iscsiTgtLoginAuthorizeFails OBJECT-TYPE**

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status 0x0202, Forbidden Target, transmitted by this target.

If this counter is incremented, an iscsiTgtLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiTargetLoginStatsEntry 4 }**iscsiTgtLoginAuthenticateFails OBJECT-TYPE**

SYNTAX

Counter32

Bakke, et al.

Expires January 4, 2012

[Page 40]

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status 0x0201, Authentication Failed, transmitted by this target.

If this counter is incremented, an iscsiTgtLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiTargetLoginStatsEntry 5 }

iscsiTgtLoginNegotiateFails OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of times a target has effectively refused a login because the parameter negotiation failed.

If this counter is incremented, an iscsiTgtLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

::= { iscsiTargetLoginStatsEntry 6 }

-- Target Logout Stats Table

iscsiTargetLogoutStatsTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiTargetLogoutStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"When a target receives a Logout command, it responds with a Logout Response that carries a status code.

This table contains counters for both normal and abnormal logout requests received by this target."

::= { iscsiTarget 3 }

iscsiTargetLogoutStatsEntry OBJECT-TYPE

SYNTAX IscsiTargetLogoutStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing counters of Logout Response

Bakke, et al.

Expires January 4, 2012

[Page 41]

PDUs that were received by this target."
 AUGMENTS { iscsiTargetAttributesEntry }
 ::= { iscsiTargetLogoutStatsTable 1 }

IscsiTargetLogoutStatsEntry ::= SEQUENCE {
 iscsiTgtLogoutNormals Counter32,
 iscsiTgtLogoutOthers Counter32
 }

iscsiTgtLogoutNormals OBJECT-TYPE

SYNTAX Counter32

UNITS "normal logouts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Logout Command PDUs received by this target,
 with reason code 0 (closes the session).

If this counter has suffered a discontinuity, the time of the
 last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.14.1](#), Reason Code"

::= { iscsiTargetLogoutStatsEntry 1 }

iscsiTgtLogoutOthers OBJECT-TYPE

SYNTAX Counter32

UNITS "abnormal logouts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Logout Command PDUs received by this target,
 with any reason code other than 0.

If this counter has suffered a discontinuity, the time of the
 last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.14.1](#), Reason Code"

::= { iscsiTargetLogoutStatsEntry 2 }

_ _*****

iscsiTgtAuthorization OBJECT IDENTIFIER ::= { iscsiObjects 7 }

-- Target Authorization Attributes Table

iscsiTgtAuthAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiTgtAuthAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of initiator identities that are authorized to

Bakke, et al.

Expires January 4, 2012

[Page 42]

access each target node within each iSCSI instance
present on the local system."

::= { iscsiTgtAuthorization 1 }

iscsiTgtAuthAttributesEntry OBJECT-TYPE

SYNTAX IscsiTgtAuthAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information
applicable to a particular target node's authorized
initiator identity."

INDEX { iscsiInstIndex, iscsiNodeIndex, iscsiTgtAuthIndex }

::= { iscsiTgtAuthAttributesTable 1 }

IscsiTgtAuthAttributesEntry ::= SEQUENCE {

iscsiTgtAuthIndex Unsigned32,

iscsiTgtAuthRowStatus RowStatus,

iscsiTgtAuthIdentity RowPointer,

iscsiTgtAuthStorageType StorageType

}

iscsiTgtAuthIndex OBJECT-TYPE

SYNTAX Unsigned32 (1..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular
target's authorized initiator identity within an iSCSI
instance present on the local system. This index value must
not be modified or reused by an agent unless a reboot has
occurred. An agent should attempt to keep this value
persistent across reboots."

::= { iscsiTgtAuthAttributesEntry 1 }

iscsiTgtAuthRowStatus OBJECT-TYPE

SYNTAX RowStatus

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This field allows entries to be dynamically added and
removed from this table via SNMP. When adding a row to
this table, all non-Index/RowStatus objects must be set.
When the value of this object is 'active', the values of
the other objects in this table cannot be changed.
Rows may be discarded using RowStatus."

::= { iscsiTgtAuthAttributesEntry 2 }

iscsiTgtAuthIdentity OBJECT-TYPE

Bakke, et al.

Expires January 4, 2012

[Page 43]

SYNTAX RowPointer
 MAX-ACCESS read-create
 STATUS current
 DESCRIPTION

"A pointer to the corresponding user entry in the IPS-AUTH
 MIB module that will be allowed to access this iSCSI target."

REFERENCE

"IPS-AUTH MIB, [RFC 4545](#)"

::= { iscsiTgtAuthAttributesEntry 3 }

iscsiTgtAuthStorageType OBJECT-TYPE

SYNTAX StorageType
 MAX-ACCESS read-create
 STATUS current
 DESCRIPTION

"The storage type for this row. Rows in this table that were
 created through an external process (e.g. not created via
 this MIB) may have a storage type of readOnly or permanent.

Conceptual rows having the value 'permanent' need not
 allow write access to any columnar objects in the row."

DEFVAL { nonVolatile }

::= { iscsiTgtAuthAttributesEntry 4 }

_ _*****

iscsiInitiator OBJECT IDENTIFIER ::= { iscsiObjects 8 }

-- Initiator Attributes Table

iscsiInitiatorAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiInitiatorAttributesEntry
 MAX-ACCESS not-accessible
 STATUS current
 DESCRIPTION

"A list of iSCSI nodes that can take on an initiator
 role, belonging to each iSCSI instance present on
 the local system."

::= { iscsiInitiator 1 }

iscsiInitiatorAttributesEntry OBJECT-TYPE

SYNTAX IscsiInitiatorAttributesEntry
 MAX-ACCESS not-accessible
 STATUS current
 DESCRIPTION

"An entry (row) containing management information
 applicable to a particular iSCSI node that has
 initiator capabilities."

```
INDEX { iscsiInstIndex, iscsiNodeIndex }
```

Bakke, et al.

Expires January 4, 2012

[Page 44]

```
::= { iscsiInitiatorAttributesTable 1 }
```

```
IscsiInitiatorAttributesEntry ::= SEQUENCE {  
    iscsiIntrLoginFailures      Counter32,  
    iscsiIntrLastFailureTime    TimeStamp,  
    iscsiIntrLastFailureType    AutonomousType,  
    iscsiIntrLastTgtFailureName IscsiName,  
    iscsiIntrLastTgtFailureAddr InetAddressType,  
    iscsiIntrLastTgtFailureAddr InetAddress  
}
```

iscsiIntrLoginFailures OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object counts the number of times a login attempt from this local initiator has failed.
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

```
::= { iscsiInitiatorAttributesEntry 1 }
```

iscsiIntrLastFailureTime OBJECT-TYPE

SYNTAX TimeStamp

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The timestamp of the most recent failure of a login attempt from this initiator. A value of zero indicates that no such failures have occurred since the last system boot."

```
::= { iscsiInitiatorAttributesEntry 2 }
```

iscsiIntrLastFailureType OBJECT-TYPE

SYNTAX AutonomousType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The type of the most recent failure of a login attempt from this initiator, represented as the OID of the counter object in iscsiInitiatorLoginStatsTable for which the relevant instance was incremented. If no such failures have occurred since the last system boot, this attribute will have the value 0.0. A value of 0.0 may also be used to indicate a type that is not represented by any of the counters in iscsiInitiatorLoginStatsTable."

```
::= { iscsiInitiatorAttributesEntry 3 }
```

iscsiIntrLastTgtFailureName OBJECT-TYPE

SYNTAX IscsiName

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A UTF-8 string giving the name of the target that failed the last login attempt. If no such failures have occurred since the last system boot, this value is a zero-length string."

::= { iscsiInitiatorAttributesEntry 4 }

iscsiIntrLastTgtFailureAddrType OBJECT-TYPE

SYNTAX InetAddressType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The type of Internet Network Address contained in the corresponding instance of the iscsiIntrLastTgtFailureAddr. The value 'dns' is not allowed. If no such failures have occurred since the last system boot, this value is zero."

::= { iscsiInitiatorAttributesEntry 5 }

iscsiIntrLastTgtFailureAddr OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"An Internet Network Address, of the type specified by the object iscsiIntrLastTgtFailureAddrType, giving the host address of the target that failed the last login attempt. If no such failures have occurred since the last system boot, this value is a zero-length string."

::= { iscsiInitiatorAttributesEntry 6 }

-- Initiator Login Stats Table

iscsiInitiatorLoginStatsTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiInitiatorLoginStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A table of counters which keep track of the results of this initiator's login attempts."

::= { iscsiInitiator 2 }

iscsiInitiatorLoginStatsEntry OBJECT-TYPE

SYNTAX IscsiInitiatorLoginStatsEntry

MAX-ACCESS not-accessible

STATUS

current

Bakke, et al.

Expires January 4, 2012

[Page 46]

DESCRIPTION

"An entry (row) containing counters of each result of this initiator's login attempts."

AUGMENTS { iscsiInitiatorAttributesEntry }

::= { iscsiInitiatorLoginStatsTable 1 }

```
IscsiInitiatorLoginStatsEntry ::= SEQUENCE {  
    iscsiIntrLoginAcceptRsps      Counter32,  
    iscsiIntrLoginOtherFailRsps   Counter32,  
    iscsiIntrLoginRedirectRsps    Counter32,  
    iscsiIntrLoginAuthFailRsps    Counter32,  
    iscsiIntrLoginAuthenticateFails Counter32,  
    iscsiIntrLoginNegotiateFails  Counter32,  
    iscsiIntrLoginAuthorizeFails  Counter32  
}
```

iscsiIntrLoginAcceptRsps OBJECT-TYPE

SYNTAX Counter32

UNITS "successful logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status 0x0000, Accept Login, received by this initiator.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiInitiatorLoginStatsEntry 1 }

iscsiIntrLoginOtherFailRsps OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs received by this initiator with any status code not counted in the objects below.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiInitiatorLoginStatsEntry 2 }

iscsiIntrLoginRedirectRsps OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

Bakke, et al.

Expires January 4, 2012

[Page 47]

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status class 0x01, Redirection, received by this initiator.
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

["RFC 3720, Section 10.13.5, Status-Class and Status-Detail"](#)

::= { iscsiInitiatorLoginStatsEntry 3 }

iscsiIntrLoginAuthFailRsps OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status class 0x201, Authentication Failed, received by this initiator.
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

["RFC 3720, Section 10.13.5, Status-Class and Status-Detail"](#)

::= { iscsiInitiatorLoginStatsEntry 4 }

iscsiIntrLoginAuthenticateFails OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of times the initiator has aborted a login because the target could not be authenticated.

No response is generated.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

["RFC 3720, Section 10.13.5, Status-Class and Status-Detail"](#)

::= { iscsiInitiatorLoginStatsEntry 5 }

iscsiIntrLoginNegotiateFails OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

Bakke, et al.

Expires January 4, 2012

[Page 48]

"The number of times the initiator has aborted a login because parameter negotiation with the target failed.

No response is generated.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 6.10](#), Negotiation Failures"

::= { iscsiInitiatorLoginStatsEntry 6 }

iscsiIntrLoginAuthorizeFails OBJECT-TYPE

SYNTAX Counter32

UNITS "failed logins"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Login Response PDUs with status 0x0202, Forbidden Target, received by this initiator.

If this counter is incremented, an iscsiIntrLoginFailure notification should be generated.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.13.5](#), Status-Class and Status-Detail"

::= { iscsiInitiatorLoginStatsEntry 7 }

-- Initiator Logout Stats Table

iscsiInitiatorLogoutStatsTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiInitiatorLogoutStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"When an initiator attempts to send a Logout command, the target responds with a Logout Response that carries a status code. This table contains a list of counters of Logout Response PDUs of each status code that was received by each initiator belonging to this iSCSI instance present on this system."

::= { iscsiInitiator 3 }

iscsiInitiatorLogoutStatsEntry OBJECT-TYPE

SYNTAX IscsiInitiatorLogoutStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing counters of Logout Response PDUs of each status code that was generated by this initiator."

AUGMENTS { iscsiInitiatorAttributesEntry }

::= { iscsiInitiatorLogoutStatsTable 1 }

```
IscsiInitiatorLogoutStatsEntry ::= SEQUENCE {
    iscsiIntrLogoutNormals      Counter32,
    iscsiIntrLogoutOthers      Counter32
}
```

iscsiIntrLogoutNormals OBJECT-TYPE

SYNTAX Counter32

UNITS "normal logouts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Logout Command PDUs generated by this initiator with reason code 0 (closes the session).
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.14.1](#), Reason Code"

::= { iscsiInitiatorLogoutStatsEntry 1 }

iscsiIntrLogoutOthers OBJECT-TYPE

SYNTAX Counter32

UNITS "abnormal logouts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Logout Command PDUs generated by this initiator with any status code other than 0.
If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiNodeDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 10.14.1](#), Reason Code"

::= { iscsiInitiatorLogoutStatsEntry 2 }

_ _*****

iscsiIntrAuthorization OBJECT IDENTIFIER ::= { iscsiObjects 9 }

-- Initiator Authorization Attributes Table

Bakke, et al.

Expires January 4, 2012

[Page 50]

iscsiIntrAuthAttributesTable OBJECT-TYPE

SYNTAX SEQUENCE OF IscsiIntrAuthAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"A list of target identities that each initiator
on the local system may access."

::= { iscsiIntrAuthorization 1 }

iscsiIntrAuthAttributesEntry OBJECT-TYPE

SYNTAX IscsiIntrAuthAttributesEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing management information applicable
to a particular initiator node's authorized target identity."

INDEX { iscsiInstIndex, iscsiNodeIndex, iscsiIntrAuthIndex }

::= { iscsiIntrAuthAttributesTable 1 }

IscsiIntrAuthAttributesEntry ::= SEQUENCE {

iscsiIntrAuthIndex Unsigned32,

iscsiIntrAuthRowStatus RowStatus,

iscsiIntrAuthIdentity RowPointer,

iscsiIntrAuthStorageType StorageType

}**iscsiIntrAuthIndex OBJECT-TYPE**

SYNTAX Unsigned32 (1..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a
particular initiator node's authorized target
identity within an iSCSI instance present on the
local system. This index value must not be modified
or reused by an agent unless a reboot has occurred.
An agent should attempt to keep this value persistent
across reboots."

::= { iscsiIntrAuthAttributesEntry 1 }

iscsiIntrAuthRowStatus OBJECT-TYPE

SYNTAX RowStatus

MAX-ACCESS read-create

STATUS current

DESCRIPTION

"This field allows entries to be dynamically added and
removed from this table via SNMP. When adding a row to

this table, all non-Index/RowStatus objects must be set.

When the value of this object is 'active', the values of the other objects in this table cannot be changed.

Rows may be discarded using RowStatus."

```
::= { iscsiIntrAuthAttributesEntry 2 }
```

```
iscsiIntrAuthIdentity OBJECT-TYPE
```

```
SYNTAX          RowPointer
```

```
MAX-ACCESS      read-create
```

```
STATUS          current
```

```
DESCRIPTION
```

"A pointer to the corresponding user entry in the IPS-AUTH MIB module to which this initiator node should attempt to establish an iSCSI session."

```
REFERENCE
```

"IPS-AUTH MIB, [RFC 4545](#)"

```
::= { iscsiIntrAuthAttributesEntry 3 }
```

```
iscsiIntrAuthStorageType OBJECT-TYPE
```

```
SYNTAX          StorageType
```

```
MAX-ACCESS      read-create
```

```
STATUS          current
```

```
DESCRIPTION
```

"The storage type for this row. Rows in this table that were created through an external process (e.g. not created via this MIB) may have a storage type of readOnly or permanent.

Conceptual rows having the value 'permanent' need not allow write access to any columnar objects in the row."

```
DEFVAL          { nonVolatile }
```

```
::= { iscsiIntrAuthAttributesEntry 4 }
```

```
_ _*****
```

```
iscsiSession OBJECT IDENTIFIER ::= { iscsiObjects 10 }
```

```
-- Session Attributes Table
```

```
iscsiSessionAttributesTable OBJECT-TYPE
```

```
SYNTAX          SEQUENCE OF IscsiSessionAttributesEntry
```

```
MAX-ACCESS      not-accessible
```

```
STATUS          current
```

```
DESCRIPTION
```

"A list of sessions belonging to each iSCSI instance present on the system."

```
::= { iscsiSession 1 }
```

```
iscsiSessionAttributesEntry OBJECT-TYPE
```

```
SYNTAX          IscsiSessionAttributesEntry
```

```
MAX-ACCESS      not-accessible
```


STATUS current

DESCRIPTION

"An entry (row) containing management information applicable to a particular session.

If this session is a discovery session that is not attached to any particular node, the iscsiSsnNodeIndex will be zero.

Otherwise, the iscsiSsnNodeIndex will have the same value as iscsiNodeIndex."

INDEX { iscsiInstIndex, iscsiSsnNodeIndex, iscsiSsnIndex }

::= { iscsiSessionAttributesTable 1 }

```
IscsiSessionAttributesEntry ::= SEQUENCE {
    iscsiSsnNodeIndex      Unsigned32,
    iscsiSsnIndex          Unsigned32,
    iscsiSsnDirection      INTEGER,
    iscsiSsnInitiatorName  IscsiName,
    iscsiSsnTargetName     IscsiName,
    iscsiSsnTSIH           Unsigned32,
    iscsiSsnISID           OCTET STRING,
    iscsiSsnInitiatorAlias  SnmpAdminString,
    iscsiSsnTargetAlias     SnmpAdminString,
    iscsiSsnInitialR2T     TruthValue,
    iscsiSsnImmediateData  TruthValue,
    iscsiSsnType            INTEGER,
    iscsiSsnMaxOutstandingR2T Unsigned32,
    iscsiSsnFirstBurstLength Unsigned32,
    iscsiSsnMaxBurstLength Unsigned32,
    iscsiSsnConnectionNumber Gauge32,
    iscsiSsnAuthIdentity   RowPointer,
    iscsiSsnDataSequenceInOrder TruthValue,
    iscsiSsnDataPDUInOrder TruthValue,
    iscsiSsnErrorRecoveryLevel Unsigned32,
    iscsiSsnDiscontinuityTime TimeStamp,
    iscsiSsnProtocolLevel  Unsigned32,
    iscsiSsnTaskReporting   BITS
}
```

iscsiSsnNodeIndex OBJECT-TYPE

SYNTAX Unsigned32 (0..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular node within an iSCSI instance present on the local system. For normal, non-discovery sessions, this value will map to the iscsiNodeIndex. For discovery sessions that do not have a node

associated, the value 0 (zero) is used."

```
::= { iscsiSessionAttributesEntry 1 }
```

iscsiSsnIndex OBJECT-TYPE

SYNTAX Unsigned32 (1..4294967295)

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular session within an iSCSI instance present on the local system. An agent should attempt to not reuse index values unless a reboot has occurred. iSCSI sessions are destroyed during a reboot; rows in this table are not persistent across reboots."

```
::= { iscsiSessionAttributesEntry 2 }
```

iscsiSsnDirection OBJECT-TYPE

SYNTAX INTEGER {
inboundSession(1),
outboundSession(2)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"Direction of iSCSI session:

inboundSession - session is established from an external initiator to a target within this iSCSI instance.

outboundSession - session is established from an initiator within this iSCSI instance to an external target."

```
::= { iscsiSessionAttributesEntry 3 }
```

iscsiSsnInitiatorName OBJECT-TYPE

SYNTAX IscsiName

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"If iscsiSsnDirection is Inbound, this object is a UTF-8 string that will contain the name of the remote initiator. If this session is a discovery session that does not specify a particular initiator, this object will contain a zero-length string.

If iscsiSsnDirection is Outbound, this object will contain a zero-length string."

```
::= { iscsiSessionAttributesEntry 4 }
```

iscsiSsnTargetName OBJECT-TYPE

SYNTAX

IscsiName

Bakke, et al.

Expires January 4, 2012

[Page 54]

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"If iscsiSsnDirection is Outbound, this object is a UTF-8 string that will contain the name of the remote target. If this session is a discovery session that does not specify a particular target, this object will contain a zero-length string.

If iscsiSsnDirection is Inbound, this object will contain a zero-length string."

::= { iscsiSessionAttributesEntry 5 }

iscsiSsnTSIH OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The target-defined identification handle for this session."

REFERENCE

"[RFC 3720, Section 10.12.6](#), TSIH"

::= { iscsiSessionAttributesEntry 6 }

iscsiSsnISID OBJECT-TYPE

SYNTAX OCTET STRING (SIZE(6))

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The initiator-defined portion of the iSCSI Session ID."

REFERENCE

"[RFC 3720, Section 10.12.5](#), ISID"

::= { iscsiSessionAttributesEntry 7 }

iscsiSsnInitiatorAlias OBJECT-TYPE

SYNTAX SnmpAdminString

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"A UTF-8 string that gives the alias communicated by the initiator end of the session during the login phase.

If no alias exists, the value is a zero-length string."

REFERENCE

"[RFC 3720, Section 12.7](#), InitiatorAlias"

::= { iscsiSessionAttributesEntry 8 }

iscsiSsnTargetAlias OBJECT-TYPE

SYNTAX SnmpAdminString

MAX-ACCESS read-only

Bakke, et al.

Expires January 4, 2012

[Page 55]

STATUS current

DESCRIPTION

"A UTF-8 string that gives the alias communicated by the target end of the session during the login phase.

If no alias exists, the value is a zero-length string."

REFERENCE

"[RFC 3720, Section 12.6](#), TargetAlias"

::= { iscsiSessionAttributesEntry 9 }

iscsiSsnInitialR2T OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"If set to true, indicates that the initiator must wait for an R2T before sending to the target. If set to false, the initiator may send data immediately, within limits set by iscsiSsnFirstBurstLength and the expected data transfer length of the request."

REFERENCE

"[RFC 3720, Section 12.10](#), InitialR2T"

::= { iscsiSessionAttributesEntry 10 }

iscsiSsnImmediateData OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"Indicates whether the initiator and target have agreed to support immediate data on this session."

REFERENCE

"[RFC 3720, Section 12.11](#), ImmediateData"

::= { iscsiSessionAttributesEntry 11 }

iscsiSsnType OBJECT-TYPE

SYNTAX INTEGER {
normalSession(1),
discoverySession(2)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"Type of iSCSI session:

normalSession - session is a normal iSCSI session

discoverySession - session is being used only for discovery."

REFERENCE

"[RFC 3720, Section 12.21](#), SessionType"

```
::= { iscsiSessionAttributesEntry 12 }
```

iscsiSsnMaxOutstandingR2T OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

UNITS "R2Ts"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The maximum number of outstanding requests-to-transmit (R2Ts) per iSCSI task within this session."

REFERENCE

"[RFC 3720, Section 12.17](#), MaxOutstandingR2T"

::= { iscsiSessionAttributesEntry 13 }

iscsiSsnFirstBurstLength OBJECT-TYPE

SYNTAX Unsigned32 (512..16777215)

UNITS "bytes"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The maximum length supported for unsolicited data sent within this session."

REFERENCE

"[RFC 3720, Section 12.14](#), FirstBurstLength"

::= { iscsiSessionAttributesEntry 14 }

iscsiSsnMaxBurstLength OBJECT-TYPE

SYNTAX Unsigned32 (512..16777215)

UNITS "bytes"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The maximum number of bytes that can be sent within a single sequence of Data-In or Data-Out PDUs."

REFERENCE

"[RFC 3720, Section 12.13](#), MaxBurstLength"

::= { iscsiSessionAttributesEntry 15 }

iscsiSsnConnectionNumber OBJECT-TYPE

SYNTAX Gauge32 (1..65535)

UNITS "connections"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The number of transport protocol connections that currently belong to this session."

::= { iscsiSessionAttributesEntry 16 }

iscsiSsnAuthIdentity OBJECT-TYPE

SYNTAX

RowPointer

Bakke, et al.

Expires January 4, 2012

[Page 57]

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"This object contains a pointer to a row in the IPS-AUTH MIB module that identifies the authentication identity being used on this session, as communicated during the login phase."

REFERENCE

"IPS-AUTH MIB, [RFC 4545](#)"

::= { iscsiSessionAttributesEntry 17 }

iscsiSsnDataSequenceInOrder OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"False indicates that iSCSI data PDU sequences may be transferred in any order. True indicates that data PDU sequences must be transferred using continuously increasing offsets, except during error recovery."

REFERENCE

"[RFC 3720, Section 12.19](#), DataSequenceInOrder"

::= { iscsiSessionAttributesEntry 18 }

iscsiSsnDataPDUInOrder OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"False indicates that iSCSI data PDUs within sequences may be in any order. True indicates that data PDUs within sequences must be at continuously increasing addresses, with no gaps or overlay between PDUs. Default is true."

REFERENCE

"[RFC 3720, Section 12.18](#), DataPDUInOrder"

::= { iscsiSessionAttributesEntry 19 }

iscsiSsnErrorRecoveryLevel OBJECT-TYPE

SYNTAX Unsigned32 (0..255)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The level of error recovery negotiated between the initiator and the target. Higher numbers represent more detailed recovery schemes."

REFERENCE

"[RFC 3720, Section 12.20](#), ErrorRecoveryLevel"

```
::= { iscsiSessionAttributesEntry 20 }
```

```
iscsiSsnDiscontinuityTime OBJECT-TYPE
```

```
    SYNTAX          TimeStamp
```

```
    MAX-ACCESS      read-only
```

```
    STATUS          current
```

```
    DESCRIPTION
```

"The value of SysUpTime on the most recent occasion at which any one or more of this session's counters suffered a discontinuity.

When a session is established, and this object is created, it is initialized to the current value of SysUpTime."

```
::= { iscsiSessionAttributesEntry 21 }
```

```
iscsiSsnProtocolLevel OBJECT-TYPE
```

```
    SYNTAX          Unsigned32 (1..65535)
```

```
    MAX-ACCESS      read-only
```

```
    STATUS          current
```

```
    DESCRIPTION
```

"The iSCSI protocol level negotiated for this session."

```
    REFERENCE
```

"[[iSCSI-SAM](#)], Section 7.1.1, iSCSIProtocolLevel"

```
    DEFVAL          { 1 }
```

```
::= { iscsiSessionAttributesEntry 22 }
```

```
iscsiSsnTaskReporting OBJECT-TYPE
```

```
    SYNTAX          BITS {
                        taskReportingRfc3720(0),
                        taskReportingResponseFence(1),
                        taskReportingFastAbort(2)
                    }
```

```
    MAX-ACCESS      read-only
```

```
    STATUS          current
```

```
    DESCRIPTION
```

"This key is used to negotiate the task completion reporting semantics from the SCSI target.

Default value is taskReportingRfc3720."

```
    REFERENCE
```

"[[iSCSI-CONS](#)], Section 13.23, Task Reporting"

```
::= { iscsiSessionAttributesEntry 23 }
```

```
-- Session Stats Table
```

```
iscsiSessionStatsTable OBJECT-TYPE
```

```
    SYNTAX          SEQUENCE OF IscsiSessionStatsEntry
```

```
    MAX-ACCESS      not-accessible
```

STATUS

current

Bakke, et al.

Expires January 4, 2012

[Page 59]

DESCRIPTION

"A list of general iSCSI traffic counters for each of the sessions present on the system."

::= { iscsiSession 2 }

iscsiSessionStatsEntry OBJECT-TYPE

SYNTAX IscsiSessionStatsEntry

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An entry (row) containing general iSCSI traffic counters for a particular session."

AUGMENTS { iscsiSessionAttributesEntry }

::= { iscsiSessionStatsTable 1 }

IscsiSessionStatsEntry ::= SEQUENCE {

iscsiSsnCmdPDUs Counter32,

iscsiSsnRspPDUs Counter32,

iscsiSsnTxDataOctets Counter64,

iscsiSsnRxDataOctets Counter64,

iscsiSsnLCTxDataOctets Counter32,

iscsiSsnLCRxDataOctets Counter32

}

iscsiSsnCmdPDUs OBJECT-TYPE

SYNTAX Counter32

UNITS "PDUs"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Command PDUs transferred on this session.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 1 }

iscsiSsnRspPDUs OBJECT-TYPE

SYNTAX Counter32

UNITS "PDUs"

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The count of Response PDUs transferred on this session.

If this counter has suffered a discontinuity, the time of the last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 2 }

iscsiSsnTxDataOctets OBJECT-TYPE

SYNTAX

Counter64

Bakke, et al.

Expires January 4, 2012

[Page 60]

UNITS "octets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"The count of data octets that were transmitted by
the local iSCSI node on this session.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 3 }

iscsiSsnRxDataOctets OBJECT-TYPE

SYNTAX Counter64
UNITS "octets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"The count of data octets that were received by
the local iSCSI node on this session.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 4 }

iscsiSsnLCTxDataOctets OBJECT-TYPE

SYNTAX Counter32
UNITS "octets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"A Low Capacity shadow object of iscsiSsnTxDataOctets
for those systems that don't support Counter64.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 5 }

iscsiSsnLCRxDataOctets OBJECT-TYPE

SYNTAX Counter32
UNITS "octets"
MAX-ACCESS read-only
STATUS current
DESCRIPTION

"A Low Capacity shadow object of iscsiSsnRxDataOctets
for those systems that don't support Counter64.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

::= { iscsiSessionStatsEntry 6 }

-- Session Connection Error Stats Table

iscsiSessionCxnErrorStatsTable OBJECT-TYPE

Bakke, et al.

Expires January 4, 2012

[Page 61]

SYNTAX SEQUENCE OF IscsiSessionCxnErrorStatsEntry
MAX-ACCESS not-accessible
STATUS current

DESCRIPTION

"A list of error counters for each of the sessions
present on this system."

::= { iscsiSession 3 }

iscsiSessionCxnErrorStatsEntry OBJECT-TYPE

SYNTAX IscsiSessionCxnErrorStatsEntry
MAX-ACCESS not-accessible
STATUS current

DESCRIPTION

"An entry (row) containing error counters for
a particular session."

AUGMENTS { iscsiSessionAttributesEntry }

::= { iscsiSessionCxnErrorStatsTable 1 }

IscsiSessionCxnErrorStatsEntry ::= SEQUENCE {
 iscsiSsnCxnDigestErrors Counter32,
 iscsiSsnCxnTimeoutErrors Counter32
}

iscsiSsnCxnDigestErrors OBJECT-TYPE

SYNTAX Counter32
UNITS "PDU's"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The count of PDUs that were received on the session and
contained header or data digest errors.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 6.7](#), Digest Errors"

::= { iscsiSessionCxnErrorStatsEntry 1 }

iscsiSsnCxnTimeoutErrors OBJECT-TYPE

SYNTAX Counter32
UNITS "connections"
MAX-ACCESS read-only
STATUS current

DESCRIPTION

"The count of connections within this session
that have been terminated due to timeout.
If this counter has suffered a discontinuity, the time of the
last discontinuity is indicated in iscsiSsnDiscontinuityTime."

REFERENCE

"[RFC 3720, Section 6.4](#), Connection Timeout Management"

Bakke, et al.

Expires January 4, 2012

[Page 62]

```
::= { iscsiSessionCxnErrorStatsEntry 2 }
```

```
_ _*****
```

```
iscsiConnection OBJECT IDENTIFIER ::= { iscsiObjects 11 }
```

```
-- Connection Attributes Table
```

```
iscsiConnectionAttributesTable OBJECT-TYPE
```

```
    SYNTAX          SEQUENCE OF IscsiConnectionAttributesEntry
```

```
    MAX-ACCESS      not-accessible
```

```
    STATUS          current
```

```
    DESCRIPTION
```

```
        "A list of connections belonging to each iSCSI instance
        present on the system."
```

```
::= { iscsiConnection 1 }
```

```
iscsiConnectionAttributesEntry OBJECT-TYPE
```

```
    SYNTAX          IscsiConnectionAttributesEntry
```

```
    MAX-ACCESS      not-accessible
```

```
    STATUS          current
```

```
    DESCRIPTION
```

```
        "An entry (row) containing management information applicable
        to a particular connection."
```

```
    INDEX { iscsiInstIndex, iscsiSsnNodeIndex, iscsiSsnIndex,
            iscsiCxnIndex }
```

```
::= { iscsiConnectionAttributesTable 1 }
```

```
IscsiConnectionAttributesEntry ::= SEQUENCE {
```

```
    iscsiCxnIndex          Unsigned32,
```

```
    iscsiCxnCid            Unsigned32,
```

```
    iscsiCxnState          INTEGER,
```

```
    iscsiCxnAddrType       InetAddressType,
```

```
    iscsiCxnLocalAddr       InetAddress,
```

```
    iscsiCxnProtocol        IscsiTransportProtocol,
```

```
    iscsiCxnLocalPort       InetPortNumber,
```

```
    iscsiCxnRemoteAddr      InetAddress,
```

```
    iscsiCxnRemotePort      InetPortNumber,
```

```
    iscsiCxnMaxRecvDataSegLength Unsigned32,
```

```
    iscsiCxnMaxXmitDataSegLength Unsigned32,
```

```
    iscsiCxnHeaderIntegrity IscsiDigestMethod,
```

```
    iscsiCxnDataIntegrity   IscsiDigestMethod,
```

```
    iscsiCxnRecvMarker      TruthValue,
```

```
    iscsiCxnSendMarker      TruthValue,
```

```
    iscsiCxnVersionActive   Unsigned32
```

```
}
```

```
iscsiCxnIndex OBJECT-TYPE
```

SYNTAX

Unsigned32 (1..4294967295)

Bakke, et al.

Expires January 4, 2012

[Page 63]

MAX-ACCESS not-accessible

STATUS current

DESCRIPTION

"An arbitrary integer used to uniquely identify a particular connection of a particular session within an iSCSI instance present on the local system. An agent should attempt to not reuse index values unless a reboot has occurred. iSCSI connections are destroyed during a reboot; rows in this table are not persistent across reboots."

::= { iscsiConnectionAttributesEntry 1 }

iscsiCxnCid OBJECT-TYPE

SYNTAX Unsigned32 (1..65535)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The iSCSI Connection ID for this connection."

::= { iscsiConnectionAttributesEntry 2 }

iscsiCxnState OBJECT-TYPE

SYNTAX INTEGER {
 login(1),
 full(2),
 logout(3)
}

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The current state of this connection, from an iSCSI negotiation point of view. Here are the states:

login - The transport protocol connection has been established, but a valid iSCSI login response with the final bit set has not been sent or received.

full - A valid iSCSI login response with the final bit set has been sent or received.

logout - A valid iSCSI logout command has been sent or received, but the transport protocol connection has not yet been closed."

::= { iscsiConnectionAttributesEntry 3 }

iscsiCxnAddrType OBJECT-TYPE

SYNTAX InetAddressType

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The type of Internet Network Addresses contained in the

Bakke, et al.

Expires January 4, 2012

[Page 64]

corresponding instances of `iscsiCxnLocalAddr` and
`iscsiCxnRemoteAddr`.

The value 'dns' is not allowed."

::= { `iscsiConnectionAttributesEntry` 4 }

`iscsiCxnLocalAddr` OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The local Internet Network Address, of the type specified
by `iscsiCxnAddrType`, used by this connection."

::= { `iscsiConnectionAttributesEntry` 5 }

`iscsiCxnProtocol` OBJECT-TYPE

SYNTAX IscsiTransportProtocol

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The transport protocol over which this connection is
running."

::= { `iscsiConnectionAttributesEntry` 6 }

`iscsiCxnLocalPort` OBJECT-TYPE

SYNTAX InetPortNumber

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The local transport protocol port used by this connection.
This object cannot have the value zero, since it represents
an established connection."

::= { `iscsiConnectionAttributesEntry` 7 }

`iscsiCxnRemoteAddr` OBJECT-TYPE

SYNTAX InetAddress

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The remote Internet Network Address, of the type specified
by `iscsiCxnAddrType`, used by this connection."

::= { `iscsiConnectionAttributesEntry` 8 }

`iscsiCxnRemotePort` OBJECT-TYPE

SYNTAX InetPortNumber

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"The remote transport protocol port used by this connection."

This object cannot have the value zero, since it represents

an established connection."
 ::= { iscsiConnectionAttributesEntry 9 }

iscsiCxnMaxRecvDataSegLength OBJECT-TYPE
 SYNTAX Unsigned32 (512..16777215)
 UNITS "bytes"
 MAX-ACCESS read-only
 STATUS current
 DESCRIPTION
 "The maximum data payload size supported for command
 or data PDUs able to be received on this connection."
 REFERENCE
 "[RFC 3720, Section 12.12](#), MaxRecvDataSegmentLength"
 ::= { iscsiConnectionAttributesEntry 10 }

iscsiCxnMaxXmitDataSegLength OBJECT-TYPE
 SYNTAX Unsigned32 (512..16777215)
 UNITS "bytes"
 MAX-ACCESS read-only
 STATUS current
 DESCRIPTION
 "The maximum data payload size supported for command
 or data PDUs to be sent on this connection."
 REFERENCE
 "[RFC 3720, Section 12.12](#), MaxRecvDataSegmentLength"
 ::= { iscsiConnectionAttributesEntry 11 }

iscsiCxnHeaderIntegrity OBJECT-TYPE
 SYNTAX IscsiDigestMethod
 MAX-ACCESS read-only
 STATUS current
 DESCRIPTION
 "This object identifies the iSCSI header
 digest scheme in use within this connection."
 ::= { iscsiConnectionAttributesEntry 12 }

iscsiCxnDataIntegrity OBJECT-TYPE
 SYNTAX IscsiDigestMethod
 MAX-ACCESS read-only
 STATUS current
 DESCRIPTION
 "This object identifies the iSCSI data
 digest scheme in use within this connection."
 ::= { iscsiConnectionAttributesEntry 13 }

iscsiCxnRecvMarker OBJECT-TYPE
 SYNTAX TruthValue
 MAX-ACCESS read-only

STATUS deprecated

Bakke, et al.

Expires January 4, 2012

[Page 66]

DESCRIPTION

"This object indicates whether or not this connection is receiving markers in its incoming data stream."

REFERENCE

"[[iSCSI-CONS](#)], 13.25 Obsoleted Keys."

::= { iscsiConnectionAttributesEntry 14 }

iscsiCxnSendMarker OBJECT-TYPE

SYNTAX TruthValue

MAX-ACCESS read-only

STATUS deprecated

DESCRIPTION

"This object indicates whether or not this connection is inserting markers in its outgoing data stream."

REFERENCE

"[[iSCSI-CONS](#)], 13.25 Obsoleted Keys."

::= { iscsiConnectionAttributesEntry 15 }

iscsiCxnVersionActive OBJECT-TYPE

SYNTAX Unsigned32 (0..255)

MAX-ACCESS read-only

STATUS current

DESCRIPTION

"Active version number of the iSCSI specification negotiated on this connection."

REFERENCE

"[RFC 3720, Section 10.12](#), Login Request"

::= { iscsiConnectionAttributesEntry 16 }

-- *****

-- Notifications

iscsiTgtLoginFailure NOTIFICATION-TYPE

OBJECTS {

iscsiTgtLoginFailures,
iscsiTgtLastFailureType,
iscsiTgtLastIntrFailureName,
iscsiTgtLastIntrFailureAddrType,
iscsiTgtLastIntrFailureAddr

}

STATUS current

DESCRIPTION

"Sent when a login is failed by a target."

To avoid sending an excessive number of notifications due to multiple errors counted, an SNMP agent implementing this notification SHOULD NOT send more than 3 notifications of this type in any 10-second time period."

`::= { iscsiNotifications 1 }`

iscsiIntrLoginFailure NOTIFICATION-TYPE

OBJECTS {

iscsiIntrLoginFailures,
iscsiIntrLastFailureType,
iscsiIntrLastTgtFailureName,
iscsiIntrLastTgtFailureAddrType,
iscsiIntrLastTgtFailureAddr

}

STATUS current

DESCRIPTION

"Sent when a login is failed by an initiator.

To avoid sending an excessive number of notifications due to multiple errors counted, an SNMP agent implementing this notification SHOULD NOT send more than 3 notifications of this type in any 10-second time period."

::= { iscsiNotifications 2 }

iscsiInstSessionFailure NOTIFICATION-TYPE

OBJECTS {

iscsiInstSsnFailures,
iscsiInstLastSsnFailureType,
iscsiInstLastSsnRmtNodeName

}

STATUS current

DESCRIPTION

"Sent when an active session is failed by either the initiator or the target.

To avoid sending an excessive number of notifications due to multiple errors counted, an SNMP agent implementing this notification SHOULD NOT send more than 3 notifications of this type in any 10-second time period."

::= { iscsiNotifications 3 }

-- *****

-- Conformance Statements

iscsiCompliances OBJECT IDENTIFIER ::= { iscsiConformance 1 }

iscsiGroups OBJECT IDENTIFIER ::= { iscsiConformance 2 }

iscsiInstanceAttributesGroup OBJECT-GROUP

OBJECTS {

iscsiInstDescr,
iscsiInstVersionMin,
iscsiInstVersionMax,
iscsiInstVendorID,


```
        iscsiInstVendorVersion,
        iscsiInstPortalNumber,
        iscsiInstNodeNumber,
        iscsiInstSessionNumber,
        iscsiInstSsnFailures,
        iscsiInstLastSsnFailureType,
        iscsiInstLastSsnRmtNodeName,
        iscsiInstDiscontinuityTime,
        iscsiInstXNodeArchitecture
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about iSCSI
        instances."
 ::= { iscsiGroups 1 }

iscsiInstanceSsnErrorStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiInstSsnDigestErrors,
        iscsiInstSsnCxnTimeoutErrors,
        iscsiInstSsnFormatErrors
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about
        errors that have caused a session failure for an
        iSCSI instance."
 ::= { iscsiGroups 2 }

iscsiPortalAttributesGroup OBJECT-GROUP
    OBJECTS {
        iscsiPortalRowStatus,
        iscsiPortalStorageType,
        iscsiPortalRoles,
        iscsiPortalAddrType,
        iscsiPortalAddr,
        iscsiPortalProtocol,
        iscsiPortalMaxRecvDataSegLength,
        iscsiPortalPrimaryHdrDigest,
        iscsiPortalPrimaryDataDigest,
        iscsiPortalSecondaryHdrDigest,
        iscsiPortalSecondaryDataDigest,
        iscsiPortalRecvMarker
    }
    STATUS deprecated
    DESCRIPTION
        "A collection of objects providing information about
        the transport protocol endpoints of the local targets.
```

This object group is deprecated because the marker key

Bakke, et al.

Expires January 4, 2012

[Page 69]

is obsolete."

REFERENCE

"[[iSCSI-CONS](#)], 13.25 Obsoleted Keys."

::= { iscsiGroups 3 }

iscsiTgtPortalAttributesGroup OBJECT-GROUP

OBJECTS {

iscsiTgtPortalPort,
iscsiTgtPortalTag

}

STATUS current

DESCRIPTION

"A collection of objects providing information about
the transport protocol endpoints of the local targets."

::= { iscsiGroups 4 }

iscsiIntrPortalAttributesGroup OBJECT-GROUP

OBJECTS {

iscsiIntrPortalTag

}

STATUS current

DESCRIPTION

"An object providing information about
the portal tags used by the local initiators."

::= { iscsiGroups 5 }

iscsiNodeAttributesGroup OBJECT-GROUP

OBJECTS {

iscsiNodeName,
iscsiNodeAlias,
iscsiNodeRoles,
iscsiNodeTransportType,
iscsiNodeInitialR2T,
iscsiNodeImmediateData,
iscsiNodeMaxOutstandingR2T,
iscsiNodeFirstBurstLength,
iscsiNodeMaxBurstLength,
iscsiNodeMaxConnections,
iscsiNodeDataSequenceInOrder,
iscsiNodeDataPDUInOrder,
iscsiNodeDefaultTime2Wait,
iscsiNodeDefaultTime2Retain,
iscsiNodeErrorRecoveryLevel,
iscsiNodeDiscontinuityTime,
iscsiNodeStorageType

}

STATUS current

DESCRIPTION

"A collection of objects providing information about all

Bakke, et al.

Expires January 4, 2012

[Page 70]

```
        local targets."
 ::= { iscsiGroups 6 }

iscsiTargetAttributesGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtLoginFailures,
        iscsiTgtLastFailureTime,
        iscsiTgtLastFailureType,
        iscsiTgtLastIntrFailureName,
        iscsiTgtLastIntrFailureAddrType,
        iscsiTgtLastIntrFailureAddr
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        local targets."
 ::= { iscsiGroups 7 }

iscsiTargetLoginStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtLoginAccepts,
        iscsiTgtLoginOtherFails,
        iscsiTgtLoginRedirects,
        iscsiTgtLoginAuthorizeFails,
        iscsiTgtLoginAuthenticateFails,
        iscsiTgtLoginNegotiateFails
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        login attempts by remote initiators to local targets."
 ::= { iscsiGroups 8 }

iscsiTargetLogoutStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtLogoutNormals,
        iscsiTgtLogoutOthers
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        logout events between remote initiators and local targets."
 ::= { iscsiGroups 9 }

iscsiTargetAuthGroup OBJECT-GROUP
    OBJECTS {
        iscsiTgtAuthRowStatus,
        iscsiTgtAuthStorageType,
```

iscsiTgtAuthIdentity

Bakke, et al.

Expires January 4, 2012

[Page 71]

```
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        remote initiators that are authorized to connect to local
        targets."
 ::= { iscsiGroups 10 }

iscsiInitiatorAttributesGroup OBJECT-GROUP
    OBJECTS {
        iscsiIntrLoginFailures,
        iscsiIntrLastFailureTime,
        iscsiIntrLastFailureType,
        iscsiIntrLastTgtFailureName,
        iscsiIntrLastTgtFailureAddrType,
        iscsiIntrLastTgtFailureAddr
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about
        all local initiators."
 ::= { iscsiGroups 11 }

iscsiInitiatorLoginStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiIntrLoginAcceptRsps,
        iscsiIntrLoginOtherFailRsps,
        iscsiIntrLoginRedirectRsps,
        iscsiIntrLoginAuthFailRsps,
        iscsiIntrLoginAuthenticateFails,
        iscsiIntrLoginNegotiateFails,
        iscsiIntrLoginAuthorizeFails
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        login attempts by local initiators to remote targets."
 ::= { iscsiGroups 12 }

iscsiInitiatorLogoutStatsGroup OBJECT-GROUP
    OBJECTS {
        iscsiIntrLogoutNormals,
        iscsiIntrLogoutOthers
    }
    STATUS current
    DESCRIPTION
        "A collection of objects providing information about all
        logout events between local initiators and remote targets."
```

```
::= { iscsiGroups 13 }
```

iscsiInitiatorAuthGroup OBJECT-GROUP**OBJECTS {**

iscsiIntrAuthRowStatus,
iscsiIntrAuthStorageType,
iscsiIntrAuthIdentity

}**STATUS current****DESCRIPTION**

"A collection of objects providing information about all
remote targets that are initiators of the local system
that they are authorized to access."

::= { iscsiGroups 14 }**iscsiSessionAttributesGroup OBJECT-GROUP****OBJECTS {**

iscsiSsnDirection,
iscsiSsnInitiatorName,
iscsiSsnTargetName,
iscsiSsnTSIH,
iscsiSsnISID,
iscsiSsnInitiatorAlias,
iscsiSsnTargetAlias,
iscsiSsnInitialR2T,
iscsiSsnImmediateData,
iscsiSsnType,
iscsiSsnMaxOutstandingR2T,
iscsiSsnFirstBurstLength,
iscsiSsnMaxBurstLength,
iscsiSsnConnectionNumber,
iscsiSsnAuthIdentity,
iscsiSsnDataSequenceInOrder,
iscsiSsnDataPDUInOrder,
iscsiSsnErrorRecoveryLevel,
iscsiSsnDiscontinuityTime,
iscsiSsnProtocolLevel,
iscsiSsnTaskReporting

}**STATUS current****DESCRIPTION**

"A collection of objects providing information applicable to
all sessions."

::= { iscsiGroups 15 }**iscsiSessionPDUStatsGroup OBJECT-GROUP****OBJECTS {**

iscsiSsnCmdPDUs,
iscsiSsnRspPDUs

}

Bakke, et al.

Expires January 4, 2012

[Page 73]

STATUS current

DESCRIPTION

"A collection of objects providing information about PDU
traffic for each session."

::= { iscsiGroups 16 }

iscsiSessionOctetStatsGroup OBJECT-GROUP

OBJECTS {

iscsiSsnTxDataOctets,
iscsiSsnRxDataOctets

}

STATUS current

DESCRIPTION

"A collection of objects providing information about octet
traffic for each session using a Counter64 data type."

::= { iscsiGroups 17 }

iscsiSessionLCOctetStatsGroup OBJECT-GROUP

OBJECTS {

iscsiSsnLCTxDataOctets,
iscsiSsnLCRxDataOctets

}

STATUS current

DESCRIPTION

"A collection of objects providing information about octet
traffic for each session using a Counter32 data type."

::= { iscsiGroups 18 }

iscsiSessionCxnErrorStatsGroup OBJECT-GROUP

OBJECTS {

iscsiSsnCxnDigestErrors,
iscsiSsnCxnTimeoutErrors

}

STATUS current

DESCRIPTION

"A collection of objects providing information about connection
errors for all sessions."

::= { iscsiGroups 19 }

iscsiConnectionAttributesGroup OBJECT-GROUP

OBJECTS {

iscsiCxnCid,
iscsiCxnState,
iscsiCxnProtocol,
iscsiCxnAddrType,
iscsiCxnLocalAddr,
iscsiCxnLocalPort,
iscsiCxnRemoteAddr,

iscsiCxnRemotePort,

```
    iscsiCxnMaxRecvDataSegLength,  
    iscsiCxnMaxXmitDataSegLength,  
    iscsiCxnHeaderIntegrity,  
    iscsiCxnDataIntegrity,  
    iscsiCxnRecvMarker,  
    iscsiCxnSendMarker,  
    iscsiCxnVersionActive  
}
```

STATUS deprecated

DESCRIPTION

"A collection of objects providing information about all connections used by all sessions.

This object group is deprecated because the marker key is obsolete."

REFERENCE

"[[iSCSI-CONS](#)], 13.25 Obsoleted Keys."

```
::= { iscsiGroups 20 }
```

iscsiTgtLgnNotificationsGroup NOTIFICATION-GROUP

```
    NOTIFICATIONS {  
        iscsiTgtLoginFailure  
    }
```

STATUS current

DESCRIPTION

"A collection of notifications that indicate a login failure from a remote initiator to a local target."

```
::= { iscsiGroups 21 }
```

iscsiIntrLgnNotificationsGroup NOTIFICATION-GROUP

```
    NOTIFICATIONS {  
        iscsiIntrLoginFailure  
    }
```

STATUS current

DESCRIPTION

"A collection of notifications that indicate a login failure from a local initiator to a remote target."

```
::= { iscsiGroups 22 }
```

iscsiSsnFlrNotificationsGroup NOTIFICATION-GROUP

```
    NOTIFICATIONS {  
        iscsiInstSessionFailure  
    }
```

STATUS current

DESCRIPTION

"A collection of notifications that indicate session failures occurring after login."

```
::= { iscsiGroups 23 }
```

iscsiPortalAttributesGroupV2 OBJECT-GROUP

Bakke, et al.

Expires January 4, 2012

[Page 75]

OBJECTS {

iscsiPortalRowStatus,
iscsiPortalStorageType,
iscsiPortalRoles,
iscsiPortalAddrType,
iscsiPortalAddr,
iscsiPortalProtocol,
iscsiPortalMaxRecvDataSegLength,
iscsiPortalPrimaryHdrDigest,
iscsiPortalPrimaryDataDigest,
iscsiPortalSecondaryHdrDigest,
iscsiPortalSecondaryDataDigest

}

STATUS current

DESCRIPTION

"A collection of objects providing information about
the transport protocol endpoints of the local targets."

::= { iscsiGroups 24 }

iscsiConnectionAttributesGroupV2 OBJECT-GROUP

OBJECTS {

iscsiCxnCid,
iscsiCxnState,
iscsiCxnProtocol,
iscsiCxnAddrType,
iscsiCxnLocalAddr,
iscsiCxnLocalPort,
iscsiCxnRemoteAddr,
iscsiCxnRemotePort,
iscsiCxnMaxRecvDataSegLength,
iscsiCxnMaxXmitDataSegLength,
iscsiCxnHeaderIntegrity,
iscsiCxnDataIntegrity,
iscsiCxnVersionActive

}

STATUS current

DESCRIPTION

"A collection of objects providing information about all
connections used by all sessions."

::= { iscsiGroups 25 }

_ _*****

iscsiComplianceV1 MODULE-COMPLIANCE

STATUS deprecated

DESCRIPTION

"Initial version of compliance statement based on

initial version of this MIB module.

Bakke, et al.

Expires January 4, 2012

[Page 76]

If an implementation can be both a target and an initiator, all groups are mandatory.

This module compliance is deprecated because the marker keys are obsolete."

REFERENCE

"[[iSCSI-CONS](#)], 13.25 Obsoleted Keys."

MODULE -- this module

MANDATORY-GROUPS {

iscsiInstanceAttributesGroup,
iscsiInstanceSsnErrorStatsGroup,
iscsiPortalAttributesGroup,
iscsiNodeAttributesGroup,
iscsiSessionAttributesGroup,
iscsiSessionPDUStatsGroup,
iscsiSessionCxnErrorStatsGroup,
iscsiConnectionAttributesGroup,
iscsiSsnFlrNotificationsGroup

}

-- Conditionally mandatory groups depending on the ability
-- to support Counter64 data types and/or to provide counter
-- information to SNMPv1 applications.

GROUP iscsiSessionOctetStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that can support Counter64 data types."

GROUP iscsiSessionLCOctetStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that provide information to SNMPv1-only applications;
this includes agents that cannot support Counter64
data types."

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI target facilities.

GROUP iscsiTgtPortalAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that have iSCSI target facilities."

OBJECT iscsiPortalMaxRecvDataSegLength

MIN-ACCESS read-only

DESCRIPTION

"Write access is not required."

Bakke, et al.

Expires January 4, 2012

[Page 77]

OBJECT iscsiNodeStorageType

MIN-ACCESS read-only

DESCRIPTION

"Write access is not required; an implementation may choose to allow this object to be set to 'volatile' or 'nonVolatile'."

GROUP iscsiTargetAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetLoginStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetLogoutStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTgtLgnNotificationsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetAuthGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI initiator facilities.

GROUP iscsiIntrPortalAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorLoginStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations

that have iSCSI initiator facilities."

GROUP iscsiInitiatorLogoutStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that have iSCSI initiator facilities."

GROUP iscsiIntrLgnNotificationsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that have iSCSI initiator facilities."

GROUP iscsiInitiatorAuthGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations
that have iSCSI initiator facilities."

OBJECT iscsiNodeErrorRecoveryLevel

SYNTAX Unsigned32 (0..2)

DESCRIPTION

"Only values 0-2 are defined at present."

::= { iscsiCompliances 1 }

iscsiComplianceV2 MODULE-COMPLIANCE

STATUS current

DESCRIPTION

"Initial version of compliance statement based on
initial version of this MIB module.

If an implementation can be both a target and an
initiator, all groups are mandatory."

MODULE -- this module

MANDATORY-GROUPS {

iscsiInstanceAttributesGroup,
iscsiInstanceSsnErrorStatsGroup,
iscsiPortalAttributesGroupV2,
iscsiNodeAttributesGroup,
iscsiSessionAttributesGroup,
iscsiSessionPDUStatsGroup,
iscsiSessionCxnErrorStatsGroup,
iscsiConnectionAttributesGroupV2,
iscsiSsnFlrNotificationsGroup

}

-- Conditionally mandatory groups depending on the ability
-- to support Counter64 data types and/or to provide counter
-- information to SNMPv1 applications.

GROUP iscsiSessionOctetStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that can support Counter64 data types."

GROUP iscsiSessionLCOctetStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that provide information to SNMPv1-only applications; this includes agents that cannot support Counter64 data types."

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI target facilities.

GROUP iscsiTgtPortalAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

OBJECT iscsiPortalMaxRecvDataSegLength

MIN-ACCESS read-only

DESCRIPTION

"Write access is not required."

OBJECT iscsiNodeStorageType

MIN-ACCESS read-only

DESCRIPTION

"Write access is not required; an implementation may choose to allow this object to be set to 'volatile' or 'nonVolatile'."

GROUP iscsiTargetAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetLoginStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetLogoutStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTgtLgnNotificationsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

GROUP iscsiTargetAuthGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI target facilities."

-- Conditionally mandatory groups to be included with
-- the mandatory groups when the implementation has
-- iSCSI initiator facilities.

GROUP iscsiIntrPortalAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorAttributesGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorLoginStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorLogoutStatsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiIntrLgnNotificationsGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

GROUP iscsiInitiatorAuthGroup

DESCRIPTION

"This group is mandatory for all iSCSI implementations that have iSCSI initiator facilities."

OBJECT iscsiNodeErrorRecoveryLevel

SYNTAX Unsigned32 (0..2)

DESCRIPTION

"Only values 0-2 are defined at present."

::= { iscsiCompliances 2 }

END

8. Security Considerations

There are a number of management objects defined in this MIB module with a MAX-ACCESS clause of read-write and/or read-create. Such objects may be considered sensitive or vulnerable in some network environments. The support for SET operations in a non-secure environment without proper protection can have a negative effect on network operations. These are the tables and objects and their sensitivity/vulnerability:

iscsiPortalAttributesTable, iscsiTgtPortalAttributesTable, and iscsiIntrPortalAttributesTable can be used to add or remove IP addresses to be used by iSCSI.

iscsiTgtAuthAttributesTable entries can be added or removed, to allow or disallow access to a target by an initiator.

Some of the readable objects in this MIB module (i.e., objects with a MAX-ACCESS other than not-accessible) may be considered sensitive or vulnerable in some network environments. It is thus important to control even GET and/or NOTIFY access to these objects and possibly to even encrypt the values of these objects when sending them over the network via SNMP. These are the tables and objects and their sensitivity/vulnerability:

iscsiNodeAttributesTable, iscsiTargetAttributesTable, and iscsiTgtAuthorization can be used to glean information needed to make connections to the iSCSI targets this module represents. However, it is the responsibility of the initiators and targets involved to authenticate each other to ensure that an inappropriately advertised or discovered initiator or target does not compromise their security. These issues are discussed in [\[RFC3720\]](#).

SNMP versions prior to SNMPv3 did not include adequate security. Even if the network itself is secure (for example by using IPsec), even then, there is no control as to who on the secure network is allowed to access and GET/SET (read/change/create/delete) the objects in this MIB module.

It is RECOMMENDED that implementers consider the security features as provided by the SNMPv3 framework (see [\[RFC3410\]](#), [section 8](#)), including full support for SNMPv3 cryptographic mechanisms (for authentication and privacy).

Further, deployment of SNMP versions prior to SNMPv3 is NOT

RECOMMENDED. Instead, it is RECOMMENDED to deploy SNMPv3 and to enable cryptographic security. It is then a customer/operator responsibility to ensure that the SNMP entity giving access to an instance of this MIB module is properly configured to give access to the objects only to those principals (users) that have legitimate rights to indeed GET or SET (change/create/delete) them.

9. IANA Considerations

The MIB module in this document uses the following IANA-assigned OBJECT IDENTIFIER values recorded in the SMI Numbers registry:

Descriptor	OBJECT IDENTIFIER value
-----	-----
iscsiMibModule	{ mib-2 142 }

10. References

10.1. Normative References

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", [BCP 14](#), [RFC 2119](#), March 1997.
- [RFC2578] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Structure of Management Information Version 2 (SMIv2)", STD 58, [RFC 2578](#), April 1999.
- [RFC2579] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Textual Conventions for SMIv2", STD 58, [RFC 2579](#), April 1999.
- [RFC2580] McCloghrie, K., Perkins, D., and J. Schoenwaelder, "Conformance Statements for SMIv2", STD 58, [RFC 2580](#), April 1999.
- [RFC3411] Harrington, D., Presuhn, R., and B. Wijnen, "An Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks", STD 62, [RFC 3411](#), December 2002.
- [RFC3720] Satran, J., Meth, K., Sapuntzakis, C., Chadalapaka, M., and E. Zeidner, "Internet Small Computer Systems Interface (iSCSI)", [RFC 3720](#), March 2004.
- [RFC4001] Daniele, M., Haberman, B., Routhier, S., and J.

Schoenwaelder, "Textual Conventions for Internet Network Addresses", [RFC 4001](#), February 2005.

[RFC4545] Bakke, M. and J. Muchow, "Definitions of Managed Objects for IP Storage User Identity Authorization", [RFC 4545](#), May 2006.

[iSCSI-CONS] Chadalapaka, M., Satran, J., and K. Meth, "iSCSI Protocol (Consolidated)", [draft-ietf-storm-iscsi-cons-02.txt](#) (work in progress), March 2011

[iSCSI-SAM] Knight, F., Chadalapaka, M., "Internet Small Computer Systems Interface (iSCSI) Update", [draft-ietf-storm-iscsi-sam-02.txt](#) (work in progress), March 2011

10.2. Informative References

[RFC3410] Case, J., Mundy, R., Partain, D., and B. Stewart, "Introduction and Applicability Statements for Internet-Standard Management Framework", [RFC 3410](#), December 2002.

[RFC4022] Raghunarayan, R., "Management Information Base for the Transmission Control Protocol (TCP)", [RFC 4022](#), March 2005.

[RFC4455] Hallak-Stamler, M., Bakke, M., Lederman, Y., Krueger, M., and K. McCloghrie, "Definition of Managed Objects for Small Computer System Interface (SCSI) Entities", [RFC 4455](#), April 2006.

[RFC4544] Bakke, M., J. Muchow, M. Krueger and T. McSweeney, "Definitions of Managed Objects for iSCSI", [RFC 4544](#), May 2006.

11. Acknowledgments

In addition to the authors, several people contributed to the development of this MIB module. Thanks especially to those who took the time to participate in our weekly conference calls to build our requirements, object models, table structures, and attributes: John Hufferd, Tom McSweeney (IBM), Kevin Gibbons (Nishan Systems), Chad Gregory (Intel), Jack Harwood (EMC), Hari Mudaliar (Adaptec), Ie Wei Njoo (Agilent), Lawrence Lamers (SAN Valley), Satish Mali (Stonefly Networks), and William Terrell (Troika).

Special thanks to Tom McSweeney, Ie Wei Njoo, and Kevin Gibbons, who wrote the descriptions for many of the tables and attributes in this MIB module, to Ayman Ghanem for finding and suggesting changes for many problems in this module, and to Keith McCloghrie for serving as advisor to the team.

Thanks to David Black (EMC) and Tom Talpey (Microsoft) for their valuable inputs.

Authors' Address

Mark Bakke
Cisco Systems, Inc
7900 International Drive, Suite 400
Bloomington, MN
USA 55425

EMail: mbakke@cisco.com

Prakash Venkatesen
HCL Technologies Ltd.
50-53, Greams Road,
Chennai - 600006
India

EMail: prakashvn@hcl.com

Authors of [RFC 4544](#):

Mark Bakke
Cisco Systems, Inc
7900 International Drive, Suite 400
Bloomington, MN
USA 55425

EMail: mbakke@cisco.com

Marjorie Krueger
Hewlett-Packard
Networked Storage Architecture
Networked Storage Solutions Org.

8000 Foothills Blvd.
Roseville, CA
USA 95747

EMail: marjorie_krueger@hp.com

Tom McSweeney
IBM Corporation
600 Park Offices Drive
Research Triangle Park, NC
USA 27709

EMail: tommcs@us.ibm.com

James Muchow
Qlogic Corp.
6321 Bury Drive
Eden Prairie, MN
USA 55346

EMail: james.muchow@qlogic.com