

Network Working Group
Internet-Draft
Intended status: Standards Track
Expires: September 26, 2013

G. Zorn
Network Zen
R. Schott
Deutsche Telekom
Q. Wu, Ed.
R. Huang
Huawei
March 25, 2013

**RTP Control Protocol (RTCP) Extended Report (XR) Blocks for Summary
Statistics Metrics Reporting
draft-ietf-xrblock-rtcp-xr-summary-stat-11**

Abstract

This document defines three RTP Control Protocol (RTCP) Extended Report (XR) Blocks that allow the reporting of loss, duplication and discard summary statistics metrics in a range of RTP applications.

Status of this Memo

This Internet-Draft is submitted in full conformance with the provisions of [BCP 78](#) and [BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF). Note that other groups may also distribute working documents as Internet-Drafts. The list of current Internet-Drafts is at <http://datatracker.ietf.org/drafts/current/>.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

This Internet-Draft will expire on September 26, 2013.

Copyright Notice

Copyright (c) 2013 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to [BCP 78](#) and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect to this document. Code Components extracted from this document must

include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

Table of Contents

1.	Introduction	4
1.1.	Summary Statistics Metrics	4
1.2.	RTCP and RTCP XR Reports	4
1.3.	Performance Metrics Framework	4
1.4.	Applicability	4
2.	Terminology	5
2.1.	Standards Language	5
3.	Transport Related End System Metrics	5
3.1.	Burst/Gap Loss Summary Statistics Metrics Block	5
3.1.1.	Report Block Structure	6
3.1.2.	Definition of Fields in Loss Summary Statistics Block	6
3.2.	Burst/Gap Discard Summary Statistics Metrics Block	8
3.2.1.	Report Block Structure	9
3.2.2.	Definition of Fields in Burst/Gap Discard Summary Statistics Block	9
4.	Application Level Metrics	11
4.1.	Frame Impairment Statistics Summary Metrics Block	11
4.1.1.	Report Block Structure	11
4.1.2.	Definition of Fields in Frame Impairment Summary Statistics Block	12
5.	SDP Signaling	13
5.1.	SDP rtcp-xr-attrib Attribute Extension	13
5.2.	Offer/Answer Usage	14
6.	IANA Considerations	14
6.1.	New RTCP XR Block Type values	14
6.2.	New RTCP XR SDP Parameters	14
6.3.	Contact information for registrations	15
7.	Security Considerations	15
8.	Acknowledgements	15
9.	References	15
9.1.	Normative References	15
9.2.	Informative References	16
Appendix A.	Metrics represented using RFC6390 Template	16
Appendix B.	Change Log	22
B.1.	draft-ietf-xrblock-rtcp-xr-summary-stat-11	22
B.2.	draft-ietf-xrblock-rtcp-xr-summary-stat-10	22
B.3.	draft-ietf-xrblock-rtcp-xr-summary-stat-09	22
B.4.	draft-ietf-xrblock-rtcp-xr-summary-stat-08	22
B.5.	draft-ietf-xrblock-rtcp-xr-summary-stat-07	22
B.6.	draft-ietf-xrblock-rtcp-xr-summary-stat-06	22

B.7. <u>draft-ietf-xrblock-rtcp-xr-summary-stat-05</u>	22
Authors' Addresses	23

1. Introduction

1.1. Summary Statistics Metrics

This draft defines three new block types to augment those defined in [\[RFC3611\]](#) for use in a range of RTP applications.

- o Burst/Gap Loss Summary Statistics Metrics Block
- o Burst/Gap Discard Summary Statistics Metrics Block
- o Frame Impairment Statistics Summary Metrics Block

The first two block types support the reporting of burst gap loss/discard summary statistics including packet loss/discard proportion, mean and variance and belong to the class of transport-related end system metrics defined in [\[RFC6792\]](#). These two blocks are intended to be used in conjunction with information from the Burst Gap Loss Metrics Block [\[BGLOSS\]](#) or Burst Gap Discard Metrics Block [\[BGDISCARD\]](#), and on which these two blocks therefore depend. The metrics in the Burst Gap Loss Metrics block or Burst Gap Discard Metrics Block are consistent with the definitions of Burst, Gap, Loss and Discard in RTCP XR [\[RFC3611\]](#).

The third block supports the reporting of detailed video statistics for each frame type, including the number of frames received, lost and discarded of each frame type in the Group of Pictures (GOP) and additional data allowing the calculation of statistical parameters (e.g., the proportion of each frame type impaired by packet loss and discard). The metrics defined in this block belong to the class of application layer metrics defined in [\[RFC6792\]](#).

1.2. RTCP and RTCP XR Reports

The use of RTCP for reporting is defined in [\[RFC3550\]](#). [\[RFC3611\]](#) defined an extensible structure for reporting using an RTCP Extended Report (XR). This document defines a new Extended Report block for use with [\[RFC3550\]](#) and [\[RFC3611\]](#).

1.3. Performance Metrics Framework

The RTP Monitoring Architectures [\[RFC6792\]](#) provides guideline for reporting block format using RTCP XR. Metrics described in this draft are in accordance with the guidelines in [\[RFC6792\]](#).

1.4. Applicability

These metrics are applicable to a wide range of RTP applications and reflect transient IP problems that affect user experience. They can be used to form an accurate assessment of users' quality of

experience and influence sender strategies to mitigate the problem.

2. Terminology

2.1. Standards Language

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [RFC 2119](#) [[RFC2119](#)].

In addition, the following terms are defined:

Frame Type

In many cases, a video frame is compressed using different algorithms. Frame type is used to identify different algorithms for video frames. Two frame Types used in the different video algorithms are the Key frame and Derived frames. The Key frame is independently coded without prediction from other pictures and used as a reference frame for predicting other pictures. Derived frames are predicatively coded and derived from a Key frame using a prediction algorithm. If there is no video image compression, all frames are Key Frames.

3. Transport Related End System Metrics


3.1. Burst/Gap Loss Summary Statistics Metrics Block

This Block extends packet loss and discard metrics defined in [section 4.7.1 of RFC3611](#). The metrics described here are intended to be used as described in this section, in conjunction with information from the Measurement Information block [[RFC6776](#)] (which MUST be present in the same RTCP packet as the Burst/Gap Loss block) and also with the metric "cumulative number of packets lost" provided in standard RTCP [[RFC3550](#)]. Instances of this Metrics Block refer by Synchronization source (SSRC) to the separate auxiliary Measurement Information block [[RFC6776](#)] which describes measurement periods in use (see [[RFC6776](#)] [section 4.2](#)). This Metrics Block relies on the measurement period in the Measurement Information block indicating the span of the report and SHOULD be sent in the same compound RTCP packet as the measurement information block. If the measurement period is not received in the same compound RTCP packet as this Metrics Block, this metrics block MUST be discarded.

The metrics carried in this Metrics Block provide information

relevant to statistical parameters, including burst loss rate, gap loss rate, burst duration mean, burst duration variance and are measured at the receiving end of the RTP stream using burst gap loss metrics defined in [\[BGLSS\]](#) and other information which is sent together with this report block.

3.1.1. Report Block Structure



3.1.2. Definition of Fields in Loss Summary Statistics Block

Block Type (BT): 8 bits

Burst/Gap Loss Summary Statistics Block is identified by the constant <BGLSS>.

Interval Metric Flag (I): 2 bits

This field is used to indicate whether the Burst/Gap Loss Summary Statistics metrics are Sampled, Interval or Cumulative metrics:

I=10: Interval Duration - the reported value applies to the most recent measurement interval duration between successive metrics reports.

I=11: Cumulative Duration - the reported value applies to the accumulation period characteristic of cumulative measurements.

I=01: Sampled Value - the reported value is a sampled instantaneous value.

In this document, the value I=00 is the reserved value and MUST NOT be used.

Reserved: 6 bits

This field is reserved for future definition. In the absence of such a definition, the bits in this field MUST be set to zero and ignored by the receiver (See [RFC6709 section 4.2](#)).

Block Length: 16 bits

The constant 3, in accordance with the definition of this field in [Section 3 of RFC 3611](#) [[RFC3611](#)].

SSRC of Source: 32 bits

As defined in [Section 4.1 of RFC3611](#) [[RFC3611](#)].

Burst Loss Rate: 16 bits

The fraction of packets lost during bursts since the beginning of reception, expressed as a fixed point number with the binary point immediately after the left-most bit. This value is calculated by dividing Packets Lost in Bursts by Total Packets Expected in Bursts, multiplying the result of the division by 32768 (0x8000), and keeping only the integer part. The maximum value is thus 0x8000. Representing this as a formula:

$$\text{integer-part} ((\text{Packets Lost in Bursts} / \text{Total Packets Expected in Bursts}) * 0x8000)$$

If the measurement is unavailable, the value 0xFFFF MUST be reported.

Gap Loss Rate: 16 bits

The fraction of packets lost during gaps since the beginning of reception expressed as a fixed point number with the binary point immediately after the left-most bit. This value is calculated by dividing the difference between number of packets lost and Packets lost in Bursts by the difference between Packets Expected and Total Packets expected in Bursts, multiplying the result of the division by 32768 (0x8000), and keeping only the integer part. The maximum value is thus 0x8000. Representing this as a formula:

$$\text{integer-part} ((\text{number of packets lost} - \text{Packets Lost in Bursts}) / (\text{Packets Expected} - \text{Total Packets expected in Bursts}) * 0x8000)$$

where "number of packets lost" is obtained from standard RTCP [[RFC3550](#)] and Packets Expected is calculated as the difference between "extended last sequence number" and "extended first sequence number" (Interval or Cumulative) provided in the Measurement Identity and Information block [[RFC6776](#)].

If the measurement is unavailable, the value 0xFFFF MUST be reported.

Note that if the metric is to be calculated on an Interval basis, a difference must be taken between the current and preceding values of "cumulative number of packets lost" in RTCP, to obtain the "number of packets lost" for the reporting interval.

Burst Duration Mean:16bits

The mean burst duration is obtained as the quotient:

$$\text{mean} = \text{Sum of Burst Durations} / \text{Number of Bursts}$$

where "Sum of Burst Durations" and "Number of Bursts" is obtained from the RTCP XR Burst/Gap Loss Block [[BGLOSS](#)].

If the measurement is unavailable, the value 0xFFFF MUST be reported.

Burst Duration Variance:16bits

The variance of the burst duration is obtained using the standard result:

$$\text{var} = (\text{Sum of Squares of Burst Durations} - \text{Number of Bursts} * \text{mean}^2) / (\text{Number of Bursts} - 1)$$

where "Sum of Squares of Burst Durations" and "Number of Bursts" is obtained from the RTCP XR Burst/Gap Loss Block [[BGLOSS](#)].

If the measurement is unavailable, the value 0xFFFF MUST be reported.

3.2. Burst/Gap Discard Summary Statistics Metrics Block

This Block extends packet loss and discard metrics defined in [section 4.7.1 of RFC3611](#). The metrics described here are intended to be used as described in this section, in conjunction with information from the Measurement Identity block [[RFC6776](#)] (which MUST be present in the same RTCP packet as the Burst/Gap Discard Summary Statistics block) .

These metrics provide information relevant to statistical parameters, including burst discard rate, gap discard rate and are measured at the receiving end of the RTP stream using burst gap discard metrics defined in [[BGDISCARD](#)] and other information which is sent together with this report block.

Instances of this Metrics Block refer by Synchronization source

(SSRC) to the separate auxiliary Measurement Information block [RFC6776] which describes measurement periods in use (see [RFC6776] [section 4.2](#)). This metrics block relies on the measurement period in the Measurement Information block indicating the span of the report and SHOULD be sent in the same compound RTCP packet as the measurement information block. If the measurement period is not received in the same compound RTCP packet as this Metrics Block, this Metrics Block MUST be discarded.

[3.2.1.](#) Report Block Structure

```

0                               1                               2                               3
0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|      BT=BGDSS      | I |   Reserved   |          block length      |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|                                     SSRC of Source                  |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+
|          Burst Discard Rate      |          Gap Discard Rate      |
+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+--+

```

[3.2.2.](#) Definition of Fields in Burst/Gap Discard Summary Statistics Block

Block Type (BT): 8 bits

Burst/Gap Discard Summary Statistics Block is identified by the constant <BGDSS>.

Interval Metric Flag (I): 2 bits

This field is used to indicate whether the Burst/Gap Discard Summary Statistics metrics are Sampled, Interval or Cumulative metrics:

I=10: Interval Duration - the reported value applies to the most recent measurement interval duration between successive metrics reports.

I=11: Cumulative Duration - the reported value applies to the accumulation period characteristic of cumulative measurements.

I=01: Sampled Value - the reported value is a sampled instantaneous value.

In this document, the value I=00 is the reserved value and MUST NOT be used.

Reserved: 6 bits

This field is reserved for future definition. In the absence of such a definition, the bits in this field MUST be set to zero and ignored by the receiver (See [RFC6709 section 4.2](#)).

Block Length: 16 bits

The constant 2, in accordance with the definition of this field in [Section 3 of RFC 3611](#) [[RFC3611](#)].

SSRC of Source: 32 bits

As defined in [Section 4.1 of RFC3611](#) [[RFC3611](#)].

Burst Discard Rate: 16 bits

The fraction of packets discarded during bursts since the beginning of reception, expressed as a fixed point number with the binary point immediately after the left-most bit. This value is calculated by dividing Packets Discarded in Bursts by Total Packets expected in Bursts, multiplying the result of the division by 32768 (0x8000), and keeping only the integer part, according to the formula:

$$\text{integer-part}((\text{Packets Discarded in Bursts} / \text{Total Packets expected in Bursts}) * 0x8000)$$

If the measurement is unavailable, the value 0xFFFF MUST be reported.

Gap Discard Rate: 16 bits

The fraction of packets discarded during gaps since the beginning of reception expressed as a fixed point number with the binary point immediately after the left-most bit. This value is calculated by dividing the difference between number of packets discarded and Packets Discarded in Bursts by the difference between Packets Expected and Total Packets expected in Bursts, multiplying the result of the division by 32768 (0x8000), and keeping only the integer part. The maximum value is thus 0x8000. Representing this as a formula:

$$\text{integer-part}((\text{number of packets discarded} - \text{Packets Discarded in Bursts}) / (\text{Packets Expected} - \text{Total Packets expected in Bursts}) * 0x8000)$$

where "number of packets discarded" is obtained from the RTCP XR

[illegible]

4.1.2. Definition of Fields in Frame Impairment Summary Statistics Block

Block type (BT): 8 bits

Frame Impairment Statistics Summary Block is identified by the constant <FISS>.

Frame type indicator (T): 1 bit

This field is used to indicate the frame type to be reported. The bit is set to 0 if the full_lost_frames, partial_lost_frames, dup_frames, discarded_frames and Number of frames received fields contain Key frame (reference frame) counts or 1 if they contain Derived frame counts. Note that if both the Key frame and Derivation frame report are sent, they should be sent in the same RTCP compound packet using two Frame Impairment Summary Statistics Blocks.

Reserved: 7 bits

This field is reserved for future definition. In the absence of such a definition, the bits in this field MUST be set to zero and ignored by the receiver (See [RFC6709 section 4.2](#)).

Block Length: 16 bits

The constant 6, in accordance with the definition of this field in [Section 3 of RFC 3611](#) [[RFC3611](#)].

SSRC of Source: 32 bits

As defined in [Section 4.1 of RFC3611](#) [[RFC3611](#)].

begin_seq: 16 bits

As defined in [Section 4.1 of RFC 3611](#) [[RFC3611](#)].

end_seq: 16 bits

As defined in [Section 4.1 of RFC 3611](#) [[RFC3611](#)].

Number of discarded frames (discarded_frames): 32 bits

Number of frames discarded in the above sequence number interval.

Number of duplicate frames (dup_frames): 32 bits

Number of duplicate frames received in the above sequence number interval.

Number of full lost frames (full_lost_frames): 32 bits

A frame is either split across multiple packets or carried in only one packet. If the whole frame or all the packets of the frame is lost, this frame is regarded as one full_lost_frame. The full_lost_frames can be inferred from packet(s) that comprise the frame. The full_lost_frames is equivalent to the number of full lost frames in the above sequence number interval.

Number of partial lost frames (partial_lost_frames): 32 bits

When a frame is split across multiple packets and some packets of the frame are lost, this frame is regarded as one partial_lost_frame. The partial_lost_frames can be inferred from packets that comprise the frame. The value of the partial_lost_frames field is equivalent to the number of partial lost frames in the above sequence number interval.

5. SDP Signaling

[RFC 3611](#) defines the use of SDP (Session Description Protocol) [[RFC4566](#)] for signaling the use of XR blocks. However XR blocks MAY be used without prior signaling (see [section 5 of RFC3611](#)).

5.1. SDP rtcp-xr-attrib Attribute Extension

This section augments the SDP [[RFC4566](#)] attribute "rtcp-xr" defined in [Section 5.1 of RFC 3611](#) by providing three additional values of "xr-format" to signal the use of the report block defined in this document.

```
xr-format = / xr-bglss-block
           / xr-bgdss-block
           / xr-fiss-block
xr-bglss-block= "burst-gap-loss-stat"
xr-bgdss-block = "burst-gap-discard-stat"
xr-fiss-block= "frame-impairment-stat"
```


5.2. Offer/Answer Usage

When SDP is used in offer-answer context, the SDP Offer/Answer usage defined in [[RFC3611](#)] for unilateral "rtcp-xr" attribute parameters applies. For detailed usage of Offer/Answer for unilateral parameter, refer to [section 5.2 of \[RFC3611\]](#).

6. IANA Considerations

New block types for RTCP XR are subject to IANA registration. For general guidelines on IANA considerations for RTCP XR, refer to [RFC 3611](#).

6.1. New RTCP XR Block Type values

This document assigns three new block type value in the "RTP Control Protocol (RTCP) Extended Report (XR) Block Type Registry" :

Name:	BGLSS
Long Name:	Burst/Gap Loss Summary Statistics Block
Value	<BGLSS>
Reference:	Section 3.1
Name:	BGDSS
Long Name:	Burst/Gap Discard Summary Statistics Block
Value	<BGDSS>
Reference:	Section 3.2
Name:	FISS
Long Name:	Frame Impairment Statistics Summary
Value	<FISS>
Reference:	Section 4.1

6.2. New RTCP XR SDP Parameters

This document also registers three new SDP [[RFC4566](#)] parameters for the "rtcp-xr" attribute in the " RTP Control Protocol (RTCP) Extended Report (XR) SDP Parameters Registry ":

- * "burst-gap-loss-stat"
- * "burst-gap-discard-stat"
- * "frame-impairment-stat"

6.3. Contact information for registrations

The contact information for the registrations is:

Qin Wu (sunseawq@huawei.com)
101 Software Avenue, Yuhua District
Nanjing, Jiangsu 210012
China

7. Security Considerations

The new RTCP XR report blocks proposed in this document introduces no new security considerations beyond those described in [RFC 3611](#).

8. Acknowledgements

The authors would like to thank Bill Ver Steeg, David R Oran, Ali Begen, Colin Perkins, Roni Even, Youqing Yang, Wenxiao Yu, Yinliang Hu, Jing Zhao, Ray van Brandenburg, Claire Bi, Dan Romascanu , Morton Jr., Alfred, Klaas Wierenga, Barry Leiba, Robert Sparks, Ralph Droms and Benoit Claise for their valuable comments and suggestions on this document.

9. References

9.1. Normative References

[BGDISCARD]

Clark, A., Huang, R., and W. Wu, "RTP Control Protocol(RTCP) Extended Report (XR) Block for Burst/Gap Discard metric Reporting", [draft-ietf-xrblock-rtcp-xr-burst-gap-discard-08](#) (work in progress), December 2012.

[BGLOSS]

Clark, A., Zhang, S., Zhao, J., and Q. Wu, "RTP Control Protocol (RTCP) Extended Report (XR) Block for Burst/Gap Loss metric Reporting", [draft-ietf-xrblock-rtcp-xr-burst-gap-loss-06](#) (work in progress), December 2012.

[DISCARD]

Clark, A., Zorn, G., and Q. Wu, "RTP Control Protocol (RTCP) Extended Report (XR) Block for Discard Count metric Reporting", [draft-ietf-xrblock-rtcp-xr-discard-09](#) (work in progress), October 2012.

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", [BCP 14](#), [RFC 2119](#), March 1997.
- [RFC3550] Schulzrinne, H., Casner, S., Frederick, R., and V. Jacobson, "RTP: A Transport Protocol for Real-Time Applications", STD 64, [RFC 3550](#), July 2003.
- [RFC3611] Friedman, T., Caceres, R., and A. Clark, "RTP Control Protocol Extended Reports (RTCP XR)", [RFC 3611](#), November 2003.
- [RFC4566] Handley, M., Jacobson, V., and C. Perkins, "SDP: Session Description Protocol", [RFC 4566](#), July 2006.
- [RFC6776] Wu, Q., "Measurement Identity and information Reporting using SDES item and XR Block", [RFC 6776](#), August 2012.

9.2. Informative References

- [RFC6390] Clark, A. and B. Claise, "Guidelines for Considering New Performance Metric Development", [RFC 6390](#), October 2011.
- [RFC6709] Carpenter, B., Aboba, B., and S. Cheshire, "Design Considerations for Protocol Extensions", [RFC 6709](#), September 2012.
- [RFC6792] Hunt, G., Wu, Q., and P. Arden, "Monitoring Architectures for RTP", [RFC 6792](#), November 2012.

[Appendix A](#). Metrics represented using [RFC6390](#) Template

RFC EDITOR NOTE: please change XXXX in [RFCXXXX] by the new RFC number, when assigned.

a. Burst Loss Rate Metric

- * Metric Name: RTP Burst Loss Rate
- * Metric Description: The fraction of packets lost during bursts since the beginning of reception for RTP traffic.
- * Method of Measurement or Calculation: See [section 3.1.2](#), Burst Loss Rate definition [RFCXXXX].
- * Units of Measurement: See [section 3.1.2](#), Burst Loss Rate definition [RFCXXXX].

- * Measurement Point(s) with Potential Measurement Domain: See [section 3.1](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 3.1](#), 1st paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

b. Gap Loss Rate Metric

- * Metric Name: RTP Gap Loss Rate
- * Metric Description: The fraction of packets lost during gaps since the beginning of reception for RTP traffic.
- * Method of Measurement or Calculation: See [section 3.1.2](#), Gap Loss Rate definition [RFCXXXX].
- * Units of Measurement: See [section 3.1.2](#), Gap Loss Rate definition [RFCXXXX].
- * Measurement Point(s) with Potential Measurement Domain: See [section 3.1](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 3.1](#), 1st paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

c. Burst duration Mean Metric

- * Metric Name: RTP Burst duration Mean
- * Metric Description: The mean duration of the burst periods that have occurred since the beginning of reception for RTP traffic.
- * Method of Measurement or Calculation: See [section 3.1.2](#), Burst Loss Rate definition [RFCXXXX].

- * Units of Measurement: This metric is expressed in milliseconds.
- * Measurement Point(s) with Potential Measurement Domain: See [section 3.1](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 3.1](#), 1st paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

d. Burst duration variance Metric

- * Metric Name: RTP Burst duration variance
- * Metric Description: The variance duration of the burst periods that have occurred since the beginning of reception for RTP traffic.
- * Method of Measurement or Calculation: See [section 4.1.2](#), Gap Loss Rate definition [RFCXXXX].
- * Units of Measurement: See [section 3.1.2](#), Burst Duration Variance definition [RFCXXXX].
- * Measurement Point(s) with Potential Measurement Domain: See [section 4.1](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 4.1](#), 1st paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

e. Burst Discard metric

- * Metric Name: RTP Burst Discard Rate
- * Metric Description: The fraction of packets discarded during bursts since the beginning of reception for RTP traffic.

- * Method of Measurement or Calculation: See [section 3.2.2](#), Burst Discard Rate definition [RFCXXXX].
- * Units of Measurement: See [section 3.2.2](#), Burst Discard Rate definition [RFCXXXX].
- * Measurement Point(s) with Potential Measurement Domain: See [section 3.2](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 3.2](#), 3rd paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

f. Gap Discard Rate metric

- * Metric Name: RTP Gap Discard Rate
- * Metric Description: The fraction of packets discarded during gaps since the beginning of reception for RTP traffic.
- * Method of Measurement or Calculation: See [section 3.2.2](#), Gap Discard Rate definition [RFCXXXX].
- * Units of Measurement: See [section 3.2.2](#), Gap Discard Rate definition [RFCXXXX].
- * Measurement Point(s) with Potential Measurement Domain: See [section 3.2](#), 2nd paragraph [RFCXXXX].
- * Measurement Timing: See [section 3.2](#), 3rd paragraph [RFCXXXX] for measurement timing and [section 3.1.2](#) [RFCXXXX] for Interval Metric flag.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

g. Number of discarded frames metric

- * Metric Name: Number of discarded frames in RTP
- * Metric Description: Number of frames discarded in a certain sequence number interval for RTP traffic.

- * Method of Measurement or Calculation: See [section 4.1.2](#), Number of discarded frames definition [RFCXXXX]. This metric is directly measured and can be inferred from packet(s) that comprise the frame.
- * Units of Measurement: This metric is expressed as 32-bit unsigned integer value.
- * Measurement Point(s) with Potential Measurement Domain: See [section 4.1](#), 1st paragraph [RFCXXXX].
- * Measurement Timing: See [section 4.1](#) [RFCXXXX], Number of discarded frames definition, this metric relies on sequence number interval and RTCP RR packet of [RFC3550](#) to determine measurement timing.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

h. Number of duplicate frames metric

- * Metric Name: Number of duplicate frames in RTP
- * Metric Description: Number of frames duplicated in a certain sequence number interval for RTP traffic.
- * Method of Measurement or Calculation: See [section 4.1.2](#), Number of discarded frames definition [RFCXXXX], This metric is directly measured and can be inferred from packet(s) that comprise the frame.
- * Units of Measurement: This metric is expressed as 32-bit unsigned integer value.
- * Measurement Point(s) with Potential Measurement Domain: See [section 4.1](#), 1st paragraph [RFCXXXX].
- * Measurement Timing: See [section 4.1](#) [RFCXXXX], Number of duplicate frames definition, this metric relies on sequence number interval to determine measurement timing.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

i. Number of full lost frames metric

- * Metric Name: Number of full lost frames in RTP
- * Metric Description: A frame is either split across multiple RTP packets or carried in only one RTP packet. If the whole frame or all the packets of the frame is lost, this frame is regarded as one full_lost_frame.
- * Method of Measurement or Calculation: See [section 4.1.2](#), Number of discarded frames definition [RFCXXXX].
- * Units of Measurement: This metric is expressed as 32-bit unsigned integer value.
- * Measurement Point(s) with Potential Measurement Domain: See [section 4.1](#), 1st paragraph [RFCXXXX].
- * Measurement Timing: See [section 4.1](#) [RFCXXXX], Number of full lost frames definition [RFCXXXX], this metric relies on sequence number interval to determine measurement timing.
- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

j. Number of partial lost frames metric

- * Metric Name: Number of partial lost frames in RTP
- * Metric Description: When a frame is split across multiple RTP packets and some RTP packets of the frame are lost, this frame is regarded as one partial_lost_frame.
- * Method of Measurement or Calculation: See [section 4.1.2](#), Number of partial lost frames definition [RFCXXXX].
- * Units of Measurement: This metric is expressed as 32-bit unsigned integer value.
- * Measurement Point(s) with Potential Measurement Domain: See [section 4.1](#), 1st paragraph [RFCXXXX].
- * Measurement Timing: See [section 4.1](#) [RFCXXXX], Number of partial lost frames definition, this metric relies on sequence number interval to determine measurement timing.

- * Use and applications: See [section 1.4](#) [RFCXXXX].
- * Reporting model: See [RFC3611](#).

[Appendix B](#). Change Log

Note to the RFC-Editor: please remove this section prior to publication as an RFC.

[B.1. draft-ietf-xrblock-rtcp-xr-summary-stat-11](#)

The following are the major changes compared to 10:

- o Incorporate the last proposed change by Barry when his DISCUSS was cleared.

[B.2. draft-ietf-xrblock-rtcp-xr-summary-stat-10](#)

The following are the major changes compared to 09:

- o Add appendix to apply [RFC6390](#) template to metrics in this draft.

[B.3. draft-ietf-xrblock-rtcp-xr-summary-stat-09](#)

The following are the major changes compared to 08:

- o Address comments in the IESG Review.

[B.4. draft-ietf-xrblock-rtcp-xr-summary-stat-08](#)

The following are the major changes compared to 07:

- o Address comments raised in Sec-DIR review.

[B.5. draft-ietf-xrblock-rtcp-xr-summary-stat-07](#)

The following are the major changes compared to 06:

- o Add comments raised in PM-DIR review by Al.

[B.6. draft-ietf-xrblock-rtcp-xr-summary-stat-06](#)

The following are the major changes compared to 05:

- o Move [RFC6709](#) to informative reference.

[B.7. draft-ietf-xrblock-rtcp-xr-summary-stat-05](#)

The following are the major changes compared to 04:

- o Editorial changes to get in line with Delay and Burst Gap related drafts.

Authors' Addresses

Glen Zorn
Network Zen
227/358 Thanon Sanphawut
Bang Na, Bangkok 10260
Thailand

Phone: +66 (0) 909-201060
Email: glenzorn@gmail.com

Roland Schott
Deutsche Telekom
Deutsche-Telekom-Allee 7
Darmstadt 64295
Germany

Email: Roland.Schott@telekom.de

Qin Wu (editor)
Huawei
101 Software Avenue, Yuhua District
Nanjing, Jiangsu 210012
China

Email: sunseawq@huawei.com

Rachel Huang
Huawei
101 Software Avenue, Yuhua District
Nanjing 210012
China

Email: Rachel@huawei.com

