

roll  
Internet-Draft  
Intended status: Standards Track  
Expires: December 29, 2016

P. van der Stok, Ed.  
consultant  
June 27, 2016

**A YANG model for Multicast Protocol for Low power and lossy Networks  
(MPL)  
draft-vanderstok-roll-mpl-yang-01**

**Abstract**

This document defines a YANG data model for management of Multicast Protocol for Low power and lossy Networks (MPL) implementations. The data model includes configuration data and state data.

**Note**

Discussion and suggestions for improvement are requested, and should be sent to [roll@ietf.org](mailto:roll@ietf.org).

**Status of This Memo**

This Internet-Draft is submitted in full conformance with the provisions of [BCP 78](#) and [BCP 79](#).

Internet-Drafts are working documents of the Internet Engineering Task Force (IETF). Note that other groups may also distribute working documents as Internet-Drafts. The list of current Internet-Drafts is at <http://datatracker.ietf.org/drafts/current/>.

Internet-Drafts are draft documents valid for a maximum of six months and may be updated, replaced, or obsoleted by other documents at any time. It is inappropriate to use Internet-Drafts as reference material or to cite them other than as "work in progress."

This Internet-Draft will expire on December 29, 2016.

**Copyright Notice**

Copyright (c) 2016 IETF Trust and the persons identified as the document authors. All rights reserved.

This document is subject to [BCP 78](#) and the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>) in effect on the date of publication of this document. Please review these documents carefully, as they describe your rights and restrictions with respect

to this document. Code Components extracted from this document must include Simplified BSD License text as described in Section 4.e of the Trust Legal Provisions and are provided without warranty as described in the Simplified BSD License.

## Table of Contents

<a href="#">1.</a>	<a href="#">Introduction . . . . .</a>	<a href="#">2</a>
<a href="#">1.1.</a>	<a href="#">Terminology . . . . .</a>	<a href="#">2</a>
<a href="#">1.1.1.</a>	<a href="#">Tree Diagrams . . . . .</a>	<a href="#">3</a>
<a href="#">2.</a>	<a href="#">MPL model . . . . .</a>	<a href="#">3</a>
<a href="#">3.</a>	<a href="#">yang-mpl modules . . . . .</a>	<a href="#">5</a>
<a href="#">3.1.</a>	<a href="#">yang-mpl-domain module . . . . .</a>	<a href="#">5</a>
<a href="#">3.2.</a>	<a href="#">yang-mpl-ops module . . . . .</a>	<a href="#">8</a>
<a href="#">3.3.</a>	<a href="#">yang-mpl-seeds module . . . . .</a>	<a href="#">11</a>
<a href="#">3.4.</a>	<a href="#">yang-mpl-statistics module . . . . .</a>	<a href="#">15</a>
<a href="#">4.</a>	<a href="#">IANA Considerations . . . . .</a>	<a href="#">19</a>
<a href="#">5.</a>	<a href="#">Acknowledgements . . . . .</a>	<a href="#">19</a>
<a href="#">6.</a>	<a href="#">Changelog . . . . .</a>	<a href="#">19</a>
<a href="#">7.</a>	<a href="#">References . . . . .</a>	<a href="#">19</a>
<a href="#">7.1.</a>	<a href="#">Normative References . . . . .</a>	<a href="#">19</a>
<a href="#">7.2.</a>	<a href="#">Informative References . . . . .</a>	<a href="#">20</a>
	<a href="#">Author's Address . . . . .</a>	<a href="#">20</a>

## [1.](#) Introduction

This document defines a YANG [[RFC6020](#)] data model for management of Multicast Protocol for Low power and lossy Networks (MPL) [[RFC7731](#)] implementations. The data model covers configuration of per-interface MPL parameters. It also provides information about which Multicast addresses are operationally used, and the seeds for which packets are forwarded

### [1.1.](#) Terminology

The key words "MUST", "MUST NOT", "REQUIRED", "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "RECOMMENDED", "MAY", and "OPTIONAL" in this document are to be interpreted as described in [[RFC2119](#)].

The following terms are defined in [[RFC6241](#)] and are not redefined here:

- o client
- o configuration data
- o server



- o state data

The following terms are defined in [[RFC6020](#)] and are not redefined here:

- o data model
- o data node

The terminology for describing YANG data models is found in [[RFC6020](#)].

Terms like domain, seed, I, k, c are defined in [[RFC7731](#)].

#### **1.1.1. Tree Diagrams**

A simplified graphical representation of the data model is used in the YANG modules specified in this document. The meaning of the symbols in these diagrams is as follows:

Brackets "[" and "]" enclose list keys.

Abbreviations before data node names: "rw" means configuration data (read-write) and "ro" state data (read-only).

Symbols after data node names: "?" means an optional node, "!" means a presence container, and "\*" denotes a list and leaf-list.

Parentheses enclose choice and case nodes, and case nodes are also marked with a colon (":").

Ellipsis ("...") stands for contents of subtrees that are not shown.

## **2. MPL model**

This document defines the YANG module "ietf-yang-mpl", which specifies a data model for MPL servers. The model consists of the following parts: (1) a "mpl-domain" part that describes the MPL-domains and associated Multicast addresses and the interfaces on which the Multicast addresses are enabled, (2) a "mpl-op" part that describes the parameters settings per seed, (3) a "mpl-seeds" part that describes the MPL buffer contents and the Trickle timer values, and (4) a "mpl-statistics" part that describes the number of lost and correctly forwarded messages. The data model, divided in four modules, has the following structure for MPL configuration per node:



```
module: ietf-yang-mpl-domain
  +--rw (single)?
    +--:(mpl-domain)
      | +--rw mpl-domain
      |   +--rw domains* [domainID]
      |     | +--rw domainID      uint16
      |     | +--rw MCList*       inet:ipv6-address
      |     +--rw addresses* [MCaddress]
      |       +--rw MCaddress      inet:ipv6-address
      |       +--rw interfaces*   string
    +--:(mpl-single)
      +--rw mpl-single
      +--rw MCaddresses*          inet:ipv6-address

module: ietf-yang-mpl-ops
  +--rw mpl-ops
    +--rw SE_LIFETIME?            uint16
    +--rw PROACTIVE_FORWARDING?   boolean
    +--rw SEED_SET_ENTRY_LIFETIME? uint64
    +--rw mpl-parameter* [domainID]
      +--rw domainID              uint16
      +--rw DATA_MESSAGE_IMIN?   uint16
      +--rw DATA_MESSAGE_IMAX?   uint16
      +--rw DATA_MESSAGE_K?      uint16
      +--rw DATA_MESSAGE_TIMER_EXPIRATIONS? uint16
      +--rw CONTROL_MESSAGE_IMIN?  uint16
      +--rw CONTROL_MESSAGE_IMAX?  uint16
      +--rw CONTROL_MESSAGE_K?     uint16
      +--rw CONTROL_MESSAGE_TIMER_EXPIRATIONS? uint16

module: ietf-yang-mpl-seeds
  +--ro mpl-seeds* [seedID domainID]
    +--ro seedID                  uint64
    +--ro domainID                uint16
    +--ro local?                  boolean
    +--ro generate-seqno?         uint8
    +--ro life-time?              uint64
    +--ro min-seqno?              uint8
    +--ro data-number?            uint8
    +--ro control-number?         uint8
    +--ro buffered-messages* [seqno]
      +--ro seqno                 uint8
      +--ro I?                    uint8
      +--ro c?                    uint8
      +--ro e?                    uint8
      +--ro t?                    uint8

module: ietf-yang-mpl-statistics
```



```

+--ro mpl-statistics* [seedID domainID]
  +--ro seedID          uint64
  +--ro domainID        uint16
  +--ro c-too-high?     uint64
  +--ro nr-forwarded?   uint64
  +--ro nr-of-messages-received? uint64
  +--ro nr-of-copies-received?  uint64
  +--ro nr-of-messages-forwarded? uint64
  +--ro nr-of-copies-forwarded?  uint64
  +--ro nr-of-refused?   uint64
  +--ro nr-of-missed?    uint64
  +--ro nr-of-notreceived? uint64
  +--ro nr-of-inconsistent-data? uint64
  +--ro nr-of-consistent-data?   uint64
  +--ro nr-of-consistent-control? uint64
  +--ro nr-of-inconsistent-control? uint64

```

### 3. yang-mpl modules

This section describes four yang modules. The model is based on the MPL specification published in [\[RFC7731\]](#) and the specification of [\[RFC6206\]](#). The identification of the interfaces follows the specification of ietf-interfaces of [\[RFC7223\]](#).

The data model allows to set values to the parameters of the MPL algorithm. This approach requires an active manager process to set the values without use of DHCP as described in: [\[RFC7774\]](#).

The names of the four modules are: yang-mpl-domain, yang-mpl-ops, yang-mpl-seeds, and yang-mpl-statistics, described in subsections with the same name.

#### 3.1. yang-mpl-domain module

This modules describes (1) the MPL domains and the associated multicast addresses, and (2) the interfaces and the multicast addresses for which they are enabled.

The model features a choice such that for constrained devices with only one "single" interface and only one "single" domain, the model specifies a list of MC addresses for which the single interface is enabled.

<CODE BEGINS>

```
module ietf-yang-mpl-domain {
```





```
yang-version 1;

namespace
  "urn:ietf:params:xml:ns:yang:ietf-yang-mpl-domain";

prefix mpl;

import ietf-inet-types{
  prefix inet;
}

organization
  "IETF ROLL (Routing Over Low power and lossy networks) Working Group";

contact
  "WG Web:  http://tools.ietf.org/wg/roll/
  WG List:  mailto:roll@ietf.org

  WG Chair: Peter van der Stok
             mailto:consultancy@vanderstok.org

  WG Chair: Ines Robles
             mailto:maria.ines.robles@ericsson.com

  Editor:    Peter van der Stok
             mailto:consultancy@vanderstok.org";

description
  "This module contains information about the state of the MPL domain.

  Copyright (c) 2016 IETF Trust and the persons identified as
  authors of the code.  All rights reserved.

  Redistribution and use in source and binary forms, with or
  without modification, is permitted pursuant to, and subject
  to the license terms contained in, the Simplified BSD License
  set forth in Section 4.c of the IETF Trust's Legal Provisions
  Relating to IETF Documents
  (http://trustee.ietf.org/license-info).

  This version of this YANG module is part of RFC XXXX; see
  the RFC itself for full legal notices."

revision "2016-05-18" {
  description "Initial revision.";
  reference
    "I-D:draft-vanderstok-roll-mpl-yang: A YANG model for Multicast
    Protocol for Low power and lossy Networks (MPL)";
}
```



```
choice single {
  description
    "A choice between single domain/interface and multiple
    domains and interfaces.";
  container mpl-domain {
    description
      "The entries describe the MPL domains, the associated
      Multicast addresses and interfaces.";

    list domains {
      key domainID;
      description
        "The entries describe a given domain identified with domainID and the
associated Multicast addresses.";

      leaf domainID {
        type uint16;
        description
          "Entry uniquely identifies the domain in the
          forwarder.";
      }

      leaf-list Mclist{
        type inet:ipv6-address;
        description
          "List of associated IPv6 Addresses.";
      }
    } // domains list

    list addresses {
      key MAddress;
      description
        "The entries describe the interfaces enabled with the specified MC
address.";

      leaf MAddress {
        type inet:ipv6-address;
        description
          "MC address belonging to a MPL domain.";
      }

      leaf-list interfaces {
        type string;
        description
          "List of names of interfaces enabled for this Multicast address.
Interface name is defined in [RFC6206].";
      }
    } // addresses list
```

```
} // container mpl-domain
container mpl-single {
    description
```

```
    "For small devices list of MC addresses for single
    interface and domain.";
    leaf-list MCAddresses{
        type inet:ipv6-address;
        description
            "list of MC addresses belonging to one single domain and
interface.";
    }
} // container mpl-simple
} // choice simple
} //module ietf-yang-mpl-domain
```

<CODE ENDS>

### **3.2. yang-mpl-ops module**

This module models the operational aspects of MPL. Per domain MPL specifies four parameters I\_MAX, I\_MIN, K, and TIMER\_EXPIRATIONS for data and control messages. The value of the MPL intervals are expressed in TUNIT. The entry SE\_LIFETIME taken over from [RFC7774] fixes TUNIT to milliseconds. For very constrained devices with only one domain there can be only one instance of mpl-parameter list.

<CODE BEGINS>

```
module ietf-yang-mpl-ops {

    yang-version 1;

    namespace
        "urn:ietf:params:xml:ns:yang:ietf-yang-mpl-ops";

    prefix mpl;

    organization
        "IETF ROLL (Routing over Low power and lossy networks) Working Group";

    contact
        "WG Web: http://tools.ietf.org/wg/roll/
        WG List: mailto:roll@ietf.org

        WG Chair: Peter van der Stok
        mailto:consultancy@vanderstok.org

        WG Chair: Ines Robles
        mailto:maria.ines.robles@ericsson.com
```



Editor: Peter van der Stok  
mailto:consultancy@vanderstok.org";

description

"This module contains information about the operation of the MPL protocol.

Copyright (c) 2016 IETF Trust and the persons identified as  
authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or

without modification, is permitted pursuant to, and subject  
to the license terms contained in, the Simplified BSD License  
set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions  
Relating to IETF Documents  
(<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see  
the RFC itself for full legal notices.";

```
revision "2016-05-18" {  
    description "Initial revision.";  
    reference  
        "I-D:draft-vanderstok-roll-mpl-yang: A YANG model for Multicast  
Protocol for Low power and lossy Networks (MPL)";  
}
```

```
container mpl-ops {  
    description  
        "Parameter settings for each MPL server and for each individual domain  
of the server.";
```

```
    leaf SE_LIFETIME {  
        type uint16;  
        description  
            "lifetime in milliseconds/(mpl timer units),  
            equivalent to SEED_SET_ENTRY_LIFETIME/TUNIT as  
            specified in RFC7774.";  
    }
```

```
    leaf PROACTIVE_FORWARDING {  
        type boolean;  
        description  
            "The boolean value indicates whether the MPL forwarder  
            schedules MPL data message transmission after  
            receiving them for the first time.";  
    }
```



```
leaf SEED_SET_ENTRY_LIFETIME {
```

```
    type uint64;
    description
      "The value indicates the minimum lifetime for an entry
       in the Seed set expressed in seconds. Default value
       is 30 minutes.";
  }

  list mpl-parameter{
    key domainID;
    description
      "Each domain has a set of MPL forwarding parameters
       which regulate the forwarding operation.";

    leaf domainID{
      type uint16;
      description
        "Each domainID must be present in  mpl-parameter list.";
    }

    leaf DATA_MESSAGE_IMIN{
      type uint16;
      description
        "The minimum Trickle timer interval, as defined in
         [RFC6206], for MPL Data Message transmissions.";
    }

    leaf DATA_MESSAGE_IMAX{
      type uint16;
      description
        "The maximum Trickle timer interval, as defined in
         [RFC6206], for MPL Data Message transmissions.";
    }

    leaf DATA_MESSAGE_K{
      type uint16;
      default 1;
      description
        "The redundancy constant, as defined in [RFC6206], for
         MPL Data Message transmissions.";
    }

    leaf DATA_MESSAGE_TIMER_EXPIRATIONS{
      type uint16;
      default 3;
      description
        "The number of Trickle timer expirations that occur
         before terminating the Trickle algorithm's
         retransmission of a given MPL Data Message.";
```



```
    }

    leaf CONTROL_MESSAGE_IMIN{
      type uint16;
      description
        "The minimum Trickle timer interval, as defined
         in [RFC6206], for MPL Control Message
         transmissions.";
    }

    leaf CONTROL_MESSAGE_IMAX{
      type uint16;
      description
        "The maximum Trickle timer interval, as defined
         in [RFC6206], for MPL Control Message
         transmissions.";
    }

    leaf CONTROL_MESSAGE_K{
      type uint16;
      default 1;
      description
        "The redundancy constant, as defined in [RFC6206],
         for MPL Control Message transmissions.";
    }

    leaf CONTROL_MESSAGE_TIMER_EXPIRATIONS{
      type uint16;
      default 10;
      description
        "The number of Trickle time expirations that occur
         before terminating the Trickle algorithm
         for MPL Control Message transmissions.";
    }

  } // list MPL-parameter
} // container MPL-ops
} // module ietf-yang-mpl-ops

<CODE ENDS>
```

### **3.3. yang-mpl-seeds module**

This module specifies the current values of the operation of the MPL forwarder. The values are acquired by the client and set by the server. The module specifies a set of message buffers, with a buffer



per seed and domain. In constrained devices there will be only one domain, but probably multiple seeds.

The message buffer contains a set of messages where each message is uniquely identified by its sequence number and seed. The associated I, c, e, and t values indicate the progress of MPL with respect to this message, as specified in [RFC7731]. A forwarder sends and receives multiple copies of a message. When a forwarder has sent (received) a copy of a message, the forwarder has sent (received) that message.

For forwarders which are seeds, local has value true and seqno is the sequence number of the next message to send.

<CODE BEGINS>

```
module ietf-yang-mpl-seeds {

  yang-version 1;

  namespace
    "urn:ietf:params:xml:ns:yang:ietf-yang-mpl-seeds";

  prefix mpl;

  organization
    "IETF ROLL (Routing over Low power and lossy networks) Working Group";

  contact
    "WG Web:  http://tools.ietf.org/wg/roll/
    WG List:  mailto:roll@ietf.org

    WG Chair: Peter van der Stok
               mailto:consultancy@vanderstok.org

    WG Chair: Ines Robles
               mailto:maria.ines.robles@ericsson.com

    Editor:   Peter van der Stok
               mailto:consultancy@vanderstok.org;

  description
    "This module contains information about the operation of the MPL protocol.

    Copyright (c) 2016 IETF Trust and the persons identified as
    authors of the code. All rights reserved.

    Redistribution and use in source and binary forms, with or
```



without modification, is permitted pursuant to, and subject to the license terms contained in, the Simplified BSD License set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions Relating to IETF Documents (<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see the RFC itself for full legal notices.";

```
revision "2016-05-18" {  
    description "Initial revision.";   
    reference  
        "I-D:draft-vanderstok-roll-mpl-yang: A YANG model for Multicast  
Protocol for Low power and lossy Networks (MPL)";  
}
```

```
list mpl-seeds{  
    key "seedID domainID";  
    config false;  
    description  
        "List describes all seeds that are active in the server. Seed  
information contains the message buffer contents and the operational values of  
I, c, sequence number and the life-times per message.";
```

```
    leaf seedID{  
        type uint64;  
        description  
            "value uniquely identifies the MPL Seed within a MPL  
            domain.";  
    }
```

```
    leaf domainID{  
        type uint16;  
        description  
            "together with seedID uniquely identifies buffer set.";  
    }
```

```
    leaf local {  
        type boolean;  
        description  
            "When local == TRUE, seed is located in this forwarder.  
            WHEN local == false, seed is located in different  
            forwarder.";  
    }
```

```
    leaf generate-seqno {  
        type uint8;  
        description
```



```
        "Sequence number of next message to be generated by this local  
seed.";  
    }
```

```
leaf life-time {
  type uint64;
  description
    " Minimum remaining lifetime of the seed entry in
      SE_LIFETIME units.";
}

leaf min-seqno{
  type uint8;
  description
    "Lower bound sequence number in the buffer of the seed.";
}

leaf data-number{
  type uint8;
  description
    "Number of currently buffered data messages.";
}

leaf control-number{
  type uint8;
  description
    "Number of currently buffered control messages.";
}

list buffered-messages{
  key seqno;
  description
    " status of trickle intervals of the buffered message identified by
seqno. and seed/domain";

  leaf seqno{
    type uint8;
    description
      "Sequence number of message.";
  }

  leaf I{
    type uint8;
    description
      "Current Trickle timer interval size in SE-LIFETIME units.";
  }

  leaf c{
    type uint8;
    description
      "number of times that copy of this message has been
        received in this interval.";
  }
}
```

}

van der Stok

Expires December 29, 2016

[Page 14]

```
    leaf e{
      type uint8;
      description
        "number of Trickle time expirations since last
        Trickle timer reset.";
    }

    leaf t{
      type uint8;
      description
        " Time expressed in SE-LIFETIME units
        that message will be (is) forwarded";
    }
  } // list seed-timers
} // list MPL-seeds
} // module ietf-yang-mpl-seeds
```

<CODE ENDS>

#### **3.4. yang-mpl-statistics module**

This module specifies the operation of the MPL forwarder expressed in number of messages and copies. The values are acquired by the client and set by the server. Statistics are specified per seed and domain. In constrained devices there will be only one domain, but probably multiple seeds.

The parameter *k* determines how many copies of a message can be forwarded. The counters *c-too-high*, *nr-forwarded*, and *nr-not-forwarded* give insight in the consequences of the current value of *k*.

The other counters give insight in the loss of messages caused by the medium or forwarding delays. The *inconsistent*/*consistent* counters indicate when consistent or inconsistent messages were received according to the definition of consistent in [\[RFC7731\]](#).

<CODE BEGINS>

```
module ietf-yang-mpl-statistics {

  yang-version 1;

  namespace
    "urn:ietf:params:xml:ns:yang:ietf-yang-mpl-statistics";
```



prefix mpl;

organization

"IETF ROLL (Routing over Low power and lossy networks) Working Group";

contact

"WG Web: <http://tools.ietf.org/wg/roll/>

[WG](mailto:roll@ietf.org) List: <mailto:roll@ietf.org>

WG Chair: Peter van der Stok  
<mailto:consultancy@vanderstok.org>

WG Chair: Ines Robles  
<mailto:maria.ines.robles@ericsson.com>

Editor: Peter van der Stok  
<mailto:consultancy@vanderstok.org>";

description

"This module contains information about the operation of the MPL protocol.

Copyright (c) 2016 IETF Trust and the persons identified as  
authors of the code. All rights reserved.

Redistribution and use in source and binary forms, with or

without modification, is permitted pursuant to, and subject  
to the license terms contained in, the Simplified BSD License  
set forth in [Section 4.c](#) of the IETF Trust's Legal Provisions  
Relating to IETF Documents  
(<http://trustee.ietf.org/license-info>).

This version of this YANG module is part of RFC XXXX; see  
the RFC itself for full legal notices.";

revision "2016-05-18" {

description "Initial revision.";

reference

"I-D:[draft-vanderstok-roll-mpl-yang](#): A YANG model for Multicast  
Protocol for Low power and lossy Networks (MPL)";

}

list mpl-statistics{  
key "seedID domainID";

config false;



## description

"List describes performance statistics integrated over the messages identified by seed and domain identifiers. A forwarder can receive and forward multiple copies of a message uniquely identified by seqno, domain, and seed.";

leaf seedID{

type uint64;

description

"value uniquely identifies the MPL Seed within a MPL domain.";

}

leaf domainID{

type uint16;

description

"together with seed-ID uniquely identifies buffer set.";

}

leaf c-too-high {

type uint64;

description

"Number of times that a copy was not forwarded because  $c > k$ .";

}

leaf nr-forwarded {

type uint64;

description

"number of times copies are forwarded, while  $c \leq k$ .";

}

leaf nr-of-messages-received{

type uint64;

description

"number of messages (one or more copies) received, must be smaller than or equal to seqno.";

}

leaf nr-of-copies-received{

type uint64;

description

"total number of message copies received.";

}

leaf nr-of-messages-forwarded{

type uint64;

description

"number of forwarded messages, must be smaller than or equal to nr-



```
of-messages-received.";
    }

    leaf nr-of-copies-forwarded{
```

```
    type uint64;
    description
        "number of forwarded copies, can be larger than number-of-copies-
received.";
}

leaf nr-of-refused{
    type uint64;
    description
        "number of refused copies because seqno too small.";
}

leaf nr-of-missed{
    type uint64;
    description
        "number of messages that were not received (derived from gaps in
received seqno's.)";
}

leaf nr-of-notreceived{
    type uint64;
    description
        "number of messages that were not received
        according to control message.";
}

leaf nr-of-inconsistent-data{
    type uint64;
    description
        "number of inconsistent data messages.";
}

leaf nr-of-consistent-data{
    type uint64;
    description
        "number of consistent data messages.";
}

leaf nr-of-consistent-control{
    type uint64;
    description
        "number of consistent control messages.";
}

leaf nr-of-inconsistent-control{
    type uint64;
    description
        "number of inconsistent control messages.";
```

```
    }  
  } // list mpl statistics
```

```
} // module ietf-yang-mpl-statistics
```

<CODE ENDS>

#### **4. IANA Considerations**

This specification has no consequences for IANA.

#### **5. Acknowledgements**

Andy Bierman has commented on the use of YANG for mpl. YANG doctors pointed out a wrong use of config.

#### **6. Changelog**

Changes from version 00 to version 01

- o config false in "statistics" and "seeds" modules
- o separated into 4 modules
- o inserted choice in domain modules
- o renamed some parameters
- o Introduced section per module

#### **7. References**

##### **7.1. Normative References**

- [RFC2119] Bradner, S., "Key words for use in RFCs to Indicate Requirement Levels", [BCP 14](#), [RFC 2119](#), DOI 10.17487/RFC2119, March 1997, <<http://www.rfc-editor.org/info/rfc2119>>.
- [RFC6020] Bjorklund, M., Ed., "YANG - A Data Modeling Language for the Network Configuration Protocol (NETCONF)", [RFC 6020](#), DOI 10.17487/RFC6020, October 2010, <<http://www.rfc-editor.org/info/rfc6020>>.
- [RFC6241] Enns, R., Ed., Bjorklund, M., Ed., Schoenwaelder, J., Ed., and A. Bierman, Ed., "Network Configuration Protocol (NETCONF)", [RFC 6241](#), DOI 10.17487/RFC6241, June 2011, <<http://www.rfc-editor.org/info/rfc6241>>.



- [RFC7223] Bjorklund, M., "A YANG Data Model for Interface Management", [RFC 7223](#), DOI 10.17487/RFC7223, May 2014, <<http://www.rfc-editor.org/info/rfc7223>>.
- [RFC7731] Hui, J. and R. Kelsey, "Multicast Protocol for Low-Power and Lossy Networks (MPL)", [RFC 7731](#), DOI 10.17487/RFC7731, February 2016, <<http://www.rfc-editor.org/info/rfc7731>>.

## **7.2. Informative References**

- [RFC6206] Levis, P., Clausen, T., Hui, J., Gnawali, O., and J. Ko, "The Trickle Algorithm", [RFC 6206](#), DOI 10.17487/RFC6206, March 2011, <<http://www.rfc-editor.org/info/rfc6206>>.
- [RFC7774] Doi, Y. and M. Gillmore, "Multicast Protocol for Low-Power and Lossy Networks (MPL) Parameter Configuration Option for DHCPv6", [RFC 7774](#), DOI 10.17487/RFC7774, March 2016, <<http://www.rfc-editor.org/info/rfc7774>>.

### Author's Address

Peter van der Stok (editor)  
consultant

Phone: +31-492474673 (Netherlands), +33-966015248 (France)  
Email: [consultancy@vanderstok.org](mailto:consultancy@vanderstok.org)  
URI: [www.vanderstok.org](http://www.vanderstok.org)

