GENERIC CONGESTION FEEDBACK MESSAGE

RMCAT Design Team

Status report

Presenter

Zaheduzzaman Sarker Ericsson Research

Status summery

Produced a draft with a proposal for Congestion Control Feedback Message

- Presented at IETF97
- Includes necessary feedback information and packet format
- Worked on optimization
 - Two proposals presented at IETF97
 - Needed to analyze the gain vs complexity
 - Compared to overhead of compound RTCP the optimization is not worthwhile
 - Since IETF97
 - Discussed need to optimization
 - Tried to produce data to justify the gain with optimization
- Aiming to finish the work before IETF99

Proposed congestion feedback - a recap

Feedback contains information about

- Packet identifier
 - RTP sequence number
- Packet Arrival Time
 - Arrival time stamp at the receiver of the media
- Packet Explicit Congestion Notification (ECN) marking
 - If ECN [RFC3168] is used, it is necessary to report on the 2-bit ECN mark in received packets, indicating for each packet whether it is marked not-ECT, ECT(0), ECT(1), or ECN-CE.

Read at : <u>https://datatracker.ietf.org/doc/draft-dt-rmcat-feedback-message/</u>

Packet format

As XR block.

Sent as a part of regular feedback

0 789012345678901 0123 4 5 6 Report count Block Length = TBD BT=RC2F Report Timestamp (32bits) SSRC of 1st media source begin seq end seq |L|ECN| Arrival time offset . . . SSRC of nth media source -+-+-+-+-+-+-+-+ begin_seq end seq +-+-+-+-+-+-+-+-+ |L|ECN| Arrival time offset

Read at : https://datatracker.ietf.org/doc/draft-dt-rmcat-feedback-message/

Packet format

As RTCP/AVPF transport layer feedback.

Needed if want to sent as early feedback

0 1		2	3			
0123456789012	345678	9 0 1 2 3 4 5 6	78901			
+-	+-+-+-+-+-+	-+-+-+-+-+-+-+	-+-+-+-+			
V=2 P FMT = 2 PT =	205	length	1			
+-	+-+-+-+-+-+	-+-+-+-+-+-+-+-+	-+-+-+-+			
SSRC of	packet sende	r	I.			
+-						
SSRC of 1st media source						
+-	+-+-+-+-+-+	-+-+-+-+-+-+-+	-+-+-+-+			
begin_seq	I.	end_seq	I.			
+-	+-+-+-+-+-+	-+-+-+-+-+-+-+	-+-+-+-+			
L ECN Arrival time offs	et					
+-	+-+-+-+-+-+	-+-+-+-+-+-+-+	-+-+-+-+			
+-						
SSRC of nth media source						
+-						
begin_seq	I.	end_seq	I.			
+-						
L ECN Arrival time offs	et		I.			
*-						
Report Timestamp (32bits)						
+-						

Read at : <u>https://datatracker.ietf.org/doc/draft-dt-rmcat-feedback-message/</u>

Is this the right information to report?

Yes. The information has been discussed with implementers and Congestion control algorithm proponents. We have not find any more information that is required to be send as feedback.

Is encoding this using RTCP XR and transport layer feedback appropriate?

Yes.

Which format to select?

- Sending a XR block is a cleaner fit architecturally
- Sending as transport layer feedback saves couple of bites
- Stick to the framework in the draft

	2	3
0 1 2 3 4 5 6 7 8 9 0 1 2 3	3 4 5 6 7 8 9 0 1 2 3 4	5678901
+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-	-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+	-+-+-+-+-+-+ h
+-	-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+	+-+-+-+-+-+-+-+-+-
	.+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_	
BT=RC2F Report cou		
+-		-+-+-+-+-+-+
	nostamp (32bits)	
	st media source	
	+-	-+-+-+-+-+-+
begin_seq	end_s	eq
	·+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-	
LECN Arrival time offset		· /
+-	+-	-+-+-+-+-+-+
•		-
--*-*-*-*-*-*-*-*-*-*-*-*-*-		-+-+-+-+-+-+
+_+_+_+_+_+_+_+_+_+_+_+_+_+_	-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+	-+-+-+-+-+
+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-		1
+-+-+-+-+-+-+-+-+-+-++ SSRC of n +-+-+-+-+-+-+-+-+-+-+-+++	ath media source	-+-+-+-+-+-+-
+-+-+-+-+-+-+-+-+-+-+-+-+-+ begin_seq +-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-	hth media source ++-+-++-+-+-+-+-+-+-+-+-+-+-+-+	-+-+-+-+-+-+ •q
+_+_+_+_+_+_+_+_+_+_+_+_+_ begin_seq	hth media source ++-+-++-+-+-+-+-+-+-+-+-+-+-+-+	-+-+-+-+-+-+ •q

	0 1 2	3						
	0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9 0 1 2 3 4 5 6 7 8 9	0 1						
	+-	-+-	;					
	V=2 P ReportCnt PT=CCFB longth		ļ					
	+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-+-	-+-	î					
SSRC								
	Report Timestamp (32bits)							
	SSRC of 1st media source							
++++++++++++++++++++++++++++++++++++++								
	begin_seq end_seq		I					
Ŀ.,	+-	+-+-	ŧ					
"	L ECN Arrival time offset		•					
	+-	+-+-	+					
	•		•					
	•		1					
+-								
	SSRC of nth media source							
	begin seq end seq		ī					
	+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_+_	-+-	÷					
	L ECN Arrival time offset		ī					
			1					
	+-	+-+-	+					

*Picture courtesy: Colin Perkins, https://www.ietf.org/proceedings/97/slides/slides-97-rmcat-rtcp-feedback-for-congestion-control-00.pdf

Optimization

- Colin Perkins presented some analysis at IETF97
 - RTCP overhead can be minimum of 80 octets per report
 - "Optimizing XR block likely not worthwhile"
 - Use of reduced sized RTCP makes a difference in overhead
- Two proposal was presented
 - RLE for loss
 - Might make a difference on a lossy channel
 - Separate ECN blocks when ECN is enabled on the path
 - Action point was to evaluate the gain vs complexity
 - Compared to RTCP overhead
- Optimization could also be done for ease of parsing

What to optimize for?

- Decision was to work with the scenarios discussed in the mailing list
 - low bitrate cases are more interesting

Low bitrate audio

- Uplink: 20 kbps
- Downlink: 20 kbps
- Audio packet rate: 50 packets/second

Low bitrate audio and video

- Uplink: 70-100 kbps
- Downlink: 70-100 kbps
- Audio packet rate: 50 packets/second
- Video framerate: 7-30 fps

High bitrate audio and video

- Uplink: 500 kbps
- Downlink: 8000 kbps
- Audio packet rate: 50 packets/second
- Video framerate: 30 fps

Data for optimization

- We got some data from Google's deployed WebRTC solution in Chrome browser. Thanks!!
- 1 audio and 1 video stream in the session
- Send-side CC uses <u>draft-holmer-rmcat-</u> <u>transport-wide-cc-extensions-01</u>
- Receive-side CC uses <u>draft-alvestrand-</u> <u>rmcat-remb-03</u>
- Every other reduced size, every other compound

Audio at 6 kbps payload bitrate, 20 ms frames:

- Average RTCP bitrate with send-side CC: 182 bps
- Average RTCP bitrate without CC: 112 bps
- Reduced size: ~100 bytes on average, 1Hz
- Compound: 156 bytes, 1Hz

Gives an deployable limit on RTCP bandwidth

Data for optimization

- Interesting data for low bitrate audio only session.
- Google uses arrival timestamp compression to reduce reporting block size.

Audio at 6 kbps payload bitrate, 20 ms frames:

Average RTCP bitrate with send-side CC: **182 bps** Average RTCP bitrate **without** CC: **112 bps** Reduced size: ~100 bytes on average, 1Hz Compound: 156 bytes, 1Hz

What would the required RTCP bandwidth using proposed packet format for this case?

Ans: 240bps

Adaptive Feedback

- Adaptive feedback based on available bandwidth
 - Impacts how much history to put into the feedback
 - Need some guidance
 - However, this is a general issue
 - RMCAT should have
 - Feedback message
 - Necessary changes to RTCP reporting
 - Separate draft on how to use feedback message

Conclusions

- The current proposal contains required information
- Send XR block in regular report and as transport layer feedback in the reduce-sized report
- Need to judge the gain of optimizing the packet format compared RTCP overhead for compound packet
 - Any optimization proposal must also provide relevant information for comparison.
- The design team feedback message proposal should stick to defining feedback information and packet format

Is there any other issues?